z/OS

Hardware Configuration Definition User's Guide

SC33-7988-01

z/OS

Hardware Configuration Definition User's Guide

SC33-7988-01

Note

Before using this information and the product it supports, be sure to read the general information under "Notices" on page 495.

Second Edition, March 2002

This edition applies to Version 1 Release 3 of z/OS (5694-A01) and to all subsequent releases and modifications until otherwise indicated in new editions.

Order publications through your IBM representative or the IBM branch office serving your locality. Publications are not stocked at the address below.

IBM welcomes your comments. A form for readers' comments is provided at the back of this publication. If the form has been removed, address your comments to:

IBM Deutschland Entwicklung GmbH
Department 3248
Schönaicher Str. 220
D-71032 Böblingen
Federal Republic of Germany

Or by FAX:
From Germany: 07031-16-3456
Other countries: +(49)+7031-16-3456

Or electronically:
Internet e-mail: s390id@de.ibm.com

Internet

Visit our homepage at http://www.ibm.com/servers/eserver/zseries/zos/hcm/

If you would like a reply, be sure to include your name, address, telephone number, or FAX number.

Make sure to include the following in your comment or note:
- Title and order number of this book
- Page number or topic related to your comment

When you send information to IBM, you grant IBM a nonexclusive right to use or distribute the information in any way it believes appropriate without incurring any obligation to you.

© Copyright International Business Machines Corporation 1994, 2002. All rights reserved.
US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Figures ix

Tables xi

About This Book xiii
Who This Book Is For xiii
How to Use This Book xiii
How This Book Is Organized xiv
How to Read Syntax Diagrams xv
Related Information xvii

Chapter 1. Hardware Configuration Definition - What Is It 1
What HCD Is and How It Differs from MVSCP and IOCP 1
Definition of Configuration Data. 1
Validation of Configuration Data 3
Reconfiguration of Configuration Data. 4
What HCD Offers You 4
How HCD Works. 5
Objects Managed in the IODF 6
IODF Used at IPL 6
Relationship of Data Sets Used by HCD 7
The Environment in which HCD Operates 8
HCD and I/O Operations (ESCON Manager) . . 9
HCD and the Coupling Facility. 10
Support of S/390 Microprocessor Clusters . . . 11
Support of the Sysplex Environment 11

Chapter 2. Change Summary and Migration 13
What is New in HCD for z/OS Version 1 Release 3 13
Coupling Facility Duplexing. 13
iQDIO and FCP Channel Support 13
FCTC Support 14
Support for FICON Cascade Switching 14
Hardware Support 14
Summary of Changes in Previous Releases 14
What is New in HCD for z/OS Version 1 Release 1 14
What Is New in HCD for OS/390 Version 2 Release 9 15
What Is New in HCD for OS/390 Version 2 Release 5 16
What Is New in HCD for OS/390 Release 3 . . 18
What Is New in HCD for MVS/ESA SP 5.2.2 . . 19
What Is New in HCD 5.2. 20
What Is New in HCD 5.1. 22
Migration Overview 27
Developing a Migration Strategy 27
Year 2000 Support for HCD 28
For Additional Migration Information 28
Migration Roadmap 28
Migration Tasks 29

Chapter 3. How to Setup, Customize and Start HCD 37
Setting Up HCD. 37
How to Invoke HCD in Dialog Mode. 38
Tailoring the CLIST CBDCHCD 39
Starting and Ending HCD 40
Defining an HCD Profile 41
Keywords 41
Customizing HCD EXEC Procedures 48

Chapter 4. How to Work with I/O Definition Files 49
IODF Naming Convention 49
Work IODF 49
Production IODF 49
Specify an IODF. 50
Sharing IODFs 51
Deciding on the Number of IODFs 51
The Master IODF Concept 52
Change to Another IODF. 54
Change a Production IODF / Create a Work IODF Based on a Production IODF 54
View Active IODF 54
Backup an IODF. 54
Maintain IODFs 54
Delete an IODF 55
Copy an IODF 55
Change IODF Description 55
View an IODF 55
Export an IODF 56
Import an IODF 57
Work with Configuration Packages 57
Upgrade an IODF 61
Activity Logging 62
IODF Release Level Compatibility 63

Chapter 5. How to Use the Dialog . . . 67
Panel Layout 67
Working with Lists 69
Numbered Selection Lists. 69
Unnumbered Single Selection Lists 70
Unnumbered Multiple Selection Lists. 70
Action Lists 71
Message Lists. 74
Promptable Fields 75
Commands and Function Keys 76
Getting Help 76
Navigating through the Dialog 77
Moving Forward and Backward within a Task. . 77
Fast Path 78
Filtering 81
Job Statement Information Used in Panels 84

© Copyright IBM Corp. 1994, 2002

Chapter 6. How to Define, Modify, or View a Configuration. 85

Creating New Objects 85
Add 85
Add like 85
Repeat (Copy) 86
Navigating through HCD. 86
Centralized Navigation 86
Hierarchical Navigation 86
Graphical Navigation 87
Navigation Map 87
Suggested Sequence to Define a Configuration . . 88
Working with Operating System Configurations . . 89
Defining Operating System Configurations . . . 89
Changing Operating System Configurations . . 90
Repeating (Copying) Operating System Configurations 91
Deleting Operating System Configurations . . . 92
Working with EDTs. 92
Defining EDTs 92
Changing EDTs 93
Repeating (Copying) EDTs 94
Deleting EDTs 95
Working with Generics 95
Working with Esoteric Groups 96
Defining Esoteric Groups 96
Changing Esoteric Groups 97
Adding Devices to Esoterics 97
Repeating (Copying) Esoteric Groups. 98
Deleting Esoteric Groups 98
Working with Processors 99
Defining Processors. 99
Changing Processors 101
Repeating (Copying) Processors 104
Priming Processor Data 105
Deleting Processors 106
Working with Partitions 106
Defining Partitions 106
Changing Partitions 108
Repeating (Copying) Partitions 108
Transferring Partition Configurations 109
Deleting Partitions. 111
Working with Channel Paths 111
Using Multiple Image Facility 111
Defining Channel Paths 112
Establishing Coupling Facility Channel Path Connections 116
Disconnecting Coupling Facility Channel Path Connections 118
Changing Channel Paths 118
Aggregating Channel Paths. 120
Deleting Channel Paths 122
Working with Control Units 122
Defining Control Units 122
Changing Control Units 127
Disconnecting Control Units from a Processor 129
Priming Control Unit Data 130
Deleting Control Units 131
Working with Devices 131
Defining Devices 131
Changing Devices 137
Disconnecting Devices from an Operating System 142
Showing or Hiding Parameter/Feature Definitions of Devices 142
Priming Device Data 144
Deleting Devices 145
Working with Operating System Consoles 145
Changing Operating System Consoles 146
Deleting Operating System Consoles 146
Viewing Information 146
Viewing Object Definitions 146
Viewing Coupling Facility Information 148
Viewing CTC Connections 148

Chapter 7. How to Work with Switches 153

Possibilities of Switch Connections 153
Advantages of Switch Definitions with HCD . . . 156
Defining Switches 156
Working with Switches 156
Defining Switch Characteristics 156
Changing Switch Data 159
Priming Switch Data 159
Moving Ports 160
Deleting Switches 162
Working with Connections to Switches 163
Defining Connections to Switches 163
Priming Switch Port Data 166
Additional Actions on the Port List Panel . . . 167
Working with Switch Configurations 168
Defining Switch Configuration Data 168
Changing the Switch Configuration ID 170
Generating a Switch Matrix 171
Deleting Switch Configurations 172
Migrating Existing Switch Configurations 173
Prerequisites. 173
Migration Steps 173
Activating Switch Configuration Data 175
Prerequisites. 175
Activation Steps 175
Saving Switch Configuration Data 176

Chapter 8. How to Activate or Process Configuration Data 179

Build a Production IODF 180
Build an IOCDS 184
Using this Procedure for Processors with an SNA Address 186
Build S/390 Microprocessor IOCDSs 186
Manage S/390 Microprocessor IPL Attributes. . . 190
Build an IOCP Input Data Set 191
How to Build an IOCP Data Set 191
IOCP Input Data Sets Using Extended Migration 192
Create JES3 Initialization Stream Checker Data . . 195
Build an OS Configuration Data Set 195
Verify a Configuration 196
Verifying a Configuration Against the Local System 196
Verifying a Configuration Against a System in the Sysplex 197
The I/O Path List 197

Activate a Configuration Dynamically 199
View Active Configuration 199
How to Activate if Hardware and Software Changes are Allowed 200
How to Activate if Software-Only Changes Are Allowed 202
Activate a Configuration Sysplex Wide 203
Displaying Active Sysplex Members 203
Activate Software Configuration Changes Only 206
Activate Software and Hardware Configuration Changes 208
Switch IOCDS for the Next POR 209
Build CONFIGxx Member 209
Process Display M=CONFIG(xx) Command . . . 211
Switch IOCDS for Next POR 212
Switch IOCDS for Processor without SNA Address Defined 212
Switch IOCDS for Processors in an S/390 Microprocessor Cluster with SNA Address Defined 213
Switch IOCDS for Systems in a Sysplex . . . 213
Specify an IODF for IPL 214
IODF Processing at IPL 214

Chapter 9. How to Print and Compare Configuration Data 215

Print Configuration Reports 215
Channel Subsystem Report 215
Switch Report 216
Operating System Report 216
CTC Connection Report 216
I/O Path Report 216
Supported Hardware Report 216
I/O Definition Reference 217
How to Print a Textual Report. 217
Create or View Graphical Configuration Reports 218
Prerequisites. 219
How to Create a Graphical Configuration Report. 219
Printing the Output 221
Viewing the Output 222
Print List Panels 225
Compare Functions 226
Compare IODFs 226
Compare CSS / Operating System Views . . . 230
View and Print the HCD Activity Log 231

Chapter 10. How to Query Supported Hardware and Installed UIMs. 233

Query Supported Processors 233
Query Supported Switches 235
Query Supported Control Units 236
Query Supported Devices 237
Query Installed UIMs 238

Chapter 11. How to Migrate Existing Input Data Sets 239

Migration Sequence 239
LPAR Considerations. 239
Preparing Your Input Data Sets for Migration . . 240
Data Requiring Attention 240
Preparing Additional Input Data Sets for Migration 242
Considerations for IBM ES/4381 Processors . . 248
Migrating Input Data Sets Using the HCD Dialog 248
Step 1: Specify the Work IODF 248
Step 2: Migrate the Input Data Sets 249
Step 3: Analyze Errors and Upgrade the Input Data Set 250
Step 4: Update Configuration Data 250
Migrating Input Data Sets Using the Batch Utility 251
Step 1: Create the Work IODF 251
Step 2: Migrate Input Data Set. 251
Step 3: Analyze Errors and Upgrade the Input Data Set 251
Step 4: Build Production IODF 252
Changing I/O Configurations by Editing Data Sets 252
Additional Parameters and Statements 253
Updating Parts of a Configuration by Migrating Input Data Sets. 267
Possible Actions on Objects Using the Incremental Update 267
How to Invoke the Incremental Update . . . 270
Resolving Migration Errors 277
Errors Detected During Assembly Process . . . 278
Errors Detected During Validation Process. . . 279
Insufficient Data Set Sizes 280

Chapter 12. How to Invoke HCD Batch Utility Functions 283

Input Parameter String 284
Function Parameter Strings. 284
Start the Dialog. 284
Initialize IODF 285
Upgrade IODF 286
Migrate I/O Configuration Statements 287
Build a Production IODF 290
Build a Work IODF from a Production IODF 291
Build an IOCDS or an IOCP Input Data Set . . 292
Build an HCPRIO Input Data Set. 295
Build I/O Configuration Statements 295
Copy IODF 298
Print Configuration Reports 299
Create a Graphical Configuration Report . . . 301
Compare IODFs or CSS/OS Reports. 303
Import an IODF 307
Export an IODF 308
Batch IODF Copy Example 310
List of Standard DD Names 312
List of Alternate DD Names 314

Chapter 13. Security and Other Considerations. 315

Security-Related Considerations 315
Defining RACF Profiles 315
Giving Users Access Authority 316
Providing Additional Security for Devices 318
Catalog Considerations 319
Data Sets Cataloged with an Esoteric Device Group Name 320

SMS-Related Considerations 321
ISPF-Related Considerations 321
VM-Related Considerations. 322

Chapter 14. LDAP Support 325
Introduction to LDAP 326
HCD LDAP Backend: Structure and Mode of Operation 327
Integrating the HCD LDAP Backend into the z/OS LDAP Server 328
Performing the Setup. 329
Customizing the HCD LDAP Backend 334
Configuration File Parameters 334
LDAP Debug Level 336
Message Translation 336
Accessing IODF Information 337
The IODF Directory Information Tree 337
Performing LDAP Requests on IODFs 337
Operational Behavior. 338
Restrictions for Search and Update Requests . . 339
Transactions 343
Prerequisites and Method of Functioning . . . 343
How is a Transaction Initiated and Closed? . . 345

Appendix A. Navigating Through the Dialog 349

Appendix B. Configuration Reports 355
Textual Configuration Reports. 355
Channel Subsystem Reports 355
Switch Reports 364
Operating System Reports 366
CTC Connection Report 370
I/O Path Report 371
Supported Hardware Report 373
I/O Definition Reference 401
Graphical Configuration Reports 405
LCU Report 405
IODF Compare Reports 406
Processor Compare Report 406
Partition Compare Report 406
Channel Path Compare Report 407
Control Unit Attachment Compare Report. . . 408
Device Attachment Compare Report. 409
Control Unit Compare Report 409
Device Compare Report 410
Switch Compare Report 410
Switch Detail Compare Report. 411
Switch Configuration Detail Compare Report 411
Esoteric Compare Report 412
OS Device Compare Report 413
OS Console Compare Report 413
CSS / Operating System Device Compare 414

Appendix C. Problem Determination for HCD 415
Identifying Problems 415
HCD Abnormal Termination 416
Error During IPL (Wait State Codes). 419
Problems with Panels and Function Key Assignment 419
Problems with Help Information Provided by HCD 420
Problems with Output of HCD Textual Reports 422
Problems with Output of HCD Graphical Reports 422
Problems During Initialization of HCD 424
Problems with UIMs 425
HCD Internal Problems 426
Problems with the Transmit Configuration Package Action 427
HCD LDAP Backend Abnormal Termination 431
Adverse LDAP Return Code from the HCD LDAP Backend 432
Error in HCD LDAP Backend 432
Diagnostic Information and Tools. 433
HCD Messages 433
HCD Trace Facility 434
IODF Dump. 440
Repair an IODF 440
MVS Dumps and Traces. 441
IPCS Reports 441
LDAP Problem Determination. 441
Searching Problem Reporting Data Bases and Reporting Problems 442
Sending an IODF to a Different Location 442

Appendix D. HCD Object Management Services 445
How to Invoke the HOM Services 445
Data Input and Output Areas 446
Request Block (HRB) 447
Functions. 448
Example 450
Return Codes 451
Reason Codes 451

Appendix E. Scenarios 453
Procedure 454
Define Operating System Configuration Data. . . 454
Define Switches 457
Define Processor Related Data. 458
Define Processor 458
Define Partitions 460
Define Channel Path Data 461
Complete Switch Definitions 465
Connect Switch Control Unit to Processor . . . 465
Complete Port Data 466
Chain the Two Switches Together. 467
Define Control Unit Data 468
Define I/O Device Data 471
Define NIPCON Data 473

Appendix F. IODF Data Model 475
IODF Object Class Definitions Within LDAP . . . 476
IODF Attribute Table 485

Appendix G. Accessibility 493
Using assistive technologies 493

Keyboard navigation of the user interface 493

Notices 495
Trademarks 496
Programming Interface Information 497
Accessing Licensed Books on the Web 497

Online Message Lookup 498

Glossary 499

Index 503

Figures

1. Multiple Data Set Configuration Definition without HCD 2
2. Single Data Set Configuration Definition with HCD 3
3. Configuration Definition with HCD 6
4. Objects Managed by HCD 6
5. Building a Production IODF and an IOCDS 7
6. Relationship of Data Sets Used by HCD . . . 8
7. Processor Configuration with Coupling Facility Implemented 10
8. Finding Your Migration Method 31
9. Sample ISPF Master Application Menu Panel 39
10. Example of an HCD Profile 47
11. Example of Create Work I/O Definition File 50
12. IODF Distribution/Merge Process 53
13. Maintain I/O Definition Files Panel 55
14. Sample Configuration Package List — Left Panel. 57
15. Add Configuration Package Panel 58
16. Transmit Configuration Package Panel . . . 60
17. Example of Information that is Added to the Activity Log 62
18. Example of an View Activity Log Panel 63
19. Example of a Panel Layout 67
20. Panel Layout of a Data Entry Panel 69
21. Primary Task Selection Panel. 70
22. Example of a Single Selection List 70
23. Example of a Multiple Selection List 71
24. Example of an Action List Panel with a Context Menu. 72
25. Example of an Action List Panel with Action Codes 73
26. Message List Panel 74
27. Explanation Message 75
28. Example of a Prompt Selection Panel 75
29. Moving within a Multi-Step Task 78
30. Using the Goto Action Bar Choice 79
31. Example of a Selection List 79
32. Filter Example 82
33. I/O Device List Filter Panel 82
34. Reduced I/O Device List (by Using Filtering) 83
35. Navigation Map 88
36. Result of the Transfer (Move) Partition Configs Action 110
37. Example of a Channel Path/Partition Matrix on the Channel Path List. 115
38. Select Processor / Control Unit (1) 124
39. Select Processor / Control Unit (2) 125
40. Change Channel Path Link Addresses 127
41. CTC/CNC Connection Established Using a Dynamic Connection. 149
42. CTC/CNC Connection Established Using Shared Channels. 150
43. Example of a Configuration with One Switch 154
44. Example of a Configuration with Two Switches 154
45. Example of a Configuration with Two Switches 155
46. Example of a Configuration with a FICON Two-Switch Cascading Switching 155
47. Switch List (Left Part). 157
48. Switch List (Right Part) 157
49. Add Switch 158
50. Change Switch Definition 159
51. Example of a Confirm Priming Switch Data List panel 160
52. Example of a Move Ports to a Target Switch panel 161
53. Example of a Confirm Delete Switch panel 163
54. Port List Panel 164
55. Example of an Activate or Process Configuration Data Panel 181
56. Example of a Build Production I/O Definition File Panel 181
57. Example of a Confirm Production IODF Name Panel 182
58. Example of a Confirm Delete I/O Definition File Panel 183
59. Example of a Define Descriptor Fields Panel 183
60. IOCDS List 184
61. S/390 Microprocessor Cluster List 187
62. IOCDS List 188
63. Example of Input Data Set for Migration Enhancements 194
64. Identify System I/O Configuration Panel 197
65. Activate New Configuration: Hardware and Software Changes 200
66. Activate Sysplex Member List - Part 1 204
67. Activate Sysplex Member List - Part 2 205
68. Activate Sysplex Member List - Part 3 206
69. Activate Software Configuration Only Panel 206
70. Message Panel with ACTIVATE Messages 207
71. View Configuration Status Panel 208
72. Activate Hardware and Software Configuration Panel 208
73. Restrict Ports Eligible for Dynamic CHPID Management Panel. 210
74. Build CONFIGxx Member Panel 210
75. Confirm Update CONFIGxx Member Panel 211
76. Process Display M=CONFIG(xx) Command Panel 212
77. Print Configuration Reports Panel 217
78. Example of a Limit Reports Panel. 218
79. Example of a Printed List Panel 226
80. Example of a Compare IODFs Panel 227
81. Example of a Limit Processor Compare Reports Panel 228
82. Example of a Limit Switch Compare Reports Panel 228
83. Example of a Limit Operating System Compare Reports Panel 229

© Copyright IBM Corp. 1994, 2002

84. Example of a Select Print Options (for Compare IODFs Only) Panel 229
85. Select Print Options (for CSS/OS Compare Only) 230
86. List of Supported Processors 234
87. IOCP Migration. 243
88. IOCP Migration. 244
89. IOCP Migration. 244
90. IOCP Migration. 245
91. IOCP Migration. 245
92. IOCP Migration. 246
93. MVSCP Migration 247
94. MVSCP Migration 247
95. MVSCP Migration 248
96. Migrate IOCP / MVSCP / HCPRIO Data Panel 249
97. Partial Migration of an IOCP Input Data Set 271
98. Partial migration of an IOCP input data set 272
99. Partial migration of an IOCP input data set 273
100. Partial migration of an IOCP input data set 274
101. Partial Migration of an IOCP Input Data Set 275
102. Partial Migration of an MVSCP Input Data Set 275
103. Message List Example 277
104. Message List Containing an Assembler Message 278
105. Example: HCD Migration Log 279
106. Standard DD names Used by HCD 313
107. CBD.CPC.IPLPARM Access Authority and HCD IPL Attribute Management Functions . 317
108. CBD.CPC.IOCDS Access Authority and HCD IOCDS Management Functions 318
109. Recommended IODF Catalog Structure 320
110. Define a VM operating system. 322
111. Define Device Parameters/Features for VM Device 322
112. Sample DIT portion of the HCD LDAP Backend 327
113. Load Module Libraries 330
114. HCD Primary Task Selection Panel 349
115. HCD - Define, Modify, or View Configuration Data - Option 1 349
116. HCD - Generic Action Bar Options 350
117. HCD - Define Operating System - Option 1.1 351
118. HCD - Define Switch - Option 1.2. 351
119. HCD - Define Processor and Channel Path - Option 1.3 352
120. HCD - Define Control Unit - Option 1.4 352
121. HCD - Define I/O Device - Option 1.5 353
122. HCD - Utility Functions - Options 2 - 7 354
123. Example of a Processor Summary Report 355
124. Example of a Partition Report 355
125. Example of an IOCDS Report 356
126. Example of a Channel Path Summary Report 357
127. Example of a Channel Path Detail Report 358
128. Example of a CF Channel Path Connectivity Report 359
129. Example of a Control Unit Summary Report 360
130. Example of a Control Unit Detail Report 361
131. Example of a Device Summary Report 362
132. Example of a Device Detail Report 363
133. Example of a Switch Summary Report 364
134. Example of a Switch Detail Report 364
135. Example of a Switch Configuration Summary Report 364
136. Example of a Switch Configuration Detail Report 365
137. Example of an Operating System Summary Report 366
138. Example of an MVS Device Report 366
139. Example of an MVS Device Detail Report 367
140. Example of an Eligible Device Table Report 367
141. Example of a NIP Console Report. 368
142. Example of a VM Device Report 368
143. Example of a VM Device Detail Report 369
144. Example of a VM Console Report. 369
145. Example of a CTC Connection Report 370
146. Sample of Diagnostic Messages coming with the CTC connection report 371
147. Example and Legend of an I/O Path Report 372
148. Supported Hardware Report - Processors 374
149. Supported Hardware Report - Control Units (1) 384
150. Supported Hardware Report - Control Units (2) 387
151. Supported Hardware Report - Devices 390
152. Supported Hardware Report - MVS Devices 394
153. Supported Hardware Report - VM Devices 398
154. Example of a I/O Definition Reference 401
155. Example of a Processor Compare Report 406
156. Example of a Partition Compare Report 406
157. Example of a Channel Path Compare Report 407
158. Example of a Control Unit Attachment Compare Report 408
159. Example of a Device Attachment Compare Report 409
160. Example of a Control Unit Compare Report 409
161. Example of a Device Compare Report 410
162. Example of a Switch Compare Report 410
163. Example of a Switch Detail Compare Report 411
164. Example of a Switch Configuration Detail Compare Report 411
165. Example of an Esoteric Compare Report 412
166. Example of an OS Device Compare Report 413
167. Example of an OS Console Compare Report 413
168. Example of a CSS / Operating System Device Compare 414
169. Symptoms of System Problems. 416
170. Where to Find HCD Messages 434
171. Example: Trace Output 436
172. Example: Trace Output in Case of Abend 437
173. Example: JCL Stream for Producing an IODF Dump 440
174. Registers Used and Parameters Passed 446
175. Functions Provided by the HOM Services 449
176. Example of a Hardware Configuration 454

Tables

1. How to Read the Syntax Diagrams xvi
2. Batch Jobs Used by the HCD Dialog 48
3. Size Considerations when Upgrading a Back-Level IODF 62
4. Coexistence Considerations for IODFs. . . . 64
5. Online Help Information 76
6. Actions on IODF Objects. 268
7. Search Argument 417
8. Problem Data 417
9. Search Argument 418
10. Problem Data 418
11. Search Argument 419
12. Problem Data 419
13. Search Argument 420
14. Problem Data 420
15. Search Argument 421
16. Search Argument 421
17. Problem Data 421
18. Problem Data 422
19. Problem Data 424
20. Search Argument 425
21. Problem Data 425
22. Search Argument 426
23. Problem Data 426
24. Search Argument 426
25. Problem Data 426
26. Problem Data 430
27. Summary of Request Block Names and Related Constants 447

© Copyright IBM Corp. 1994, 2002

About This Book

This book explains how to use Hardware Configuration Definition (HCD) to accomplish the following:
- Define new hardware configurations
- Modify existing hardware configurations
- View existing hardware configurations
- Activate configurations
- Query supported hardware
- Maintain IODFs
- Compare two IODFs
- Compare an IODF with an actual configuration
- Print reports of configurations
- Create graphical reports of a configuration
- Migrate existing configuration data

Note

Unless otherwise noted, the term "MVS" as used in this book refers collectively to the older MVS operating system as well as to its successors OS/390 and z/OS, in which MVS is one of the basic components. For purposes of this book, "MVS" used alone and without reference to a specific release is to be understood as the generic operating system type supported by HCD.

Who This Book Is For

This book is for the person who is responsible for defining the hardware configuration for a z/OS system. It is assumed that:
- The person has a basic knowledge of z/OS, and hardware configuration.
- Configuration planning has been completed *before* HCD is used to enter definition data. For information on configuration planning, refer to *z/OS HCD Planning*.

For the person responsible for problem determination, this book also explains what to do if a problem arises with HCD.

This information is for system programmers and system operators.

How to Use This Book

Before you start to use HCD, you should read
- Chapter 1, "Hardware Configuration Definition - What Is It" on page 1 and
- Chapter 5, "How to Use the Dialog" on page 67.

These chapters provide information about the general concepts and facilities of HCD.

When you want to use HCD to define a new configuration, you should read
- Chapter 5, "How to Use the Dialog" on page 67,
- Chapter 6, "How to Define, Modify, or View a Configuration" on page 85, and
- Chapter 7, "How to Work with Switches" on page 153.

© Copyright IBM Corp. 1994, 2002

Chapter 5 explains how to use the HCD panels, get online help information, enter data and select items such as tasks, objects and actions. Chapter 6 and Chapter 7 explain how to define operating system (OS) configurations, processors, control units, I/O devices, and switches.

How This Book Is Organized

Chapter 1, "Hardware Configuration Definition - What Is It" on page 1 explains how HCD fits into the context of hardware configurations and systems management. It also explains the environment in which HCD is used.

Chapter 2, "Change Summary and Migration" on page 13 identifies changes made in various HCD releases and discusses moving from a previous HCD release to HCD under z/OS. It also refers to other sections in this book dealing with migration and conversion tasks.

Chapter 3, "How to Setup, Customize and Start HCD" on page 37 provides information on how to install, customize, and start HCD, and how to set up an HCD installation for the first time in z/OS.

Chapter 4, "How to Work with I/O Definition Files" on page 49 explains how to work with I/O definition files (IODFs), for example, creating, changing, viewing, and deleting them. It also explains how to use configuration packages to create subset IODFs for distribution.

Chapter 5, "How to Use the Dialog" on page 67 explains the general facilities of the HCD dialog, that is panels, online help, navigation, making selections, and entering data.

Chapter 6, "How to Define, Modify, or View a Configuration" on page 85 explains the navigation through the HCD dialog and how to define, change, copy, delete, and view operating system configurations, processors, control units, and devices. It also explains how to prime processor, control unit, and device data.

Chapter 7, "How to Work with Switches" on page 153 includes basic information about switches and explains how to define, change, prime, and delete switches, how to define and prime switch connections (ports), and how to work with switch configurations. It also describes how to migrate, activate, and save switch configuration data.

Chapter 8, "How to Activate or Process Configuration Data" on page 179 explains how to make a configuration available for use by the system. It further explains how to compare a configuration defined in an IODF with the configuration sensed on the system. It includes information on activating a configuration dynamically, activating a configuration sysplex-wide, and on remote IOCDS management functions.

Chapter 9, "How to Print and Compare Configuration Data" on page 215 explains how to build textual and graphical reports about channel subsystem, switch, and operating system configuration, I/O paths, and CTC definitions and how to compare IODFs. It also explains how to print the data that is currently displayed on a list panel.

Chapter 10, "How to Query Supported Hardware and Installed UIMs" on page 233 explains how to use HCD to view system data.

Chapter 11, “How to Migrate Existing Input Data Sets” on page 239 contains information for migrating existing IOCP/MVSCP/HCPRIO definitions and explains the steps in the migration process.

Chapter 12, “How to Invoke HCD Batch Utility Functions” on page 283 describes the HCD programming interface.

Chapter 13, “Security and Other Considerations” on page 315 provides information on various HCD related topics.

Chapter 14, “LDAP Support” on page 325 explains the provision for retrieving and updating IODF data via LDAP protocol.

Appendix A, “Navigating Through the Dialog” on page 349 illustrates the flow from the HCD main panel options and the various actions that can be taken from each option.

Appendix B, “Configuration Reports” on page 355 contains examples of the various reports that can be printed by using HCD.

Appendix C, “Problem Determination for HCD” on page 415 explains what to do if problems occur with HCD.

Appendix D, “HCD Object Management Services” on page 445 explains how to use the HCD application programming interface to retrieve configuration data, such as switch data, device type, or control unit type, from the IODF.

Appendix E, “Scenarios” on page 453 contains scenarios which cover the main definition tasks required to produce the IODF illustrated in the diagram at the beginning of the appendix.

Appendix F, “IODF Data Model” on page 475 describes the IODF data model in terms of object classes and attribute definitions as used by the HCD LDAP Backend.

How to Read Syntax Diagrams

Syntax diagrams are used to illustrate the HCD commands and the HCD batch invocation with parameter strings.

The syntax structure is defined below:

- Read the syntax diagrams from left to right, from top to bottom, following the path of the line.

  The ►►── symbol indicates the beginning of a statement.

  The ──► symbol indicates that the statement syntax is continued on the next line.

  The ►── symbol indicates that a statement is continued from the previous line.

  The ──►◄ symbol indicates the end of a statement.

  Diagrams of syntactical units other than complete statements start with the ►── symbol and end with the ──► symbol.
- If punctuation marks, parentheses, arithmetic operators, or such symbols are shown, you must enter them as part of the syntax.

Table 1. How to Read the Syntax Diagrams

Syntax Diagram Description	Example
Required Items Required items appear on the horizontal line (the main path). *Keywords* appear in uppercase (for example, `STATEMENT`). They must be spelled exactly as shown. *Variables* appear in all lowercase letters (for example, *`required_item`*). They represent user-supplied names or values.	▶▶—STATEMENT—*required_item*——▶◀
Optional Items Optional items appear below the main path.	▶▶—STATEMENT—┬──────┬——▶◀ └*optional_item*┘
Required Choice If you can choose from two or more items, they appear vertically, in a stack. If you *must* choose one of the items, one item of the stack appears on the main path.	▶▶—STATEMENT—┬*required_choice1*┬——▶◀ └*required_choice2*┘
Optional Choice If choosing one of the items is optional, the entire stack appears below the main path.	▶▶—STATEMENT—┬──────────┬——▶◀ ├*optional_choice1*┤ └*optional_choice2*┘
Default Choice If one of the items is the default, it will appear above the main path and the remaining choices will be shown below. If you do not choose anything, the default is used.	▶▶—STATEMENT—┬*default_choice*┬——▶◀ ├──────────┤ ├*optional_choice*┤ └*optional_choice*┘
Repetitions An arrow returning to the left above the main line indicates an item that can be repeated.	▶▶—STATEMENT—┬──────────┬——▶◀ └▼*repeatable_item*┘

Table 1. How to Read the Syntax Diagrams (continued)

Syntax Diagram Description	Example
Syntax Fragments: When the parameter list is long or complex, the syntax diagram is fragmented. The fragment's label appears between vertical bars in the diagram, the fragment is placed later in the diagram.	►►STATEMENT──PARM──┤ Fragment String ├──►◄ **Fragment String:** ├─┬─────────┬─┤ Start ├──────────────┤ └─TRACE,─┘
Separators In a syntax diagram, commas are used as separators between the parameters. In programming languages that use commas as separators, interpret the lines before and after the commas as nulls; do not code blanks next to the commas. This example should be coded as follows: `EXEC,pgm=,parm`	►►──EXEC──,──*pgm=*──,──*parm*──────────►◄

Related Information

Please see the *z/OS Information Roadmap*, SA22-7500 for an overview of the documentation associated with z/OS.

Chapter 1. Hardware Configuration Definition - What Is It

Overview

This chapter explains:

- What HCD is and how it differs from MVSCP and IOCP
- What HCD offers you
- How HCD works
- The environment in which HCD operates

What HCD Is and How It Differs from MVSCP and IOCP

The channel subsystem (CSS) and the IBM z/OS operating system need to know what hardware resources are available in the computer system and how these resources are connected. This information is called *hardware configuration*.

Hardware Configuration Definition (HCD) provides an interactive interface that allows you to define the hardware configuration for both the channel subsystem and the operating system.

Before HCD was available, you had to use IOCP to define the hardware to the channel subsystem and the MVS Configuration Program (MVSCP) to define the hardware to the MVS operating system. The following sections explain in what way HCD differs from MVSCP and IOCP when defining, validating and reconfiguring configuration data.

Definition of Configuration Data

How MVSCP and IOCP Worked

With MVSCP and IOCP you were limited to defining one processor or operating system per input data set. This meant that you needed more than one data set when you used MVSCP or IOCP.

Figure 1 on page 2 illustrates the definition process using several sources for writing and modifying the hardware configuration using IOCP and MVSCP data sets.

© Copyright IBM Corp. 1994, 2002



Figure 1. Multiple Data Set Configuration Definition without HCD

What HCD Does

The configuration you define with HCD may consist of multiple processors, each containing multiple partitions. HCD stores the entire configuration data in a central repository, the ***input/output definition file (IODF)***. The IODF as single source for all hardware and software definitions for a multi-processor or multi-partition system eliminates the need to maintain several independent MVSCP or IOCP data sets. That means that you enter the information only once using an interactive dialog.

Figure 2 on page 3 illustrates the definition process using one source for writing and modifying configuration data in the IODF:



Figure 2. Single Data Set Configuration Definition with HCD

Validation of Configuration Data

How MVSCP and IOCP Worked

MVSCP and IOCP were separately running independent programs. Prior to IPL it was not checked whether the MVSCP output matched the configuration in the I/O configuration data set (IOCDS). Even if the definitions of both programs were not identical, it was possible for an IPL to be successful if the devices needed to start the system were included in both programs. Therefore, discrepancies would be detected only after the system had been running for some time. Such a discovery could have happened at a very inconvenient moment.

What HCD Does

The data entered with HCD is validated and checked for consistency and completeness. Because the check is performed when the data is defined, rather than when the device is accessed, inconsistencies can be corrected right away, and unplanned system outages resulting from inconsistent definitions can be avoided.

If you include ESCON or FICON Director definitions in the IODF, HCD also validates the switch port usage and connection information for all devices and channels connected to each of the directors in the configuration. In addition, HCD validates the complete path from the processor through the switch to the control unit and device.

Planned I/O paths, as defined in an IODF, can be checked against the active configuration on the system. Discrepancies are indicated and can be evaluated before and after the IODF is activated.

Reconfiguration of Configuration Data

How MVSCP and IOCP Worked

The IOCP updated the input/output configuration data set (IOCDS) that resided in the hardware support processor. This information was loaded into the hardware system area during power-on reset (POR). If the configuration was changed, it was necessary to write a new IOCDS using IOCP and to load it into the hardware system area with a POR.

MVSCP created the control information (such as UCBs, EDTs, and NIPCONs) needed by MVS to describe the hardware configuration and stored this information in the SYS1.NUCLEUS data set. The nucleus information was loaded at IPL time into storage. If a change was made to the I/O configuration, it was necessary to IPL to make the information available to MVS.

What HCD Does

Dynamic reconfiguration management is the ability to select a new I/O configuration during normal processing and without the need to perform a power on reset (POR) of the hardware or an initial program load (IPL) of the z/OS operating system.

The ability of HCD to provide equivalent hardware and software I/O definitions and to detect when they are not in sync is essential for dynamic I/O reconfiguration management. HCD compares both the old and the new configuration and informs the hardware and software about the differences. You may add, delete, and modify definitions for channel paths, control units and I/O devices without having to perform a POR or an IPL.

What HCD Offers You

This section summarizes what you can do with HCD and how you can work with HCD.

Single Point of Control: With HCD you have a single source, the IODF, for your configuration data. This means that hardware and software definitions as well as ESCON or FICON director definitions can be done from HCD and can be activated with the data stored in the IODF.

Increased System Availability: HCD checks the configuration data when it is entered and therefore reduces the chance of unplanned system outages due to inconsistent definitions.

Changing Hardware Definitions Dynamically: HCD offers dynamic I/O reconfiguration management. This function allows you to change your hardware and software definitions on the fly - you can add devices, or change devices, channel paths, and control units, without performing a POR or an IPL. You may also perform software-only changes, even if the hardware is not installed.

Sysplex Wide Activate: HCD offers you a single point of control for systems in a sysplex. You can dynamically activate the hardware and software configuration changes for systems defined in a sysplex.

Migration Support: HCD offers a migration function that allows you to migrate your current configuration data from IOCP, MVSCP, and HCPRIO data sets into HCD. Migration support also allows you to make bulk changes to the configuration using an editor on the IOCP/MVSCP/HCPRIO macro statements.

Accurate Configuration Documentation: The actual configuration definitions for one or more processors in the IODF are the basis for the reports you can produce with HCD. This means that the reports are accurate and reflect the up-to-date definition of your configuration.

HCD provides a number of textual reports and graphical reports, that can be either printed or displayed. The printed output can be used for documentation purposes providing the base for further configuration planning tasks. The display function allows you to get a quick overview of your logical hardware configuration.

Guidance through Interactive Interface: HCD provides an interactive user interface, based on ISPF, that supports both the hardware and the software configuration definition functions. The primary way of defining the configuration is through the ISPF dialog. HCD consists of a series of panels that guide you through all aspects of the configuration task. The configuration data is presented in lists.

HCD offers extensive online help and prompting facilities. Help includes information about panels, commands, data displayed, available actions, and context-sensitive help for input fields. A fast path for experienced users is also supported.

Batch Utilities: In addition to the interactive interface, HCD also offers a number of batch utilities. You can use these utilities, for instance, to migrate your existing configuration data; to maintain the IODF; or to print configuration reports. For a complete list of batch utility functions, refer to Chapter 12, "How to Invoke HCD Batch Utility Functions" on page 283.

Cross Operating System Support: HCD allows you to define both MVS type (for example OS/390 or z/OS) and VM type configurations from z/OS.

Support of S/390 Microprocessor Clusters: HCD provides functions for IOCDS and IPL attributes management, which simplify the configuration and operational support for those processors that are configured in an S/390 microprocessor cluster.

LDAP Interface Capability: HCD provides you with search and update capabilities for IODF data via an LDAP interface.

How HCD Works

HCD stores the hardware configuration data you defined in the IODF. A single IODF can contain definitions for several processors (or LPARs) and several MVS or VM operating systems. It contains all information used to create IOCDSs and the information necessary to build the UCBs and EDTs. When HCD initiates the function to build the IOCDS, the IODF is used as input. The IOCDS with the channel subsystem definitions of a processor is then used to perform POR. The same IODF is used by MVS to read the configuration information directly from the IODF during IPL. If your environment includes MVS and VM on different processors or as logical partitions on the same processor, the IODF can be used to create an HCPRIO input data set for VM system generation.

Figure 3 on page 6 shows an example of a configuration using HCD.



Figure 3. Configuration Definition with HCD

Objects Managed in the IODF

HCD lets you define the configurations as objects and their connections. The following objects and their connections are managed by HCD:

```
IODF
 ├─Operating System
 │  ├─EDT (MVS-type only)
 │  │  ├─Esoteric (MVS-type only)
 │  │  └─Generic (MVS-type only)
 │  └─Console
 ├─Switch
 │  ├─Switch Configuration
 │  └─Port
 ├─Processor
 │  ├─Channel Path (CHPID)
 │  └─Partition
 ├─Control Unit
 └─Device
```

Figure 4. Objects Managed by HCD

For all these objects the HCD dialog provides action lists where you can define the characteristics and the relation between the objects.

IODF Used at IPL

After you complete the input of your configuration data, you have to build a production IODF. The production IODF is used by the operating system to build the configuration data at IPL time. This active production IODF is used for building the IOCDS.

Figure 5 illustrates the build phase of a production IODF and of an IOCDS.



Figure 5. Building a Production IODF and an IOCDS

The production IODF cannot be updated (read-only). This ensures that the data in the production IODF used at IPL remains the same during the run time of that system.

Relationship of Data Sets Used by HCD

Figure 6 on page 8 shows the relationship between the data sets used by HCD and how you can work with or change these data sets.

By using the define and modify tasks or by migrating MVSCP, IOCP, and HCPRIO input data sets you create a work IODF. After finishing the definition, you build a production IODF from your work IODF, which you can use to IPL your system or to activate your configuration dynamically. The data sets shown at the bottom of the figure are created by the appropriate tasks like Build IOCDS, Build IOCP input data set, Build HCPRIO input data set, and Activate switch configuration.



Figure 6. Relationship of Data Sets Used by HCD

The Environment in which HCD Operates

HCD is part of z/OS. It needs a running z/OS system before it can be used to define a hardware configuration. Therefore, an installation should first load a z/OS system, using an old IODF, or a ServerPac Starter IODF to IPL the z/OS system for the first time. HCD can then be used on that system to define the full configuration.

HCD uses the unit information modules (UIMs) of z/OS. UIMs contain device dependent information, such as parameters and features of devices. The UIMs

must be installed in the z/OS system before you use HCD to define a configuration. The UIMs are also used at IPL time to build the UCBs. That is why they have to be installed in SYS1.NUCLEUS at IPL time.

UIMs are provided for the IBM devices supported by z/OS, OS/390, or MVS by the device product owners. You can write your own UIMs for non-IBM devices. To get information about UIMs, see *z/OS MVS Device Validation Support*.

HCD and I/O Operations (ESCON Manager)

The ESCON and FICON architectures are supported by a class of devices called Directors (switches) that manage the switching functions. These switches may be connected to a processor (via channel path), a control unit, or another switch. The switches connect channel paths and control units only for the duration of an I/O operation. The "internal" configuration of a switch is called switch configuration.

The I/O Operations component of System Automation for OS/390 (formerly known as ESCON Manager) maintains and manages configurations in switches.

I/O Operations functions, such as the activation of switch configurations and the retrieval of the active configuration data, can be invoked from HCD. This gives you a single point of control for all switch configuration activities, as well as the possibility to check whether a certain data path (from processor to device) is fully configured or not.

Moreover, you can use HCD to migrate switch configurations into HCD from three different sources: directly from the switches, from a saved switch file, or from ISPF tables saved by I/O Operations. You also can save switch configuration data in a switch file, as well as activate the switch configuration. Thus, the switch is activated using the switch configuration stored in the IODF.

I/O Operations permits retrieval of information from the active system. Parts of this information (serial numbers, VOLSERs, port names) can be provided by HCD via the functions "Priming", "Sensing", "Verification" and "Prompting for VOLSER"; I/O Operations must be installed for this purpose.

Prerequisites

For migrating existing switch configurations and activating switch configurations:

- The ESCON Manager Version 1 Release 2, or higher, or System Automation for OS/390 (I/O Operations), must be installed and active.
- To migrate from a saved director file and use the save switch function. ESCON Manager Version 1 Release 2 at PTF level UN90108 or System Automation for OS/390 is required.

If you want to prime or verify I/O definitions or generate an I/O Path report:

- ESCON Manager Version 1 Release 3 at PTF level UN94223 and UN94761 or System Automation for OS/390 is required.

  To obtain the data for a system in a sysplex there must also be a VTAM session between the local system and the target system, and the target system must have I/O Operations installed and running.

For more information on installation requirements, refer to the *z/OS Program Directory*.

In addition, refer to the PSP Bucket for the latest information about the prerequisites.

HCD and the Coupling Facility

HCD provides the user interface to support processors that have coupling facility capability.

The coupling facility itself is implemented as an extension to PR/SM features on selected processors (refer to *z/OS HCD Planning* for a list) and runs in a PR/SM partition. It enables direct communication between processors through a specific communication partition (coupling facility partition), connected by coupling facility channels.

You use HCD to specify whether a logical partition is running a coupling facility or an operating system. New channel path definitions in the IODF are used to connect a coupling facility-capable processor to a coupling facility partition:

- The coupling facility receiver channel (CFR channel) path that accesses the partition the coupling facility is running on.
- The coupling facility sender channel (CFS channel) path that accesses the partition the operating system is running on.
- The coupling facility peer channel path that accesses either partition bidirectionally on IBM zSeries 900 processors or their successors.

HCD automatically generates the coupling facility (CF) control unit and devices that are necessary for the IOCP. Figure 7 shows a processor configuration with coupling facility implemented.



Figure 7. Processor Configuration with Coupling Facility Implemented

HCD enables you to dynamically reconfigure the coupling facility channels that are connected to the operating system partition.

Note: With CF duplexing, a CF logical partition can use the coupling facility sender function to communicate with another CF logical partition. That means, you can define sender channel paths (CFS, CBS, ICS) besides the

receiver channel paths (CFR, CBR, ICR) in a CF partition. CF duplexing is supported starting with the 9672 Parallel Enterprise Servers G5 and G6 models and the 2064 zSeries models.

For more information on HCD and coupling facility, refer to *z/OS Parallel Sysplex Overview*.

Support of S/390 Microprocessor Clusters

Note on Terminology

The term S/390 microprocessor cluster, used in the HCD panels and throughout this book, refers to central processor complexes (CPCs) controlled through the Hardware Management Console.

HCD allows you to define and control configuration data for each CPC that is configured in an S/390 microprocessor cluster. You use HCD for those CPCs that can have their IOCDS and IPL attribute management functions controlled remotely:

- Writing IOCDSs
- Managing write-protection
- Marking the IOCDS as active POR IOCDS
- Updating IPL address and LOAD parameter values

HCD displays all CPCs that are configured in an S/390 microprocessor cluster and controlled by the Hardware Management Console. The CPCs are connected to the same network as the Hardware Management Console through a Token-Ring LAN. A CPC is identified by the system network architecture (SNA) address of its support element, which is specified when the processor complex is configured on the Hardware Management Console. HCD uses the SNA address to be able to write and manage IOCDSs from any processor in an S/390 microprocessor cluster, and to view and update IPL attributes.

Support of the Sysplex Environment

If you have interconnected systems, it is important to have a single point of control for systems in such a sysplex environment. HCD offers the support of the sysplex environment in several ways:

- You can define all processor and operating system configurations in one IODF.
- After a complete definition you can download the IOCDSs for all processors. This can be initiated from the controlling HCD.
- If you want to change configurations dynamically within the sysplex, you can initiate the activation of the hardware and software configuration changes for systems defined in a sysplex from the controlling HCD.

In addition, HCD offers a function that compares the active I/O configuration against the defined configuration in an IODF. This function can produce reports or lists of I/O paths to show the sensed data against the logical definitions of the paths in the IODF. HCD provides this function to get the data for your local system and for systems in a sysplex.

Based on a production IODF, HCD can also build CONFIGxx members for your local system or for systems in the sysplex.

For systems which are members of a sysplex, CONFIGxx members can be verified against selected systems. Responses are displayed in a message list.

Refer to Chapter 12, “How to Invoke HCD Batch Utility Functions” on page 283, if you want to run batch jobs in a sysplex environment.

Chapter 2. Change Summary and Migration

Overview

This chapter explains:

- Changes made to HCD in the current and previous releases
- An overview of the migration process
- Steps needed for migrating to HCD for z/OS Version 1 from a lower level HCD release

This book contains terminology, maintenance, and editorial changes. Technical changes or additions to the text and illustrations are indicated by a vertical line to the left of the change.

What is New in HCD for z/OS Version 1 Release 3

This section summarizes the updates that have been introduced to HCD in z/OS Version 1 Release 3 (z/OS V1R3). The enhancements are available as SPEs:

- "Coupling Facility Duplexing"
- "iQDIO and FCP Channel Support"
- "FCTC Support" on page 14
- "Support for FICON Cascade Switching" on page 14

Note:
An appendix with z/OS product accessibility information has been added.

Coupling Facility Duplexing

With coupling facility duplexing, a CF logical partition can use the CF sender to communicate with another CF logical partition. That means, you can define sender channel paths (CFS, CBS, ICS) besides the receiver channel paths (CFR, CBR, ICR) in a CF partition. CF Duplexing is supported starting with the 9672 Parallel Enterprise Servers G5 and G6 models and the 2064 zSeries models.

iQDIO and FCP Channel Support

In addition,

HCD supports two new channel types:

- **IQD:** In zSeries processors, a virtual internal queued direct I/O (iQDIO) transport layer enables memory-to-memory message delivery across logical partitions. So, IQD channels will be used for Fast Message Passing between z/OS Logical Partitions and the Linux for zSeries partition.
- **FCP:** This channel path type is introduced to allow access to SCSI devices, for example, a DVD device, via the Fibre Channel Protocol from a Linux for zSeries image.

© Copyright IBM Corp. 1994, 2002

FCTC Support

IBM eServer zSeries 900 exploits the FICON capability to provide channel-to-channel host communication between processors. FICON CTC (FCTC) provides CTC communication at a higher bandwidth and with greater connectivity than with ESCON CTC.

In order to be usable as an FCTC connection channel, an FC channel path must be defined to an FCTC control unit which is connected to FCTC devices. At least one end of an FCTC connection must be a 2064 zSeries processor, since the FCTC control unit function is only contained in an FC channel of a 2064 zSeries machine at the corresponding EC level and follow-on machines.

Support for FICON Cascade Switching

HCD supports fabrics containing cascade switching using FICON switches. Such a fabric consists of two or more FICON switches. Within a fabric, the connection from a channel path to a control unit is dynamically established using the link address of the target control unit provided.

For addressing control units in FICON cascade switching environments, HCD supports the use of two-byte link addresses. The first byte specifies the switch address and the second byte specifies the port address of the FC switch to which the control unit is attached.

Hardware Support

HCD supports zSeries 900 (Type 2066) processors.

Summary of Changes in Previous Releases

What is New in HCD for z/OS Version 1 Release 1

This section summarizes the updates that have been introduced to HCD in z/OS Version 1 Release 1 (z/OS V1R1). If you are migrating from OS/390, you should review the information in the detailed section for each item.

> **Note**
> This release of z/OS does not include a new release of HCD. For this reason, HCD is presented with its FMIDs of OS/390 Release 9.

Hardware Support

- zSeries 900 (Type 2064) processor
- Support of native FICON (FC) channels and up to 288K HSA subchannels for System/390 Parallel Enterprise Server Generations 5 and 6.

Dynamic Channel Path Management (DCM)

As part of the z/OS Intelligent Resource Director, Dynamic Channel Path Management allows the system to dynamically re-assign channel paths to connected control units based on the current work load and its service goals. HCD allows channel paths to be designated as static (fixed) or managed (re-assignable) when they are defined.

Support for Peer Coupling Channels

For the zSeries 900 processor, a new type of coupling channel, a *peer coupling channel*, has been introduced. HCD supports peer coupling channels via 3 new channel path types:

- CFP - Peer mode ISC-3, defined on ISC-3 links
- CBP - Peer mode ICB-3, defined on 1 GB STI link
- ICP - Peer mode IC-3, defined on uninstalled channel path numbers

Migration Support from ESCON to Native FICON

HCD allows intermixing both ESCON and native FICON channels on the same control unit. Thus, it is possible to switch from ESCON to native FICON channel channels on the control unit via two subsequent dynamic activates without the need to vary the devices off-line.

Support of a Generic Fibre Channel Switch

HCD supports a generic fibre channel switch (FC switch, type FCS), with available port addresses 00 to FF. This switch type does not support a switch control unit port.

What Is New in HCD for OS/390 Version 2 Release 9

The following section describes the new functions that were made available for OS/390 Release 9 HCD. You need to read this section only if you have worked with HCD for previous releases.

Hardware Support

HCD supports the following new processors:

- S/390 Parallel Enterprise Server Generation 5 and 6 (9672 R6 and X7 models)
- S/390 Coupling Facility 9674 Model C05
- S/390 Application StarterPak (Type 3000 models)
- Support of Multiprise processor, 2003-202
- Support of S/390 Multiprise 3000 (7060 models)
- Support of 4-port parallel channels

Move Ports

This is a new action that you can perform on selected switches. It allows you to move ports or a range of ports on the selected switch to different positions, or to move them from other switches to the selected (target) switch. This is described in “Moving Ports” on page 160.

Aggregate Channel Paths

This is a new action that allows you to aggregate channel paths together. It is described in “Aggregating Channel Paths” on page 120.

Generate Switch Matrix

This is a new action that allows you to create the port matrix of a switch configuration dependent on the logical paths defined in the IODF. This is described in “Generating a Switch Matrix” on page 171.

LDAP Support

LDAP (Lightweight Directory Access Protocol) is an Internet protocol designed for fast read access to data. It can be used to manage system data for OS/390 on an enterprise (or at least sysplex) level.

HCD provides IODF search and update capabilities via LDAP using the OS/390 Security Server LDAP Server and the HCD LDAP Backend. For more information on LDAP support see Chapter 14, “LDAP Support” on page 325.

Other Enhancements

In addition to the above, there are a number of additional enhancements listed below:

- You can specify a different maximum number of lines per report page other than the default value of 55 using a new profile option (see "Options for Text Reports" on page 42).
- You can set a profile option to ensure that all output texts are written in uppercase. This allows you to use printer code pages that do not support lowercase English letters (see also "Options for Text Reports" on page 42).
- You can extend the attachable device list of a control unit supported with a UIM via a new profile option (see "Extension of the Attachable Device List of a Control Unit" on page 45).
- Using a profile option you can bypass the attempt of HCD to update the IOCDS status in the IODF when an IOCDS is written for a processor that has an SNA address defined. HCD retrieves that information from the Support Element directly (see "Bypass IODF Information Update" on page 44).
- It is possible to write an IOCDS regardless of the processor type. This is particularly useful if you are preparing for a processor upgrade (see "Build an IOCDS" on page 184).
- The previous limit of 8 switch port connections when adding or changing a control unit has been eliminated. The related control unit panels let you specify up to 32 ports (see "Defining the Control Unit Characteristics" on page 122).

What Is New in HCD for OS/390 Version 2 Release 5

The following section describes the new functions that were made available for OS/390 Release 5 HCD. You need to read this section only if you have worked with HCD for previous releases.

Hardware Support

HCD supports the following new processors:

- S/390 Parallel Enterprise Server Generation 4 (9672 R5 models)
- S/390 Coupling Facility 9674 Model C05
- S/390 Application StarterPak (Type 3000 models)

Verification of Defined I/O Configuration

The verify function, which compares the definitions in an IODF with the sensed I/O data, is now available as an action on the HCD activate dialog.

From the HCD activate dialog the verify function is performed as an action for a specified single system or partition. You can choose to compare the sensed system data against the active IODF or against the target IODF of an activate request.

If the verify function is invoked via the dialog, the output is presented on a new panel, the I/O Path List. For each channel path defined in the IODF the sensed data and the IODF data are listed. In addition, the list contains the following information:

- Indication of discrepancies,
- Information on whether a sensed path is online or offline, and
- Information on whether a sensed device is online or offline.

A filter facility allows the list to be reduced to the entries of interest. These can then be saved into a data set and subsequently printed.

Building and Processing CONFIGxx Members

From a production IODF individual CONFIGxx members can be built. Existing CONFIGxx members can be updated or replaced.

For systems which are members of a sysplex, CONFIGxx members can be verified against selected systems. Responses are displayed in a message list.

Support of Large IODFs

Within large enterprises IODFs describing the entire I/O configuration may become too big for an effective management. To remedy this problem, while preserving the benefits of keeping a single repository for all I/O definitions, HCD can now build subset IODFs based on configuration packages from a centrally administered master IODF. Configuration packages define subsets of the master IODF, which allows selective distribution of I/O data to target systems, while keeping the processor token in sync. Configuration packages also allow configuration changes made at a remote system to be merged back into the master IODF.

It is now possible to opt for IODFs to be stored in a data space, relieving constraints to the IODF space imposed by user address space limitations.

Panel Enhancements

For all attributes that can be primed prompts have been provided on the object definition panels, e. g. for the serial number and port names on the control unit or switch definition panels.

The channel path list has been improved in design by showing the partitions according to their image numbers. Up to 15 partitions can now be shown on the panel.

The device list has been extended by an extra two columns where the number of operating systems and processors accessing the device are stated. If called from the processor list, it is stated how many partitions of the selected processor are accessing the device.

Occupied Indication for Ports and Coupling Facility Channel Paths

Ports and coupling facility CHPIDs already connected in another IODF can now be shown as occupied. The HCD dialog does not permit occupied ports to be connected, thus avoiding inadvertent conflicting connections. The user can add or remove the occupied indicator using the dialog.

Removed Restrictions

HCD profile options no longer need to be located in a cataloged data set. For batch jobs, profile options can now also be defined inline.

When processors are repeated, HCD now also copies related coupling facility connections, as well as switches not present in the target IODF. Device preference values for user defined generics are now copied when repeating operating systems.

HCD can now be used to create OS and switch configuration control statements. HCD extended migration allows these to be migrated back into the IODF.

JES3 initialization stream checker data can now be created using a batch utility. A batch utility function is provided which allows creating a work IODF from a production IODF.

What Is New in HCD for OS/390 Release 3

The following sections describe the functions that were made available for OS/390 Release 3 HCD.

Hardware Support

Support for New Channel: HCD 5.1, HCD 5.2, and OS/390 Release 3 HCD support the definition of the Internal System Device (ISD) channel.

New Processor Support: HCD continues to support new processors. These are:
- S/390 Multiprise 2000 models,
- S/390 Parallel Enterprise Server Generation 3 (9672 R4 models),
- S/390 Coupling Facility 9674 Model C04.

Ease of Upgrading a Processor Type or Model::
- The Update Channel Path Identifiers panel is issued with every ***Change Processor*** action. It permits rearrangement of the channel path IDs.
- New channel path IDs are already preset to support the upgrade from a 9672 R2 to a 9672 R4 model.

I/O Definition Reference: A new report is provided that generates IOGEN configuration documentation from the installed UIMs.

This report is called the I/O Definition Reference, and contains a description of the parameters to define the devices to the Channel Subsystem, as well as a description of the parameters and features to define the devices to the OS/390 operating system.

Verification of Defined I/O Configuration

This function compares an active I/O configuration against a defined I/O configuration in an IODF. The function is provided as an I/O Path report. It shows the sensed I/O paths of an active system and compares this data with the definitions in the IODF.

Priming the IODF with Actual Configuration Data

This function allows you to prime the IODF with device self-description data (for example, the serial number), and configuration related data that are known by the ESCON Manager (for example, the port names, and port connections).

Report Enhancements

Device Detail Report: Contains device groups rather than the individual device numbers, and includes a matrix of the partitions that have access via the channel path access or candidate list rather than listing the partition names.

Channel Path Detail Report: Shows the switch connections that can be determined without requiring a switch configuration to be defined.

Channel Path Summary Report: Includes a matrix of the partitions that have access via the channel path access list or candidate list.

Selection of Individual Compare Reports: You can select individual compare reports for specific object classes (for example, control units) rather than always getting all Channel Subsystem compare reports.

Limit IODF Compare Report: The IODF compare function allows limiting the processor related compare reports to a single partition. As a result, reports of

- Channel path compare only contain channel paths which have the limiting partition in their access list or candidate list.
- Control unit compare only include the control units related to channel paths which have the limiting partition in their access or candidate list.
- Device compare only include the devices related to channel paths which have the limiting partition in their access or candidate list.

Year 2000 Support

The support for dates beyond year 2000 is provided. The data areas of HCD are extended to hold the 4 character year format.

The reports and generated data sets show the year as 4 characters. HCD panels that contain a date in the format yy-mm-dd are left unchanged.

Ease-of-Use Changes

Reduced Number of Messages During Build Production IODF: The number of information and warning messages that are generated when building a production IODF is reduced.

These messages are now collected for each object class, and the number of messages is no longer dependent on the number of defined objects. The generated message lists are shorter and provide a better overview of the messages than before.

Replace Production IODF in Dialog: When building a production IODF in the dialog, you can replace an existing IODF.

Function Key Consolidation: Function key F3=Exit is offered on all HCD panels. It exits the current unit of work, except for add, change and similar actions, where, when exiting with F3, data is saved before stepping back.

Removed Restrictions

Specification of VOLIDs for Generated Output Files: You can direct the HCD generated output data sets to a specific volume, for the
- JES3 INISH data set,
- IOCP input data set, and
- HCPRIO input data set.

Support of Multiple Switch CUs: This function allows you to attach multiple switch control units to switch port FE.

By this, it is possible to define alternate paths to the ESCON director from any of the LPARs.

IODF Checker Function

The IODF checker function is provided with the TRACE ID=IODF command and its REPAIR option. It
- Supports the analysis of the inconsistencies within an IODF, and
- Corrects certain inconsistencies.

What Is New in HCD for MVS/ESA SP 5.2.2

The following sections describe the functions that were made available for MVS/ESA SP 5.2.2.

Sysplex Wide Activate

HCD offers you a single point of control for systems in a sysplex. You can dynamically activate the hardware and software configuration changes for systems defined in a sysplex.

CTC Report

To allow an easier definition of CTC connections, HCD offers a facility to display and print a CTC connection report for those CTC connections that use a dynamic switch. In case of incorrect definitions you get a message list with diagnostic information.

Migration Enhancements

The extended migration function allows you to specify additional parameters in your MVSCP and IOCP input data set to define, for example, coupling facility connections or switch related data.

IOCP Changes

Restrictions are removed when building IOCP input data sets:

- The generated IOCP data set now contains control unit and device types of 8 characters and a device model of up to 4 characters. Such an IOCP input data set can be processed by IOCP (with APAR OW13343) and re-migrated to HCD without the need to correct the control unit and device types that exceed the 5 character UNIT and 2 character MODEL value limitation.
- The generated IOCP data set now contains an all-character readable token which allows the user to preserve the dynamic capability when performing a stand-alone IOCP run on a S/390 microprocessor cluster CPC and having the IOCP input data set loaded to the support element using a diskette.

Save Command

A new command has been added that allows you to save the current data displayed on an HCD list panel into a data set for printing.

Checking of Channel Packaging Rules

HCD includes checking of channel packaging rules for the new processor types when building a production IODF. Note that there must be access to IZPIOCP while building the production IODF.

Processor Upgrade

HCD now contains channel path conversion tables which facilitates processor upgrades from 9672-Rx1 to 9672-Rx2 or 9672-Rx3 models.

Old Action Codes Valid Again

For HCD 5.2, several action codes (marked as white type on a black background) were changed from **V** (view), or **C** (change) to **S** (select/work with) due to consistency reasons. For easier usage, the old action codes are also accepted on the following panels:

- Define Device to Operating System Configuration
- View Device / OS Configuration Definitions
- Select Processor / Control Unit
- Device / Processor Definition
- Change Device Group / Operating System Configuration

What Is New in HCD 5.2

You need to read this section only if you have worked with HCD in the past. It summarizes the changes that were made for HCD 5.2.

Improved Navigation

Context Menu: The ***Add***, ***Modify***, ***View***, and ***Build*** actions have been removed from the action bar. Instead, you will now see a context menu when you select an object on an action list panel and press the Enter key. The context menu shows all options available for the selected object. If there is only one action possible, the action is performed without showing the context menu.

View Objects and Work with Objects: HCD 5.2 makes a clear distinction between viewing objects and working with objects to change them. Whenever you used ***View*** in the past to navigate to a list panel and perform some changes, you now have to select ***Work with ...*** from the context menu.

Selecting ***View ...***, on the other hand, displays a list panel on which you can view information but cannot change it.

Consistent Usage of Action Code V: For consistency reasons, the action code **v** is now used exclusively to view objects. Therefore, the action code to request an Esoteric List panel from an EDT List panel has been changed from **v** to **s**.

Consistent Usage of Action Code S: The action to select an object has been made consistent. On the Define Device to Operating System Configuration panel, and on the Select Processor / Control Unit panel, you now have to select an operating system or a processor by using action code **s** instead of **c**.

GOTO Enhancements: ***Goto*** is now made available as an action bar choice and displays all possible targets in the pull-down menu. This means that you do not have to worry about the GOTO command syntax but simply select the target object you want to work with.

The GOTO command has been further enhanced and you can now go directly to the switch configuration and port matrix panels.

Extended Filtering: Additional filter criteria give you more flexibility in limiting the number of objects displayed. For instance, you can now get an overview of objects that are not attached to another object (such as CUs not attached to a processor or devices not attached to a CU) or you can get an overview of CHPIDs and ports that are free for establishing connections.

Confirm Leaving HCD: To prevent you from unintentionally leaving HCD when pressing the F3=Exit key or F12=Cancel key when on the primary panel, you are now asked to confirm that you want to leave HCD.

Streamlined Dialog

EDT/Esoteric Dialog: Some EDT/Esoteric panels have been combined to reduce the number of panels you have to go through when assigning devices to esoterics.

Channel Path/Partition Assignment Matrix: The Channel Path List panel has been extended and includes now the partition's access and candidate list assignments. You can view the assignments by scrolling the panel to the right. You can easily update the information by typing over the new assignments.

Removed Restrictions

Virtual Storage Constraint Relief: When defining devices, the UCBs for the devices are appended to the SQA located below the 16 MB line. You could run out

of storage below the 16 MB line when defining a large number of devices. To overcome this problem, you are now allowed to specify that the UCBs are located above the 16 MB line. The UCBs will then be located in the Extended SQA, which is above the 16 MB line in 31-bit storage. Use the LOCANY parameter in HCD to define where you want the UCBs for your devices to be located.

Exporting Between Different HCD Versions: You can now export an IODF from a higher HCD version to a lower HCD version. The version of the IODF remains the same. For example, if you export an IODF from HCD 5.2 to HCD 4.3, the IODF remains a 5.2 IODF. When using this IODF you have to consider the restrictions as described in Table 4 on page 64.

New and Improved Reports

Coupling Facility Report: You can now create or view a graphical report showing the connections that exist between a coupling facility and the other processors defined in the IODF.

Improved Readability of Reports: The readability of a number of reports has been increased by grouping devices with the same characteristics. The grouping is done by showing the starting device number and the range (Example: 110,8) rather than listing each device on a separate line. The device grouping is done for the following reports:
- Device summary report
- MVS Device report
- VM Device report
- EDT Device report

Reports Showing Supported Hardware: You can use the HCD batch utility "Print a Configuration or Supported Hardware Report" to print the actual status of the hardware supported in your installation. This is particularly useful for installation planning. The report shows the following supported hardware:
- Processors
- Control units
- Devices (including device characteristics and attachments)
- MVS devices (including device capabilities and parameters/features)
- VM devices (including device capabilities and parameters/features)

What Is New in HCD 5.1

You need to read this section only if you have worked with an HCD version lower than 5.1 so far. It summarizes the functional and ease-of-use improvements included in HCD 5.1.

Hardware Support

- Support for New Channels

  HCD 5.1 supports the definition of OpenSystem Adapter (OSA) and ESCON converter byte (CBY) channels.
- S/390 Microprocessor Cluster Support

  An S/390 microprocessor cluster is a group of new CPCs whose support elements are attached to the same local area network as the hardware management console, on which the CPCs are configured and operated. HCD running on one of the CPCs provides a single point of control to perform group actions.
- Coupling Facility (CF) Support

This support enables high-performance data sharing among processors. CF-capable processors allow the use of a PR/SM partition as a communication partition and high-speed channels to connect the partition with other processors.

Startup Profile

HCD 5.1 provides a profile data set for setting processing options. For example:

- You can map the control unit types in IOCP input data sets to valid control unit types supported by HCD. This means that you do not have to change the data sets before migrating them.
- You can select trace options with the HCD dialog or with an HCD batch job.
- You can specify defaults for colors and for the layout of the graphical configuration report.

Graphical Configuration Reports

HCD 5.1 allows you to create or view various types of graphical configuration reports of logical configurations in an IODF. To print the reports created, use either DCF, BookMaster, or GDDM. To display a report, you need GDDM.

- Print

  The printed output can be used for documentation purposes and serve as a base for further configuration planning. You can limit the report by means of filtering.
- Display

  The display function allows you to get a quick overview of your logical hardware configuration. You can use the LOCATE command to find a specific object, and you can jump from an object to the related object list. You can use the SAVE command to store a graphical configuration displayed on your screen in a partitioned data set for printing via GDDM later on.

IODF Enhancements

- Copy/Merge IODF Data

  The existing ***Repeat*** pull-down choice of the ***Add*** action has been extended to enable you to copy a selected object together with its dependent objects and I/O attachments not only within the same IODF but also to another IODF. This is useful if you want to consolidate configuration data from several IODFs into a single IODF or to repeat configuration data that is used several times in an IODF.

  The target objects may or may not exist in the target IODF. If the objects do not exist in the target IODF, new ones are created by copying the values and definitions of the objects in the source IODF. If some of the objects already exist, a merge action takes place, that is, the definitions of the objects in the source IODF are combined with those of the objects in the target IODF.
- View Active IODF

  View information about the currently active IODF and, if available, the configuration token which is currently active in the HSA (hardware system area). You can also see the current activation scope (software changes, hardware changes, or recovery required) and examine the reasons for any limitations to the scope.
- IODF Default Size

  The default size of the IODF has been increased to 1024 blocks of 4KB.

Switch Enhancements

- Save/Migrate ESCON Director File Configuration

So far you could migrate switch configurations from an active ESCON Director or an ISPF table only with HCD. If you have ESCON Manager V.1.2 installed with its capability to read and update ESCON Director files, HCD 5.1 allows you to:

- Save a switch configuration, which you do not want to activate immediately, in an ESCON Director file.
- Migrate the saved switch configuration from the ESCON Director file for further processing and manipulating by HCD.

- Connect New Switch

  When defining a new switch, you can now connect this switch to a switch control unit and switch device that you added to the IODF when migrating your IOCP or MVSCP input data set.

- Port Range

  Up to now HCD set the minimum port range to 'Installed' when you added a switch. You can now set a port range larger than the minimum range to 'Installed' when defining a switch.

Improved Navigation

- Primary Task Selection Panel

  This panel has been restructured (see Figure 21 on page 70). All options for defining a configuration have been moved to a separate panel showing the hierarchy of the objects you work with.

  The HCD release level and a command line have been added to the primary task selection switch.

- GOTO Command

  The GOTO command has been enhanced and allows you to go directly to the list panels of dependent objects or to a specific object within a list. For example, you can now go directly to a specific partition or channel path list of a processor from any other action list panel.

Ease-of-Use Changes

- Reduced Keystrokes
  - Type `L` for the LOCATE command.
  - Type `LEFT` or `RIGHT` for the HLEFT or HRIGHT commands.
  - Press the Enter key just once on a scrollable confirm delete panel to delete all selected objects.

- Removed Selection Markers

  List element selections, which were done using the single or group selection markers are no longer in effect after an operation has been completed successfully. They are removed automatically. You no longer have to remove them by pressing the F5=Reset key twice.

- Auto-Assign

  Select `Auto-assign` on the Add Control Unit panel to have some control unit and processor attachment parameters automatically proposed by HCD when defining a control unit which is to be connected to one or more switches.

- Group Changes

  In the past, when you defined or changed the settings of a control unit that was attached to a group of processors, you had to change the attributes for each processor in the group one at a time. HCD 5.1 allows you to select the range of processors to which the attachment parameters will be applied, when you add a new or modify an existing control unit definition.

- Saving of Messages

In addition to displaying messages, you can now save all messages in the message log file.

- IODF Name in Activity Log

  The IODF name is now shown in the activity log, which allows you to associate the changes with the IODF, for which you made them.

- CSS Reports

  Instead of getting all CSS reports you can now select the types of CSS reports you want to produce and print. The devices in the CHPID and control unit detail reports are grouped to improve readability.

Removed Restrictions

- Channel Path Change

  HCD 5.1 allows you to change the channel path type from parallel to serial (or vice versa), and the operation mode from nonshared to shared (or vice versa). However, changing the type or operation mode of one channel path will result in changing all channel paths attached to the logical control units affected.

- SYS1.NUCLEUS

  HCD 5.1 no longer requires that SYS1.NUCLEUS is contained in the TSO STEPLIB concatenation or in the ISPLLIB load library concatenation chain. Instead, HCD allocates the library automatically at initialization time. You may use the HCD profile to specify the name and the volume serial number of the library that contains the UIMs. If you do not specify a name in the profile, SYS1.NUCLEUS is assumed as default name for the UIMs. For IPL, however, the UIMs and UDTs must be in SYS1.NUCLEUS.

  Note that the UIMs and UDTs have to be in the same data set, if you specify a library name in the HCD profile statement, or if you accept SYS1.NUCLEUS as the default name.

- Partition Name Change

  You may give a partition a new name by changing the name displayed on the Change Partition Definition panel.

- Control Unit Number Change

  You may give a control unit a new number by changing the number displayed on the Change Control Unit Definition panel.

- Esoteric Order in EDT

  HCD 5.1 introduces a token when specifying esoterics. This allows you to control the order of the esoterics in the EDT. You no longer have to maintain a chronological order and may delete and add esoterics without getting access problems for data sets that are cataloged using esoterics.

- Four-Digit Device Numbers

  HCD 5.1 allows you to specify four digits (numbers higher than ’0FFF’) for device numbers and connect these devices to an MVS operating system. HCD validation will check whether the specified devices can have four-digit numbers. This validation is based on the UIMs installed on your system. The device numbers for MVS/ESA SP 4.3 and prior versions are still restricted to three digits.

Support No Longer Provided

MVS/ESA SP 4.3 is the last release that supports MVSCP. This means that you have to use an IODF to IPL your MVS/ESA SP Version 5. The migration facilities have been enhanced to ease the transition to HCD. A short summary is given

below. For details see "Required Changes when Migrating from MVS/XA or MVS/ESA" on page 30 and Chapter 11, "How to Migrate Existing Input Data Sets" on page 239.

Enhanced Migration

- Update Parts of a Configuration

  You can update existing processor and operating system configuration definitions in an IODF with IOCP, MVSCP, or HCPRIO control statements. In particular, you can:
  - Add or replace control units, devices, channel paths, and partitions.
  - Replace list of consoles.
  - Update EDTs, generics, and esoterics.

  This is described in detail in "Updating Parts of a Configuration by Migrating Input Data Sets" on page 267.
- Retain Entries on Migration Panel

  The last values entered for the input data sets on the migration panel are retained. You do not have to re-enter the values for a subsequent migration.
- Merge Device Connections

  Devices defined in the IODF and in the IOCP input data sets need not be connected to exactly the same set of control units. If one set is the subset of the other, the definitions are merged. Previously, the definitions were rejected.
- Device Number Conflicts

  In the past, device numbers could be associated with the wrong processor or partition in the IODF when migrating the MVSCP input data sets if they did not specify control unit numbers. To resolve this conflict, you are now able to associate an MVSCP input data set with a processor or a logical partition.
- Duplicate Device Numbers

  An improved mapping algorithm for devices results in fewer duplicate device numbers and in fewer migration failures due to control unit configuration mismatches.
- Duplicate Labels

  Labels in the input data sets no longer need to be unique anymore. Duplicate labels are now ignored.
- Map Control Unit Types

  You can use the startup profile to map the control units to valid HCD control units and reduce the need to change the IOCP input data sets before migrating them.
- Assigning Esoteric Tokens when Migrating MVSCP Input Data Sets

  You can use the HCD profile to specify if you want HCD to assign esoteric tokens in ascending order when migrating MVSCP input data sets.

  To assign individual tokens to esoterics during migration, HCD introduced a new keyword for the UNITNAME parameter. This keyword is only valid for migration purposes and cannot be used for processing the data sets with MVSCP.

Back-Level Release Activate

An HCD 5.1 production IODF can be used by an MVS/ESA SP 4.3 system to activate changes as long as HCD 5.1 specific definitions, such as coupling facility channel paths, are not involved in the activation. The activation is done using the operator command ACTIVATE. This function requires PTF UW90022 for MVS/ESA SP 4.3.

Migration Overview

Your plan for migrating to the new level of HCD should include information from a variety of sources. These sources of information describe topics such as coexistence, service, hardware and software requirements, installation and migration procedures, and interface changes.

The following documentation, which is supplied with your product order, provides information about installing your z/OS system. In addition to specific information about HCD, this documentation contains information about all of the z/OS elements.

- *z/OS and z/OS.e Planning for Installation*

  This book describes the installation requirements for z/OS at a system and element level. It includes hardware, software, and service requirements for both the driving and target systems. It also describes any coexistence considerations and actions.
- *z/OS Program Directory*

  This document, which is provided with your z/OS product order, leads you through the specific installation steps for HCD and the other z/OS elements.
- *ServerPac Installing Your Order*

  This is the order-customized, installation book for using the ServerPac Installation method. Be sure to review "Appendix A. Product Information", which describes data sets supplied, jobs or procedures that have been completed for you, and product status. IBM may have run jobs or made updates to PARMLIB or other system control data sets. These updates could affect your migration.

"Migration Roadmap" on page 28

- identifies the migration paths that are supported with the current level of HCD
- describes the additional publications that can assist you with your migration to the current level

Developing a Migration Strategy

The recommended steps for migrating to HCD under z/OS are:

1. Become familiar with the supporting migration and installation documentation for the release.

   You should determine what updates are needed for products that are supplied by IBM, system libraries, and non-IBM products. Review *z/OS and z/OS.e Planning for Installation* and the *z/OS Introduction and Release Guide* for information about HCD and other z/OS elements.
2. Develop a migration plan for your installation.

   When planning to migrate to a new release of HCD, you must consider high-level support requirements, such as machine and programming restrictions, migration paths, and program compatibility.
3. Obtain and install any required program temporary fixes (PTFs) or updated versions of the operating system.

   Call the IBM Software Support Center to obtain the preventive service planning (PSP) upgrade for HCD, which provides the most current information about PTFs for HCD. Check RETAIN again just before testing HCD. For information about how to request the PSP upgrade, refer to the *z/OS Program Directory*. Although the *z/OS Program Directory* contains a list of the required PTFs, the most current information is available from the IBM Software Support Center.

4. Install the product using the *z/OS Program Directory* or the *ServerPac Installing Your Order* documentation.
5. Contact programmers who are responsible for updating applications at your installation.

   Verify that your installation's applications will continue to run, and, if necessary, make changes to ensure compatibility with the new release.
6. Use the new release before initializing major new function.
7. If necessary, customize the new function for your installation.
8. Exercise the new functions.

Year 2000 Support for HCD

HCD is an element of z/OS. Beginning with Version 1 Release 2, OS/390 was certified as a Year 2000–ready operating system by the Information Technology Association of America (ITAA). Follow-on releases, including z/OS, are also Year 2000 ready.

Previous products, such as OS/390 Version 1 Release 1, and all releases of MVS/ESA SP V5, are Year 2000 ready with maintenance applied. Previous products that are not Year 2000 ready have not been marketed since December 31, 1997.

For HCD, the following changes were made to ensure Year 2000 readiness:

- All control blocks used externally maintain time stamps in the format `YYYY-MM-DD`.
- All reports show the extended date format.
- The activity and message log files show the extended date format.

For further information on Year 2000 Support, see *Year2000 and 2-Digit Dates: Guide*, GC28-1251. For additional information on Year 2000, see:

`http://www.ibm.com/IBM/year2000/`

For Additional Migration Information

For information about migrating to z/OS, see *z/OS and z/OS.e Planning for Installation*, GA22-7504.

For information about migrating to MVS/ESA SP V5, see:

- *MVS/ESA SP V5 Planning: Installation and Migration JES2*, GC28–1428.
- *MVS/ESA SP V5 Planning: Installation and Migration JES3*, GC28–1429.
- *Conversion Notebook for System Product Version 5* , GC28-1436
- *Conversion Notebook for System Product Version 4* , GC28-1608
- *Conversion Notebook for System Product Version 3* , GC28-1568
- *Conversion Notebook for System Product Version 2* , GC28-1567

Migration Roadmap

This section describes the migration paths that are supported by the current release of HCD. It also provides information about how you can obtain the HCD migration information from previous releases.

Migration Tasks

The following sections contain additional migration procedures or information:

- "Enhanced Migration" on page 26
- "Back-Level Release Activate" on page 26
- "Upgrade an IODF" on page 61
- "IODF Release Level Compatibility" on page 63
- "Migrating Existing Switch Configurations" on page 173
- "IOCP Input Data Sets Using Extended Migration" on page 192
- Chapter 11, "How to Migrate Existing Input Data Sets" on page 239
- "Upgrade IODF" on page 286
- "Migrate I/O Configuration Statements" on page 287

Information on IODF coexistence can be found in "IODF Release Level Compatibility" on page 63.

Required Changes When Migrating from HCD 5.n or an OS/390 Release

The IODFs of HCD 5.n, HCD for OS/390, and HCD for z/OS are compatible. That is, no changes have to be made when you upgrade from HCD 5.n or an OS/390 release to HCD for z/OS.

Required Changes When Migrating from HCD Version 4

This section explains what you have to change when moving from HCD Version 4 to HCD for z/OS Release 1. These changes do not apply when you upgrade from HCD 5.n or an OS/390 release to HCD for z/OS Release 1.

- IPL

  You now have to IPL z/OS using an IODF.
- UIMs and UDTs in the Same Data Set

  Make sure that the UIMs and the UDTs are contained in the same data set, if you specify a library name in the HCD profile statement, or if you accept SYS1.NUCLEUS as the default name. Note that, for IPL, the UIMs and UDTs must be in SYS1.NUCLEUS.
- NEWAPPL Parameter Used when Invoking HCD

  The NEWAPPL parameter has changed from `HCD` to `CBD`. Change the NEWAPPL parameter used for the invocation of HCD to CBD.
- IBM-Supplied UIMs

  IBM-supplied UIMs that run with HCD start with CB**DUS**xxx. Make sure that these UIMs and their associated UDTs (CBDESxxx) are installed for your devices.
- Convert Installation-Written MVSCP UIMs to HCD UIMs

  If you have installation-written UIMs that were used for MVSCP (UIM names start with CB**PUC**xxx) you need to convert those UIMs to run with HCD because the requirements for an HCD UIM differ from those for an MVSCP UIM. For details refer to *z/OS MVS Device Validation Support*.

  If you do not wish to convert your MVSCP UIMs right away, you can treat the devices and control units as unsupported devices; that is, you can:

  – Specify an equivalent IBM device, or, if there is none, specify the device as DUMMY device.

– Define the control units with type NOCHECK. However, you should use this only as a temporary solution, because it bypasses IBM-specific attachment validation rules in the corresponding standard UIMs.

Required Changes when Migrating from MVS/XA or MVS/ESA

Overview

This section describes how to migrate your MVS/XA SP 2.n, MVS/ESA SP 3.n, 4.n, or 5.n operating systems to z/OS regarding HCD.

- How to upgrade a MVS/ESA SP 4.n IODF to a z/OS IODF? You do not have to upgrade your IODF when you move from HCD Version 5 to z/OS HCD.
- How to migrate your MVS/XA SP 2.n or MVS/ESA SP 3.n operating system to z/OS.
- How to migrate your MVS/ESA SP 4.n operating system to z/OS when you have not used HCD before.

Before the introduction of MVS/ESA SP Version 5, you used either an IODF or an MVSCP input data set to perform an IPL. To IPL MVS/ESA SP Version 5 or later systems, you use an IODF.

If you used a 4.1 or 4.2 IODF, you have to upgrade your IODF before selecting any other option from the primary task selection panel. If you used a 4.3 IODF, you only have to upgrade the IODF when you want to change it.

If you used MVSCP and IOCP input data sets so far, HCD provides a migration function via dialog or batch utility that lets you easily migrate your input data sets to an IODF. You can then use this IODF to IPL your z/OS operating system. Depending on your current operating system environment, there are different ways to migrate your operating system to z/OS.

Use the diagram shown in Figure 8 on page 31 to find the migration method that applies to your needs. The boxes in the diagram contain references to the appropriate sections in this chapter.



Figure 8. Finding Your Migration Method

If you want to share an IODF among multiple z/OS or OS/390 systems that are at different release levels, you have to consider some restrictions concerning IPL, IODF usage, and dynamic reconfiguration. For more information on compatibility considerations for IODF data sets, refer to “IODF Release Level Compatibility” on page 63.

Upgrading an IODF to z/OS: If you used HCD in a previous MVS/ESA SP 4.n release, you can IPL the z/OS operating system with your old IODF but have to

upgrade your back-level IODF if you want to update it with z/OS HCD. You do not have to upgrade your MVS/ESA Version 5 IODF if you want to use it with z/OS.

The point in time when HCD asks you to upgrade the 4.n IODF depends on the release level of your IODF:

MVS/ESA SP 4.1 or 4.2 IODF
: HCD asks you to upgrade the IODF as soon as you select a task from the primary task selection panel.

MVS/ESA SP 4.3 IODF
: HCD asks you to upgrade the IODF only when you try to change the IODF. You can, for example, import and export your IODF without having to upgrade it.

The following procedure is a step-by-step instruction on how to upgrade an MVS/ESA SP 4.n IODF to a z/OS IODF when starting the dialog:

1. Invoke HCD and blank out the IODF name on the primary task selection panel.
2. Select ***Maintain I/O definition files*** on the primary task selection panel and then ***Upgrade I/O definition file to new format***. Specify the name of the old MVS/ESA SP 4.n IODF to be upgraded and select the option `To new IODF`.
3. On the following panel, specify the new IODF name. HCD suggests an appropriate space allocation value.
4. After the IODF has been successfully upgraded, you can enter additional configuration changes in the z/OS work IODF.
5. Create a production IODF from the work IODF and a corresponding LOADxx member.
6. Do one of the following:
   - Activate the z/OS production IODF dynamically.

     Note: Before activating the new configuration, you have to configure offline the affected channel paths or vary offline the affected devices. See *z/OS HCD Planning* for information about avoiding disruptions to I/O operations during dynamic changes.
   - Use the z/OS production IODF to create an IOCDS, then perform a power-on reset with the new IOCDS and IPL using the new IODF.

Migrating to HCD for the First Time:

Migrating from MVS/370: Users who change from MVS/370 to z/OS should proceed as follows:

1. Install z/OS (including HCD) using the z/OS driver system shipped with your ServerPac order.
2. Under the control of z/OS, define your configuration.

Migrating from MVS/ESA SP 4.n: Since the introduction of MVS/ESA SP Version 5, you can no longer use your MVSCP input data sets to perform an IPL. That means, to IPL your z/OS, OS/390, or MVS/ESA SP Version 5 operating system, you have to use an IODF.

In this scenario you are running MVS/ESA SP 4.1, 4.2, or 4.3 and want to upgrade to z/OS. To migrate your MVSCP or IOCP input data sets, you have the following possibilities:

- Invoke HCD running on your MVS/ESA SP 4.n system and migrate your input data sets into an IODF using the HCD migration function as described in the *IBM HCD User's Guide* for MVS/ESA SP 4.n. Then IPL your z/OS operating system with this MVS/ESA SP 4.n IODF and upgrade it to a z/OS IODF as described in "Upgrading an IODF to z/OS" on page 31.
- To avoid later upgrading to the new IODF format of z/OS, you can use z/OS HCD for your migration. Install z/OS HCD and allocate the new z/OS HCD libraries. For information on allocation, refer to "Setup Considerations for Migration". Then you can migrate your input data sets into a z/OS IODF using the HCD dialog or the HCD batch utility. Chapter 11, "How to Migrate Existing Input Data Sets" on page 239 describes how to migrate your input data sets.

Migrating from MVS/XA SP 2.n or MVS/ESA SP 3.n: When you are using an operating system lower than MVS/ESA SP 4.1 and want to migrate your operating system to z/OS, you are confronted with the following problem:

You cannot run HCD on an operating system lower than 4.1 and therefore cannot create an IODF via the HCD dialog. But without having an IODF you cannot IPL your new z/OS operating system.

Therefore, HCD offers you the following possibilities:

- If you have ordered ServerPac for z/OS you probably have also ordered a driver to install z/OS. The ServerPac installation support provides an IODF that can be used to IPL the system for the first time. Having IPLed z/OS once, you can run z/OS HCD to define your configuration, or use the HCD migration function to migrate the old MVSCP input data sets. For information on how to use the HCD migration function with the dialog, refer to the step-by-step instructions under "Migrating Input Data Sets Using the HCD Dialog" on page 248.
- Use the HCD batch utility to migrate your MVSCP or IOCP input data set. Note that you have to install z/OS and allocate the new z/OS HCD libraries using STEPLIB or JOBLIB statements because they are not cataloged. For the actual migration step (see "Step 2: Migrate Input Data Set" on page 251), do not allocate SYS1.LINKLIB but copy the CBDxxxxx modules from SYS1.LINKLIB of z/OS into a private library and allocate this library using the STEPLIB statement. Refer to "Setup Considerations for Migration" for further HCD installation considerations.

  For a step-by-step instruction on how to migrate your MVS/XA SP 2.n or MVS/ESA SP 3.n input data sets through the HCD batch utility, refer to "Migrating Input Data Sets Using the Batch Utility" on page 251.

Setup Considerations for Migration: If you want to migrate your input data sets to a z/OS IODF, z/OS HCD must be available on your pre-MVS/ESA SP Version 5 operating system. You can either install z/OS HCD on your MVS operating system in separate libraries, or you can share DASD volume where the z/OS system libraries reside. Note that when sharing the DASD volume, the HCD libraries are not cataloged in your running system. You have to access the libraries by specifying the volume and unit parameter.

If you migrate your input data sets through the HCD batch utility:

- Ensure that the products containing the necessary UIMs are installed.
- Access the SYS1.LINKLIB of the new z/OS operating system through the STEPLIB or JOBLIB statement.

If you migrate from MVS/XA SP 2.n or MVS/ESA SP 3.n, do not allocate SYS1.LINKLIB but copy the CBDxxxxx modules from SYS1.LINKLIB of z/OS into a private library and allocate this library using the STEPLIB statement.

- Access the parsing macro in SYS1.MACLIB of z/OS through the HCDLIB statement.
- For IOCP input data set migration, ensure you know the support level ID of your processor. Use the batch utility to print the Supported Hardware report for assistance when checking the support level ID. An example is shown in "Supported Hardware Report" on page 373.
- Ensure that SYS1.NUCLEUS of z/OS is used. Specify the following statement in your batch jobs:

  ```
  //HCDPROF DD DSN=BPAN.HCD.PROF,DISP=SHR
  ```

  In the HCD profile (in our example BPAN.HCD.PROF) you have to specify the following statements to access the z/OS UIMs:

  Example:

  ```
  UIM_LIBNAME=SYS1.NUCLEUS
  UIM_VOLSER=510D18
  ```

If you migrate your input data sets through the HCD dialog:

- Ensure that the products containing the necessary UIMs are installed.
- Specify the library containing the UIMs in the z/OS HCD profile.

  Example:

  ```
  UIM_LIBNAME=SYS1.NUCLEUS
  UIM_VOLSER=510D18
  ```

- Access SYS1.LINKLIB and SYS1.SCBDHENU of the z/OS operating system using a TSO logon procedure that contains the following DD statements to allocate the load libraries.

  Example:

  ```
  //ISPLLIB  DD DSN=SYS1.LINKLIB,DISP=SHR,UNIT=3380,VOL=SER=510D18
  //         DD DSN=SYS1.SCBDHENU,DISP=SHR,UNIT=3380,VOL=SER=510D18
  ```

  With this TSO logon procedure you can use your TSO session for HCD only. Before using another program than HCD, start a TSO session without the HCD DD statements.

  If your target LINKLIB contains an IDCAMS level incompatible with the driver system, HCD may terminate with the error message IDC3009I. Is this the case, create a new library and copy the modules starting with CBD from the target system into this library. Then, change the ISPLLIB to point to this new library.
- For the migration of the input data sets, specify the volume serial number of the DASD, which contains the MACLIB, on the panel Migrate IOCP / MVSCP / HCPRIO Data to access the parsing macro.
- Copy the HCD CLISTs CBDCHCD, CBDCHCD1, and CBDCACTL from SYS1.SCBDCLST of the new z/OS system with a new name (for example, HCDCHCD and HCDCHCD1) to SYS1.SCBDCLST of your old system. Note that you also have to replace the old name of CBDCHCD1 in the new HCD CLIST (in our example, HCDCHCD) with the new name (HCDCHCD1). In the new CLIST (HCDCHCD), change the allocation of the Panel, Table, and Message library:

```
/* Allocate Panel library                  */
ALLOCATE F(PLIB) DA('SYS1.SCBDPENU') SHR  +
 UNIT(3380) VOLUME(510D18)
ISPEXEC LIBDEF ISPPLIB LIBRARY ID(PLIB)
/* Allocate Table library                 */
ALLOCATE F(TLIB) DA('SYS1.SCBDTENU') SHR  +
 UNIT(3380) VOLUME(510D18)
ISPEXEC LIBDEF ISPTLIB LIBRARY ID(TLIB)
/* Allocate Message library               */
ALLOCATE F(MLIB) DA('SYS1.SCBDMENU') SHR  +
 UNIT(3380) VOLUME(510D18)
ISPEXEC LIBDEF ISPMLIB LIBRARY ID(MLIB)
```

Use this changed CLIST to start the HCD dialog.

Note: If you want to use the HCD utility functions
- Print report
- Build IOCP
- Build IOCDS
- Compare IODFs
- Compare CSS / operating system views

specify GO.STEPLIB in the offered EXEC procedures (see "Customizing HCD EXEC Procedures" on page 48) to access the new data sets:

```
//GO.STEPLIB DD DSN=SYS1.LINKLIB,DISP=SHR,VOL=SER=510D18,UNIT=3380
//GO.HCDPROF DD DSN=BPAN.HCD.PROF,DISP=SHR
```

In the HCD profile (in our example BPAN.HCD.PROF) you have to specify the following statements to access the z/OS UIMs.

Example:

```
UIM_LIBNAME=SYS1.NUCLEUS
UIM_VOLSER=510D18
```

If you are running under an MVS prior to MVS/ESA SP 4.3 and want to use the utility functions, copy the respective EXEC procedure (see "Customizing HCD EXEC Procedures" on page 48) in SYS1.PROCLIB of z/OS to SYS1.PROCLIB of MVS/ESA 4.n.

Accessing Old Modules: When running HCD you might get warning messages that you access HCD modules from previous release. These modules does not exist in your ISPLLIB but are found in the LINKLIB of the driver system. They existed in previous HCD releases but are not used anymore.

Chapter 3. How to Setup, Customize and Start HCD

Overview

This chapter explains:
- Setting up HCD
- Tailoring the CLIST CBDCHCD
- Starting and ending HCD
- Defining an HCD profile
- Customizing HCD EXEC procedures

Setting Up HCD

HCD is a base element of z/OS and therefore installed with the z/OS product. For more information, refer to *z/OS and z/OS.e Planning for Installation*.

The installation of HCD is carried out using SMP/E. The install logic and the JCLIN are provided by HCD. For the installation, refer to the *z/OS Program Directory*.

Note

This release of z/OS does not include a new release of HCD. For this reason, HCD is presented with its FMIDs of OS/390 Release 9.

Setting up HCD requires the following steps:

1. Install z/OS with the HCD FMIDs.
2. Install other products that are required for HCD (refer to *z/OS and z/OS.e Planning for Installation*).
3. Before you start HCD, you have to establish at least the ISPF Version 3 Release 5 (with toleration PTF UW21495) environment for HCD, and set up the load libraries that contain the HCD help modules. You can achieve this in one of the following ways:
   - Include SYS1.SCBDHENU (or SYS1.SCBDHJPN for Kanji) in the linklist concatenation (LNKLSTxx member), or
   - Allocate data set SYS1.SCBDHENU (or SYS1.SCBDHJPN for Kanji) to ISPLLIB.

   If you choose to access the libraries through the ISPLLIB concatenation, ISPLLIB must be allocated prior to invoking ISPF with the TSO ALLOC command or through a CLIST. ISPLLIB is used as a tasklib by ISPF as it is searched first.

   When using the View graphical configuration report:
   - Include the GDDM load library in the linklist concatenation (LNKLSTxx member).
   - Allocate the GDDM sample data set:

© Copyright IBM Corp. 1994, 2002

For GDDM 2.1 and 2.2:

```
ALLOCate F(ADMPC) DSN('pplib.GDDM.GDDMSAM') SHR REUSE
```

For GDDM 2.3 or later:

```
ALLOCate F(ADMPC) DSN('pplib.GDDM.SGDDMSAM') SHR REUSE
```

If you are using a programmable workstation and you communicate with the host using a 3270 emulator session, the GDDM-OS/2 link files must be installed on your workstation. Note that the high-level qualifier for the GDDM data set might vary from installation to installation.

4. Allocate the data set SYS1.SCBDCLST to the SYSPROC ddname concatenation.

   Note: SYS1.SCBDCLST has a fixed record format (RECFM=FB). If your other SYSPROC data sets have a variable record format (RECFM=V or VB), copy SYS1.SCBDCLST to a data set with variable record format. You have to remove sequence numbers (in the CLIST) after copying the members to a data set with variable record format.

5. For processing of large IODFs, the size of your TSO region may not be sufficient. When you specify the region size on the TSO logon panel, calculate as follows:

   ```
   2 x IODF size + 4 MB
   ```

   Example:

   ```
   Assumed IODF size:  8000 blocks, 4 KB per block = 32 MB

   Suggested region size:  68 MB
   ```

   Note: You can avoid the problem of storage space restrictions by including the option `IODF_DATA_SPACE=YES` in your HCD profile. This will load the IODF into a separate data space. For details refer to "Loading an IODF into a Data Space" on page 45.

6. For setup requirements when using HCD via the HCD LDAP Backend, see Chapter 14, "LDAP Support" on page 325.

How to Invoke HCD in Dialog Mode

To invoke HCD in dialog mode, ISPF must be active. After you have invoked ISPF, you can use the CLIST CBDCHCD to activate the HCD function. You may add HCD to an ISPF selection menu, for example, the ISPF/PDF Master Application Menu (ISP@MSTR), and invoke HCD using the CLIST CBDCHCD. Figure 9 on page 39 shows a sample panel that illustrates how to include HCD on the main ISPF/PDF panel. Alternatively, the CLIST can be invoked from the ISPF option 6, or from the command line.

Note that HCD must be invoked with the "NEWAPPL" parameter.

To ensure that the CBDCHCD CLIST can successfully allocate the following libraries, make sure that these libraries are cataloged:

- SYS1.SCBDPENU --> HCD Panel Library
- SYS1.SCBDMENU --> HCD Message Library
- SYS1.SCBDTENU --> HCD Table Library

Note: The HCD Panel, Message, and Table libraries are allocated by the CBDCHCD CLIST using the LIBDEF function of ISPF. If other ISPF Dialogs are using the LIBDEF function of ISPF, and you do not want HCD to

overlay their allocations, you can update your ISPF startup by adding the HCD data sets to the ISPF ISPPLIB, ISPMLIB, and ISPTLIB concatenations.

```
%------------------------  ISPF MASTER APPLICATION MENU  -----------------------
%OPTION  ===>_ZCMD                                          +USERID   - &ZUSER +
%                                                           +TIME     - &ZTIME
%                                                           +TERMINAL - &ZTERM
%                                                           +PF KEYS  - &ZKEYS
%   1 +ISPF/PDF    - ISPF/Program Development Facility
%   2 +SMP/E       - System Modification Program/Extended
%   3 +HCD         - Hardware Configuration Definition
%   4 +SDSF        - SYSTEM Display and Search Facility
%   5 +RACF        - Resource Access Control Facility
%   X +EXIT        - Terminate ISPF using list/log defaults
%
+Enter%END+command to terminate ISPF.
%
)INIT
  .HELP    = ISP00005     /* Help for this master menu            */
  &ZPRIM   = YES          /* This is a primary option menu        */
)PROC
  &ZSEL = TRANS( TRUNC (&ZCMD,'.')
               1,'PANEL(ISR@PRIM)  NEWAPPL(ISR)'
               2,'PGM(GIMSTART) PARM(&ZCMD) NOCHECK NEWAPPL(GIM)'
               3,'CMD(CBDCHCD) PASSLIB'
               4,'PGM(DGTFMD01) PARM(&ZCMD) NEWAPPL(DGT) NOCHECK '
               5,'PANEL(ICHP00) NEWAPPL(RACF)'
              ' ',' '
                X,'EXIT'
                *,'?' )
IF (&ZCMD = '%VSDSF')
    &ZSEL = 'PGM(ISFISP) NEWAPPL(ISF)'
)END
```

Figure 9. Sample ISPF Master Application Menu Panel

Tailoring the CLIST CBDCHCD

A sample CLIST CBDCHCD (CBDCHCDJ for Kanji) is provided in SYS1.SCBDCLST to assist you in invoking HCD from the ISPF dialog. It allocates the HCD message log file (HCDMLOG), the trace data set (HCDTRACE), and the HCD term file (HCDTERM) with a default high-level qualifier of the user ID (&SYSUID.). The CLIST also allocates the HCD data sets SYS1.SCBDPENU, SYS1.SCBDMENU, and SYS1.SCBDTENU (or SYS1.SCBDPJPN, SYS1.SCBDMJPN, and SYS1.SCBDTJPN for Kanji).

In CBDCHCD and CBDCHCDJ, the ISPEXEC LIBDEF statement for ISPPLIB, ISPTLIB and ISPMLIB is done with the STACK option. This leaves existing LIBDEFs untouched, so that after exit, the existing HCD libraries ISPPLIB, ISPTLIB and ISPMLIB are freed again.

If the prefixes for message, trace, and term data sets do not conform to the installation conventions, you may tailor the CLIST to match your installation defaults. If you want HCD to use your TSO prefix as the high level qualifier, you can call CBDCHCD with the parameter NOPREF(YES). This causes HCD to use the qualifiers &PREFIX..&SYSUID.

CBDCHCD invokes another CLIST, CBDCHCD1. You may tailor this CLIST as well.

In any case, use the application ID for HCD: NEWAPPL(CBD).

The CLIST also tailors the ISPF environment by:

- Setting PFSHOW on. This forces all 24 function keys to be shown (if ISPF is defined to show 24 function keys).
- Setting lower PFKEYS as primary function keys.

Note: HCD can be invoked with the activated TRACE option, when you have specified parameter TRACE(YES) in the default CLIST. The size of the trace data set can be changed by modifying the CLIST. In addition, you can delete the HCD provided trace data set and allocate one according to your specific needs.

Starting and Ending HCD

You start HCD like any other ISPF application in your TSO/E system. The procedure for starting an application is different for each installation but you can probably select HCD from a menu of applications that are available in your system. This causes a TSO/E CLIST to be executed. The sample CLIST that is supplied with HCD is CBDCHCD in library SYS1.SCBDCLST.

After you start HCD, the first panel that you see contains a menu of the HCD primary tasks:

```
                              OS/390 Release 9 HCD
Command ===> ____________________________________________________________

                             Hardware Configuration

Select one of the following.

__  1.  Define, modify, or view configuration data
    2.  Activate or process configuration data
    3.  Print or compare configuration data
    4.  Create or view graphical configuration report
    5.  Migrate configuration data
    6.  Maintain I/O definition files
    7.  Query supported hardware and installed UIMs
    8.  Getting started with this dialog
    9.  What's new in this release

For options 1 to 5, specify the name of the IODF to be used.

I/O definition file . . . 'DOCU.IODF01.WORK'                     +


F1=Help     F2=Split    F3=Exit     F4=Prompt   F9=Swap    F12=Cancel
F22=Command
```

To end an HCD session, either return to the primary task selection panel and press the F12=Cancel key or the F3=Exit key twice or use the fast path command GOTO X.

Chapter 12, “How to Invoke HCD Batch Utility Functions” on page 283 explains how you can invoke HCD from another program using the HCD programming interface.

Defining an HCD Profile

Before you start HCD, you can define an HCD profile to tailor HCD supplied defaults and processing options to your specific installation needs. Using a profile is optional and will remain in effect for the entire HCD session. At initialization time, HCD reads the profile and processes each statement in turn.

The profile statements are contained in a data set allocated to the DD name HCDPROF. The following statement, for example, allocates the data set to HCDPROF:

```
//HCDPROF DD DSN=&SYSUID..HCD.PROFILE,DISP=SHR
```

The data set must have the following characteristics:
- Be either a sequential or a member of a partitioned data set
- Have fixed-length, fixed-blocked record format
- Have 80 character records.

It is possible to define profile options using inline statements. The following example shows an inline profile definition:

```
//HCDPROF DD *
MIGRATE_EXTENDED = YES
VM_UIM = NO
/*
```

Note: When starting an HCD batch job from the dialog, the HCD profile dataset is not passed automatically to the job but, if required, has to be specified in the JCL.

The following rules apply to a profile statement:

```
                    ┌─,──────┐
►►──keyword──┬─┬──────┴─value──┴──────────────────────────────────────────►◄
             └─=─┘
```

The specifications for a profile statement are as follows:

keyword
Is the name of the HCD keyword. Each keyword starts on a new line.

= Can be omitted, if the keyword is followed by a blank.

value
Specifies one or more values to be assigned to the keyword.

Use /* and */ as delimiters for comments in a profile statement. An asterisk (*) in column one can be used for comments as well; a single comment can span several lines. Do not use sequence numbers in your HCD profile.

Keywords

The following keywords are supported for a profile statement:

Volume Serial Number to Allocate Output Data Sets

To place the IOCP, HCPRIO, and JES3 INISH stream checker data sets to a specific volume within HCD, you can specify this target volume via two profile options:

HCDDECK_VOL
Specifies the volume serial number to allocate to a new IOCP, HCPRIO or other data set containing I/O configuration statements.

HCDJES3_VOL
Specifies the volume serial number to allocate a new JES3 initialization stream checker input data set.

In a non-SMS managed environment, the generated corresponding output data set is placed on the indicated volume if you specify one of these options in the HCD profile. The profile option is not used, if the specified output data set already exists on a different volume. In this case, the new output data set replaces the existing data set on this volume.

The two options have no effect in an SMS managed environment since SMS overrules the VOLUME parameter.

If the keywords are omitted, the placements of the IOCP, HCPRIO, JES3 INISH, and other I/O configuration data sets are controlled via SMS or ESOTERIC system defaults (ALLOCxx of SYS1.PARMLIB or the UADS, respectively).

Volume Serial Number for Activity Log

ACTLOG_VOL
Specifies the volume serial number to allocate a new activity log; can be up to 6 characters long. Using an asterisk (*) indicates that the activity log file will be placed on that volume the associated IODF resides on.

Name and Volume Serial Number for UIM Library

UIM_LIBNAME
Specifies the name of the data set containing the UIMs, the associated UDTs, and any help members for the UIMs. If the keyword is omitted, SYS1.NUCLEUS is assumed (Note: only UIMs residing in SYS1.NUCLEUS are read during IPL!). If you specify an asterisk (*) as data set name, HCD assumes that the UIM data set is part of the ISPF load library concatenation chain, contained in the JOBLIB/STEPLIB concatenation chain, or specified in the active LNKLSTxx member.

You can only define one data set with the UIM_LIBNAME statement. If you want to specify several data sets, specify an asterisk (*) as data set name and specify the data sets in the JOBLIB/STEPLIB concatenation chain.

UIM_VOLSER
Specifies the volume serial number of the UIM library. Required only if the data set is not cataloged and specified via keyword UIM_LIBNAME.

Load VM UIMs

VM_UIM
YES/NO. Specifies that VM UIMs will or will not be loaded. The default is YES. Installations without VM should specify NO to gain some performance improvement during HCD initialization.

Options for Text Reports

LINES_PER_REPORT_PAGE
Specifies the maximum number of lines per page for reports. The default value is 55.

UPPERCASE_ONLY
YES/NO. Specifies whether all HCD reports will be written in uppercase or not. This is useful when using printers that do not have the English codepage. The default is NO.

Layout of Graphical Reports

GCR_SCALE
Specifies the scaling factor for graphical reports when using BookMaster. The default is *GCR_SCALE=.6*.

GCR_COMPACT
YES/NO. Specifies whether to see more objects in a graphical report. The default is NO. Depending on the report type, a different maximum number of objects is shown on one page:

Report Type	COMPACT=NO	COMPACT=YES
CU	12 channels, 8 control units	16 channels, 10 control units
LCU	8 channels, 8 control units	8 channels, 8 control units
CHPID	8 channels, 64 control units	16 channels, 64 control units
Switch	1 switch	1 switch
CF	1 coupling facility	1 coupling facility

GCR_FORMAT
Specifies the formatting type:
BOOKIE
For BookMaster. This is the default.
DCF To create a data set for DCF containing script commands.
GML To create a data set for DCF containing GML tags.
GDF To create one or more members in GDF format for printing with GDDM (not for batch).

GCR_FONT
Specifies the font to be used for printing; applicable only if GCR_FORMAT=DCF or GCR_FORMAT=GML was specified. Use the appropriate font supported by your installation. For information on how to create a graphical report, see "Create or View Graphical Configuration Reports" on page 218.

Color Settings for Graphical Display Function

(The following colors are valid specifications: green, red, blue, black, purple, pink, yellow, brown, and white.)

COLOR_NORM
Specifies the color used when drawing the picture. Make sure that the color is visible on defaulted or specified background. The default is GREEN.

COLOR_TEXT
Specifies the color used for any text in the picture. The default is GREEN.

COLOR_HIGH
Specifies the color to be used when identifying a focused object. The default is RED.

COLOR_BACKGROUND
Specifies the background color. If nothing is specified, the graphical display function uses the standard background of the terminal.

Display of Processor/Control Unit Panel

PANEL_CUP0

Specify SCREEN to display the *Select Processor/Control Unit* (CBDPCUP0) panel using the entire screen; otherwise a pop-up window is displayed.

TRACE Command

TRACE

Activates and deactivates the HCD trace facility. All parameters of the TRACE command are valid except the ID=IODF parameter. You cannot use anything else (for example, no comments and no line numbers) in the same line except the TRACE statement. For information on syntax and description on TRACE command, see "TRACE Command" on page 437.

Support of TSO Option NOPREFIX

TSO_NOPREFIX

YES/NO. Specifies whether the TSO profile option NOPREFIX is recognized by HCD. The default is NO. If you specify TSO_NOPREFIX=YES, and the TSO option NOPREFIX is active, all data set names specified in the HCD dialog are taken as is, i.e. HCD does not add a high-level qualifier. Data set names that are generated by HCD act independent of the TSO option NOPREFIX, and the user ID is added as the high-level qualifier.

Esoteric Token when Migrating MVSCP Input Data Sets

ESOTERIC_TOKEN

YES/NO. YES specifies that HCD will assign esoteric tokens in ascending order when migrating an MVSCP input data set. NO specifies that no tokens will be assigned. The default is NO.

Control Unit Type when Migrating IOCP Input Data Sets

MAP_CUTYPE

Specifies how a control unit type in an IOCP input data set is mapped to a control unit type in the IODF. Specify one or more of the following parameters:

```
MAP_CUTYPE = xxxxx,yyyy-yy
```

xxxxx
: is the control unit type specified in an IOCP input data set

yyyy-yy
: is the control unit type and model to be used in the IODF.

For example parameters, see the sample profile in Figure 10 on page 47.

Extended Migration

MIGRATE_EXTENDED

YES/NO. Specify YES to exploit the extended migration possibilities as described in "Changing I/O Configurations by Editing Data Sets" on page 252.

If you specify NO (which is the default), the additional keywords are not generated during IOCP build and when re-migrating IOCP input data sets, the migration function ignores the commented *$HCDC$ and *HCD tags.

Bypass IODF Information Update

BYPASS_UPD_IODF_FOR_SNA

YES/NO. This provides a possibility of bypassing the attempt to update the IODF information for SNA processors after having successfully built the IOCDS. This avoids the attempt to update the IODF with IOCDS status

information, which usually will fail as a result of the IODF being in an exclusive access mode with the dialog.

If you specify NO (which is the default), then for SNA and non-SNA processors, an attempt is made to update IOCDS information in the IODF after the IOCDS has been built successfully.

If you specify YES then, for SNA processors, no attempt is made to update the IODF after the IOCDS has been built successfully.

Display Information during TEST ACTIVATE

SHOW_IO_CHANGES

YES/NO. When performing both a hardware and software change with the TEST option, specify YES to get information about the channel paths, control units, and devices that are deleted, modified, or added.

Loading an IODF into a Data Space

IODF_DATA_SPACE

YES/NO. If you specify YES, the IODF is loaded into a data space, thereby removing restrictions on the size of the IODF imposed by address space limitations.

If you specify NO (which is the default), the IODF is loaded into the user address space.

IODF Name Verification for Batch Jobs

BATCH_IODF_NAME_CHECK

YES/NO. If you specify YES, HCD checks if the IODF specified for a batch job conforms to the naming convention as described in "IODF Naming Convention" on page 49. Processing of IODFs with invalid names is limited to deletion.

If you specify NO (which is the default), HCD does not check the IODF names specified for batch jobs.

Default Settings for OS Parameters

OS_PARM_DEFAULT

This keyword overrides a parameter default value set by the UIM. The value is used as a default on the HCD Define Device Parameters/Features panel. The command structure is:

```
OS_PARM_DEFAULT = xxxxxx,yyyyyy

where:

xxxxxx is the parameter keyword
yyyyyy is the new parameter default value
```

The LOCANY default value, for example, is NO. It can be changed to YES by specifying the HCD profile option:

```
OS_PARM_DEFAULT = LOCANY,YES
```

Note: Default values cannot be set differently for different device types. Features, for example SHARED, cannot be defaulted using this keyword.

Extension of the Attachable Device List of a Control Unit

CU_ATTACHABLE_DEVICE

This keyword allows the attachable device list of a control unit to be extended to include additional device types. Both the control unit type and the device type must be defined via UIMs. The command structure is:

```
CU_ATTACHABLE_DEVICE = xxxxxx,yyyyyy

where:

xxxxxx is the control unit type
yyyyyy is the additional device type
```

Note that more than one device type can be added to the same control unit type.

```
Example:
  CU_ATTACHABLE_DEVICE = RS6K,3174
  CU_ATTACHABLE_DEVICE = RS6K,3274
```

Example

The following figure shows a profile with sample data:

```
/*********************************************************************/
/*                                                                   */
/*             HCD PROFILE FOR OS/390 RELEASE 9 HCD                  */
/*                                                                   */
/*********************************************************************/
/*                                                                   */
/* Options relieving storage constraints                             */
/*                                                                   */
IODF_DATA_SPACE = YES         /*IODF IN OWN DATASPACE               */
/*                                                                   */
/* Options for tailoring the HCD dialog                              */
/*                                                                   */
PANEL_CUP0 = SCREEN           /*DISPLAY ENTIRE SCREEN FOR CBDPCUP0  */
TSO_NOPREFIX = NO             /*ENABLE TSO  NOPREFIX                */
OS_PARM_DEFAULT = LOCANY,YES  /*   DEFAULT PARAMETERS               */
OS_PARM_DEFAULT = DYNAMIC,NO  /*   DEFAULT PARAMETERS               */
/*                                                                   */
/* Options for migration                                             */
/*                                                                   */
MIGRATE_EXTENDED = YES        /*ENABLE MIGRATION ENHANCEMENTS       */
MAP_CUTYPE = 3880,3880-23     /*REPLACE CU TYPE DURING MIGRATION    */
MAP_CUTYPE = 3705,3745        /*REPLACE CU TYPE DURING MIGRATION    */
ESOTERIC_TOKEN = YES          /*ESOTERIC TOKEN IN ASCENDING ORDER   */
/*                                                                   */
/* Options for  print/display                                        */
/*                                                                   */
LINES_PER_REPORT_PAGE = 60    /*MAX. NUMBER OF LINES PER PAGE       */
GCR_FORMAT = DCF              /*GRAPHIC DATA FORMAT BOOKMASTER      */
GCR_FONT = X0GT20             /*GOTHIC TEXT 20-PITCH (FOR 3820 PRT) */
GCR_COMPACT = YES             /*GRAPHIC COMPACT VIEW                */
COLOR_NORM=BLACK              /*DEFAULT = GREEN                     */
COLOR_TEXT=BLUE               /*DEFAULT = YELLOW                    */
/*                                                                   */
/* Options for activation                                            */
/*                                                                   */
BYPASS_UPD_IODF_FOR_SNA = YES /*NO IODF UPDATE WITH IOCDS DATA       */
SHOW_IO_CHANGES = YES         /*ENABLE MESSAGE SHOW FOR DYN. ACTIVATE */
/*                                                                   */
/* Options controlling placement of data sets                        */
/*                                                                   */
ACTLOG_VOL = *                /*ACTIVITY LOG ON SAME VOLUME AS IODF */
HCDDECK_VOL = D83WL2          /*VOLUME FOR CONFIGURATION DATA SET   */
HCDJES3_VOL = D83WL4          /*VOLUME FOR JES3 OUTPUT DATA SET     */
/*                                                                   */
/* Options for enhanced validation                                   */
/*                                                                   */
BATCH_IODF_NAME_CHECK = YES   /* CHECKS IODF NAMING CONVENTIONS      */
CU_ATTACHABLE_DEVICE = RS6K,3274   /* EXTENT ATTACHABLE DEVICE LIST  */
```

Figure 10. Example of an HCD Profile

Customizing HCD EXEC Procedures

Some of the HCD tasks, invoked from the dialog, generate batch jobs. These batch jobs use EXEC procedures, as shown in Table 2.

Your installation can use normal ISPF or TSO/E facilities to change the job control statements in these EXEC procedures. They are stored in the library SYS1.PROCLIB. You can customize these procedures according to your own needs.

You can also modify the EXEC procedures by using JCL overwrite statements in the HCD dialog. Thus, you can, for example, add a statement that refers to the HCD profile. See "Job Statement Information Used in Panels" on page 84 on how to specify JCL statements in the HCD dialog.

Table 2. Batch Jobs Used by the HCD Dialog

HCD Task	EXEC Procedure	Job Step Name	More Details
Build an IOCDS	CBDJIOCP	GO	see "Build an IOCDS or an IOCP Input Data Set" on page 292
Build an IOCP input data set	CBDJIOCP	GO	see "Build an IOCDS or an IOCP Input Data Set" on page 292
Print a configuration report	CBDJRPTS	GO	see "Print Configuration Reports" on page 299
Compare IODFs and CSS/OS views	CBDJCMPR	GO	see "Compare IODFs or CSS/OS Reports" on page 303
Import an IODF	CBDJIMPT	IMP	see "Import an IODF" on page 307
Transmit part of an IODF	CBDJXMIT	GO	see "Transmit a Configuration Package" on page 60

Chapter 4. How to Work with I/O Definition Files

Overview

This chapter includes:

- IODF naming convention
- Working with I/O definition files (specify, change, create, view, backup, delete, copy, export, import, and upgrade IODFs)
- Working with large IODFs
- Activity Logging
- Using an IODF among different release levels

When you start an HCD session, you need to specify the IODF that HCD is to use. How to do this, how to change to another IODF, and how to use HCD tasks to maintain your IODFs is described below.

Before you can activate your configuration, you must build a production IODF. This task is described in "Build a Production IODF" on page 180.

Note: The IODF data sets must be cataloged so that you can use them with HCD.

IODF Naming Convention

Work IODF

The data set name for a work IODF has the format of:

```
'hhhhhhhh.IODFcc.yyyyyyyy.yyyyyyyy'
```

hhhhhhhh
is the high-level qualifier; up to 8 characters long.

cc is any two hexadecimal characters (that is, 0-9 and A-F).

yyyyyyyy
are optional qualifiers; up to 8 characters long. The following qualifiers must not be used as last qualifier: CLUSTER, ACTLOG, or MSGLOG.

You can use any number of optional qualifiers but do not make the total name longer than 35 characters because, in some circumstances, HCD appends an additional qualifier.

If you omit the high-level qualifier and the enclosing single quotes, HCD automatically adds your user prefix (your user ID is the default).

Production IODF

The data set name for a production IODF has the same format as a work IODF. You may specify additional qualifiers to differentiate among IODFs (for example for backup reasons). However, the optional qualifiers must be omitted if the IODF is to be used for IPL or dynamic activation. Thus, the format would be:

```
'hhhhhhhh.IODFcc'
```

© Copyright IBM Corp. 1994, 2002

hhhhhhhh
is the high-level qualifier; up to 8 characters long.

cc is any two hexadecimal characters (that is, 0-9 and A-F).

The IODF is a VSAM LINEAR data set with different names for the cluster and the data component. The name of the data set with a cluster component has the format:

```
'hhhhhhhh.IODFcc.yyyyyyyy.yyyyyyyy.CLUSTER'
```

The name of the data set with a data component has the format:

```
'hhhhhhhh.IODFcc.yyyyyyyy.yyyyyyyy'
```

Specify an IODF

You specify the name of the IODF that you want to use on the primary task selection panel. The first time you use the dialog, HCD puts the default name `SYS1.IODF00.WORK` in the IODF name field (see Figure 21 on page 70). You can type over this name to specify the name you want to use.

If you specify an IODF name that does not exist, HCD assumes that you intend to create a new IODF and displays a panel to let you specify the required attributes. HCD then creates and automatically catalogs the IODF.

```
                  Create Work I/O Definition File

 The specified I/O definition file does not exist. To create a new
 file, specify the following values.

 IODF name  . . . . . . 'BPAN.IODF01.WORK'

 Volume serial number . ______  +

 Space allocation . . . 1024   (Number of 4K blocks)

 Activity logging . . . Yes    (Yes or No)

 Description  . . . . . ________________________________________
                        ________________________________________
                        ________________________________________


  F1=Help    F2=Split   F3=Exit    F4=Prompt  F9=Swap   F12=Cancel
```

Figure 11. Example of Create Work I/O Definition File

- Volume serial number (of the data volume the IODF will reside on)

  This entry is ignored if your system is managed by SMS, otherwise it is mandatory.
- Space allocation

  The online HELP gives advice on how much space to allocate. If you run out of space while working with an IODF, you can use the ***Copy IODF*** task to copy the IODF to a larger data set.
- Activity logging

You have to decide now whether you want HCD to maintain an activity log for the IODF; you cannot specify it later. If you want to use an activity log, your system must have Program Development Facility (PDF) installed.

- Description

  Here you may enter any useful additional information concerning the IODF, e. g. the system it applies to, special uses it is intended for, or the author.

The IODF remains in effect throughout all tasks of your current session and later HCD sessions, until you change it.

Sharing IODFs

If you want to share an IODF across two or more systems, you must:

1. Catalog the IODF in the user catalog that is shared by those systems.
2. Define an ALIAS to that catalog in the master catalog of each system that uses the IODF (for details, refer to "Catalog Considerations" on page 319).

Note: Control of sharing the IODF resource between multiple systems is achieved via Global Resource Serialization (GRS).

Important

If you update an IODF simultaneously from different systems that are *not* in the same GRS complex, you may destroy data in the IODF.

Deciding on the Number of IODFs

The decision whether to create one IODF for each processor, or to combine the I/O definitions for two or more processors in a single IODF, depends on your environment. This section explains when it is advantageous or even necessary to keep the I/O definitions of two or more processors in the same IODF.

Shared control units and devices

If control units and devices are shared by different processors, the I/O definitions for these processors should be kept in the same IODF to keep change effort to a minimum and to avoid conflicting definitions.

Processor and related OS configuration(s)

For a full dynamic reconfiguration, the IPLed OS configuration must be in the same production IODF as the processor configuration selected for POR.

Coupling facility support

For coupling facility support, you have to maintain your coupling facility definitions for the processors to be connected in the same IODF.

Switch connections

It is recommended that you maintain your switch configurations in the same IODF as the hardware and software configuration definitions to provide complete validation of the data path.

In order to lookup the port connections of a switch, all connected objects to the ports of a switch have to be defined in the same IODF.

CPCs of an S/390 microprocessor cluster

To manage IODFs and IPL parameters within the CPCs of an S/390 microprocessor cluster from a focal-point HCD, the corresponding processor configurations have to be kept in the same IODF.

Dynamic sysplex reconfiguration
To dynamically reconfigure the I/O configuration of a system within a sysplex from a focal-point HCD, the processor and OS configuration of the sysplex system have to be defined in the same IODF.

CTC connection report
All CTC connections listed in a CTC connection report must be defined in the same IODF. Misconfigurations can be detected only within the scope of one IODF.

Reporting
The scope of the reports (textual or graphical) is a single IODF. All I/O definitions required for a report must be kept in the same IODF.

Validation
The scope of the validation function is a single IODF.

HCM The scope of the configuration shown by HCM is a single IODF.

These requirements and recommendations may lead to a large IODF, depending on the size of the installation. The number of elements in the single IODF may be too large for effective management. HCD provides the possibility of creating manageable *subset IODFs* with a scope limited to a part of the I/O configuration from a *master IODF* describing the entire configuration. For details on this IODF management strategy refer to "The Master IODF Concept".

The Master IODF Concept

In order to take full advantage of the available HCD functions and to keep a maximum of freedom for reconfigurations it is proposed to keep a master IODF. A master IODF may contain the I/O definitions for an entire enterprise structure. However, a user may decide to divide the I/O configuration definitions of the whole enterprise into several master IODFs, where little or no interference is expected.

Major configuration changes are done in the master IODF. These include:
- processor configurations,
- OS configurations,
- switch configurations, and
- definitions spanning multiple configurations, e. g. coupling facility connections.

After such changes have been made, a production IODF is built. From this IODF comprehensive reports can be obtained.

HCD provides a set of functions which allows the management of very large IODFs for their activation on individual systems, like POR, IPL, dynamic I/O changes, or for S/390 microprocessor management tasks. Using these functions, subset IODFs containing I/O definitions relevant to only one particular system may be built from the master IODF .

There are no strict rules about what a subset IODF must consist of. Typically it contains:
- a processor configuration with its related OS configuration, or
- all I/O configurations describing the CPCs in an S/390 microprocessor cluster, or
- all I/O configurations describing the systems of a sysplex.

The content of a subset IODF is specified in a configuration package (see "Work with Configuration Packages" on page 57).

The subset IODF is transferred to the corresponding target system where it is imported and used as the IODF for that system. A subset IODF constitutes a fully functional IODF. When it is built from a master IODF, the processor tokens are preserved. If necessary, updates concerning the target system alone may be carried out using the subset IODF. Subsequently, the subset IODF can be sent back to the system administering the master IODF and merged back into the master IODF, thereby updating it with the changes made at the target system.

The following chart illustrates the possible flow of I/O information according to the master IODF concept.



Figure 12. IODF Distribution/Merge Process

Change to Another IODF

You can work with only one IODF at a time. If, during an HCD session, you want to change to another IODF, you must return to the primary task selection panel and specify the new IODF. If the old IODF has an activity log and has been modified, a panel is displayed to let you add a comment into the activity log ("Activity Logging" on page 62 tells you how). The new IODF now becomes the current IODF.

Change a Production IODF / Create a Work IODF Based on a Production IODF

HCD allows you to perform all tasks on the data stored in a production IODF as long as you do not try to change it. If you try though, HCD displays the Create Work I/O Definition File panel where you can define a new work IODF based on the current production IODF.

HCD then copies the production IODF to that new work IODF, makes the work IODF the currently accessed IODF, and applies to it all further changes.

You must specify a new data set for the work IODF; you cannot use an existing one. HCD creates a default work IODF name by appending the qualifier WORK to the production IODF name. You can change this default work IODF name.

When you have completed the changes, you can use HCD to build a new production IODF from the work IODF.

View Active IODF

HCD provides information about the IODF that has been used for last POR/IPL or for dynamic activation (that is, the currently active IODF); in addition the operating system ID and EDT ID used for IPL are shown, and the configuration token that is currently active in the HSA (hardware system area). For a description of this function, see "View Active Configuration" on page 199.

Backup an IODF

You can use the HCD backup facility to copy the work IODF to a backup data set, thus you can keep track of different stages of the configuration as well as retrieve data lost by accident. You need to specify the name of the backup data set only once for each IODF (when you do the first backup); the same data set is then reused for each backup (though you can change it if you want).

When you do the first backup, you must also specify the volume serial number, if applicable, and the space allocation for the backup data set.

To backup an IODF, select the ***Backup*** action bar choice on any action list panel.

Maintain IODFs

HCD provides the tasks listed on the Maintain I/O Definition Files panel (Figure 13 on page 55) to help you maintain your IODFs. You can reach this panel from the primary task selection panel (see Figure 21 on page 70).

```
──────────────── Maintain I/O Definition Files ────────────────

Select one of the following tasks.

__  1.  Delete I/O definition file
    2.  Copy I/O definition file
    3.  Change I/O definition file description
    4.  View I/O definition file information
    5.  Export I/O definition file
    6.  Import I/O definition file
    7.  Work with Configuration Packages
    8.  Upgrade I/O definition file to new format

 F1=Help     F2=Split    F3=Exit     F9=Swap    F12=Cancel
```

Figure 13. Maintain I/O Definition Files Panel

Delete an IODF

This task deletes an IODF. If the IODF has an activity log, that log is also deleted. HCD asks you for confirmation before actually deleting the IODF.

Copy an IODF

This task copies any IODF to another IODF (either existing or new). You must specify the name, volume serial number, if applicable, and the space allocation of the target data set. If the IODF has an activity log, that log may also be copied. During a definition task, you can use ***Copy IODF*** to copy the existing data to a larger data set if you have allocated insufficient space to a work IODF. In this case, you need to return afterwards to the primary task selection panel to specify the new data set as the IODF you are working with from now on.

You can also invoke the ***Copy IODF*** task in batch mode. For details refer to "Copy IODF" on page 298.

Change IODF Description

This task changes the IODF description, for example, to indicate new purposes the IODF is intended for.

View an IODF

This task displays information about the currently accessed IODF. The information includes the type of the IODF, its description, the creation date, the last update, and how much of the space that is allocated to the data set has been used.

You can also invoke the ***View IODF*** task from the ***View*** action bar, and by issuing the SHOWIODF command from the command line.

```
View I/O Definition File Information

IODF name  . . . . . . : 'IODFST.IODFD0'
IODF type  . . . . . . : Production

Creation date  . . . . : 1997-10-09
Last update  . . . . . : 1997-10-09  14:06

Volume serial number . : CMNSTC
Allocated space  . . . : 2973   (Number of 4K blocks)
Used space . . . . . . : 2965   (Number of 4K blocks)

Activity logging . . . : Yes
Backup IODF name . . . :

Description  . . . . . : IODF for raised floor 710
                         For system D0, D2, D4 and D6
                         incl. sensed data and mig. SW data

ENTER to continue.

F1=Help    F2=Split   F3=Exit    F9=Swap   F12=Cancel
```

Export an IODF

This task sends an IODF, and optionally, its activity log file to another (local or remote) system. On the Export IODF panel, specify or revise the IODF name you want to export, the user ID, or the nickname (only for an attended target system), node ID, and status (attended or unattended) of the operating system (OS) to which the IODF is to be sent.

If the target system is unattended, the IODF is sent as a job to the target system, which must be a system of type MVS. In this case no explicit action on the target system is required. You can specify whether to replace an existing IODF with the same name. If the existing IODF is the active IODF for the remote system HCD is running on, replace will not be possible.

If the target system is attended (receiving to be done by the user on the remote system), the IODF is sent to the target system as a sequential data set. There it has to be received by using the TSO RECEIVE command. As a second step the IODF is imported on the target system (see also "Import an IODF" on page 57).

To export an IODF, HCD uses the TSO command TRANSMIT. Therefore, HCD creates a cataloged sequential data set named *tsoid*.EXPORTED.*iodfname*, where *tsoid* is the sending TSO user ID or the TSO prefix, and *iodfname* is the part of the IODF data set name after the high-level qualifier.

After processing the TRANSMIT command, the sequential data set is deleted.

You can also invoke the ***Export IODF*** task by using the ***Export*** task in batch mode. For details refer to "Export an IODF" on page 308.

Prerequisites:

1. Network Job Entry (NJE) must be active.
2. The source as well as the target system have to run HCD 4.3 or above.
3. The target user ID and password, and, if the target system is not SMS managed, the volume serial number of the receiving data volumes have to be known when the IODF is exported to an unattended system.

Import an IODF

This task imports previously received IODF data into HCD. You can export and import IODFs between different HCD versions. You can, for example, export an IODF from HCD 4.3 and import it with HCD 5.1. Note that in this case you have to upgrade the lower version IODF before using it with HCD, because the export/import function does not change the format of the IODF.

You can also invoke the ***Import IODF*** task by using the ***Import*** task in batch mode. For details refer to "Import an IODF" on page 307.

At an unattended target system, the IMPORT batch utility is invoked automatically when an IODF, with its associated job control, arrives at the system.

Work with Configuration Packages

When invoked with option ***Work with Configuration Packages*** from the panel shown in Figure 13 on page 55, this task displays the Configuration Package list. Configuration packages can be added and edited, transmitted from a production IODF, and they can be deleted. Configuration packages define subset IODFs which are extracted from the accessed IODF (master IODF) and distributed for activation at specified target systems.

```
  Goto  Backup  Query  Help
--------------------------------------------------------------------------------
                           Configuration Package List  Row 1 of 2 More:         >
Command ===> ___________________________________________________ Scroll ===> PAGE

Select one or more packages, then press Enter. To add, use F11.

IODF name  . . . . : IODFST.IODF11.MASTER

  Package  ------Target----- ----Last sent---
/ Name     User     Node     Date       Time  Description
_ CB88     OS390H1  PKSTCB88 1997-10-22 06:28 For A/T system M88TSO
_ CB89     OS390H1  PKSTCB88 1997-10-21 04:34 For A/T system M89TSO
****************************** Bottom of data ******************************


 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 14. Sample Configuration Package List — Left Panel

The target user and node as well as the description of a configuration package can be edited by overwriting the information on the panel. When scrolling to the right you can also overwrite the target IODF name and attended/unattended information.

Define a Configuration Package

To define a new configuration package perform the following steps:

1. On the Configuration Package List panel use F11=Add. If you want to use an existing configuration package as a model, select the package and the ***Add like*** action from the context menu (or use action code **a**). The Add Configuration Package panel is displayed.

```
                    Add Configuration Package

 Specify the following values.

 Package name . . . . . . CB8A____
 Package description  . . For A/T system M8ATSO

 User ID  . . . . . . . . OS390H1
 Node ID  . . . . . . . . PKSTCB88

 Operating system status  2  1. Attended
                             2. Unattended (MVS only)

 Target IODF name . . . . 'IODFST.IODF8A'
 Target volume  . . . . . CMNSTC  (for unattended, if not SMS)

  F1=Help     F2=Split    F3=Exit     F5=Reset    F9=Swap    F12=Cancel
```

Figure 15. Add Configuration Package Panel

2. Enter a package name and other entry data as appropriate. The user ID and node specify the destination of the corresponding subset IODF. The name of the accessed IODF is used as default for the name of the IODF at the target system and for the `Descriptor field 1` and `Descriptor field 2` parameters during the Build Production IODF step, when the configuration package is transmitted (see step 5 on page 61 in section "Transmit a Configuration Package" on page 60). If no value is entered for the Operating system status, `Attended` is assumed which means that a user has to import the subset IODF into HCD at the target system. This is done automatically if `2 (Unattended)` is specified.
3. After you press ENTER, HCD displays the updated Configuration Package list.

Edit a Configuration Package

The target user and node, the attended/unattended information, the target IODF name, and the description of a configuration package can be edited on the Configuration Package List panel (see Figure 14 on page 57).

To edit a configuration package perform the following steps:

1. Display the Configuration Package List panel.
2. Make changes to the configuration package by overwriting the entries on the list panel.

   To change the IODF name and attended/unattended information scroll to the right and overwrite.
3. Press ENTER.

Delete a Configuration Package

To delete a configuration package perform the following steps:

1. On the Configuration Package List panel select the package and the ***Delete*** action from the context menu (or use action code **d**). The Confirm Delete Configuration Package panel is displayed.
2. Press the Enter key to confirm the deletion. HCD displays the updated Configuration Package list.

Work with Configuration Package Objects

Configuration package objects are operating systems or processors. The objects in a configuration package determine the scope of the corresponding subset IODF. To

change the content of a configuration package select the package from the Configuration Package List panel (see "Work with Configuration Packages" on page 57) and the ***Work with Configuration Package Objects*** action from the context menu (or use action code **s**). The Configuration Package Objects List panel is displayed.

Add a Configuration Package Object: To add a configuration package object to a configuration package perform the following steps:

1. Use F11=Add or select an object from the Configuration Package Object List panel and the ***Add like*** action from the context menu (or use action code **a**). The Add Configuration Package Object panel is displayed.
2. Select the `Configuration type`, processor (PR) or OS configuration (OS), and specify the `Configuration ID` of the object.
3. Press the Enter key. The updated Configuration Package Object List panel is displayed.

Merging Changes into a Master WORK IODF: If a system has been supplied with a subset IODF and configuration changes have been made using the subset IODF, you may want to update the master IODF with these changes. This can be done by merging the changed configuration package objects from the subset IODF back into the master work IODF.

First the updated subset IODF is exported on the corresponding system and imported at the system administering the master IODF. You can update the master work IODF by merging or by replacing configuration package objects.

The ***Merge*** action updates new/changed data in the master work IODF.

The ***Replace*** action first deletes the object configuration present in the master work IODF and then replaces it with the new one.

To merge a configuration package object into a master IODF perform the following steps:

1. Access the master work IODF the configuration package belongs to.
2. Display the Configuration Package Object List panel and select one or more objects. Select ***Merge*** (action code **m**) or ***Replace*** (action code **r**) from the context menu.
3. Specify the source IODF the configuration package refers to and press the Enter key.
4. The master work IODF is updated and a new master production IODF can be built.

Notes:

1. Switch configurations are not repeated by ***Merge*** and ***Replace***. If necessary, switch configuration changes should be made in the master IODF before ***Merge*** or ***Replace*** are performed.
2. The ***Merge*** and ***Replace*** actions utilize the ***Repeat*** action for entering the new configuration data into the master work IODF. Refer to "Repeating (Copying) Processors" on page 104 and "Repeating (Copying) Operating System Configurations" on page 91 for details on the ***Repeat*** action.

Delete Configuration Package Objects: To delete a configuration package object from a configuration package perform the following steps:

1. Select an object from the Configuration Package Object List panel and the ***Delete*** action from the context menu (or use action code **d**).
2. Press the Enter key. The updated Configuration Package Object List panel is displayed.

Transmit a Configuration Package

Transmitting a configuration package means building a subset IODF and transmitting it to the target system specified in the configuration package. This action can only be carried out from a production IODF. To transmit a configuration package perform the following steps:

1. Select the package from the Configuration Package List panel and the ***Transmit configuration package*** action from the context menu (or use action code **x**).
2. If the following conditions are fulfilled, the Transmit Configuration Package panel is displayed:
   - The accessed IODF is a production IODF.
   - The selected configuration package contains at least one configuration object (OS or processor).
   - In the selected configuration package a destination user and node are specified.
   - In the selected configuration package a target IODF is specified.

   `Descriptor field 1` is defaulted to the HLQ of the target IODF name in the configuration package; `Descriptor field 2` is defaulted to the 2nd qualifier of the target IODF name in the configuration package.

```
                      Transmit Configuration Package

Package name . . . . . : CB88         For A/T system M88TSO
High level qualifier . . HCDI         Volume . . . . DS7001  +
JCL member used  . . . . CBDJXMIT     Space  . . . . 1536    (4K blocks)
Descriptor field 1 . . . IODFST
Descriptor field 2 . . . IODF8A

Specify or revise the job control statements for the transmit job.

//HCDIXMT  JOB (ACCOUNT),'WEID'
//JOBLIB   DD DSN=SYS1.SCBDHENU,DISP=SHR
//*
//*
//*
//*
//*
//*
//*
```

Figure 16. Transmit Configuration Package Panel

3. Review the entry data displayed. You may change `Descriptor field 1`, `Descriptor field 2`, the high level qualifier and/or the volume of the IODFs and other data sets to be generated temporarily, as well as the estimated size of the target IODF.

   If you want to use a customized transmit procedure you can specify a different JCL member and/or a JCLLIB parameter in the job control statement area. Once changed, the statements will be retained across sessions. If you want to use different load libraries, specify JOBLIB, because the procedure contains several steps.

If the transfer is performed unattended, the Export Unattended dialog is displayed. Refer to "Export an IODF" on page 56 for a description of the export function.

The master production IODF is updated with the last sent date and time when the job stream is built. The JCL member provided, CBDJXMIT, consists of the following steps:

1. A temporary work and a temporary production IODF, according to the values entered in the Transmit Configuration Package panel are initialized.
2. The processor configurations included in the selected configuration package are written to a data set and then migrated to the temporary work IODF.

   To generate coupling facility connections, HCD needs both the CF sender and CF receiver channel paths, or peer channel definitions, within the same IODF. Therefore, if a processor of the configuration package contains a connected sending CF channel path, the processor containing the coupling facility partition will be included (with the coupling facility partition only) even if it is not part of the configuration package. (The receiving CF channel paths of the CF partition are indicated as occupied if they have connections to processors outside of the package.)

   The switches and ports which contain connections to a processor of the configuration package are distributed as well. Ports that contain connections to a processor, switch or control unit outside of the scope of the configuration package are indicated as occupied.
3. The OS configurations related to the selected configuration package are written to a data set and then migrated to the temporary work IODF.
4. The switch configurations related to the selected configuration package are written to a data set and then migrated to the temporary work IODF.
5. A temporary production IODF is built from the temporary work IODF.

   The processor token is not changed by this action.
6. The production IODF is exported to the specified user ID and node, attended or unattended, as selected.
7. The temporary work and production IODFs are deleted.

The transmit action can also be carried out using a batch utility. A sample job, CBDSXMIT, has been provided in SYS1.SAMPLIB.

Upgrade an IODF

This task upgrades an IODF from a back-level format to the new format that is required for the current release of HCD. Table 3 on page 62 shows the options you have. You can either:

- Upgrade into a new work IODF
- Upgrade in place

Table 3. Size Considerations when Upgrading a Back-Level IODF

Upgrade IODF			
From	**To**	**Upgrade into New IODF**	**Upgrade in Place**
4.2	4.3 or 5.n	Default size of new IODF: 4.2 IODF + 80%. You can change this default size, if necessary.	Size required for 4.3 or 5.n definitions: 50% - 80% more than 4.2 definitions. If 4.2 IODF is not large enough, perform upgrade into new IODF.
4.3	5.n	Default size of new IODF: Size of 4.3 IODF You can change this default size, if necessary.	5.n IODF has same size as 4.3 IODF
Note: 5.n applies to HCD Version 5, OS/390, or z/OS HCD. You do not need to upgrade your IODF from HCD Version 5 to z/OS HCD.			

Notes:

1. The ***Upgrade in place*** option cannot be requested for a production IODF (as a production IODF cannot be altered). Further, the final result of the upgrade IODF function is always a work IODF.
2. If you plan to add or change many devices in the configuration, please ensure that you increase the space allocation when creating the IODF to allow for these changes.

You can invoke the ***Upgrade IODF to new format*** task from the Maintain I/O Definition Files panel (Figure 13 on page 55).

Activity Logging

When you end an HCD session or change to another IODF after modifying some configuration data, and if an activity log is enabled for the currently accessed IODF (“Specify an IODF” on page 50 explains how to specify an activity log), then HCD displays the following panel showing the information which will be added to the activity log.
This information contains the date and time, the user ID of the user who modified

```
Date & Time . . . . . . :   1996-11-22  10:54:46
User  . . . . . . . . . :   BOKA
I/O definition file . . :   'BOKA.IODF00.ACT'
Change reference number :   000002

****** ************************* Top of Data ****************************
'''' Connect devices 0C00 to 0C1F to operating system MVSLG
''''
''''
''''
****** ************************* Bottom of Data *************************
```

Figure 17. Example of Information that is Added to the Activity Log

the IODF, the IODF for which the change was made, and a change reference number.

You can add your own comment to the log (describing what you have done, for example). This is an ISPF/PDF panel, so the normal ISPF/PDF rules apply to it. Activity log editing requires the profile option AUTOSAVE ON. When calling the ISPF editor, macro CBDCACTL is used. You can tailor this macro to your installation needs (e. g. for setting specific profile options). Use the F3=Exit key to continue.

HCD appends the qualifier ACTLOG to the IODF data set name to create the data set name for the activity log. If the ACTLOG data set does not yet exist, HCD dynamically allocates one using ESOTERIC system defaults (see "SMS-Related Considerations" on page 321). If you want to use a specific volume, you can specify the volume serial number to allocate a new activity log in the HCD profile (see "Defining an HCD Profile" on page 41).

You can view or print the activity log associated with the currently accessed IODF during an HCD session by selecting the option ***Print or compare configuration data.*** from the primary task selection panel and then ***View the activity log,*** or ***Print the activity log***.

```
                              View Activity Log

 Command ===>                                              Scroll ===> PAGE

 Activity log . . : BOKA.IODF00.ACT.ACTLOG

 ****************************** Top of Data ********************************
 REFERENCE   DATE        TIME      USER ID              IODF NAME
 ______________________________________________________________________________
 000001:     1996-11-20  10:49:40  BOKA                           BOKA.IODF
         New Dasd string added with address 0A00 - 0A0F
 ______________________________________________________________________________
 000002:     1996-11-22  10:54:46  BOKA                           BOKA.IODF
         Connect devices 0C00 to 0C1F to operating system MVSLG
 ______________________________________________________________________________
 ***************************** Bottom of Data ******************************

  F1=HELP        F2=SPLIT       F3=END         F4=RETURN      F5=RFIND
  F6=RCHANGE     F7=UP          F8=DOWN        F9=SWAP       F10=LEFT
 F11=RIGHT      F12=RETRIEVE
```

Figure 18. Example of an View Activity Log Panel

You can also use the ISPF/PDF facilities to browse or print an activity log.

IODF Release Level Compatibility

If you plan to share an IODF among multiple z/OS, OS/390, or MVS systems that are at different release levels, you have to consider several restrictions concerning IPL, IODF usage, and dynamic reconfiguration.

If you have two or more MVS/ESA SP 4.n systems that share an IODF, Table 4 on page 64 can help you to determine if you can migrate one of the MVS/ESA SP 4.n systems to z/OS Release 1 and still share the IODF with the remaining MVS/ESA SP 4.n systems.

Table 4 shows possible z/OS, OS/390, or MVS and HCD levels that could be installed on your system (see rows A—G). Rows B, C, and E represent the situation in which a higher-level HCD version is installed on a lower-level MVS operating system.

For each z/OS, OS/390, or MVS, and HCD combination, the table shows you whether you can take the following actions:

IPL IPL the z/OS, OS/390, or MVS release

HCD Use HCD to work with the IODF

Dyn Do a dynamic reconfiguration

Dynamic Reconfiguration in a Sysplex: If your sysplex contains an MVS 4.3 system, it cannot be reconfigured dynamically using the sysplex-wide activate function. You have to use HCD running on that system or the ACTIVATE command on that system to initiate the dynamic activation.

If you use JES3, the OS/390 or MVS system on which HCD is running in the sysplex must be MVS 5.2 or higher and JES3 5.2.1 or higher.

Table 4. Coexistence Considerations for IODFs

MVS/ESA and HCD Levels Installed	**Action**	**IODF Level**			
		4.1 IODF	**4.2 IODF**	**4.3 IODF**	**5.n IODF**
-A- **SP 4.2 with** **HCD 4.2**	**IPL** **HCD** **Dyn**	**Yes** **Yes** **Yes (2)**	**Yes** **Yes** **Yes**	**Yes** **No** **No**	**Yes (6)** **No** **No**
-B- **SP 4.2 with** **HCD 4.3**	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes** **Yes (5,8)**	**Yes (6)** **No** **Yes (6,7,8)**
-C- **SP 4.2 with** **HCD 5.n** (1)	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes (4)** **Yes (8)**	**Yes (6)** **Yes** **Yes (6,8,10)**
-D- **SP 4.3 with** **HCD 4.3**	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes** **Yes**	**Yes (6)** **No** **Yes (6,7,8,11)**
-E- **SP 4.3 with** **HCD 5.n** (1)	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes (4)** **Yes**	**Yes (6)** **Yes** **Yes (6,8)**
-F- **SP 5.n with** **HCD 5.n** (9)	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes (4)** **Yes**	**Yes** **Yes (12)** **Yes**
-G- **OS/390 Rn with** **HCD** (9)	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes (4)** **Yes**	**Yes** **Yes (12,13)** **Yes (13,14)**
-H- **z/OS V1 with** **HCD**	**IPL** **HCD** **Dyn**	**Yes** **Yes (3)** **Yes (2)**	**Yes** **Yes (3)** **Yes**	**Yes** **Yes (4)** **Yes**	**Yes** **Yes** **Yes**
Note: HCD 5.n refers to HCD Version 5, z/OS, or OS/390 HCD; OS/390 Rn refers to all OS/390 releases with the corresponding HCD levels. See *z/OS MVS Migration* for information about this support.					

Notes:

1. Installing HCD 5.n on MVS/ESA SP 4.2, 4.2.2, or 4.3 is only supported to migrate to a 5.n IODF. This restriction does not apply when you install the HCD 5.1 Usability Feature for MVS/ESA SP 4.3.
2. To do a dynamic reconfiguration using a target 4.1 IODF, you must install PTF UY90788 (token support) on MVS/ESA SP 4.1 before building the 4.1 production IODF. Also, the IOCDS must be created on a system that has the token support. See *z/OS HCD Planning*.
3. Before using the back-level IODF, you have to upgrade it. As soon as you enter the IODF name in HCD and try to select an action, HCD prompts you to upgrade the IODF.
4. You can only do a few limited actions with the back-level IODF. For example, you can view, import, or export the back-level IODF. However, as soon as you try to update the back-level IODF, HCD prompts you to upgrade the IODF.
5. To make dynamic changes on a processor which has no MIF definitions, but is MIF capable, PTF UY90964 must be installed. If a processor definition contains shared channels, no dynamic changes are possible even if the change does not affect a MIF channel. The request is rejected with message CBDA859I.
6. To allow an operating system definition that contains four-digit devices to be IPLed or dynamically reconfigured, you must install the required PTF on your MVS/ESA SP V4. If the operating system detects a four-digit device, it ignores this device and does not create a UCB.
7. The only way to dynamically reconfigure an MVS/ESA system with HCD 4.3 with a 5.n-level IODF is the ACTIVATE operator command. In this case you must install PTF UW90022 on your MVS/ESA system.
8. Not allowed if the higher-level IODF contains hardware definitions for the processor to be activated that are not known to the back-level operating system. For example, if an MVS/ESA SP Version 5 IODF contains coupling facility definitions for the processor to be activated that are not known to an MVS/ESA SP 4.3 operating system.

   If a 4.3 or 5.n IODF contains MIF definitions (shared channels), a dynamic activate for the corresponding processor is rejected under MVS/ESA SP 4.2 or MVS/ESA SP 4.2.2.
9. If you are running DFSMS/MVS 1.2, you can share an IODF that defines multiple exposure devices between an MVS/ESA SP 5.2 or a z/OS or OS/390 system, and a pre-MVS/ESA SP 5.2 system. However, MVS/ESA SP 5.2, z/OS, or OS/390 will not build UCBs for any of the multiple exposure device types at IPL or dynamic reconfiguration.

   If you are running a higher release of DFSMS/MVS, and you perform the dynamic reconfiguration changes which attempt to activate an I/O configuration definition that contains multiple exposure devices, the system, in addition, issues informational messages.
10. HCD 5.n does not support activation of OSA/CBY channel paths/devices that are not supported under MVS/ESA SP 4.2. However, HCD does not reject the activation. Therefore, the activation result is undetermined. It is strongly recommended, not to perform a dynamic reconfiguration if the processor has this kind of hardware defined.
11. Dynamic reconfiguration is not allowed, if the higher level IODF contains hardware definitions that are not known to the back-level HCD version, even if the back-level operating system supports this new hardware. For example, OSA/CBY type channel paths will cause the activation to be rejected, although it is supported by MVS/ESA SP 4.3.

12. If you work with configuration packages in your OS/390 R5 or higher IODF and want to share the IODF definitions with HCD releases prior to OS/390 R5, you should install the corresponding PTFs for coexistence APAR OW29964. The PTFs recognize the new objects and prevent destroying the configuration package structure by pre-OS/390 R5 HCD releases.

    Example: If you have two systems at MVS/ESA SP 4.2 that share an IODF, and you migrate one of them to z/OS, can you still share the 4.2 level IODF? The answers are in row H, in the column named 4.2 IODF. Row H describes what you can do from z/OS or OS/390 systems:

    - Can you IPL the z/OS using the 4.2-level IODF? YES.
    - Can you use HCD on the z/OS system to work with the 4.2-level IODF? YES, after you upgrade the 4.2-level IODF (see the "back-level IODF" in note 3 on page 65) to z/OS.
    - Can you do dynamic reconfiguration management on the z/OS system using the 4.2-level IODF? YES.
13. If the IODF contains processor configurations with hardware definitions that are not known to all z/OS or OS/390 releases, you have to use a z/OS or OS/390 system that has the corresponding support installed.
14. If the IODF contains managed channel path definitions and is used with OS/390 Release 5 or higher, a software-only activate with hardware validation is accepted.

Chapter 5. How to Use the Dialog

Overview

This chapter explains the following topics:

- Panel layout
- Working with lists
- Promptable fields
- Commands and function keys
- Getting help
- Navigating through the dialog
- Filtering
- Job statement information used in panels

Panel Layout

HCD provides an action bar-driven interface that exploits many of the usability features of the Common User Access (CUA) interface. Figure 19 explains the areas of an HCD panel. These areas appear in the same position on every panel unless you use ISPF to change the position of the command line. Not all areas are included on all panels.

```
  Goto  Filter  Backup  Query  Help                                          1
------------------------------------------------------------------------------
                              I/O Device List       Row 1 of 14   More:      > 2
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more devices, then press Enter. To add, use F11.                3

  -------Device------- --#-- --------Control Unit Numbers + --------
/ Number Type +        PR OS 1--- 2--- 3--- 4--- 5--- 6--- 7--- 8--- Base
_ 0001   3278-3        3  2  00E1 ____ ____ ____ ____ ____ ____ ____
_ 0002   3279-2        3  4  ____ ____ ____ ____ ____ ____ ____ ____
_ 0098   9033          2     0098 ____ ____ ____ ____ ____ ____ ____
_ 0099   9032          2     0099 ____ ____ ____ ____ ____ ____ ____           4
_ 00C1   3480          2  1  00C1 ____ ____ ____ ____ ____ ____ ____
_ 01D1   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D2   3390          2     00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D3   3390          2     00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D4   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
# FFFC   CFS                FFFE ____ ____ ____ ____ ____ ____ ____
# FFFD   CFS                FFFE ____ ____ ____ ____ ____ ____ ____
# FFFE   CFS                FFFE ____ ____ ____ ____ ____ ____ ____
# FFFF   CFS                FFFE ____ ____ ____ ____ ____ ____ ____
 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 19. Example of a Panel Layout. The markings **n** at the right-hand side of the example do not appear on the screen; they serve to explain the panel areas.

1 Action bar.

You can select any of the action bar choices and display pull-down choices. Use F10=Actions to move the cursor to the action bar.

© Copyright IBM Corp. 1994, 2002

2 Title Line.

- Shows the panel title.
- Displays panel identifiers (on the left-hand side, if you have asked for them).
- Displays positional information for the work area:

  `Row 1 of 3302` specifies that the first row of data that is displayed in the work area is the first row of 3302 available rows.

  `More:  >` specifies that more data can be seen by moving the work area to the right using F20=Right. This can also be `More:  <`, which means moving is possible to the left, or `More:  <  >`, which means moving is possible to the left and right.

  Instead of `Row 1 of 3302`, `Filter Mode` would be shown if the action list is filtered. For additional information, refer to "Filtering" on page 81.

3 Instruction Area.

Tells you how to proceed on the panel. On action list panels (see "Action Lists" on page 71) you can get more instruction information by pressing the F13=Instruct key or by using the INSTRUCT command.

4 Work Area.

You can use the following facilities to control the work area:

- The ***Filter*** action reduces the number of objects in an object list; this is described further in "Filtering" on page 81.
- The F7=Backward and F8=Forward keys scroll the work area backward and forward. The end of the information is indicated by a line containing `- end -` or `BOTTOM OF DATA`.
- The F19=Left and F20=Right keys move the work area of an action list panel left and right (or RIGHT and LEFT command).
- The LOCATE command scrolls an object list so that a specific object (or the nearest lower match) is at the top of the work area. Search criteria is the object identifier shown in the leftmost data column.
- The TOP command scrolls backward to the top of the work area.
- The BOTTOM command scrolls forward to the bottom of the work area.

The following Figure 20 on page 69 shows the panel areas of a data entry panel.

```
                          Add Channel Path


 Specify or revise the following values.

 Processor ID . . . : FR38LPAR     Raised Floor Production
 Configuration mode : LPAR

 Channel path ID  . . . . __   +
 Number of CHPIDs . . . . 1
 Channel path type  . . . ___  +
 Operation mode . . . . . DED  +
 Managed  . . . . . . . . No   (Yes or No)   I/O Cluster ________  +
 Description  . . . . . . ________________________________

 Specify the following values only if connected to a switch:

 Dynamic switch ID  . . . __  + (00 - FF)
 Entry switch ID  . . . . __  +
 Entry port . . . . . . . __  +
```

Figure 20. Panel Layout of a Data Entry Panel

This panel has the following characteristics:

- The position and length of empty entry fields are shown by underscore characters (_) and highlighting. If an entry field contains an entry, the underscore characters are not shown.
- Fields that you cannot change are preceded by a colon (:).
- Fields that you must complete may (depending on the terminal) be highlighted by a different color.
- Input fields with a plus sign (+) indicate that you can prompt information for this field using F4=Prompt. For more information on the prompt facility, refer to "Promptable Fields" on page 75.

Working with Lists

HCD presents most of the information in form of lists. Depending on the list, there are different methods to select an item from the list or to perform actions. The different types of lists are:

- Numbered selection lists
- Unnumbered single selection lists
- Unnumbered multiple selection lists
- Action lists
- Message lists

This section describes the different types of lists and the respective selection methods.

Numbered Selection Lists

To select an item from a numbered selection list, type the number you want to select in the input field (left of the first list item) and press the Enter key. An example of a numbered list is the HCD primary task selection panel (see Figure 21 on page 70), displayed when you start an HCD session.

```
                          OS/390 Release 9 HCD

                          Hardware Configuration

Select one of the following.

 1 _1.  Define, modify, or view configuration data
    2.  Activate or process configuration data
    3.  Print or compare configuration data
    4.  Create or view graphical configuration report
    5.  Migrate configuration data
    6.  Maintain I/O definition files
    7.  Query supported hardware and installed UIMs
    8.  Getting started with this dialog
    9.  What's new in this release

For options 1 to 5, specify the name of the IODF to be used.

I/O definition file . . . 'SYS1.IODF00.WORK'                    +
```

Figure 21. Primary Task Selection Panel. If you press the Enter key, you trigger the task ″1. Define, modify, or view configuration data″ using the IODF ’SYS1.IODF00.WORK’.

Unnumbered Single Selection Lists

To select a list item from an unnumbered list from which you can select only one item, you can:

- Place the cursor in front of a list item and press the Enter key
- Select a list item with an **s** or a **/** (slash) and press the Enter key

Figure 22 is an example of a list of IODFs from which you can select one IODF.

You can request a list like the one in Figure 22 by pressing F4=Prompt while your cursor is on the `I/O definition file` entry field (Figure 21). For more details concerning prompting, refer to “Promptable Fields” on page 75.

```
──────────────────────────── Available IODFs ────────────────────────────
                                                          Row 1 of 3
Command ===> ____________________________________________________

Select an IODF name.

  IODF Name                                    Volume
  DOCU.IODF00.FP                               TSO001
  DOCU.IODF00.WORK                             TSO001
  DOCU.IODF01.WORK                             TSO001
************************ Bottom of data ************************
```

Figure 22. Example of a Single Selection List

Unnumbered Multiple Selection Lists

To select a list item from an unnumbered list, from which you can select one or more list items, place a slash (**/**) in front of one or several list items and press the Enter key. In some cases, list items in unnumbered multiple selection lists are already preselected. You can overwrite this preselection.

To select a range of objects, you can place a left parenthesis **(** in front of the first item in the range and a right parenthesis **)** in front of the last item in the range. See also “Using the Context Menu”.

Figure 23 is an example of an unnumbered multiple selection list.

```
                        Define Access List
                                                              Row 1 of 4

 Select one or more partitions for inclusion in the access list.

 Channel path ID  . . : 20      Channel path type  . : CNC
 Operation mode . . . : SHR     Number of CHPIDs . . : 1

 / Partition Name   Number Usage Description
 _ PROD1            1      OS    First production partition
 / PROD2            2      OS    Second production partition
 / TEST1            3      OS    First test system
 _ TEST2            4      OS    Second test system
 ************************ Bottom of data ******************************
```

Figure 23. Example of a Multiple Selection List

Action Lists

Figure 25 on page 73 is an example of an action list panel. You see a panel like this one when you want to define, modify, or view I/O devices.

HCD uses the concept of object-to-action processing. That is, to work with an object, you first have to select the object, and then the action. For some actions, you do not have to explicitly select an object; for example, to add an object to an action list.

In an action list, you have several possibilities to perform an action on a list object:
- Using the context menu
- Using the action code
- Typing over data in the panel

Using the Context Menu

To perform an action on one or several objects in an action list, you can use the context menu:

1. Select an object by placing a slash **/** in front of a list item.

   To select a range of objects, you can place a left parenthesis **(** in front of the first item in the range and a right parenthesis **)** in front of the last item in the range.
2. Press the Enter key. HCD displays a context menu showing all valid actions for the selected objects.

```
  Goto  Filter  Backup  Query  Help
-------------  ┌──────────────── Actions on selected devices ────────────────┐
               │                                                             │
Command ===>   │                                                             │
               │ Select by number or action code and press Enter.            │
Select one or  │                                                             │
               │ 2  1.  Add like  . . . . . . . . . . . . . . (a)            │
  -------Devi  │    2.  Change  . . . . . . . . . . . . . . . (c)            │
/ Number Type  │    3.  CSS group change  . . . . . . . . . . (g)            │
( 0001   3278  │    4.  OS group change . . . . . . . . . . . (o)            │
_ 0098   9033  │    5.  Device type group change  . . . . . . (t)            │
_ 0099   9032  │    6.  Prime serial number and VOLSER  . . (i)              │
_ 00C1   3480  │    7.  Delete  . . . . . . . . . . . . . . . (d)            │
_ 01D1   3390  │    8.  View device definition  . . . . . . . (v)            │
_ 01D2   3390  │    9.  View logical CU information . . . . (l)              │
_ 01D3   3390  │    10. View related CTC connections  . . . (k)              │
) 01D4   3390  │    11. View graphically  . . . . . . . . . . (h)            │
_ 01D5   3390  │                                                             │
/ 01D6   3390  │  F1=Help     F2=Split    F3=Exit     F9=Swap    F12=Cancel  │
_ 01D7   3390  └─────────────────────────────────────────────────────────────┘
_ 01D8   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 24. Example of an Action List Panel with a Context Menu

3. Select an action by entering the number or action code (letter in parentheses) in the entry field. After pressing the Enter key, the context menu is closed and the action is performed for the selected rows.

   If only one action is possible on an action list panel, the context menu is not shown, but the action is performed immediately after entering a **/** (slash) or an **s** .

In the example in Figure 24, the following objects are changed:
- Objects 0001 through 01D4, and
- Object 01D6

A # marker in the selection column indicates that the row is disabled and not available for processing. For example, coupling facility devices are marked in such a way.

Using the Action Code

As you get familiar with the dialog, you might find it easier to select a list item and an action in one operation by means of an action code. To do this, enter the action code in the entry field to the left (the action column) of the associated list item; then press the Enter key. Figure 25 on page 73 shows an example (**d** for delete and **c** for change).

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                              I/O Device List       Row 1 of 1443 More:       >
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more devices, then press Enter. To add, use F11.

  -------Device------- --#-- --------Control Unit Numbers + --------
/ Number Type +        PR OS 1--- 2--- 3--- 4--- 5--- 6--- 7--- 8--- Base
_ 0001   9032-3        3  4  0001 ____ ____ ____ ____ ____ ____ ____
_ 0002   9032-3        3  4  0002 ____ ____ ____ ____ ____ ____ ____
d 0020   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0021   BSC2          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0022   BSC2          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0023   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0024   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
c 0025   BSC2          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0026   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
d 0027   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0028   TWX           1  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 0029   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 002A   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 002B   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 002C   BSC2          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
_ 002D   BSC1          4  4  00E0 ____ ____ ____ ____ ____ ____ ____
# FFFC   CFS           1  4  FFFE ____ ____ ____ ____ ____ ____ ____



 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 25. Example of an Action List Panel with Action Codes

You can select more than one list element and, if necessary, you can specify different action codes for each of the objects. You are first asked to confirm the deletions. Then the other actions (in the example above a change **c**) are performed.

To get a list of action codes, place the cursor in the action column field and then press the F4=Prompt key. The same context menu is shown as when using the **/** in front of a list item and pressing the Enter key. For an example, see Figure 24 on page 72, or Appendix A, “Navigating Through the Dialog” on page 349. If you press the F1=Help key instead of the F4=Prompt key, you get a list from which you can request explanation of the action codes.

Action Codes and Selection Markers: You can also specify individual action codes within a marked range. If you do so, the following rules apply:

- When you press the Enter key, the single action codes are processed. The row selected with selection markers are not processed, they are still shown after processing the action codes.
- When you press the Enter key again, HCD shows the context menu for the rows selected with selection markers.

After successful operation, selection markers and action codes are removed from the list. If the operation is interrupted due to an error, selection markers and action codes not yet processed are still shown. You can remove them by pressing the F5=Reset key.

Typing over Existing Data

You can also make changes to editable fields by typing in new data or typing over existing data directly on the displayed panel.

You have to press the Enter key to process the changes. HCD then validates the data and displays the panel again. When you exit action list panels, all changes to the list since you last pressed the Enter key, are cancelled.

You can use the F5=Reset key to reset the values of all fields that you have changed since you last pressed the Enter key.

Message Lists

One single operation can produce multiple messages. In this case, HCD displays a message list. You can then:

- Use the ***Explain message*** action from the context menu (or action code **e**) to get an explanation of the message.

```
                              Message List
  Save  Query  Help
 ------------------------------------------------------------------------
                                                                Row 1 of 52
 Command ===> ____________________________________________ Scroll ===> PAGE

 Messages are sorted by severity. Select one or more, then press Enter.

 / Sev Msg. ID  Message Text
 e E   CBDG060I A switch and a port must be specified for control unit
 #              0090 to connect the control unit to channel path 34 of
 #              processor CTC01.
 _ E   CBDG060I A switch and a port must be specified for control unit
 #              0098 to connect the control unit to channel path 34 of
 #              processor CTC01.
 _ E   CBDG060I A switch and a port must be specified for control unit
 #              0300 to connect the control unit to channel path 61 of
 #              processor PR9672.
 _ E   CBDG065I The switch control unit 0000 of switch 00 has no channel
 #              path attached via the switch.
  F1=Help        F2=Split       F3=Exit        F4=Prompt      F5=Reset
  F7=Backward    F8=Forward     F9=Swap       F10=Actions    F12=Cancel
 F13=Instruct   F22=Command
```

Figure 26. Message List Panel

```
──────────────────────────── Message List ────────────────────────────

Command ===>                                          Scroll ===> PAGE
CBDG060I A switch and a port must be specified for control unit
 0090 to connect the control unit to channel path 34 of processor
 CTC01.
Explanation:
 A channel path is connected to a switch, therefore all control
 units on this channel path must be connected to a switch also.

System Action:
 System waits for user action.

User Response:
 Specify a switch and a port for the control unit.
- end -
```

Figure 27. Explanation Message

- Use the ***Delete message*** action from the context menu (or action code **d**) to delete a message from the message list.
- Select ***Save messages*** from the ***Save*** action bar to save the displayed messages in the corresponding message log file.

Promptable Fields

The HCD prompt facility reduces what you have to remember, what you have to type, and, possibly, what you have to correct due to typing errors. You can use the prompt facility if there is a plus sign (+) to the right of an entry field (or its column heading on an action list panel). Just place the cursor on the entry field and press the F4=Prompt key.

HCD then displays a prompt selection menu that lists all the values that are currently valid for the field. For long lists (of I/O devices, for example), HCD first displays a menu to let you limit the values listed (to only DASD devices, for example).

```
──────────────────────── Add Partition ────────────────────────

Specify the following values.

Partition name . . . PROD
Partition number . . 1
Partition usage  . . OS     +
          ──────────── Available Partition Usage Types ────────────
Descrip                                            Row 1 of 3

          Select one.
 F1=Hel
 F9=Swa     Usage   Explanation
            OS      Operating system
          # CF      Coupling facility
          # CF/OS   Coupling facility or operating system
          ***************** BOTTOM OF DATA ******************
```

Figure 28. Example of a Prompt Selection Panel

Prompt is also available for the action column. For this purpose you must place the cursor on the action column. HCD displays the same context menu as when using the / (slash) in the action column and pressing the Enter key. For an example, see Figure 24 on page 72. Note that there is no '+' sign shown for the action column heading.

To select a value, place the cursor to the left of (or on) that value or select the value with s or / (slash), then press the Enter key. HCD inserts that value into the entry field or, in case of selecting an action, performs that action immediately.

The prompt list is built dynamically; if a value can be used only once in a configuration then, after it has been selected, either it does not appear in the list again, or it is marked as nonselectable - with the hash sign (#).

Note: It is possible that HCD initially accepts a selection, but rejects it later after further validation when the entered context information is completed.

Commands and Function Keys

All HCD list panels have a command line on which you can enter the usual ISPF commands, TSO commands, or specific HCD commands.

You can use F22=Command to move the cursor to the command line. When the cursor is in the command line, F22=Command lets you step back through the commands that you have previously entered (including ISPF commands).

The HCD dialog uses 24 function keys, if your ISPF session allows the use of 24 function keys. The function keys assignments can be shown or hidden by entering PFSHOW in the command line.

To perform a function, just press that function key.

Getting Help

HCD offers an extensive help facility. From any panel, you can get context-sensitive help by pressing the F1=Help key. Table 5 shortly explains the available types of help and how to obtain it.

Table 5. Online Help Information

Type of Help	Description	How to Get Help
Field	An explanation of what you can enter in a specific entry field on the current panel.	Place the cursor in the entry field and press the F1=Help key.
Extended	Gives information on the content and task of a function panel.	Move the cursor to a non-interactive field in the function panel and press F1, or select Extended help in the action bar, or press F2=Ex_help in field help panels.
Instruction	Specific instructions on what you can do on the current action list panel.	Press the F13=Instruct key. Or select ***Help*** from the action bar.

Table 5. Online Help Information (continued)

Type of Help	Description	How to Get Help
Command	An explanation of the HCD commands that you can enter in the command line.	Place the cursor in the command line and press the F1=Help key. For detailed help on a specific command, type the name of the command and press the F1=Help key.
Keys	An explanation of the function keys.	Press the F1=Help key, then press the F9=Keyshelp key from the help panel. Or select ***Help*** from the action bar.
Reference Phrase	An explanation of any of the highlighted words or phrases that appear on a help panel.	Place the cursor on the word or phrase and press the Enter key.
Message	An explanation of a message that is displayed on the current panel.	Press the F1=Help key when a message is displayed, regardless of the cursor position.
Help for Help	A general explanation of how to use the help facility.	Press the F1=Help key, then press the F1=Help key again from the help panel. Or select ***Help*** from the action bar.
Action Bar	An explanation of the action bar of a panel.	Request extended help, then place the cursor on the reference phrase of the action you want help for, and press Enter.

On a help panel, you can use F5=Window to change the size of the window, to reduce the scrolling required, or to see more of the underlying panel.

Navigating through the Dialog

Most tasks you do with HCD are done in one step; when you complete the step, you select the next task.

However, some tasks need more than one step. For example, when you define an I/O device, you usually want to define the processor and operating system data for that device at the same time. HCD lets you define this data together, in one task, by displaying a sequence of panels in a predefined order. These are called *multi-step tasks*.

Moving Forward and Backward within a Task

The following function keys are available to move forward and backward in a multi-step task.

Enter Displays the next panel in the predefined order. HCD validates your data, but does *not* save it in the IODF until you complete the task. At the end of the task, HCD redisplays the action list panel that precedes the task.

F3=Exit Completes the task. HCD saves in the IODF all valid data that you have entered so far in the task (plus any data in the following steps that has been inherited by, for example, an ***Add like*** action). It then redisplays the action list.

F6=Previous Available on the second and subsequent steps. It cancels the current step and redisplays the previous panel. Any data that you have entered on the current panel is lost.

F12=Cancel Cancels the current task. Data entered in the current step is lost but, if you have entered data in any of the previous steps, HCD gives you the option to save that data (and any inherited data in the following steps) in the IODF.



Figure 29. Moving within a Multi-Step Task

Fast Path

HCD offers you a fast path to jump directly from an action list panel to another panel without having to navigate through the dialog.

HCD offers you two possibilities to use this fast path:

- Using the ***Goto*** action bar choice
- Using the GOTO command

Using the Action Bar Choice

Select the ***Goto*** action bar choice and on the resulting pull-down menu the target object you want to navigate to.

```
 Goto  Filter  Backup  Query  Help
 ------------------------------------
 ce List         Row 1 of 16 More:       >
 ___________________ Scroll ===> PAGE

 s Enter. To add, use F11.

 Control Unit Numbers + --------
 - 3--- 4--- 5--- 6--- 7--- 8--- Base
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ ____ ____ ____ ____ ____ ____
 _ 01D7   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
 _ 01D8   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
  F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
  F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
 F20=Right    F22=Command
```

Figure 30. Using the Goto Action Bar Choice

Objects marked with **...** are associated with another object (for example, an EDT list is associated with an operating system). If you select such an object, HCD displays a list on which you can select the associated object:

```
  Goto  Backup  Query  Help
 ------------------------------------------------------------------------------
                    Operating System Configuration List              Row 1 of 2
 Command ===> ___________________________________________ Scroll ===> CSR

 Select one or more operating system configurations, then press Enter. To
 add, use F11.

 / Config. ID   Type     Description
 _ MVSVM        MVS      MVS Testsystems
 _ VM           VM       VM for Testsystems
 ****************************** Bottom of data ********************************


F1=Help      F2=Split    F3=Exit      F4=Prompt    F5=Reset     F7=Backward
F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel
```

Figure 31. Example of a Selection List. Here, the Operating System Configuration List is displayed, when you have selected the object EDT from the pull-down menu of the action bar choice ***Goto***.

Using the GOTO command

Specify GOTO (or just GO) and the target you want to jump to in the HCD command line. If you type GOTO without a target, a panel is displayed showing the same list of target objects as when using the ***Goto*** pull-down menu.

You can also jump to list panels that are associated with another object (for example, to the EDT list associated with an operating system). In this case, specify

both the target and the object with which it is associated. If you omit this object, a selection list is displayed (for example, the Available Operating System list appears when going to the EDT list).

Optionally, you can also specify the object that will be shown as the first element of a list if you jump to a list panel.

The following figure shows you the syntax of the command. The parameters can be separated by either blank, comma, or dot.

GOTO command:

```
►►──┬─GOTO─┬──┬─CHPID──┬──────────────────────┬──────────────────────────────────────►◄
    └─GO───┘  │        └─processor ID─┬──────┬─┘                                       │
                                        └─first list element─┘                          │
              ├─CONS───┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─OS ID─┬──────┬─┘  └─first list element─┘                       │
                               └─first list element─┘                                    │
              ├─CU─────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─first list element─┘  └─first list element─┘                    │
              ├─DEV────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─first list element─┘  └─first list element─┘                    │
              ├─EDT────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─OS ID─┬──────┬─┘  └─first list element─┘                       │
                               └─first list element─┘                                    │
              ├─ESO────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─OS ID─┬──────┬─┘  └─first list element─┘                       │
                               └─EDT ID─┬──────┬─┘  └─first list element─┘                │
                                        └─first list element─┘                          │
              ├─GEN────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─OS ID─┬──────┬─┘  └─first list element─┘                       │
                               └─EDT ID─┬──────┬─┘  └─first list element─┘                │
                                        └─first list element─┘                          │
              ├─MIG────────────────────────────────────────────────────────────────────┤
              ├─OS─────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─first list element─┘  └─first list element─┘                    │
              ├─PART───┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─processor ID─┬──────┬─┘  └─first list element─┘                │
                                      └─first list element─┘                            │
              ├─PORT───┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─switch ID─┬──────┬─┘  └─first list element─┘                   │
                                   └─first list element─┘                                │
              ├─PR─────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─first list element─┘  └─first list element─┘                    │
              ├─SW─────┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─first list element─┘  └─first list element─┘                    │
              ├─SWCON──┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─switch ID─┬──────┬─┘  └─first list element─┘                   │
                                   └─first list element─┘                                │
              ├─MATRIX─┬──────────────┬──┬──────┬──────────────────────────────────────┤
                       └─switch ID─┬──────┬─┘  └─switch conf. ID─┬──────┬─┘  └─first list element─┘  │
                                   └─first list element─┘                                │
              └─X──────────────────────────────────────────────────────────────────────┘
```

CHPID	Channel path list	**OS**	OS configuration list
CONS	Console list	**PART**	Partition list
CU	Control unit list	**PORT**	Port list
DEV	Device list	**PR**	Processor list
EDT	EDT list	**SW**	Switch list
ESO	Esoteric list	**SWCON**	Switch configuration
GEN	Generic list	**MATRIX**	Port matrix
MIG	Migrate configuration data	**X**	Leave HCD

First list element
The object that will be shown as the first element of a list if you jump to a list panel (same as if using the LOCATE command).

Examples: To go to the channel path list of processor SYSA and display CHPID 27 as the first element of the list, enter:

```
GO CHPID SYSA 27
```

To go to the esoterics list of EDT A1 in operating system MVSPROD and display the esoteric group ESO12 as the first element in the list, enter:

```
GO ESO MVSPROD A1 ESO12
```

Filtering

If a displayed object list is too long, and scrolling back and forth is getting cumbersome, you may use the ***Filter*** function that aids you in limiting the displayed information. The ***Filter*** function is available when the action bar shows a ***Filter*** action bar choice. This is the case in a:

- Processor list
- Channel path list
- CTC connection list
- CF channel path connectivity list
- Switch list
- Port list
- Control unit list
- Device list
- Esoteric list
- I/O Path list

For example, on the device list, you can limit the displayed information by the following filter criteria:

- Device type
- Device group
- Whether the devices are defined to an operating system or not
- Serial number and description
- Volume serial number
- Device parameters and features (if you navigated to the I/O device list via the operating system configuration list)
- Whether the devices are connected to a control unit or not
- Up to four control units, to which the devices may be connected

Rather than seeing all devices defined in the IODF, you see only those devices that are, for example, of a certain type connected to a certain control unit.

You can request filtering as follows:

1. Tab to the action bar and select ***Filter*** from the action bar. The pull-down menu shown in Figure 32 is displayed:

```
  Goto  Filter  Backup  Query  Help
-----  ┌──────────────────┐  ---------------------------------------------
       │  1. Set Filter   │  I/O Device List        Row 1 of 16 More:      >
Comma  │  2. Clear Filter │  ___________________________ Scroll ===> PAGE
       └──────────────────┘
Select one or more devices, then press Enter. To add, use F11.

  -------Device------- --#-- --------Control Unit Numbers + --------
/ Number Type +        PR OS 1--- 2--- 3--- 4--- 5--- 6--- 7--- 8--- Base
_ 0001   3278-3        2  2  00E1 ____ ____ ____ ____ ____ ____ ____
_ 0098   9033          1  2  0098 ____ ____ ____ ____ ____ ____ ____
_ 0099   9032          1  2  0099 ____ ____ ____ ____ ____ ____ ____
_ 00C1   3480          1  1  00C1 ____ ____ ____ ____ ____ ____ ____
_ 01D1   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D2   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D3   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D4   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D5   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D6   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D7   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D8   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 32. Filter Example

2. Select ***Set Filter***. This causes the filter criteria panel tailored for the appropriate list panel to be displayed. See Figure 33 for the Filter I/O Device List panel. Similar panels are displayed for the other lists.

   An alternative way to select filtering is to tab to the command line and type in FILTER SET.

```
──────────────── Filter I/O Device List ────────────────

 Specify or revise the following filter criteria.

 Device type  . . . . 3705____  +
 Device group . . . . ________  +

 Defined to OSs . . . Y  (Y = Yes; N = No)

 Serial number  . . . _________
 Description  . . . . ______________________________

 Volume serial number . . . . . . . ______  (for DASD)

 Connected to CUs . . Y  (Y = Connected; N = Not connected)
 Specific CUs . . . . 01E0  or  ____  or  ____  or  ____


  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset
  F9=Swap    F12=Cancel
```

Figure 33. I/O Device List Filter Panel

3. On this filter panel you can specify one or more filter criteria. All specified filter criteria must match to display the item. For example, when you specify a device type and a control unit the device is to be attached to and press the Enter key, the I/O device list is displayed again, now showing only those devices that have the specified device type and are connected to the specified control unit. Figure 34 shows an example of a filtered list. If `Filter Mode` is displayed in the right top corner of the panel, it indicates that the filter mode is active.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                             I/O Device List        Filter Mode. More:       >
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more devices, then press Enter. To add, use F11.

  -------Device------- --#-- --------Control Unit Numbers + --------
/ Number Type +        PR OS 1--- 2--- 3--- 4--- 5--- 6--- 7--- 8--- Base
_ 01E2   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E3   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E4   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E5   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E6   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E7   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
_ 01E8   3705          4  4  01E0 11E0 ____ ____ ____ ____ ____ ____
****************************** Bottom of data ******************************




 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

Figure 34. Reduced I/O Device List (by Using Filtering)

Most of the entry fields support wildcards, that means that an asterisk (*) can be specified in front and/or after the specified term. The following table illustrates the wildcard processing using the device type field as an example.

Specified Term	Result
3380	Displays all devices of type 3380
3380*	Displays all devices of type 3380 regardless of its model
338*	Displays all devices whose type starts with '338'
*80	Displays all devices whose type ends with '80'
42	Displays all devices containing the string '42' within the type, for example 3420.

Use Field Help on the Filter panel to get information on whether wildcards are supported or not.

To remove the filter, use ***Clear Filter*** from the ***Filter*** action bar, or enter FILTER CLEAR in the command line.

Job Statement Information Used in Panels

Some of the HCD tasks, invoked from the dialog, generate batch jobs. These batch jobs use EXEC procedures as shown in Table 2 on page 48.

The first time you use a task that generates an HCD batch job, you must specify a JOB control statement for the job. This statement can contain user-specific information, such as an account number and SYSOUT class. For example:

```
//WASR    JOB (3259,BOX10),'SMITH',NOTIFY=WAS,
//            CLASS=A,REGION=4M,MSGCLASS=F,MSGLEVEL=(1,1)
```

You need to specify the statement only once; it is saved in your user profile and reused for all subsequent HCD batch jobs that you request (in this and following HCD sessions) until you change it. HCD does not validate the JOB statement.

With JCL overwrite statements you can modify the EXEC procedures that are invoked by the job.

Notes:

1. A batch job requires a region size large enough to contain the HCD code (4M bytes) as well as the IODF (or two IODFs when you compare two IODFs).

   To relieve space requirements you can specify the HCD profile option `IODF_DATA_SPACE = YES`.
2. A batch job to build an IOCDS must run on the processor on which the IOCDS is to be updated, except for processors configured in an S/390 microprocessor cluster.
3. A batch job generated by HCD cannot run when the HCD dialog has exclusive access to the same IODF that the batch job uses. You can release the IODF by changing to another IODF or by ending the HCD session.
4. To use the HCD profile options (e.g. UIM_LIBNAME=*) for a batch job that is started from the dialog, you need to allocate the HCD profile data set to xx.HCDPROF, where xx is the job step name.
5. In a sysplex environment, use the JOBPARM parameter to specify in which system of the sysplex you want the batch job to run. For additional information, see Chapter 12, “How to Invoke HCD Batch Utility Functions” on page 283.

Table 2 on page 48 lists the HCD tasks that use batch jobs. It also lists their job step names, and EXEC procedure names.

Chapter 6. How to Define, Modify, or View a Configuration

Overview

This chapter describes:

- The possibilities for creating new objects
- The navigation methods through HCD
- A suggested sequence to define a configuration
- Step-by-Step instructions on how to work with (for example, define, change, prime, delete):
  - Operating system configurations
  - EDTs
  - Generics
  - Esoteric groups
  - Processors
  - Partitions
  - Channel paths
  - Control units
  - Devices
  - Consoles
- The possibilities to view information about objects

The information on how to work with switches is described in Chapter 7, "How to Work with Switches" on page 153.

Before using the dialog of HCD to define a hardware configuration, you should have a plan of what your configuration should look like, and what you have to do to accomplish that. Preferably, the requirements of your configuration should be established in a configuration plan. Refer to *z/OS HCD Planning* (for a z/OS, OS/390, or MVS configuration) and *VM/ESA Planning and Administration* (for a VM configuration) for a description of what needs to be considered when this plan is prepared.

Creating New Objects

You have three possibilities to create new objects: add, add like, and repeat (copy).

Add

Use the F11=Add key to define a new object. Initially, the entry fields contain (where applicable) default values supplied by HCD.

Add like

Use the ***Add like*** action from the context menu to define a new object that is based on the definition of an existing object. You just have to enter the fields that are different. A field that needs a unique value, such as the object's identifier, is not copied.

© Copyright IBM Corp. 1994, 2002

Repeat (Copy)

The action ***Repeat (copy)*** from the context menu is similar to ***Add like***, but the definitions of all related objects are also copied. For example, if you repeat an operating system configuration, HCD also copies the definitions for all EDTs and consoles, and the connections to all I/O devices attached to that operating system. You can repeat parts of a configuration within the same or to another IODF.

This function is useful when you want to consolidate configuration data from several IODFs into one single IODF or to repeat configuration data (for example, esoterics) that is used several times in an IODF.

When copying parts of a configuration, the source data and the target data are merged.

- If the source object does not exist in the target IODF

  The new object is defined using the attributes you specified while copying the object. The objects and connections that are related to the object you want to copy are created with the same attributes as the source objects and connections.
- If the source object already exists in the target IODF

  The attributes of the target object are updated according to the attributes of the source object. If related objects or connections do not yet exist, they are created. If they already exist, their attributes are updated according to the attributes of the source.

Navigating through HCD

HCD offers three methods to navigate to objects:
- Centralized navigation
- Hierarchical navigation
- Graphical navigation

Centralized Navigation

Centralized navigation means that you always navigate to objects starting from the Define, Modify, or View Configuration Data panel.

The tasks described in this section use this navigation method.

Hierarchical Navigation

Hierarchical navigation means that you navigate to objects from top to bottom.

In Figure 35 on page 88 you start, for example, with option 3 to open the processor list. From the processor list, you can navigate to channel paths, from channel paths to control units, and finally from the control unit list to the device list. This device list —called Device List (attached) in Figure 35 on page 88— is different from the device list you reach with option 5 from the Define, Modify, or View Configuration panel:

- The devices on this list are limited to the control unit you selected on the preceding control unit list.
- The actions offered on this list differ from the actions available on the device list reached with option 5 from the Define, Modify, or View Configuration panel.

Hierarchical navigation is useful, for example, when you want to use the ***Attribute group change*** action necessary to change the DYNAMIC parameter for a group of devices. In this case, you have to navigate to the device list via the operating system configuration list.

Graphical Navigation

Graphical navigation means that you navigate to objects by viewing a graphical configuration report and jumping to the object lists using the F4=Jump function. Refer to "Create or View Graphical Configuration Reports" on page 218 for information on how to use the graphical configuration report.

The graphical navigation is useful when you prefer a graphical representation of your configuration to navigate from object to object.

Navigation Map

Figure 35 on page 88 illustrates how you can navigate from object to object. You can either navigate to objects by using the ***Work with object*** actions from the context menu or by using the appropriate action code, for example **s** . Note that you can reach the generic list with two action codes: **g** (ordered by name) or **p** (ordered by preference value). For information on how to use action codes refer to "Using the Action Code" on page 72.

Control Unit List and Device List

You reach these lists with option 4 and 5 from the Define, Modify, or View Configuration Data panel. These lists show all devices defined in the IODF.

The control unit list (attached) and the Device list (attached) can only be reached from an object higher in the hierarchy. These lists are limited to the object higher in the hierarchy and the actions available on these lists differ from the actions available on the device and control unit lists you reach with option 4 and 5 from the Define, Modify, or View Configuration panel (refer to "Hierarchical Navigation" on page 86). You can, for example, limit a control unit list to the control units attached to one specific channel path by opening the list from the channel path list.



Figure 35. Navigation Map

Suggested Sequence to Define a Configuration

A hardware configuration consists of:

- Information needed by z/OS, OS/390, or MVS/ESA, and by VM/ESA. This is known as the *operating system configuration* or *OS configuration*.
- Information needed by the channel subsystem (CSS). This defines all the hardware resources (such as control units, channel paths, and I/O devices) and how they are connected.
- In some cases, your configuration contains information needed by the switch. For definitions and modifications of switches, refer to Chapter 7, “How to Work with Switches” on page 153.

You can define the objects of a configuration in almost any order but at one point you have to connect objects together. You can only connect objects that are already

defined; therefore it is useful to define the objects in a logical order. For example, when defining I/O devices during the hardware definition, you are prompted to add devices to existing operating system definitions. Therefore, it is useful to define the operating system before the devices.

The suggested sequence to define a configuration is:

1. Operating systems
2. EDTs (MVS-type only)
3. Esoterics (MVS-type only))
4. Switches (explained in Chapter 7, “How to Work with Switches” on page 153)
5. Processors
6. Partitions (if processor in LPAR mode)
7. Channel paths
8. Control units
9. Devices
10. Consoles

Working with Operating System Configurations

An operating system (OS) configuration defines the data that is used by z/OS, OS/390, MVS/ESA, or VM/ESA to build its control blocks. An IODF can contain more than one OS configuration; MVS/ESA, z/OS, or OS/390 is told which one to use at IPL time.

Defining Operating System Configurations



It is recommended to define the operating system configuration before you define anything else. Proceed as follows to define an operating system configuration:

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***. HCD displays the Operating System Configuration List of all operating system configurations currently defined in the IODF:

```
  Goto  Backup  Query  Help
------------------------------------------------------------------------------
                   Operating System Configuration List             Row 1 of 1

Select one or more operating system configurations, then press Enter. To
add, use F11.

/ Config. ID   Type     Description
_ OPSYS02      VM       VM operating system
****************************** BOTTOM OF DATA *******************************
```

   If there are no existing configurations in the IODF, the operating system configuration list is empty.

2. Use F11=Add to define a new configuration. The data-entry fields are shown below, with sample data:

```
Add Operating System Configuration

Specify or revise the following values.

OS configuration ID  . . . . . OPSYS01_
Operating system type  . . . . MVS       +

Description  . . . . . . . . . MVS operating system
```

3. After you press the Enter key, HCD displays the updated operating system configuration list.

Changing Operating System Configurations



You can change the description of an operating system by just typing over the `Description` column or by using the ***Change*** action from the context menu (or action code **c**) on the Operating System Configuration List panel.

Changing the Operating System Configuration ID



To change the ID of an operating system, perform the following steps:

1. On the OS Configuration List panel select the operating system and the ***Repeat (copy) OS configurations*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
2. Press the Enter key to accept the default target IODF name, that is the IODF you are currently working with. The Repeat Operating System Configuration panel is displayed.

```
Repeat Operating System Configuration

Specify or revise the following values.

OS configuration ID  . . . . . ________
Operating system type  . . . : MVS

Description  . . . . . . . . . MVS operating system
```

3. Specify the new identifier for the operating system and press the Enter key.

   HCD displays the OS Configuration List panel now showing the new operating system.
4. Delete the old operating system by selecting the operating system and the ***Delete*** action from the context menu (or action code **d**). HCD displays a confirmation panel before showing the updated OS Configuration List panel.

Repeating (Copying) Operating System Configurations

You can copy operating systems within the same or to another IODF. When copying an operating system, the following related objects and connections are also copied:

- Devices defined for the operating system
- List of consoles (NIPCONs for MVS)
- EDTs including their esoterics and generic groups



In the following example, you copy an operating system to another IODF that already contains an operating system with the same ID that you specify in the repeat panel.

1. Make sure that the operating system in the target IODF has the same operating system type as the one in the source IODF.
2. On the Operating System Configuration List panel copy the operating system using the ***Repeat (copy) OS configurations*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
3. Specify the IODF to which the selected operating system is to be copied. The default IODF is the IODF you are currently working with.
4. On the following Repeat Operating System Configuration panel, specify the required values and press the Enter key.

   If a device defined to the operating system already exists in the target IODF, HCD tries to map the device. If more than one device with the same type and number exist, HCD maps the device to the first device found. To avoid this sometimes erroneous mapping, specify a processor and partition on the Repeat Operating System Configuration panel in which the operating system is to be run. Refer to "Migrating Additional MVSCP or HCPRIO Input Data Sets" on page 246 for detailed rules when a device is mapped.

   Console devices (NIPCONs for MVS) from the source operating system are copied to the beginning of the target's console chain.
5. Because you copy an operating system that already exists in the target IODF, HCD displays a panel to confirm the merging of configuration data.

Deleting Operating System Configurations



You can delete the complete definition of an operating system by using the ***Delete*** action from the context menu (or action code **d**) on the Operating System Configuration List panel. This also deletes all EDTs, esoterics, consoles, and connections to devices defined for this operating system.

Working with EDTs

For an MVS-type operating system, you have to define at least one eligible device table (EDT). An EDT can consist of one or more esoteric device groups and names of the generic device types. Esoteric device groups are installation-defined groupings of I/O devices.

An OS configuration can contain more than one EDT; z/OS or OS/390 is told which one to use at IPL time. For background information about I/O device allocation in MVS that you need to understand before defining EDTs and esoteric groups, refer to *z/OS HCD Planning*.

Defining EDTs



Before you can define EDTs, you must have defined an operating system. You define an EDT as follows:

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***. HCD displays the operating system configuration list of all operating system configurations currently defined in the IODF.
2. On the Operating System Configuration List panel, select the OS configuration and the ***Work with EDTs*** action from the context menu (or action code **s**). HCD displays the EDT List panel.

```
EDT List
  Goto  Backup  Query  Help
-------------------------------------------------------------------------
                                                                Row 1 of 1
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more EDTs, then press Enter. To add, use F11.

Configuration ID . : OPSYS01      MVS operating system

/ EDT Last Update By       Description
_ AS  1994-10-04  DOCU     basic
************************** BOTTOM OF DATA ****************************
```

If there are no EDTs defined in the IODF, the EDT list is empty.

3. Use F11=Add to add a new EDT. The data-entry fields are shown below, with sample data:

```
Add EDT

    Specify the following values.

    Configuration ID . : OPSYS01      MVS operating system

    EDT identifier . . . A1
    Description  . . . . special
```

4. After you press the Enter key HCD displays the updated EDT List.

Changing EDTs



You can change the description of an EDT by just typing over the `Description` column or by using the ***Change*** action from the context menu (or action code **c**) on the EDT List panel.

Changing the EDT ID



To change the ID of an EDT, perform the following steps:

1. On the EDT List panel select the EDT and the ***Repeat (copy) EDTs*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
2. Press the Enter key to accept the default target IODF name, that is the IODF you are currently working with. The Repeat EDT panel is displayed.

```
                         Repeat EDT


 Specify or revise the following values.

 Configuration ID . . OPSYS01   +

 EDT identifier . . . __
 Description  . . . . special
```

3. Specify the new identifier for the EDT and press the Enter key. HCD displays the EDT List panel now showing the new EDT.
4. Delete the old EDT by selecting the EDT and the ***Delete*** action from the context menu (or action code **d**). HCD displays a confirmation panel before showing the updated EDT List panel.

Repeating (Copying) EDTs

You can copy EDTs within the same or to another IODF. When copying an EDT, the esoteric groups and the VIO eligible parameter are also copied. Perform the following steps to repeat an EDT:



1. Make sure that the devices are already defined to the target operating system.
2. On the EDT List panel, select an EDT and the ***Repeat (copy) EDTs*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
3. Specify the IODF to which the selected operating system is to be copied. The default IODF is the IODF you are currently working with.

4. On the following Repeat EDT panel, specify the required values and press the Enter key.

   If the EDT already exists in the target IODF, the esoteric groups and their devices are merged. In this case, HCD displays a panel to confirm the merging of data.

Deleting EDTs



You can delete the definition of an EDT by using the ***Delete*** action from the context menu (or action code **d**) on the EDT List panel. This also deletes the esoterics.

Working with Generics



Device types with similar characteristics are logically grouped together and assigned a name to by the system. Such a group is called a generic device type. Reference to a generic device type is made by its name. To request a device allocation, a user can specify a generic device type rather than a specific device number. z/OS or OS/390 then allocates a device from the specified generic device type.

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***. HCD displays the OS Configuration List of all operating system configurations currently defined in the IODF.
2. On the Operating System Configuration List panel, select the OS configuration and the ***Work with EDTs*** action from the context menu (or action code **s**). HCD displays the EDT List.
3. To change the generics, select either the action ***Work with generics by name*** from the context menu (or action code **g**), or the action ***Work with generics by preference value*** (or action code **p**) on the EDT List panel. On the resulting panels you can then change the VIO indicator, the preference value for a generic, and you can display a subsequent panel that lists the devices belonging to the specific generic.

Working with Esoteric Groups

An esoteric device group identifies the I/O devices that are included in that group. The name you assign to an esoteric device group is called the esoteric name. To request allocation of a device from an esoteric device group, specify the esoteric name on the UNIT parameter of a JCL DD statement. The name *esoteric device group* is often shortened to *esoteric group* or simply *esoteric*.

Defining Esoteric Groups



You can define which esoteric device groups are in each EDT after you have defined the OS configuration. But you cannot assign I/O devices to an esoteric device group until the devices have been defined.

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***. HCD displays the OS Configuration List of all operating system configurations currently defined in the IODF.
2. On the Operating System Configuration List panel, select the OS configuration and the ***Work with EDTs*** action from the context menu (or action code **S**). HCD displays the EDT List.
3. On the EDT List panel, select the EDT and the ***Work with esoterics*** action from the context menu (or action code **S**). HCD displays the Esoteric List.

```
                          Esoteric List
  Goto  Filter  Backup  Query  Help
 ------------------------------------------------------------------------
                                                              Row 1 of 1

 Select one or more esoterics, then press Enter. To add, use F11.

 Configuration ID . : OPSYS01      MVS operating system
 EDT identifier . . : AS           basic

 / Esoteric  VIO    Token  State
 _ ES001     No     ____   No device defined
 ************************** BOTTOM OF DATA ****************************
```

4. Use F11=Add to add a new esoteric group. The data-entry fields are shown below, with sample data:

```
                    Add Esoteric


 Specify the following values.

 Esoteric name  . . . ES002___
 VIO eligible . . . . No     (Yes or No)
 Token  . . . . . . . ____
```

5. After you press the Enter key HCD displays the updated Esoteric List.

Assigning Devices to Esoterics

You must define the I/O devices before you can assign them to an esoteric group. This is described in "Defining Devices" on page 131. The `State` column on the Esoteric List panel indicates the esoteric groups that have no devices defined; so you can check later that your groups are properly defined.

If I/O devices are already defined, you can assign them to esoteric groups as described in "Adding Devices to Esoterics".

Changing Esoteric Groups



You can change the following data of an esoteric group by just typing over the corresponding columns or by using the ***Change*** action from the context menu (or action code **C**) on the Esoteric List panel:

- Esoteric name
- VIO eligible parameter
- Token

Adding Devices to Esoterics

You have two possibilities to add devices to esoterics:

While Defining Devices

When you define a device, HCD automatically prompts you to define the device to an operating system, then to an EDT and esoterics. Refer to "Defining Devices" on page 131 for a step-by-step instruction on how to do that.

While Modifying Esoterics



You can add existing devices to esoterics at any time from the Esoteric List panel as follows:

1. On the Esoteric List panel, select the esoteric and the ***Assign devices*** action from the context menu (or action code **S**). HCD displays the Assign/Unassign Devices to Esoterics panel.
2. On the Assign/Unassign Devices to Esoterics panel, overwrite the values in the `Assigned` column to assign (`YES`) or unassign (`NO`) devices to the esoterics of the selected row.

   If you do not want to assign a complete group of devices, you can limit the range by specifying a starting number and the number of devices. If you omit the number of devices, 1 is assumed.

```
──────────────── Assign/Unassign Devices to Esoteric ────────────────
  Goto  Filter  Backup  Query  Help
-------------------------------------------------------------------
                                                          Row 1 of 4

Specify Yes to assign or No to unassign.

Configuration ID . : OPSYS01        MVS operating system
EDT.Esoteric . . . : A1.ES001       VIO eligible . : No

                              Generic             Starting  Number of
Devices       Device Type     Name      Assigned  Number    Devices
0001,1        3278-3          3277-2    Yes       ____      ____
0098,1        9033            SWCH      No        ____      ____
00C1,1        3480            3480      No        ____      ____
01D1,8        3390            3390      No        ____      ____
```

3. Press the Enter key to process the changes. Then press the F3=Exit key to return to the Esoteric List panel.

Repeating (Copying) Esoteric Groups

You can copy esoterics within the same or to another IODF. When copying an esoteric, the list of assigned devices is also copied.



Perform the following steps to repeat esoterics:

1. Make sure that the devices are already defined to the target operating system.
2. On the Esoteric List panel select an esoteric and the ***Repeat (copy) esoterics*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
3. Specify the IODF to which the selected operating system is to be copied. The default IODF is the IODF you are currently working with.
4. On the following Repeat Esoteric panel, specify the required values and press the Enter key.

   If the esoteric already exists in the target IODF, the devices defined for the esoteric are merged. In this case, HCD displays a panel to confirm the merging.

Deleting Esoteric Groups



You can delete the definition of an esoteric by using the ***Delete*** action from the context menu (or action code **d**) on the Esoteric List panel.

Working with Processors

You can define more than one processor in an IODF and for each defined processor you can configure processor-related data for further use by the CSS.

HCD allows you to define and control I/O configurations for a local as well as for all other processors that are part of an S/390 microprocessor cluster.

For processors that are physically partitioned, you must define each physical partition as an individual processor.

Defining Processors



Define a processor as follows:

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Processors***. HCD displays the Processor List of all processors currently defined in the IODF.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                                Processor List        Row 1 of 1 More:       >
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more processors, then press Enter. To add, use F11.


/ Proc. ID Type +   Model +  Mode+ Serial-# + Description
_ PROC2    9021     720      BASIC 2345679021 This is the second processor
****************************** Bottom of data ********************************
```

2. Use F11=Add to add a new processor. The data-entry fields are shown below, with sample data:

```
                    Add Processor
 Specify or revise the following values.

 Processor ID . . . . . . . . . PROC1

 Processor type . . . . . . . . 9021     +
 Processor model  . . . . . . . 942      +
 Configuration mode . . . . . . LPAR   +

 Serial number  . . . . . . . . 1234569021
 Description  . . . . . . . . . This is the main processor

 Specify SNA address only if part of an S/390 microprocessor cluster:

 Network name . . . . . . . . . ________ +
 CPC name     . . . . . . . . . ________ +
```

On the Add Processor panel, you can specify the network name and the CPC name, when the processor is configured in an S/390 microprocessor cluster. If you specify an SNA address, refer for specific access authority to "Security-Related Considerations" on page 315.

Use `Prompt` on the Add Processor panel for the SNA addresses for those CPCs that are currently configured in the S/390 microprocessor cluster.

3. Depending on the processor type/model, there may be more than one support level for the processor type. The support level defines the supported channel path types, and the features such as Dynamic I/O Reconfiguration, MIF, and coupling facility support. If the processor has several support levels, HCD displays another panel showing a list of available support levels for the processor.

```
                    Available Support Levels
                                                 Row 1 of 3 More:       >

 Select one.


   Support Level
   With parallel and ESCON channels, DYNAMIC and EMIF
   Parallel, ESCON, CF channels, DYNAMIC, EMIF
   Parallel, ESCON (CBY), CF, OSA channels, DYNAMIC, EMIF
**************************** BOTTOM OF DATA ****************************
```

Select the appropriate support level. HCD uses this level when validating the configuration for this processor. It relates to the installed microcode.

4. After you press the Enter key HCD displays the updated Processor List panel.

   You can now use the F20=Right key to scroll to the right to see the SNA address, if you have defined one.

Changing Processors



You can change the following data of the processor:

- Type
- Model
- Configuration Mode
- Serial Number
- Description
- Network name
- CPC name

1. On the Processor List panel select the processor and apply the ***Change*** action from the context menu (or action code **c**). The Change Processor Definition panel is displayed.

```
                    Change Processor Definition


 Specify or revise the following values.

 Processor ID . . . . . . . . : PROC1
 Support level:
 With parallel and ESCON channels, DYNAMIC and EMIF

 Processor type . . . . . . . . 9021      +
 Processor model  . . . . . . . 900       +
 Configuration mode . . . . . . LPAR   +

 Serial number  . . . . . . . . 1234569021  +
 Description  . . . . . . . . . This is the main processor

 Specify SNA address only if part of an S/390 microprocessor cluster:

 Network name . . . . . . . . . ________  +
 CPC name . . . . . . . . . . . ________  +

  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

2. To change the processor type, or model, overtype the old processor type, or model values, and press the Enter key. To change the support level for the same processor type, press the Enter key. If you have installed a new processor type or model, or a new processor support level, you need to upgrade the processor definition within HCD. No dynamic change is possible. HCD selects the proper configuration rules that are dependent on the processor type, and support level, and generates the correct input for the IOCDS download process.
3. If more than one support level is available for the processor type, the Available Processor Support Levels panel is displayed where you can select the correct support level for your processor. Then press Enter.
4. The Update Channel Path Identifiers panel is displayed. This panel shows the old channel path definitions, which you can change according to your new processor configuration.

```
                    Update Channel Path Identifiers
                                                                  Row 1 of 24
Command ===> ___________________________________________ Scroll ===> CSR

Specify any changes to the channel path identifiers in the list below.

Processor ID . . . : PROC1

CHPID  Type  Side  Until CHPID   New CHPID +
20     BL          __            20
21     BL          __            21
22     BL          __            22
24     CVC         __            24
25     CVC         __            25
26     CVC         __            26
27     CVC         __            27
28     CVC         __            28
29     CVC         __            29
2A     CNC         __            2A
2B     CNC         __            2B
2C     CNC         __            2C
 F1=Help        F2=Split       F3=Exit        F4=Prompt      F5=Reset
 F7=Backward    F8=Forward     F9=Swap       F12=Cancel
```

The column New CHPID shows the channel path IDs to which the values of column CHPID are mapped by default.

- You can overtype the values of the column New CHPID. Leave the column Until CHPID blank. Press the Enter key to move the old channel path IDs to the new channel path IDs.
- If you enter a value in the column Until CHPID, you move all defined CHPIDs in the range defined by the channel paths specified in the CHPID and Until CHPID column to the new range that starts with the value in the New CHPID column. If the values for the CHPID column have a 'gap', the 'gap' is also reflected in the New CHPID column range. When you entered a value in the Until CHPID column, press the Enter key. The Update Channel Path Identifiers panel is redisplayed where the new range is resolved in the New CHPID. The Until CHPID column is shown as blank. To process the updates, press the Enter key again.

To change the ID of a Processor, or to change the processor configuration mode from BASIC to LPAR, or from LPAR to BASIC, see "Changing the Processor ID" on page 103, "Changing the Processor Mode from BASIC to LPAR" on page 103, and "Changing the Processor Mode from LPAR to BASIC" on page 103.

Note: If the processor upgrade changed the SYSTEM value of the corresponding IOCP configuration, it may not be possible to do an IOCDS download. It is only possible to perform an IOCDS download for specific processor types because IOCP validates the generated IOCP statements according to the configuration rules of the executing processor. See "Supported Hardware Report" on page 373 for the processor type which allows you to download an IOCDS in preparation for a processor upgrade.

If a processor type change leads to change of the SYSTEM value of the corresponding IOCP configuration see "Build an IOCDS" on page 184 and "Build S/390 Microprocessor IOCDSs" on page 186.

Changing the Processor ID



To change the ID of a processor, perform the following steps:

1. On the Processor List panel select the processor and the ***Repeat (copy) processor configurations*** action from the context menu (or action code **r**). The Identify Target IODF panel is displayed.
2. Press the Enter key to accept the default target IODF name, that is the IODF you are currently working with. The Repeat Processor panel is displayed.

```
                          Repeat Processor


Specify or revise the following values.

Processor ID . . . . . . . . . _________

Processor type . . . . . . . : 9021
Processor model  . . . . . . : 942
Configuration mode . . . . . : LPAR

Serial number  . . . . . . . . 1234569021
Description  . . . . . . . . . This is the main processor

Specify SNA address only if part of an S/390 microprocessor cluster:

Network name . . . . . . . . . _________  +
CPC name . . . . . . . . . . . _________  +
```

3. Specify the new identifier for the processor and press the Enter key. HCD creates a new processor with the same characteristics and connections as the old one.
4. On the resulting Processor List panel, delete the old processor by selecting the processor and selecting the ***Delete*** action from the context menu (or action code **d**). HCD displays a confirmation panel before showing the updated Processor List.

Changing the Processor Mode from BASIC to LPAR

Before you can change the processor mode from BASIC to LPAR, you first have to define partitions for the processor and add them to the channel path access and/or candidate lists. Then change the processor configuration mode, and adapt the channel path modes if needed.

Refer to *z/OS HCD Scenarios* for detailed step-by-step instructions on how to change a processor mode from BASIC to LPAR.

Changing the Processor Mode from LPAR to BASIC

Before you change the processor mode from LPAR to BASIC, you must change all channel path operation modes that are defined as shared to DED, or REC. In addition, you must delete the duplicate devices (you can also disconnect the

channels from the control units instead of deleting the devices directly). Then change the processor configuration mode from LPAR to BASIC.

Note: A POR is required when the processor mode is changed.

Refer to *z/OS HCD Scenarios* for detailed step-by-step instructions on how to change a processor mode from LPAR to BASIC.

Repeating (Copying) Processors

You can copy processors within the same or to another IODF. When copying a processor, the following related objects and connections are also copied:

- Partitions
- Channel paths
- Control units
- Devices

When you copy a processor within the same IODF, you create a new processor. When you copy a processor into a different IODF, you can either create a new processor with the ***Repeat (copy) processor configuration*** action, or, with the same action, merge the configuration of the source processor into an existing configuration of the target processor.

Before copying the processor to an existing processor in another IODF (merge the processor configurations), check the following:

1. Make sure that source and target processor have the same type-model and support level.
2. Check the partition usage type if the processor has several partitions.

   You cannot replace a partition that has a different usage type (except if there are no channel paths defined for this partition):

Usage Type in Source IODF	Matching	Usage Type in Target IODF
OS	→	OS
CF	→	CF
CF/OS	→	CF, OS, or CF/OS

   If the partition usage types do not match, change them in the target IODF.
3. If a channel path already exists in the target IODF, make sure that it has the same type.
4. If the target channel path connects to another dynamic switch than the source channel path, disconnect the channel in the target IODF.
5. To replace a shared channel path mode by a dedicated or reconfigurable channel path mode, change the mode or delete the incompatible channel path in the target IODF.



Copy a processor as follows:

1. Copy the processor using the ***Repeat (copy) processor configurations*** action from the context menu (or action code **r**) on the Processor List panel. The Identify Target IODF panel is displayed.
2. Specify the IODF to which the selected processor configuration is to be copied. The default IODF is the IODF you are currently working with.
3. On the following Repeat Processor panel, specify the required values and press the Enter key.

   Definitions for source partitions are merged with the definitions of the target partitions. If a target partition has another partition number than the source partition, HCD keeps the target partition number.

   If control units, devices, or CHPIDs already exist in the target IODF (same number and type), HCD tries to map them. "Migrating Additional IOCP Input Data Sets" on page 243 explains in detail when a device or control unit is mapped. If they are mapped, the attributes of the target control unit or device are kept.

   See "Explicit Device Candidate Lists" on page 110 on how to handle explicit device candidate lists.

Priming Processor Data



You can prime your I/O configuration in a work IODF with the processor serial number for the active processor.

To prime, select the action ***Prime serial number*** from the context menu (or action code **i**) on the Processor List panel.

The Confirm Priming Processor List panel shows the selected processors with the sensed data for the processor type and serial number of the active processor and their corresponding definitions in the IODF. If the processor type of the active processor and the defined processor match, they are shown in the Confirm Priming Processor List panel.

The sensed data for the processor serial numbers can be confirmed before being taken into the IODF. If a value is blanked out, the defined IODF value is not changed. If you use the F12=Cancel key, none of the sensed values is taken.

```
──────────────── Confirm Priming Processor List ────────────────
                                                      Row 1 of 1
Command ===> ________________________________ Scroll ===> CSR

Press Enter to confirm priming, or Cancel to leave the list.
A blank value will not change the IODF definition.

Processor ---------- Type ----------- --- Serial Number ---
ID        actual        defined       sensed     defined
VMABASIC  9672-R61      9672-R61      0645049672
************************ Bottom of data ************************

 F1=Help      F2=Split     F3=Exit      F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F12=Cancel
```

Deleting Processors



You can delete the definition of a processor by using the ***Delete*** action from the context menu (or action code **d**) on the Processor List panel. If you delete a processor, all channel paths, partitions, and connections to control units and devices for that processor are also deleted; the control units and devices are not deleted.

Working with Partitions

The following section describes how to work with partitions. Note that you can define partitions for a processor regardless of whether it is defined with configuration mode BASIC or LPAR.

Defining Partitions



Define partitions as follows:

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Processors.*** HCD displays the Processor List of processors currently defined in the IODF.
2. On the Processor List panel, select the processor and the ***Work with partitions*** action from the context menu (or action code **p**). HCD displays the Partition List panel showing the currently defined partitions for the designated processor.

```
                          Partition List
  Goto  Backup  Query  Help
-------------------------------------------------------------------------
                                                                Row 1 of 2

Select one or more partitions, then press Enter. To add, use F11.

Processor ID  . . . . : PROC1     This is the main processor
Configuration mode  . : LPAR

/ Partition Name   Number Usage + Description
_ PROD1            1      OS      First production partition
_ PROD2            2      OS      Second production partition
*************************** Bottom of data ****************************
```

3. Use F11=Add to add the partitions. The data-entry fields are shown below, with sample data:

```
                        Add Partition


 Specify the following values.

 Partition name . . . TEST3
 Partition number . . 5
 Partition usage  . . CF     +

 Description  . . . . CF partition
```

The `partition usage` field marks a partition to be used for coupling facility support or for operating system usage. The type of partition usage can be either: `CF`, `OS`, or `CF/OS`.

Specify `CF/OS` if the partition usage will be determined at partition activation. You can then include this partition into the access list of all channel path types. At partition activation those definitions are ignored that are not valid for the actual usage.

4. Press the Enter key. HCD displays the updated Partition List, if you have not yet defined any channel paths.

   If you have already defined channel paths, HCD displays the Update CHPID Access and Candidate Lists panel, where you can include the partition in the access or candidate list of a channel path. For an explanation of access and candidate list, refer to "Defining Channel Path Access and Candidate List" on page 114.

   After pressing the Enter key HCD displays the Update Device Candidate Lists panel, if the new partition is given access to a channel path that attaches devices with an explicit device candidate list. Use this panel to add the new partition to the device candidate list of the listed devices.

Changing Partitions



You can change the following data of a partition by using the ***Change*** action from the context menu (or action code **c**) on the Partition List panel. On the resulting Change Partition panel, you can change:

- Name
- Number
- Usage
- Description

If there are already channel paths attached to the partition, HCD displays the channel path access and candidate lists after pressing the Enter key on the Change Partition panel. On these lists, you can update the channel path access of the partition.

Note: You can also change these partition definitions (except the name) by simply typing over the appropriate columns on the Partition list panel.

Repeating (Copying) Partitions

You can copy partitions within the same or to another IODF. When copying a partition, the following related objects and connections are also copied:

- Channel paths having the partition in their access list
- Control units reached by the partition
- Devices reached by the partition

Before copying the partition, perform the same checks as when repeating a processor (see "Repeating (Copying) Processors" on page 104). Omit step 1 that applies to a processor repetition only.



Then copy a partition as follows:

1. Copy the partition using the ***Repeat (copy) partitions*** action from the context menu (or action code **r**) on the Partition List panel. The Identify Target IODF panel is displayed.
2. Specify the IODF to which the selected partition is to be copied. The default IODF is the IODF you are currently working with.
3. On the following Repeat Partition panel, specify the required values and press the Enter key.

Definitions for the source partition are merged with the definitions of the target partition. If the target partition has another partition number than the source partition, HCD keeps the target partition number.

If control units or devices already exist in the target IODF (same number and type), HCD tries to map them. “Migrating Additional IOCP Input Data Sets” on page 243 explains in detail when a device or control unit is mapped. If they are mapped, the attributes of the target control unit or device are kept.

See “Explicit Device Candidate Lists” on page 110 how to handle device candidate lists.

Transferring Partition Configurations



Use this function to transfer control units and devices attached to a channel path from one partition to another within the same IODF.

In contrast to the ***Repeat (copy)*** function, you do not copy the partition and channel paths, but move the attached control units and devices to another partition, possibly in another processor.

Before transferring the data, you must define the target channel path with its partition access and candidate list, dynamic switch ID, entry switch ID and entry port.

The new channel path may have a different type than the source channel path.

1. On the Partition List panel, select the ***Transfer (move) partition configs*** action from the context menu (or action code **X**).
2. On the Identify Target Partition panel, specify the target processor and partition.
3. The Transfer Partition Configuration panel is shown. To transfer all control units and devices reached by the source partition, specify a new CHPID value for every source CHPID. The new CHPID of the target partition must exist.

   The data-entry fields with sample data are shown below.

```
──────────── Transfer Partition Configuration ────────────────────
                                                   Row 1 of 8
Specify the new CHPID values.

From:                            To:
Processor ID . . . : PROC1       Processor ID . . . : PROC2
Partition name . . : PROD1       Partition name . . : PROD2

CHPID  Type   Mode               New CHPID +
01     BL     DED                __
02     BL     DED                __
03     BL     DED                __
04     BL     DED                __
20     CNC    SHR                __
21     CNC    SHR                __
25     CNC    DED                __
26     CNC    DED                __
```

4. After you press the Enter key the partition list is displayed again.

   The attribute values of the transferred control units and devices remain the same for unit address/range, destination link address, time-out, and STADET. The logical address, protocol, and I/O concurrency level of a control unit remain the same if they are compatible with the target processor and channel path. If they are not compatible, default values are used.

Explicit Device Candidate Lists

If the devices that are affected by the ***Transfer (move) partition configs*** action from the context menu (or action code **x**) have an explicit device candidate list, the result of the transfer action depends on whether or not the device was already connected to the target processor. See Figure 36 for the different combinations. These combinations also apply to the ***Repeat Partition*** and ***Repeat Processor*** actions.

Transfer source partition	**Transfer target partition**			
	Device already connected to target partition			**Device not connected to target partition**
	no cand	**cand +**	**cand -**	
no cand	=	=	cand +	no cand
cand + (partition included)	=	=	cand +	cand +
cand - (partition not included)	cand - (*)	=	=	cand - (*)

Note: Result of the Transfer Action, Relation of Device to Partition:

= no action, target partition remains unchanged

no cand no explicit device candidate list exists for partition

cand + partition included in explicit device candidate list

cand – partition not included in explicit device candidate list

Figure 36. Result of the Transfer (Move) Partition Configs Action

Note: (*) The source partition is not included in the explicit device candidate list. During the transfer, HCD checks whether all partitions of the source processor in the candidate list have the same name on the target processor. If partitions with the same name on the target processor are identified they

are added to the device candidate list for the target processor. If no partition with the same name is found for the target processor, no explicit device candidate list is built. Therefore, a partition transfer can result in a loss of candidate lists, if all partition names between source and target processor are different. It is recommended to run a device compare report after the partition has been transferred.

CF Channel Paths

Connections of CF sender and CF receiver channel paths will not be transferred. You have to connect them again after having transferred the partition.

Deleting Partitions



You can delete the definition of a partition by using the ***Delete*** action from the context menu (or action code **d**) on the Partition List panel.

Working with Channel Paths

Channel paths can be dedicated, reconfigurable, or shared. The following list explains when to use which channel path operation mode.

DED Dedicated; if you want only one logical partition to access a channel path, specify that channel path as dedicated. You cannot reconfigure a dedicated channel path. This is the default mode.

REC Reconfigurable; if you want only one logical partition at a time to access a channel path and you want to be able to reconfigure the channel path from one partition to another, specify that channel path as reconfigurable.

SHR Shared; if you want more than one logical partition to access a channel path simultaneously, specify that channel path as shared.

On the Add Channel Path panel, enter a channel path type and use F4=Prompt for the operation mode to find out the allowed operation modes for the specified type.

Channel paths can also be categorized as static or managed. For more information, see "Defining Managed Channel Paths" on page 113.

Using Multiple Image Facility

If a processor complex has Multiple Image Facility (MIF) capability, and is running in LPAR mode, multiple logical partitions can access the same shared channel paths, thereby reducing the number of required physical connections. In contrast, if a processor complex does not have MIF capability, all logical partitions must use separate channel paths to share I/O devices. For more information about LPAR mode and MIF, see the *PR/SM Planning Guide*.

Defining Channel Paths

You need two steps to define a channel path:

- Define the channel path characteristics
- Define channel path access to logical partitions of PR/SM and MIF capable processors.



Define Channel Path Characteristics

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Processors***. HCD displays the Processor List of processors currently defined in the IODF.
2. On the Processor List, select the processor and the ***Work with attached channel paths*** action from the context menu (or action code **S**). HCD displays the following Channel Path List showing all channel paths defined for the selected processor.

```
                              Channel Path List     Row 9 of 120 More:       >

Select one or more channel paths, then press Enter. To add use F11.

Processor ID . . . : FR38LPAR     Raised Floor Production
Configuration mode : LPAR

                    DynEntry Entry +
/ CHPID Type+ Mode+ Switch + Sw Port Con Mngd Description
_ 0A    CNC   SHR   77       77 EB       NO    ________________________________
_ 0B    CNC   SHR   77       77 31       No    ________________________________
_ 0C    CNC   SHR   89       89 D6       No    ________________________________
_ 0D    CNC   SHR   89       89 43       No    ________________________________
_ 0E    CNC   SHR   71       71 73       No    ________________________________
_ 0F    CVC   DED   __       __ __       No    console for F38C
_ 10    CNC   SHR   65       65 A9       No    ________________________________
_ 11    CNC   SHR   66       66 A9       Yes   ________________________________
_ 12    CNC   SHR   67       67 A9       No    ________________________________
_ 13    CNC   SHR   68       68 A9       Yes   ________________________________
_ 14    CNC   SHR   6D       6D F7       Yes   ________________________________
_ 15    CNC   SHR   6E       6E F7       No    ________________________________
_ 7E    FCV   SHR   89       89 F4       Yes   ________________________________
_ 7F    CBP   SHR   __       __ __    Y  No    CFQ1 ICB Sender Channel
_ 80    CBP   DED   __       __ __    Y  No    CFQ1 ICB Receiver Channel
```

   If the `Type` contains three asterisks (***), the IODF channel path type is unknown to the currently used HCD.

3. Use F11=Add to add channel paths. The data-entry fields are shown in the following panel, with sample data:

```
                          Add Channel Path


Specify or revise the following values.

Processor ID . . . : FR38LPAR     Raised Floor Production
Configuration mode : LPAR

Channel path ID  . . . . 02   +
Number of CHPIDs . . . . 1
Channel path type . . .  FCV  +
Operation mode. . . . .  SHR  +
Managed  . . . . . . . . yes  (Yes or No)   I/O Cluster UTCPLX38  +
Description  . . . . . . ______________________________

Specify the following values only if connected to a switch:

Dynamic switch ID  . . . 65  + (00 - FF)
Entry switch ID  . . . . 65  +
Entry port . . . . . . . 84  +
```

Defining Managed Channel Paths: You can define a channel path as being managed by Dynamic Channel Path Management (DCM). DCM will use such a channel path to dynamically assign the logical paths to control units in order to optimize I/O activity. A managed channel path must connect to a dynamic switch and may be used for control units that connect to the same switch. If a channel path is defined as managed in an LPAR mode processor, it must be defined as shared. It cannot be connected to logical partitions but must specify an I/O cluster name. An I/O cluster is a sysplex that owns the managed channel path. All systems of the sysplex on the given processor are allowed to share the managed channel path. A managed channel path cannot be connected to a control unit by HCD.

Defining Multiple Channel Paths in One Step: You can define, in one step, a group of channel paths of the same type and mode and with consecutive identifiers. It is recommended to define only a group of channel paths that have the same partitions in their access and candidate lists. Otherwise, you have to change the channel paths that have different partitions in their access and candidate list in a further step.

1. Define the group by specifying the first channel path identifier (CHPID) and the number of channel paths in the group. Define a channel path type, mode, and description. HCD applies the definition to all channel paths in the group.
2. Type over the fields that are different, for example description, in the Channel Path List panel.

Connecting a Channel Path to a Switch: If you have already defined a switch, you can connect the channel path to the switch on the Add Channel Path panel. Specify the dynamic switch ID, the entry switch ID, and the entry port to connect the channel path to a switch.

The values are only valid for the first channel path if you have defined a group of channel paths in one step. To define values for the other channel paths of the group, HCD displays an additional panel. This panel allows you to define the entry ports for all subsequent channel paths of the group. For information on dynamic switch ID and entry switch ID, refer to “Possibilities of Switch Connections” on page 153.

```
Update Switch Connections
                                        Row 1 of 2

Specify or revise the following values.

Processor ID . . . : PROC1

       Dyn +  --Entry +--
CHPID  Switch Switch Port
20     98     98     C1
21     98     98     __
**************** BOTTOM OF DATA ****************
```

Defining the Maximum Frame Size: For an IQD channel path type, HCD allows you to specify the maximum frame size to be used for iQDIO requests on that channel path. If you define or update an IQD channel path, HCD will display a dialog panel that allows you to specify a maximum frame size for the channel path.

```
          Specify Maximum Frame Size


Specify or revise the value below.

Maximum frame size
in KB  . . . . . . . 16  +

 F1=Help     F2=Split    F3=Exit     F4=Prompt
 F5=Reset    F9=Swap    F12=Cancel
```

Defining Channel Path Access and Candidate List

For each static channel path you can specify which logical partitions can access that channel path.

1. After you press the Enter key on the Add Channel Path panel, HCD displays the Define Access List panel.

```
Define Access List
                                                        Row 1 of 6

Select one or more partitions for inclusion in the access list.


Channel path ID  . : 20     Channel path type  . : CNC
Operation mode . . : SHR    Number of CHPIDs . . : 4


/ Partition Name Number Usage Description
/ PROD1          1      OS    First production partition______
/ PROD2          2      OS    Second production partition_____
_ TEST1          3      OS    First test system_______________
_ TEST2          4      OS    Second test system______________
_ TEST3          5      CF    CF partition____________________
_ TEST4          6      CF/OS OS partition____________________
```

If you want a logical partition to access a dedicated, reconfigurable, or shared channel path when you initially activate the logical partition, place that logical partition in the channel path's access list. For a shared channel path, you can place more than one partition in the access list.

2. If you do not include all partitions in the access list, you are prompted for the candidate list (for reconfigurable and shared channel paths) after pressing the Enter key.

   From the IOCP point of view, the channel path candidate list includes the channel path access list. From the HCD point of view, the channel path candidate list does not include the channel path access list. The partitions already in the access list do not appear in the candidate list.

```
──────────────────── Define Candidate List ────────────────────────────
                                                          Row 1 of 4

Select one or more partitions for inclusion in the candidate list.

Channel path ID  . : 20     Channel path type  . : CNC
Operation mode . . : SHR    Number of CHPIDs . . : 2

/ Partition Name Number Usage Description
_ TEST1          3      OS    First test system_______________
/ TEST2          4      OS    Second test system______________
_ TEST3          5      CF    CF partition____________________
_ TEST4          6      CF/OS OS partition____________________
```

   If you want to be able to configure a reconfigurable or shared channel path online to a logical partition, place that logical partition in the channel path's candidate list.

3. After pressing the Enter key, you return to the Channel Path List panel. Scroll to the right to get an overview of the access and candidate list of a channel path. The following matrix is displayed:

```
                              Channel Path List     Row 9 of 120 More: <

Select one or more channel paths, then press Enter. To add, use F11.

1=F38B      2=F38C      3=F38D      4=F38E      5=F38F
6=F38G      7=F38H      8=CFQ1      9=CFQ2      A=F38A
B=          C=          D=          E=          F=
                          I/O Cluster  --------- Partitions --------
/ CHPID Type+ Mode+ Mngd  Name +       1 2 3 4 5 6 7 8 9 A B C D E F
_ 0A    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 0B    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 0C    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 0D    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 0E    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 0F    CVC   DED   No    ________     _ a _ _ _ _ _ _ _ _ _ _ _ _ _
_ 10    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 11    CNC   SHR   Yes   UTCPLX38     * * * * * * * _ _ * _ _ _ _ _
_ 12    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
_ 13    CNC   SHR   Yes   UTCPLX38     * * * * * * * _ _ * _ _ _ _ _
_ 14    CNC   SHR   Yes   UTCPLX38     * * * * * * * _ _ * _ _ _ _ _
_ 15    CNC   SHR   No    ________     a a a a a a a _ _ a _ _ _ _ _
```

Figure 37. Example of a Channel Path/Partition Matrix on the Channel Path List

   The legend above the partition matrix shows how the partition names are associated with the columns of the partition matrix. The column numbers correspond to the partition numbers. In the example above, column 1 shows the definitions for the partition with partition number 1.

An 'a' indicates that the partition is in the channel path's access list. A 'c' indicates that the partition is in the candidate list. A managed channel path shows an asterisk (*) in all logical partitions that potentially can access that channel path.

Establishing Coupling Facility Channel Path Connections



Before you start to establish a Coupling Facility (CF) channel path connection, you must have defined a processor that supports coupling facilities, a coupling facility partition, a coupling facility receiver (CF receiver) channel path and coupling facility sender (CF sender) channel path, or peer channel paths.

1. On the Channel Path List (Figure 37 on page 115) select a channel path and the ***Connect CF channel path*** action from the following ***Actions on selected channel paths*** context menu (or type action code **f**). HCD displays the CF Channel Path Connectivity List panel showing all CF channel paths defined for a processor.

   To show that a CHPID is already connected in another IODF you can set the indicator in the Occ (occupied) column to Y (yes). You cannot connect a CHPID labeled Y. However, you can change the occupied status by overwriting.

```
   Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                 CF Channel Path Connectivity List           Row 1 of 4
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more channel paths, then press Enter.

Source processor ID . . : PROC1
Source partition name . : *

  -------Source--------   ----------Destination-------
/ CHPID  Type  Mode Occ   Proc. ID   CHPID  Type  Mode
_ 70     CFR   DED  N
_ 71     CFS   SHR  N
_ 72     CFR   DED  N
_ 73     CFS   SHR  Y
****************************** Bottom of data ******************************
```

   Note: The "Source partition name" field indicates a name only when the Filter function is employed.

2. Select the source channel path for a coupling facility connection and the ***Connect to CF channel path*** action from the context menu (or action code **p**). HCD displays the Connect to CF Channel Path panel. The data-entry fields are shown below, with sample data:

```
Connect to CF Channel Path

Specify the following values.

Source processor ID . . . . . : PROC1
Source channel path ID  . . . : 70
Source channel path type. . . : CFR

Destination processor ID  . . . PROC1     +

Destination channel path ID . . 71  +
```

3. To establish the CF channel path connection, specify the destination processor ID and destination channel path ID.

   If the CF control unit definition does not yet exist, HCD automatically generates a CF control unit and CF devices for a sending channel path when CF channel paths are connected. HCD uses type CFS for a (legacy) CF sender channel path and type CFP for a CF peer channel path. The sending CF channel paths that connect one processor to a CF partition are assigned to the same CF control unit. For each CF sender channel path connection, HCD generates two CF devices. For each sending CF peer channel path, HCD generates seven CF devices. HCD proposes the highest unused control unit number and highest unused consecutive device numbers in the IODF. If a CF peer channel path does not connect to a target CF partition (i.e., the sending function is not used), HCD does not connect the channel path to CF control unit and CF devices.

   The following panel is displayed, where you have to confirm or revise the values for the CF control unit and CF devices. The data-entry fields are shown below, with sample data:

```
Add CF Control Unit and Devices

Confirm or revise the CF control unit number and device numbers
for the CF control unit and devices to be defined.

Processor ID . . . . . : PROC1
Channel path ID  . . . : 71         Operation mode . . : SHR
Channel path type  . . : CFS

Control unit number  . . FFFE  +

Device number  . . . . . FFFE
Number of devices  . . : 2
```

   Note: The CF control unit and device definitions are displayed on the Control Unit List panel and on the Device List panel, but in a disabled state where they cannot be modified or deleted.

4. After you press the Enter key, HCD redisplays the CF Channel Path Connectivity List panel with the new connection defined.

Disconnecting Coupling Facility Channel Path Connections



Perform the following steps to break a coupling facility channel path connection:

1. On the Channel Path List panel select any channel path and the ***Connect CF channel path*** action from the context menu (or action code **f**) HCD displays the CF Channel Path Connectivity List panel showing all CF channel paths defined for a processor.
2. Select the source channel path for a coupling facility connection and the ***Disconnect*** action from the context menu (or action code **n**).

   Note: The appropriate CF control unit definition is removed implicitly with the last broken connection to the coupling facility to which the control unit belongs. The appropriate CF device definitions are removed implicitly, when the coupling facility connection to which they belong is broken.

Changing Channel Paths



To change channel path data you have to follow the same panel flow as for defining channel path data:

- Changing channel path characteristics
- Changing channel path access and candidate list

The following steps describe the panel flow and where you can change the data.

1. On the Channel Path List panel select a channel path and the ***Change*** action from the context menu (or action code **c**).
2. On the following Change Channel Path Definition panel you can change channel path definitions such as:
   - Channel path ID (see also "Changing Processors" on page 101 for an example of the Update Channel Path Identifiers panel, and how to change the CHPID values)
   - Channel path type (see "Changing the Type of a Channel Path" on page 119)
   - Operation mode (see "Changing the Operation Mode of a Channel Path" on page 119)
   - Description

- If connected to a switch
  Dynamic switch ID
  Entry switch ID
  Entry port

3. After pressing the Enter key, the Define Access List is displayed. Select one or more partitions to be included in the access list.
4. After pressing the Enter key again, the Define Candidate List panel is displayed (if applicable). Select one or more partitions to be included in the candidate list.

You can also change channel path definitions (except the channel path ID) and the channel path's access and candidate list by simply typing over the appropriate values on the Channel Path List panel. To change the access and candidate list definitions, scroll to the right to see the channel path/partition matrix (refer to Figure 37 on page 115). Overwrite the values in the channel path/partition matrix with either `a` for access list and `c` for candidate list.

Changing the Type of a Channel Path

Changing the type of a channel path from parallel to serial (or vice versa) will result in changing the type of all other channel paths that are attached to the affected logical control units. When changing the type of a channel path:

- The new/changed channel path type must not conflict with the already existing channel path IDs, control unit and device parameters. Adjust the values of the affected control units and devices according to the rules of parallel or serial channel path type. (For information on how to change control unit processor attachment and device parameters, see: "Changing Control Units" on page 127.)
- When changing from serial to parallel, you have to disconnect the entry switch and entry port first, if the channel path is connected to a switch.
- When changing a channel path of type BL or BY that is connected to more than one control unit, the channel path has to be defined to a corresponding CVC (converter channel path) first and then be changed to serial.

Note: A channel path type change cannot be performed in one step while changing the channel path ID.

Changing the Type of a Coupling Facility Channel Path: To change the type of CF channel paths, disconnect the channel path you want to change before performing the type change. Any coupling facility devices associated with the changed channel path are removed by HCD. The associated control unit is removed only when the last connection to the coupling facility to which the control unit belongs is broken. (For details on that task, see "Establishing Coupling Facility Channel Path Connections" on page 116.)

Changing the Operation Mode of a Channel Path

Changing the operation mode of a channel path is dependent on its type. For example, BL, BY, CVC, CBY, and CF receiver channel paths cannot be shared.

Before you can change the operation mode of a channel path, the rules for partition access and candidate lists of those channel paths that are attached to the affected logical control units must conform to the rules for the new operation mode. You have to check which partitions have access to these channel paths. When changing the channel path operation mode from SHR to non-SHR, you first have to remove partitions in the appropriate access and candidate lists. The partition lists for the affected logical control units have to be changed when the mode change has been done.

CF channel paths that connect a processor to the same coupling facility partition must be either all shared or all nonshared. Hence, if you want to change the operation mode for one channel path (from non-SHR to SHR), you have to change it for all. To do this proceed as follows:

1. Disconnect all receiving CF channel paths that connect a processor to the same coupling facility partition (see "Disconnecting Coupling Facility Channel Path Connections" on page 118).
2. Change the operation mode of all sending CF channel paths.
3. Re-establish the connections for all channel paths that you disconnected in step 1.

The associated coupling facility control unit and coupling facility devices are removed and generated again by HCD.

Changing a Coupling Facility Connection

To change a coupling facility connection:

1. Disconnect a connection (see "Disconnecting Coupling Facility Channel Path Connections" on page 118).
2. Establish the new connection (see "Establishing Coupling Facility Channel Path Connections" on page 116).

Note: A `Y` (yes) in column `Occ` (occupied) of the channel path list indicates that this CHPID is occupied. This is useful if you have another IODF where the CF connection is already defined. If you wish to connect this path, you must first change the occupied status by overwriting the `Y` with `N`.

It is not possible to include the first CF or CF/OS LP in, or remove the last CF or CF/OS LP from, the combined access and candidate list of a connected CF peer channel. Instead, the CF connection first has to be removed. Then, the CF LP can be connected to or disconnected from the CF peer channel path; afterwards, the CF peer connection can be reestablished. This is to avoid implicit generations of deletions of CF control units and devices.

Aggregating Channel Paths



When selecting ***Aggregate channel paths*** from the Channel Path List panel against a channel path, HCD offers the possibility of moving all control units from a source channel path to the selected target channel path of the same processor. This is useful for combining several under-utilized channel paths to a single one.

You can aggregate channel paths using the ***Aggregate channel paths*** action. The following steps describe the procedure:

1. On the Channel Path List panel select a channel path and then the ***Aggregate channel paths*** action from the context menu or type action code **g** next to the selected CHPID.
2. On the following Aggregate CHPID definition panel you can enter the target channel path ID for the aggregate action.

```
                         Aggregate CHPID


 Specify a CHPID to be aggregated with the selected target CHPID.

 Processor ID . . . : PROC1
 Channel path ID  . : 00
 Channel path type  : CNC

 CHPID to aggregate . . . __  +




  F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
 F12=Cancel
```

After successful aggregation, a message will be displayed and the Aggregate CHPID panel will remain to allow you to aggregate additional channel paths. If aggregation fails because of validation errors, the validation errors are displayed. If prompting for channel paths for aggregation, HCD will only show the channel paths that allow aggregation without validation errors. Prompting is thus a useful planning aid.

The **Aggregate Channel Paths** action is only possible if the following prerequisites are fulfilled:

- Source and target channel paths must be different.
- All control units connected to the source channel path must be connectable to the target channel path.
- The source channel path must not be connected to a control unit which is already connected to the target channel path. In addition, a link address - unit address - CUADD combination used by a control unit connected to the source channel path must not also be used by a control unit connected to the target channel path.
- Either the source channel path must have the same channel path mode as the target channel path, or all devices accessible by the source channel path must be connected to only one channel path.
- A dynamic switch is required and source and target channel paths must have the same dynamic switch defined.
- Source and target channel paths must be connected to the same entry switch or must have no entry switch defined.
- The user must not lose connectivity by a channel path aggregate action. The source channel path access and candidate list must be the same as or a subset of the target channel path access and candidate list.
- By connecting all control units of the source channel path to the target channel path, the defined maximum value for the target channel path type (e.g. maximum number of unit address ranges) must not be exceeded.

As a result of an aggregation action, HCD will:

- Change the preferred channel path of a device to the target channel path if the source channel path was the preferred channel path of the device initially.
- Leave the reachability of devices by logical partitions unchanged.
- Move the CTC control units of the source channel path port to the entry port to which the target channel is connected.

Deleting Channel Paths



You can delete the definition of a channel path by using the ***Delete*** action from the context menu (or action code **d**) on the Channel Path List panel.

Working with Control Units

The following section describes how to work with control units.

Defining Control Units



You need two steps to define a control unit:
- Define the control unit characteristics
- Define how the control unit is attached to processors.

Before you define a control unit, you should have defined the processors and channel paths to which the control unit is to be attached.

Defining the Control Unit Characteristics

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Control units***. HCD displays the Control Unit List panel showing all control units currently defined in the IODF.

```
                          Control Unit List

Select one or more control units, then press Enter.  To add, use F11.

/ CU   Type +        #PR #MC Serial-# + Description
_ 14C0 3990          3       90331      ims6.1 dasd pool
_ 2000 2105          3   5   90439      shark logical subsystem LSS1
_ 2200 2105          3   5   90015      shark logical subsystem LSS3
_ 2400 2105          3   6   __________ shark logical subsystem LSS5
_ 2600 2105          3   5   __________ shark logical subsystem LSS7
_ 2700 2105          2   6   __________ shark logical subsystem LSS1
_ 2800 2105          2   6   __________ shark logical subsystem LSS1
```

Column #PR shows the number of processor configurations to which a control unit is connected. This column contains a value only if a connection exists.

Column #MC shows the greater of the number of managed channel paths defined for the connected processors or the number of managed channel paths defined for the selected processor when coming down from the processor. This column contains a value only if managed channel paths are defined for the control unit.

Note: The CF control units generated when connecting CF channel paths are listed but are disabled for any action. It is not possible to add a new such control unit via this dialog.

2. Use F11=Add to define a new control unit. The data-entry fields are shown below, with sample data:

```
                        Add Control Unit


 Specify or revise the following values.

 Control unit number  . . . . 00D1  +
 Control unit type  . . . . . 3990-3______  +

 Serial number  . . . . . . . _________
 Description  . . . . . . . . DASD control unit______________

 Connected to switches  . . . __ __ __ __ __ __ __ __  +
 Ports  . . . . . . . . . . . __ __ __ __ __ __ __ __  +

 If connected to a switch:

 Define more than eight ports . . 2   1.  Yes
                                      2.  No

 Propose CHPID/link addresses and
 unit addresses . . . . . . . . . 2   1.  Yes
                                      2.  No
```

Defining Switch Connections: The Add Control Unit panel can also be used to specify the switches and ports the control unit is attached to.

If you specify `Yes` for `Define more than eight ports`, a further panel will be displayed to allow you to specify up to 32 control unit switch/port connections.

If you specify `Yes` for `Propose CHPID/link addresses and unit addresses` and the control unit is connected to at least one switch, HCD suggests control unit to processor attachment parameters (channel path/link addresses and the unit address range) based on the switch/ports the control unit is connected to. HCD

will propose up to eight channel path/link address pairs, starting with the channel path that has the lowest number of devices attached to it.

If you add a new control unit (via Add or Add-like), HCD automatically assigns as many logical paths as possible for all processors defined.

The following prerequisites must be fulfilled for this function:

- The control unit must support ESCON or FICON attachments and not be used for channel-to-channel (CTC) connections.
- The control unit must have physical switch / port connections (switch entry ports) defined.
- Channel paths that use the connected switch as a dynamic switch must exist.

HCD then automatically selects the channel paths and link addresses according to the following rules for each processor that has been defined.

- All channel paths that use a switch that connects to the control unit as a dynamic switch are candidates for assignment.
- The channel paths are sorted ascending by the value of the reversed channel path ID. The resulting sequence is again sorted ascending by the number of connected devices.
- The connected control unit ports are ordered ascending by the numbers of already connected control units and path connections, respectively.
- For each connected switch port in the resulting sequence, the channel paths are tested in sequence. If the switch port can be used as a link address, the CHPID/link address is taken.
- A maximum number (up to 8) of possible CHPID/link address combinations is assigned.

On the following ***Select Processor/Control Unit*** panel you can type over the fields that are different from the suggested attachment values.

Defining Processor Attachment Data

1. After pressing the Enter key on the Add Control Unit panel HCD displays a list panel that shows all the defined processors. You can then define how the control unit is to be attached to one or more processors.

```
                        Select Processor / Control Unit

Command ===> ____________________________________________ Scroll ===> PAGE

Select processors to change CU/processor parameters, then press Enter.

Control unit number . . : 2000     Control unit type . . . : 2105

           ---------------Channel Path ID . Link Address + ---------------
/ Proc. ID 1------ 2------ 3------ 4------ 5------ 6------ 7------ 8------
_ P2064A   C8.04__ _______ _______ _______ _______ _______ _______ _______
_ P2064B   01.2104 _______ _______ _______ _______ _______ _______ _______
_ FR38LPAR 07.9B__ 0C.70__ 6B.9E__ *       *       *       *       *
```

Figure 38. Select Processor / Control Unit (1)

```
                    Select Processor / Control Unit

                                                   Row 1 of 3 More: <     >
Command ===> ____________________________________________ Scroll ===> PAGE

Select processors to change CU/processor parameters, then press Enter.

Control unit number . . : 2000     Control unit type . . . : 2105

               CU   --------------Unit Address . Unit Range + -------------
/ Proc. ID Att ADD+ 1----- 2----- 3----- 4----- 5----- 6----- 7----- 8-----
_ P2064A     Y   1  00.004 ______ ______ ______ ______ ______ ______ ______
_ P2064B     Y   1  00.004 ______ ______ ______ ______ ______ ______ ______
_ FR38LPAR   Y   1  00.256 ______ ______ ______ ______ ______ ______ ______
```

Figure 39. Select Processor / Control Unit (2)

A `Yes` in the `Att.` column indicates that the control unit is attached to the processor.

2. Select a processor and the ***Select (connect/change)*** action from the context menu (or action code **s**).

   When a control unit is attached to multiple processors, you can use the ***Group connect*** action from the context menu (or action code **g**). This group action is particularly useful when performing symmetric changes, for example, on CPCs defined in an S/390 microprocessor cluster. The changes are applied to all selected processors, when you issued the change action against a group of processors.

   When you issue a change or group connect action, the following panel for processor-dependent control unit information is displayed:

```
                          Add Control Unit

 Specify or revise the following values.

 Control unit number  . : 0099         Type . . . . . . : 2105
 Processor ID . . . . . : FR38LPAR     Raised Floor Production

 Channel path IDs . . . . 07    08     *     *     *     __    __    __    +
 Link address . . . . . . 80__  81__  ____  ____  ____  ____  ____  ____  +

 Unit address . . . . . . 00   __   __   __   __   __   __   __   +
 Number of units  . . . . 256  ___  ___  ___  ___  ___  ___  ___

 Logical address  . . . . __  + (same as CUADD)

 Protocol . . . . . . . . __  + (D,S or S4)
 I/O concurrency level  . 2  + (1, 2 or 3)
```

3. On the Add Control Unit panel specify the channel paths that connect the control unit to the processor.

   If the control unit is attached to a switch, you have to define a link address for each channel path. The link address is the port to which the control unit attaches. If the control unit attaches only to one port, the link address is the same for each channel. For addressing the target control unit in a fabric

containing cascade switching, a two-byte link address is used, which specifies as first byte the switch address and as second byte the port address to which the control unit is attached.

For a description what the link address is, see Figure 43 on page 154, Figure 44 on page 154 and Figure 46 on page 155.

Note: For managed control units, i.e., control units that can have managed channel paths assigned by DCM, you must indicate how many managed channel paths can be connected to the control unit. Enter at least one static channel path and the corresponding link address, and, in addition, an asterisk (instead of the channel path ID and link address) for each managed channel path.

You must also specify the unit address and the number of units, that is the unit address range of I/O devices that the control unit recognizes. Serial control units may have specified only one unit address range starting with 00.

If the path to the control unit is not unique, and more than one serial control unit connects to the same channel path via the same link address, you have to specify a logical address (CUADD parameter). For more information refer to the explanation of the CUADD in the *IOCP User's Guide* for your processor.

4. Press the Enter key. HCD displays the updated Select Processor/Control Unit panel. There you may scroll to the right (using F20=Right) to see the data that you have entered on the previous panel.
5. Repeat defining processor attachment data for all processors the control unit should be attached to.
6. Press the Enter key to return to the Control Unit List panel.

Upgrading to two-byte Link Addresses

In a FICON fabric, all one-byte link addresses on a channel path may need to be migrated to a two-byte link address. HCD supports this definition change via the Change Channel Path Link Addresses dialog. If you specify a two-byte link address on a control unit for a specific channel path, and there are already one-byte link addresses specified on that path, the panel shown in Figure 40 on page 127 appears.

This panel shows all link addresses specified for the specific channel path that must be changed. If there has been an entry switch defined for the channel, its ID and switch address (if defined) are displayed; else the displayed information is taken from the dynamic switch.

You can change the switch address. HCD then uses the modified value to preset the two-byte link addresses in the displayed `New` column. Its value is stored, if the entry switch is defined. Alternatively, the new two-byte link addresses can be entered.

Pressing Enter will change the control unit link addresses on the corresponding control units.

```
                    Change Channel Path Link Addresses

Command ===> ___________________________________________ Scroll ===> PAGE

Specify or revise the following values.

Processor ID . . . . . : PROC100
Channel Path ID  . . . : 81
Entry Switch ID  . . . : 06
Switch address . . . . . 26

Control unit                Link Address
number                   Current         New
6000                     02              2602
6200                     03              2603
6400                     04              2604
6600                     05              2605
7000                     09              2609
0E06                     FE              26FE
C000                     310B            310B
**************************** Bottom of data **************************


F1=Help        F2=Split       F3=Exit        F5=Reset       F7=Backward
F8=Forward     F9=Swap       F12=Cancel     F22=Command
```

Figure 40. Change Channel Path Link Addresses

You may want to change link addresses from two byte to one byte. This is possible, as long as all affected control units are attached to the channel path switch. If a defined two-byte link address is changed to a one-byte link address on a given channel path, all other two-byte link addresses defined for control units attached to that channel have to be changed to a one-byte link address also.

Changing Control Units



To change control unit data you have to follow the same panel flow as for defining control units.

- Changing Control Unit Characteristics
- Changing Processor Attachment Data

The following steps describe the panel flow and where you can change the data.

1. On the Control Unit List panel select a control unit and the ***Change*** action from the context menu (or action code **c**).
2. On the following Change Control Unit Definition panel you can change the following data:
   - Control unit number
   - Type-model
   - Serial number

- Description
- Connections to switches/ports

Note: You can also change these control unit definitions (except the control unit number and the connections to switches/ports) by simply typing over the appropriate columns on the Control Unit List panel.

3. After pressing the Enter key you see the Select Processor / Control Unit panel. Select a processor and the ***Select (connect/change)*** action from the context menu (or action code **s**).
4. On the following Change Control Unit Definition panel you can change the processor attachment data:
   - Channel paths / Link addresses
   - Unit addresses / Number of units
   - Logical address
   - Protocol
   - I/O concurrency level

When changing control unit data of control units that affect other control unit or device data (like unit address/ranges), a list panel is displayed that shows all affected control units and proposed new address ranges for those control units. A panel like the following one is displayed:

```
──────────────── Modify Affected Control Unit Parameters ────────────────
                                                              Row 1 of 2

Specify or revise any changes to the control unit parameters in the
list below.

Processor ID  . . . . . : PROC2

CU   Prot. I/O +   -------------Unit Address . Unit Range + --------------
     +     Conc.   1----- 2----- 3----- 4----- 5----- 6----- 7----- 8-----
0012  S     2      20.016
0013  S     2      20.016
```

After you modified control unit data (like protocol, I/O concurrency level, or unit address range), and pressed the Enter key, the Modify Device Parameters panel is shown with the devices attached to the affected control units. The devices are grouped by ranges:

```
──────────────────────── Modify Device Parameters ────────────────────────
                                                 Row 1 of 1 More:      >

Specify or revise any changes to the device parameters in the list below.
To view attached control units, scroll to the right.

Processor ID  . . . . . : PROC2        This is the second processor

---------Device--------- ---UA----                   Preferred  Exposure
No., Range Type          Old New + Time-Out  STADET  CHPID +    Device
0012,016   3390          12  20    Yes       No      __
```

HCD proposes starting unit addresses for the listed device groups.

Use the F20=Right key to scroll to the right to see the attached control units. Accept or change the definitions for unit address (UA New), Time-Out, STADET, and preferred CHPID.

Changing Control Unit Attachment Parameters for Multiple Processors



You can change control unit (CU) attachment parameters or attach a control unit for a group of processors. If all parameters to be changed are identical, use the following group action.

1. On the Control Unit List panel, select a control unit that is attached to the group of processors and use the ***Change*** action from the context menu (or action code **c**).
2. On the Change Control Unit panel press the Enter key. HCD then displays a Select Processor/Control Unit panel with a list of processors already defined (see xref refid="selprocu">).
3. Select the processors for which you want to change the control unit-processor definitions and use the ***Group change*** action from the context menu (or action code **g**).
4. The Change Control Unit Definition panel is displayed showing the values/attributes for the first processor in the group. An asterisk (*) in the Processor ID field indicates that you are using the ***Group connect*** action from the context menu and the changes will be applied to more than one processor.

Disconnecting Control Units from a Processor



1. On the Control Unit List panel select a control unit and the ***Change*** action from the context menu (or action code **c**). HCD displays the Change Control Unit Definition panel.
2. On the Change Control Unit Definition panel, press the Enter key. HCD displays the Select Processor / Control Unit panel.
3. On the Select Processor / Control Unit panel select a processor and the ***Disconnect*** action from the context menu (or action code **n**).

Disconnecting Multiple Control Units from a Processor

If you want to disconnect multiple control units from one processor in one step, open the control unit list via the channel path list. On the Control Unit List panel, select one or multiple control units and use the ***Disconnect*** action from the context menu (or action code **n**).

Priming Control Unit Data



You can prime your I/O configuration in a work IODF with the control unit serial number for the active processor. For the prerequisites for this function refer to "Prerequisites" on page 9.

To prime the control unit serial number, select the action ***Prime serial number*** from the context menu (or action code **i**) on the Control Unit List panel. The Confirm Priming Control Unit Data List panel shows the selected control units with the sensed data for the control unit types and serial numbers, and their corresponding definitions in the IODF.

```
──────────── Confirm Priming Control Unit Data List ────────────
                                                   Row 1 of 9
Command ===> ____________________________ Scroll ===> CSR

Press Enter to confirm priming, or Cancel to leave the
list. A blank value will not change the IODF definition.

CU     ---------- Type ----------- --- Serial Number ---
Number actual        defined       sensed     defined
90C1                 3990          __________ 33333   1
9100   3990-L03      3990          30984              2
9101   3990-L03      3990          30984      30984
9140   3990-L03      3990          37160      A7199   3
9141   3990-L03      3990          37160      A7199
9180   3990-L03      3990          37201
9181   3990-L03      3990          37201
91C0   3990-L03      3990          37163      37163
91C1   3990-L03      3990          37163      37163
******************** Bottom of data **********************

 F1=Help        F2=Split       F3=Exit        F5=Reset
 F7=Backward    F8=Forward     F9=Swap       F12=Cancel
```

1 The control unit serial number is defined in the IODF, but no sensed data is available on the active system.

2 No control unit serial number is defined in the IODF, but the sensed data of the active system is available. To confirm the sensed data, and to define them in the IODF, press Enter.

3 The control unit serial numbers that are defined in the IODF, and that are sensed are different. Press Enter, to overwrite the defined data by the sensed data.

Note: The sensed values can only be blanked out or left unchanged. Blank out the sensed values, if you don't want to change the defined IODF values. To confirm priming, press Enter. Use the F12=Cancel key, if you don't want to use the sensed values, and to leave the list.

Deleting Control Units



You can delete the definition of a control unit using the ***Delete*** action from the context menu (or action code **d**). Deleting a control unit means that all connections to channel paths, switches, and I/O devices are also deleted; these objects are not deleted.

Working with Devices

Operating systems need I/O device data to address the devices. The CSS also needs the data to provide the required information for performing I/O operations to a specific device.

Four-Digit Device Numbers: Since MVS/ESA SP Version 5, HCD has supported the definition of four digits (numbers higher than '0FFF') for device numbers for the MVS operating system. The four-digit device numbers make it easier for large installations to use unique device numbers across their installation. The device numbers for MVS/ESA SP 4.3 and lower versions are still restricted to three digits. If you use four-digit definitions, these are ignored when you IPL or dynamically activate an MVS/ESA SP 4.2 or 4.3 system. The software products installed need to support four-digit device numbers as well.

Defining Devices



You need three steps to define an I/O device:

- Define device characteristics and control unit connection
- Define CSS-related definitions for a device
- Define OS-related definitions for a device (including EDT and esoteric group assignment - MVS-type only).

Before you define a device that should be defined to an operating system and to the channel subsystem (CSS), you must have defined the operating system configuration, processor, channel path, and control unit. HCD omits some steps if data is missing. For example:

- You cannot define the processor data for the device if the device is not attached to a control unit or the control unit is not attached to a processor.
- You cannot define the EDT/esoteric group data for the device until you have defined an EDT for the OS.

Defining Device Data

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel ***I/O devices***. HCD displays the I/O Device List panel showing all I/O devices currently defined in the IODF.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                              I/O Device List       Row 1 of 14   More:      >
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more devices, then press Enter. To add, use F11.

  -------Device------- --#-- --------Control Unit Numbers + --------
/ Number Type +        PR OS 1--- 2--- 3--- 4--- 5--- 6--- 7--- 8--- Base
_ 0001   3278-3        3  2  00E1 ____ ____ ____ ____ ____ ____ ____
_ 0002   3279-2        3  4  ____ ____ ____ ____ ____ ____ ____ ____
_ 0098   9033          2     0098 ____ ____ ____ ____ ____ ____ ____
_ 0099   9032          2     0099 ____ ____ ____ ____ ____ ____ ____
_ 00C1   3480          2  1  00C1 ____ ____ ____ ____ ____ ____ ____
_ 01D1   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D2   3390          2     00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D3   3390          2     00D1 ____ ____ ____ ____ ____ ____ ____
_ 01D4   3390          2  1  00D1 ____ ____ ____ ____ ____ ____ ____
# FFFC   CFS                 FFFE ____ ____ ____ ____ ____ ____ ____
# FFFD   CFS                 FFFE ____ ____ ____ ____ ____ ____ ____
# FFFE   CFS                 FFFE ____ ____ ____ ____ ____ ____ ____
# FFFF   CFS                 FFFE ____ ____ ____ ____ ____ ____ ____
 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F20=Right    F22=Command
```

   The # sign in front of a row indicates that this row is disabled. You cannot modify or delete it. In this example, you can see four devices of type CFS that are used for coupling facility connections.

   Columns PR and OS state the number of processors and operating systems accessing the device. If called from the processor list, the number in the IM column states how many partitions (images) of the selected processor are accessing the device. For basic processors this value is one.

2. Use F11=Add to add I/O devices. The data-entry fields are shown below, with sample data:

```
                              Add Device

 Specify or revise the following values.

 Device number  . . . . . . . . 01E1  (0000 - FFFF)
 Number of devices  . . . . . . 8
 Device type  . . . . . . . . . 3745          +

 Serial number  . . . . . . . . _________
 Description  . . . . . . . . . ______________________________

 Volume serial number . . . . . ______  (for DASD)

 Connected to CUs . . 01E1  ____  ____  ____  ____  ____  ____  ____  +


  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

This panel can also be used to specify the control units the devices are connected to.

Since VM dummy devices are definable with an arbitrary device type, a device with an unknown device type is accepted by HCD. It is treated like an unsupported device with the device type DUMMY. For MVS-type systems, you have to explicitly define the device as DUMMY.

Defining Multiple Devices in One Step: You can define, in one operation, a group of I/O devices of the same type and with consecutive device numbers. You define the group by specifying the first device number and the number of devices in the group. Then HCD applies the definition to all devices in the group. On the I/O Device List panel you can type over the values that should be different.

Use and Definition of Serial Number of Device: HCD allows you to assign the same device number to more than one I/O device; that is, device numbers alone do *not* uniquely identify a device in an IODF. To clearly identify devices, HCD keeps track of each occurrence of the same device number by appending an internal suffix to the device number.

When ***activating a configuration dynamically***, HCD might be unable to determine whether certain I/O devices in the ***currently active IODF*** and the ***IODF to be activated*** are physically the same. This may happen, if the new IODF was not created by copying or updating the current IODF but was newly created by migrating with IOCP or using the HCD dialog. In this case HCD is unable to determine which of the devices are physically identical.

To avoid problems that might surface when activating a configuration dynamically, you should check if more than one device uses the same device number attached to the same control units in the current IODF and in the newly created (not copied) IODF. If so, specify the same *serial number* for the devices that HCD should treat as physically the same.

Defining CSS-Related Definitions for a Device

If you have defined a connection to a control unit on the Add Device panel, HCD displays an action list that shows the processors the control units are attached to.

```
──────────────────── Device / Processor Definition ────────────────────
                                                              Row 1 of 1

Select processor(s) to change device/processor definitions, then
press Enter.

Device number  . . : 01E1           Number of devices  . : 8
Device type  . . . : 3745

/ Processor ID   UA +  Time-Out  STADET  Preferred Explicit Device
                                         CHPID +   Candidate List
_ PROC1          __     No        Yes     __        No
************************** BOTTOM OF DATA ***************************
```

1. On the Device / Processor Definition panel you can specify the CSS-related definitions by either typing over the fields in each column or by selecting a processor and pressing the Enter key. The Define Device / Processor panel is displayed.

```
────────────────────Define Device / Processor ────────────────────────


Specify or revise the following values.

Device number  . : 01E1           Number of devices . . . . : 8
Device type  . . : 3745
Processor ID . . : PROC1

Unit address . . . . . . . . . . E1  + (Only necessary when different from
                                     the last 2 digits of device number)
Time-Out . . . . . . . . . . . . . No   (Yes or No)
STADET . . . . . . . . . . . . . . Yes  (Yes or No)

Preferred CHPID  . . . . . . . . . __  +
Explicit device candidate list . No   (Yes or No)
```

Restricting Partition Access for Devices: You can restrict logical partition access to an I/O device on a shared channel path by using the explicit device candidate list to select which logical partitions can access that I/O device. On the Define Device / Processor panel enter `Yes` or `No` in the `Explicit device candidate list` field to specify whether you want to restrict logical partition access to an I/O device:

A `No` specifies that all logical partitions can access this I/O device. `No` is the default; all logical partitions are in this I/O device's candidate list.

A `Yes` specifies that only your selected logical partitions can access this I/O device. Note that the partition must also be in the channel path access or candidate list to access the device. On the Define Device Candidate List panel, place a slash (/) character to the left of each selected Partition Name.

If you specify `Yes` in the `Explicit device candidate list` field, the following panel is displayed:

```
──────────────── Define Device Candidate List ────────────────
                                                     Row 1 of 6

Select one or more partitions to allow them to access the
device, or ENTER to continue without selection.

Device number  . . : 01E1      Number of devices  . . . : 8
Device type  . . . : 3745
Processor ID . . . : PROC1     This is the main processor

/ Partition Name  Description                      Reachable
_ PROD1           First production partition       Yes
_ PROD2           Second production partition      Yes
_ TEST1           First test system                No
_ TEST2           Second test system               Yes
_ TEST3           CF partition                     No
_ TEST4           OS partition                     No
```

A `Yes` in the `Reachable` column indicates that the device can be reached from the respective partition, through at least one physical channel.

Defining OS-Related Definitions for a Device

1. After pressing the Enter key on the Define Device / Processor panel, the Device / Processor Definition panel is displayed again. Select another processor or press the Enter key again to display the Define Device to Operating System Configuration panel that shows all the defined OS configurations. You can then define the data about device parameters and features that is required by the operating system configuration.

```
──────────── Define Device to Operating System Configuration ────────────
                                                            Row 1 of 2

Select OSs to connect or disconnect devices, then press Enter.

Device number  . : 01E1          Number of devices  : 8
Device type  . . : 3745

/ Config. ID   Type     Description                      Defined
_ OPSYS01      MVS      MVS operating system
_ OPSYS02      VM       VM operating system
************************* BOTTOM OF DATA ***************************
```

2. Select an operating system and the ***Select (connect/change)*** action from the context menu (or action code **s**). A panel like the following one is displayed:

```
──────────────── Define Device Parameters / Features ────────────────
                                                            Row 1 of 4

Specify or revise the values below.

Configuration ID . : OPSYS01      MVS operating system
Device number  . . : 01E1         Number of devices  : 8
Device type  . . . : 3745

Parameter/  Value    P Req.  Description
Feature
ADAPTER     TYPE7    + Yes   Channel adapter type
OFFLINE     No               Device considered online or offline at IPL
DYNAMIC     Yes              Device supports dynamic configuration
OWNER       VTAM     +       Subsystem or access method using the device
**************************** BOTTOM OF DATA ************************
```

   The `Parameter/Feature` fields vary depending on the I/O device type and operating system type.

   A plus sign (+) in the `P` column indicates that you can use F4=Prompt to get a list of possible values for the parameter/feature in the same row.

   A `Yes` in the `Req.` field indicates that a value for the parameter/feature in the same row is required.

   You accomplish the change by accepting the default values or by changing the `Value` entries and pressing the Enter key. The default values are set in the UIM for the device type. For parameters you can specify different default values via the OS_PARM_DEFAULT keyword in the HCD profile.

3. After you have defined the device parameter and feature data and pressed the Enter key, HCD displays the Assign/Unassign Device to Esoteric panel.

```
──────────────────── Assign/Unassign Device to Esoteric ────────────────────
                                                                  Row 1 of 2

Specify Yes to assign or No to unassign. To view devices already assigned
to esoteric, select and press Enter.

Configuration ID : OPSYS01          MVS operating system
Device number  . : 01E1             Number of devices  : 8
Device type  . . : 3745             Generic  . . . . . : 3745

/ EDT.Esoteric  Assigned  Starting Number Number of Devices
_ A1.ES001      No        ____           ____
_ A2.ES002      No        ____           ____
**************************** BOTTOM OF DATA ******************************
```

4. On the Assign / Unassign Devices to Esoterics panel, overwrite the values in the `Assigned` column to assign (`Yes`) or unassign (`No`) devices to the selected esoterics.

   If you do not want to assign a complete group of devices, you can limit the range by specifying a starting number and the number of devices. If you omit the number of devices, 1 is assumed.

Changing Devices



To change device data, you have to follow the same panel flow as for defining a device:

1. Changing device and control unit definitions
2. Changing CSS-related definitions
3. Changing OS-related definitions

The following steps describe the panel flow and where you can change which data.

1. On the Device List panel select a device and the ***Change*** action from the context menu (or action code **c**).
2. On the following Change Device Definition panel you can change device and control unit definitions such as:
   - Serial number
   - Description
   - Control unit connections
   - Volume serial number

Note: You can also change these definitions as well as the device type by simply typing over the appropriate fields on the Device List panel.

3. After pressing the Enter key, the Device / Processor Definition panel is displayed. Select a processor and press the Enter key to change the following CSS-related definitions:
   - Unit address
   - Time-Out
   - STADET
   - Preferred CHPID
   - Explicit device candidate list
4. After pressing the Enter key twice , the Define Device to Operating System Configuration panel is displayed. Select an operating system and the ***Select (connect/change)*** action from the context menu (or action code **s**) if you want to change the following OS-related definitions:
   - Parameters/Features
   - Assignments to esoterics
5. After pressing the Enter key again, the Assign/Unassign Device to Esoteric panel is displayed. If you want to change the assignment of devices to esoterics, type over the values in the `Assigned` column by either `Yes` or `No`.
6. Press the Enter key twice to return to the Device List panel.

Changing CSS-Related Definitions of a Group of Devices



You can change CSS-related definitions of a group of devices by using the ***CSS group change*** action. This helps you, for example, to attach a group of DASDs to another control unit. To do this, the devices to be changed must be in the same device group, that is, they must all be of type, for example, DASD or TAPE.

1. On the I/O Device List panel select one or more devices and use the ***CSS group change*** action from the context menu (or action code **g**). The Change Device Group panel is displayed.

```
──────────────────────────── Change Device Group ────────────────────────────

 Specify the control units the devices are attached to.

 Connected to CUs . . 00D1  00D2  ____  ____  ____  ____  ____  ____  +
```

   HCD displays the definition of the first device in the group. You can modify this definition and HCD applies the definition to all devices in the group.
2. After pressing the Enter key HCD displays the Change Device Group / Processor Definition panel, where you can select the processors for which you want to change the CSS-related definitions. For an example of this panel, see page 133 that shows the Device / Processor Definition panel which is similar to the one you see here.

Changing Esoterics for a Group of Devices

For a description of how to change esoterics for multiple devices, refer to "Adding Devices to Esoterics" on page 97.

Changing OS-Related Definitions of a Group of Devices



You can change OS-related definitions for a group of devices by using the ***OS group change*** action. This helps you, for example, to attach a group of devices to another operating system. The device parameter/features will be the same for all devices in the group.

1. On the I/O Device List panel select one or more devices and use the ***OS group change*** action from the context menu (or action code **o**). HCD displays the Change Device Group / Operating System Configuration panel.

```
Change Device Group / Operating System Configuration
                                                          Row 1 of 1
 Command ===> ____________________________________________ Scroll ===> PAGE

 Select OSs to connect or disconnect devices, then press Enter.

 / Config. ID   OS Type  Description                      Defined
 _ OPSYS01      MVS      MVS Operating System             Yes
 ***************************** Bottom of data ******************************

F1=Help        F2=Split       F3=Exit        F4=Prompt      F5=Reset
F7=Backward    F8=Forward     F9=Swap       F12=Cancel     F22=Command
```

2. Select the operating system to which you want to attach the group of devices and the ***Select (connect/change)*** action from the context menu (or action code **s**). A panel like the following one is displayed.

```
Define Device Group Parameters / Features
                                                          Row 1 of 4
 Command ===> ____________________________________________ Scroll ===> PAGE

 Specify or revise the values below.

 Configuration ID . : OPSYS01      MVS Operating System

 Parameter/
 Feature     Value    P Req.  Description
 ADAPTER     TYPE7    + Yes   Channel adapter type
 OFFLINE     No               Device considered online or offline at IPL
 DYNAMIC     Yes              Device supports dynamic configuration
 OWNER       VTAM     +       Subsystem or access method using the device
 ***************************** Bottom of data ******************************

 F1=Help        F2=Split       F3=Exit        F4=Prompt      F5=Reset
 F7=Backward    F8=Forward     F9=Swap       F12=Cancel     F22=Command
```

3. You accomplish the change by accepting the default values or by changing the `Value` entries and pressing the Enter key.

The specified device parameters/features are applied to all devices of the group.

Changing the DYNAMIC or LOCANY Parameter of a Group of Devices



You can change the DYNAMIC or LOCANY parameter of a group of devices by using the ***Attribute group change*** action. This function helps you to change parameters for a group of devices without having to use the ***Change*** action for each device individually.

This function can only be invoked from the I/O Device List accessible from the Operating System Configuration List panel.

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***.
2. Select an operating system and select the ***Work with attached Devices*** action from the context menu (or action code **u**). HCD displays the I/O Device List panel.
3. Select one or more devices on the I/O Device List panel and the ***Attribute Group change*** action from the context menu (or action code **e**). HCD displays the Attribute Group Change panel:

```
──────────────────────── Attribute Group Change ────────────────────────


For all devices in the selected group, choose whether ...

__   1.  Allow dynamic configuration ........... DYNAMIC=YES
     2.  Do not allow dynamic configuration .... DYNAMIC=NO
     3.  UCB can reside in 31 bit storage ...... LOCANY=YES
     4.  UCB can not reside in 31 bit storage .. LOCANY=NO
```

   Select the appropriate parameter.

HCD only changes the single parameter for all devices of the group, leaving the other parameters/features of the group unchanged.

Changing Type/Model of a Group of Devices



You can change the type or model for a group of devices by using the ***Device type group change*** action. However, you have to make sure that all devices to be changed in one step have the same device type and model. The control units the devices are attached to, have to support the attachment of the new device type as

well, and required parameters have to be identical. The new device type has to be supported by the same operating system type.

1. Select one or more devices on the I/O Device List panel.
2. Use the ***Device type group change*** action from the context menu (or action code **t**). HCD displays the Device Type Group Change panel.

```
──────────────── Device Type Group Change ────────────────

Specify a new device type-model.

Current device type-model  . : 3380

New device type-model  . . . . 3390_________  +
```

Specify a new device type-model.

Changing the Device Number



To change the number of a device:

1. Remove the connections to the control units for the devices to be changed as follows:
   a. On the Device List panel, select the devices to be changed and the ***CSS group change*** action from the context menu (or action code **g**). The Change Device Group panel is displayed.
   b. Remove the control unit numbers from the panel and press the Enter key.
2. On the Device List panel select the device and the ***Add like*** action from the context menu (or action code **a**). The Add Device panel is displayed.
3. Specify the new number for the device and the control unit numbers to which the devices are to be attached. Press the Enter key. HCD now displays a series of panels showing the settings of the previously selected device (the one to be changed). The settings are propagated to the new devices. Press the Enter key until HCD redisplays the Device List panel now showing the new device.
4. Delete the old device by selecting the device and selecting the ***Delete*** action from the context menu (or action code **d**).

Disconnecting Devices from an Operating System



Perform the following steps to disconnect a device from an operating system.

1. On the I/O Device List panel select a device and the ***Change*** action from the context menu (or action code **c**).
2. On the following Change Device Definition panel, press the Enter key.
3. On the following Device / Processor Definition panel, press the Enter key once again. HCD displays the Define Device to Operating System Configuration panel.

```
──────────── Define Device to Operating System Configuration ──────────────
                                                              Row 1 of 2

Select OSs to connect or disconnect devices, then press Enter.

Device number  . : 01D1          Number of devices  : 1
Device type  . . : 3390

/ Config. ID   Type     Description                      Defined
  OPSYS01      MVS      MVS operating system             Yes
_ OPSYS02      VM       VM operating system
************************* BOTTOM OF DATA ***************************
```

4. On the Define Device to Operating System Configuration panel select an operating system and the ***Disconnect from OS*** action from the context menu (or action code **n**). The Define Device to Operating System Configuration panel is displayed again without showing a `Yes` in the `Defined` column.

Disconnecting Multiple Devices from an Operating System

If you want to disconnect multiple devices from one operating system in one step, open the I/O device list via the OS configuration list. On the I/O Device List panel, select one or multiple devices and use ***Disconnect from OS*** action from the context menu (or action code **n**).

Showing or Hiding Parameter/Feature Definitions of Devices



You can define up to five parameters/features for a device that can be shown on the I/O Device List panel in addition to the default information. These parameters/features will be retained across sessions.

1. On the Operating System Configuration List panel, use the ***Work with attached devices*** action from the context menu (or action code **u**).
2. On the following Device List panel select the ***Show device parameters/features*** pull-down choice from the ***Show/Hide*** action bar (no action code available).
3. On the following Device Parameters/Features Profile panel, you can specify up to five parameters/features that will be displayed on the I/O Device List panel.

```
──────────────────── Device Parameters / Features Profile ────────────────────


 Specify or revise the device parameters or features to be displayed in the
 I/O Device List for an operating system configuration.

 Parameters/
 features . . LIBRARY     SHARED      OFFLINE     __________  __________  +

  F1=Help   F2=Split   F3=Exit   F4=Prompt   F5=Reset   F9=Swap   F12=Cancel
```

4. On the I/O Device List panel, use the F20=Right key to scroll to the rightmost part of the panel, where the information is displayed. Note that the DYNAMIC parameter and LOCANY parameter are default information that is also shown on the leftmost part of the I/O Device List panel.

```
  Goto  Show/Hide  Filter  Backup  Query  Help
-------------------------------------------------------------------------------
                                I/O Device List       Row 1 of 11 More: <

Select one or more devices, then press Enter. To add, use F11.

Configuration ID . . : OPSYS01      MVS operating system

  -------Device-------
/ Number Type          LIBRARY    SHARED     OFFLINE
_ 0001   3278-3                              No
_ 0098   9033                                Yes
_ 00C1   3480          No                    No
_ 01D1   3390                     No         No
_ 01D2   3390                     No         No
_ 01D3   3390                     No         No
_ 01D4   3390                     No         No
_ 01D5   3390                     No         No
_ 01D6   3390                     No         No
_ 01D7   3390                     No         No
_ 01D8   3390                     No         No
```

You can filter the shown devices by device parameters and features using the ***Set Filter*** function. On the Filter I/O Device List panel, you can specify a value for any displayed parameter/feature you want to use for filtering.

In case you no longer need the parameters/features to be displayed, you use ***Hide device parameters/features*** pull-down choice from the ***Show/Hide*** action bar on the I/O Device List panel.

Priming Device Data



You can prime your I/O configuration in a work IODF with the device serial numbers and volume serial numbers (VOLSER) for the active processor. For the prerequisites for this function refer to "Prerequisites" on page 9.

To prime, select the action ***Prime serial number and VOLSER*** from the context menu (or action code **i**) on the I/O Device List panel.

The Confirm Priming Device Data List panel shows the selected devices with the sensed data for the device types and serial numbers, and their corresponding definitions in the IODF. For DASD devices, the sensed VOLSER is also shown on this panel.

```
                    Confirm Priming Device Data List
                                                                  Row 1 of 8
Command ===> ___________________________________________ Scroll ===> CSR

Press Enter to confirm priming, or Cancel to leave the list. A blank value
will not change the IODF definition.

Device ---------- Type ----------- --- Serial Number --- --- VOLSER ---
Number actual        defined       sensed     defined    sensed defined
0AF0   3390-B3C      3390          B9888      B9888      PETHS2 PETHS2
0AF1   3390-B3C      3390          B9888      B9888      D83NE2 D83NE2
0AF2   3390-B3C      3390          B9888      B9888      D83WL4 D83WL4
0AF3   3390-B3C      3390          B9888      B9888      D83WL5 PETOFF   1
0AF4   3390-B3C      3390          B9916      A9999      PETCAT PETCAT
0AF5   3390-B3C      3390          B9916      B9916      PETDL2 PETDL2
0AF6   3390-B3C      3390          B9916                 TSOPAK         2
0AF7   3390-B3C      3390          B9916      B9916      CMNAF7 CMNAF7
**************************** Bottom of data ******************************



 F1=Help        F2=Split       F3=Exit        F5=Reset       F7=Backward
 F8=Forward     F9=Swap       F12=Cancel
```

1 The values that are defined in the IODF and that are sensed are different. Press Enter, to overwrite the defined data by the sensed data.

2 No values are defined in the IODF, but the sensed data of the active system is available. To confirm the sensed data, and to define them in the IODF, press Enter.

Note: The sensed values can only be blanked out or left unchanged.

Blank out the sensed values, if you don't want to change the defined IODF values.

To confirm priming, press Enter.

Use the F12=Cancel key, if you don't want to use the sensed values, and to leave the list.

Deleting Devices



You can delete the definition of a device by using the ***Delete*** action from the context menu (or action code **d**). If you delete a device, all connections to the operating system including esoterics and EDTs are also deleted.

Working with Operating System Consoles



The following procedure describes how to specify which devices MVS can use as NIP consoles and which devices VM can use as VM consoles. Before you can define consoles you must have defined these I/O devices to the operating system.

1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Operating system configurations***. HCD displays the Operating System Configuration List panel showing all OS configurations currently defined in the IODF.
2. Select an OS configuration and the ***Work with consoles*** action from the context menu (or action code **n**). HCD displays the NIP or VM Console List panel (depending on the type of the selected operating system).

```
──────────────────────────── NIP Console List ────────────────────────────
  Goto  Backup  Query  Help
 ------------------------------------------------------------------------
                                                                Row 1 of 1

 Select one or more consoles, then press Enter. To add, use F11.

 Configuration ID . : OPSYS01      MVS operating system

 / Order   Device  Device Type
   Number  Number
 _   1     0001    3278-3
 ************************** BOTTOM OF DATA ****************************
```

3. Use F11=Add to define each console. The following panel is displayed:

```
                    Add NIP Console
 Specify the following values.

 Device number of console . . . . . . ____

 Order number . . . . . . . . . . . . 1
```

The order number is the sequence the consoles are used by the operating system.

Changing Operating System Consoles



You can change the order number of an operating system console by just typing over the corresponding column or by using the ***Change*** action from the context menu (or action code **c**) on the Console List panel.

Deleting Operating System Consoles



You can delete the definition of an operating system console by using the ***Delete*** action from the context menu (or action code **d**) on the Console List panel. The devices are not deleted.

Viewing Information

HCD offers several possibilities to view information that might be helpful when defining or maintaining your configuration data.

Viewing Object Definitions

To view information about objects that are defined in your configuration, select the ***Define, modify, or view configuration data*** option from the primary task selection panel. From the resulting panel, select the desired object to get the appropriate list panel, on which you can use ***Work with object*** actions from the context menu that lead to further list panels that display other related objects. You can use these panels to define, modify, and view configuration data. See Figure 35 on page 88 on how to navigate to related list panels of different objects.

Viewing Full Definition of an Object

You can ask HCD to display, for viewing only, the full definition of an object. This might include additional information that is not displayed on the action list panel.

To view object definitions select an object on an action list and use the ***View object definition*** action (or action code **v**).

This following lists offer this possibility:

- Processor list
- Channel path list
- Control unit list
- Device list

Viewing Additional Object Lists

Besides the action list panels shown in Figure 35 on page 88, there are list panels, on which you can only view information about objects without being able to change it. You can navigate to these lists by using the ***View objects*** actions from the context menu. HCD offers ***View objects*** actions on the following panels:

List Panel	View
Channel Path List	Connected switches
Partition List	Attached channel paths Attached control units Attached devices
Operating System List	Generics
Generics List	Devices
Esoteric List	Devices

Viewing Graphically

HCD offers you the possibility to view a graphical representation of the configuration.

Use the ***Create or view graphical configuration report.*** on the primary task selection panel to view the entire configuration. To view objects in context of their attached objects you can also select an object from an action list panel and use the ***View graphically*** action from the context menu (or action code **h**). The following object lists support this possibility:

- Channel path list
- Control unit list
- I/O device list (only for devices that connect to a control unit)
- Partition list
- Switch list

For more information on how to view a graphical report, refer to "Create or View Graphical Configuration Reports" on page 218.

Viewing Logical Control Units

On a control unit or device list panel, you can display the groups of *logical control units* that HCD has created to represent the physical control units defined in a configuration. Logical control units are used by the CSS to schedule the processing of I/O requests.

Viewing Coupling Facility Information

HCD lets you view information for a specific CF channel path. You can view, for example, access and candidate list of selected channel paths and information on the CF control units and devices in a CF channel path connection.

On the CF Channel Path Connectivity List panel, select a channel path and one of the following actions:

- The ***View source channel path definition*** action displays the View Channel Path Definition panel for the source channel path of the CF connection.
- The ***View destination channel path def.*** action displays the View Channel Path Definition panel for the destination path of the CF connection.
- The ***View CF control unit and devices*** action displays the View CF Control Unit and Devices panel that shows the CF control unit number(s), the starting CF device number(s), and the range of devices defined for a CF connection.

Viewing CTC Connections

HCD offers you the possibility to view and verify your CTC connections that are defined through a switch. You can view existing CTC connections including online diagnostic messages on the following lists:

- Processor list
- Partition list
- Channel path list
- Control unit list
- Device list

These CTC connection lists lets you immediately verify whether your definitions are done correctly.

A CTC connection requires a CTC channel at one end of the connection and a CNC or FCV channel at the other end of the connection. The two channels can be considered as communicating directly with each other in a peer-to-peer fashion. Each channel defines the channel at the other end of the CTC connection as a CTC control unit. This is illustrated in Figure 41 on page 149.

FICON Channel-to-Channel Support

FCTC support differs from ESCON CTC support not only in the channel types used. The main differences are as follows:

- An FCTC connection is given via a FICON channel path on each side of the FCTC communication line.
- It is possible to have an FCTC connection between the LPARs of the same CEC via a single FICON channel path in a switched environment.

In order to be usable as an FCTC connection channel, a FICON channel path must be defined to an FCTC control unit which is connected to FCTC devices.



Figure 41. CTC/CNC Connection Established Using a Dynamic Connection.

The entry port of the channel at the other end of the CTC connection corresponds to the link address of the control unit representing the channel.

The CTC devices associated with the control units at both ends of the CTC connection may have different device numbers, but they must have the same unit address. The device type of both devices must be the same (for example, SCTC or BCTC).

Restrictions: HCD can only show CTC connections, if the connected processors are defined in one IODF and the CNC/FCV and CTC channel paths have a dynamic connection to the same ESCON director. CTC connections using a stand-alone CTC adapter cannot be shown. Furthermore, CTC connections running via chained ESCON directors cannot be determined.

CTC Connections with Shared Channels

If your processor has MIF support you can share your channels among several partitions to save physical connections. The following figure shows you the case when a CNC channel is shared between two partitions. The CTC channel will need a separate control unit definition for each partition sharing the CNC channel. Each of these control unit definitions has the same destination link address but the control unit logical addresses (CUADD) must be different. The control unit logical address must correspond to the image number of the logical partition.

Note: If the target channel path is non-shared, either you must not specify a control unit logical address, or its value must be 0.



Figure 42. CTC/CNC Connection Established Using Shared Channels.

For further specification rules, refer to the *IOCP User's Guide* for your processor.

How to View CTC Connections

You can use the new action ***View related CTC connections*** (or action code **k**) on the following lists:

- Processor list
- Partition list
- Channel path list
- Control unit list
- Device list

A panel similar to the following one is displayed:

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                             CTC Connection List     Row 1 of 14 More:       >

Select CTC connections to view CTC Messages, then press Enter.

  -------------CTC side------------- -----------CNC/FCV side-----------
/ Proc.    Part.    Devices  CH CU   Proc.    Part.    Devices  CH CU   Msg.
_ PROC001A          0500,5   20 1020 PROC001           0100,5   10 1010 G750I
_ PROC001A          0690,1   20 0069                                    G752I
_ PROC002           0650,1   11 0065 PROC002           0660,1   13 0066 G753I
_ PROC002           0680,1   11 0068                                    G752I
_ PROC002           0701,1   12 0050 PROC003  PART1    0301,1   10 1012
_ PROC002           0800,5   22 0060 PROC003  PART2    0400,5   11 1013
_ PROC002           0805,1   22 0060 PROC003  PART2    0405,1   11 1013 G751I
_ PROC002           0806,3   22 0060 PROC003  PART2    0406,3   11 1013
_ PROC002           2400,1   24 0024                                    G756I
_ PROC003  PART1    1105,1   21 0105 PROC001           1106,1   10 0106
_ PROC003  PART1    1107,1   21 0107 PROC002           1108,1   26 0108 G750I
                                      PROC002           0200,2   10 1011 G757I
                                      PROC003  PART1    0300,1   10 1012 G754I
                                      PROC003  PART2    0300,2   10 1012 G754I
```

This panel shows the definitions of the CNC/FCV side in relation to the definitions of the CTC side, such as processor, partition, channel path, control unit, and device information.

Incomplete CTC Definitions: If the CTC connection is not correctly defined, the fields on the CTC Connection List panel can be incomplete and an error message is shown. For example, G754I in column Msg. refers to message CBDG754I, which indicates that HCD cannot determine the connection, because no control units and devices match to the processor, partition, control unit, and device of the same row.

Displaying More Detailed Information

Scroll to the right to see more detailed information about the CTC side of the connection, such as channel path mode, switch information, detailed control unit and device information.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                       CTC Connection List (CTC or FC)  Row 1 of 14 More: <>

Select CTC connections to view CTC Messages, then press Enter.

           -Partition-- --Devices-----     -CHPID- Entry Dyn      Link CU
/ Proc.    Name     Num Number  Type OS UA ID Mode SW PO SW  CU   Addr ADD
_ PROC001A              0500,5  BCTC N  00 20 DED  05 F0 05  1020 E120
_ PROC001A              0690,1  SCTC N  00 20 DED  05 F0 05  0069 E728
_ PROC002               0650,1  SCTC N  00 11 DED  05 E7 05  0065 E840
_ PROC002               0680,1  SCTC N  00 11 DED  05 E7 05  0068 F0
_ PROC002               0701,1  SCTC N  01 12 DED  05 D0 05  0050 F4   1
_ PROC002               0800,5  SCTC N  00 22 DED  05 D7 05  0060 F3   2
_ PROC002               0805,1  BCTC N  05 22 DED  05 D7 05  0060 F3   2
_ PROC002               0806,3  SCTC N  06 22 DED  05 D7 05  0060 F3   2
_ PROC002               2400,1  SCTC N  00 24 DED  04 E0 05  0024 E0
_ PROC003  PART1    1   1105,1  SCTC N  00 21 DED  05 F7 05  0105 E1
_ PROC003  PART1    1   1107,1  SCTC N  00 21 DED  05 F7 05  0107 F8
```

Scroll once again to the right to see the same detailed information for the CNC/FCV side of the connection.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                         CTC Connection List (CNC/FCV or FC)  Row 1 of 14 More: <

Select CTC connections to view CTC Messages, then press Enter.

           -Partition-- ----Devices-----    -CHPID- Entry Dyn      Link CU
/ Proc.    Name     Num Number   Type OS UA ID Mode SW PO SW  CU   Addr ADD
_ PROC001               0100,5   BCTC N  00 10 DED  05 E1 05  1010 F0   0
_
_ PROC002               0660,1   SCTC N  00 13 DED  05 E8 05  0066 E7
_
_ PROC003  PART1    1   0301,1   SCTC N  01 10 SHR  05 F4 05  1012 D0
_ PROC003  PART2    2   0400,5   SCTC N  00 11 SHR  05 F3 05  1013 D7
_ PROC003  PART2    2   0405,1   SCTC N  05 11 SHR  05 F3 05  1013 D7
_ PROC003  PART2    2   0406,3   SCTC N  06 11 SHR  05 F3 05  1013 D7
_
_ PROC001               1106,1   SCTC N  00 10 DED  05 E1 05  0106 F7
_ PROC002               1108,1   SCTC N  00 26 DED  05 F8 05  0108 F7   1
_ PROC002               0200,2   SCTC N  00 10 DED            1011 C5
_ PROC003  PART1    1   0300,1   SCTC N  00 10 SHR  05 F4 05  1012 D0
_ PROC003  PART2    2   0300,2   SCTC N  00 10 SHR  05 F4 05  1012 D0
```

Filtering CTC Definitions

To get a better overview of your CTC connections you can filter the list by specifying different filter criteria. Select action bar ***Filter*** and then ***Select filter***. The following panel appears:

```
                         Filter CTC Connections

 Specify or revise the following filter criteria and press Enter.

 Message ID  . . . . _____
 Device type . . . . ____  (SCTC/BCTC/FCTC)
 Dynamic switch  . . __  +

 CTC side                          CNC/FCV or FC side
 Processor . . . . . _______  +    Processor . . . . . _______  +
 Partition . . . . . _______  +    Partition . . . . . _______  +
 CHPID . . . . . . . __            CHPID . . . . . . . __

 CU number . . . . . ____          CU number . . . . . ____
 Starting device no. ____          Starting device no. ____
 Defined to OS . . . _  (Y/N)      Defined to OS . . . _  (Y/N)
```

Printing CTC Connection Lists

You can also print the list panel by using the SAVE command as described in "Print List Panels" on page 225.

Displaying Diagnostic Messages

Select one or more CTC connections and press the Enter key to display diagnostic messages for the connections.

For each connection, HCD displays one message, even if the connection includes several errors. HCD displays the messages according to the following priority list:

1. CBDG750I — Logical address (CUADD) is specified for CU @1, but CHPID @2 of processor @3 is not defined as shared.
2. CBDG751I — Device type of device @1 connected to processor @2, CHPID @3 does not match with device type of device @4 on the other side.
3. CBDG752I — Channel path type error. CHPID @1 of processor @2 is connected to a CHPID @3 of processor @4 with the same type.
4. CBDG753I — Wrap around connection detected for processor @1 (partition @2) via CHPID @3 and CHPID @4.

A message list may look as follows. The messages are sorted by severity.

```
  Save  Query  Help
-------------------------------------------------------------------------
                              Message List                    Row 1 of11
Command ===> ___________________________________________ Scroll ===> PAGE

Messages are sorted by severity. Select one or more, then press Enter.

/ Sev Msg. ID  Message Text
_ E   CBDG750I Logical address (CUADD) is specified for CU 1010,
#              but CHPID 20 of processor PROC001A is not defined as
#              shared.
_ E   CBDG752I Channel path type error. CHPID 20 of processor PROC001A
#              is connected to CHPID 11 of processor PROC002 with the
#              same type.
_ W   CBDG753I Wrap around connection detected for processor PROC002
#              (partition - none -) via CHPID 11 and CHPID 13.
_ I   CBDG756I HCD cannot determine connection. CHPID 24 of processor
#              PROC002 is connected via chained switches.
```

Chapter 7. How to Work with Switches

Overview

This chapter explains:

- The possibility of switch (ESCON Director or Fibre Channel switch) connections
- The advantages when you define switches with HCD
- How to work with switches (defining, changing, priming, deleting)
- How to work with connections to switches (channel paths, control units, priming switch port names and connections, actions on the Port List panel)
- How to work with switch configuration data (defining, changing, deleting)
- How to migrate, activate, and save switch configuration data

With the introduction of the ESCON architecture and its supporting hardware, ESCON Directors (switches) became an integral part of the configuration. With the FICON architecture, FC switches are supported.

You can define switches, switch connections and how the switches are physically cabled. A switch configuration, also called port matrix, defines how the various ports of the switch connect to each other. For example, the switch configuration defines whether a port is blocked, has a dedicated connection to another port, or whether dynamic connections to other ports are allowed or prohibited. In other words, the switch configuration defines the inside of a switch.

Possibilities of Switch Connections

ESCON Directors (ESCDs) enable either dynamic connections or dedicated connections. FC switches allow only the definition of dynamic connections.

HCD supports fabrics containing cascade switching using FICON switches. Such a fabric consists of two or more FICON switches.

Note: Other than for chained ESCON switches where the dynamic switch for a channel path specifies the switch containing the port address that is used as link address, in the FICON case the dynamic switch ID is always the channel path entry switch.

The following four figures illustrate the path types of switch connections for ESCON Directors or FC switches. For FC switches, only the first and the fourth configuration type is supported. Figure 43 on page 154 shows a configuration with a single switch; the entry switch is the dynamic switch. (The dynamic switch in HCD corresponds to the SWITCH keyword of the CHPID macroinstruction from the IOCP point of view.)

© Copyright IBM Corp. 1994, 2002



Figure 43. Example of a Configuration with One Switch

Figure 44 shows a configuration with two switches, where the entry switch is different from the dynamic switch. (The two switches are chained and the entry switch for the channel path has a dedicated connection.)



Figure 44. Example of a Configuration with Two Switches

Figure 45 on page 155 shows a configuration with two switches, where the entry switch is the same as the dynamic switch. (The two switches are chained and the CU switch has a dedicated connection.)



Figure 45. Example of a Configuration with Two Switches

Figure 46 shows a configuration with cascading switches. The fabric in this figure contains two cascading FICON switches. The link address `5904` specifies `59` as switch address and `04` as port address.

> **Note:**
> The switch address is unique within a fabric, but may occur also in other cascaded switch fabrics. However, as HCD has no knowledge of which switches are within the same fabric, it is highliy recommended to assign unique switch addresses across fabrics, for example, by using the switch IDs as switch addresses.



Figure 46. Example of a Configuration with a FICON Two-Switch Cascading Switching

Advantages of Switch Definitions with HCD

You have the following advantages when you define switches with HCD:

- More rigorous validation of the configuration definition.

  If all switches between the channels and control units are defined, HCD can determine whether a valid path exists between the processor and control unit. For example, HCD can validate that the destination link address specified for a channel path is a valid port on the dynamic switch.
- The possibility to define several switch configurations for each switch.
- The possibility to define and activate switch configurations without leaving HCD (from the same *workplace*).

  If you have defined a switch configuration using HCD, you can activate the switch configuration without leaving HCD and do not need any knowledge about other operating system components that are involved in the activation process.
- The possibility to define a switch as CU, device, and switch as such, to:
  1. Migrate an active switch configuration from a switch, or a saved switch configuration from a switch file, or convert an ISPF table to a HCD switch configuration for later manipulation by HCD.
  2. Send switch configuration data from an IODF to a switch, making it the active port matrix, or save it in a switch file.
- Graphical configuration reports include switch connections.

Note: HCD supports a generic FC switch (type FCS) supporting port addresses 00 to FF. This switch type does not support a switch control unit and switch device and therefore can not be accessed by I/O Operations functions like migrate or activate switch configuration.

Defining Switches

To define switches and their associated ports, you need to

- define switch characteristics,
- define connections to channel paths, control units, and other switches,
- define switch configuration data (port matrix).

Working with Switches

In this section, you can learn how to define, change, prime, and delete switches.

Defining Switch Characteristics



1. On the primary task selection panel, select ***Define, modify, or view configuration data*** and on the resulting panel the object ***Switches***. HCD displays the list of all switches currently defined in the IODF.

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                                Switch List         Row 1 of 6 More:       >
Command ===> ___________________________________________________ Scroll ===> PAGE

Select one or more switches, then press Enter. To add, use F11.


                                                                  CU   Dev
/ ID Type +        Ad Serial-# + Description                      Num. Num.
_ 01 2032          21 10145      Switch 01                        0701 0701 >
_ AA 9032          __ 10146      Switch AA                        001A 001A >
_ AB 9032          __ 10147      Switch AB                        001B 001B >
_ AC 9032          __ 10678      Switch AC                        001C 001C
_ AD 9032          __ 10679      Switch AD                        001D 001D
_ AE 9032-3        __ 20995      Switch AE                        001E 001E
****************************** Bottom of data ********************************


F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Back
F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Inst
F20=Right    F22=Command
```

Figure 47. Switch List (Left Part)

The Switch List panel (left part), Figure 47, lists one switch control unit and device. If there is more than one switch control unit and device, the list entry gets an indication ('>'). With the F20=Right key, you can scroll to the right part of the Switch List panel. Up to five switch control units and devices can be shown. If there are more, an indication is given for the corresponding entry ('Yes' in column 'More?' on the right part of the Switch List panel). These additional switch control units and devices can be viewed, for example, on the Port List for port FE.

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                                Switch List                        Row 1 of 6
Command ===> ___________________________________________ Scroll ===> PAGE  <

Select one or more switches, then press Enter. To add, use F11.

                   CU   Dev   CU   Dev   CU   Dev   CU   Dev   CU   Dev   More?
/ ID Type +        #1   #1    #2   #2    #3   #3    #4   #4    #5   #5
--------------------------------------------------------------------------------
_ 01 2032          0701 0701  0702 0702  0703 0703  0704 0704  0705 0705  Yes
_ AA 9032          001A 001A  002A 002A  003A 003A
_ AB 9032          001B 001B  002B 002B  003B 003B
_ AC 9032          001C 001C
_ AD 9032          001D 001D
_ AE 9032-3        001E 001E
****************************** Bottom of data ********************************


  F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
  F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
 F19=Left     F22=Command
```

Figure 48. Switch List (Right Part)

2. Use the F11=Add key to add a new switch.

```
                          Add Switch


Specify or revise the following values.

Switch ID . . . . . . . . 99  (00-FF)
Switch type . . . . . . . 9032          +
Serial number . . . . . . ASW3333333
Description . . . . . . . First Switch___________________
Switch address  . . . . . __  (00-FF) for a FICON switch

Specify the port range to be installed only if a larger range
than the minimum is desired.

Installed port range  . . C0  -  FB  +

Specify either numbers of existing control unit and device, or
numbers for new control unit(s) and device(s) to be added.

Switch CU number(s) . . . 0099  ____  ____  ____  ____  +
Switch device number(s) . 0099  ____  ____  ____  ____

F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
F12=Cancel
```

Figure 49. Add Switch

HCD allows you to specify the port range of a switch to be set to installed, if more ports are to be used than the minimum range. Specify the first and last port of the range you want to use. If you do not specify values for the Installed port range field, the hardware status of the minimum range of supported ports is set to installed.

In order to allow consistency checks for the configuration, when adding a new switch, you can optionally define a switch address for a FICON switch.

You can also specify control unit numbers and device numbers for the switch.

On the Add Switch panel you can initially define up to five switch control units and devices for the switch. To define more than five switch control units and devices, or to add additional switch control units and devices later, you must use the control unit and device definition dialogs.

If you specify switch control units that do not yet exist, they are automatically added as new objects to the IODF, and are connected to the switch through the switch control unit port. In this case, you need to specify new switch devices. The switch devices are also automatically added as new objects to the IODF and connected to the switch through the switch control units. However, to complete the configuration path, you must attach the switch control units and switch devices to a processor, and then you can assign the switch devices to an operating system.

If the switch control units already exist, they are automatically connected to the control unit port on the newly defined switch. In this case, you do not need to specify switch devices. If you do, the switch devices must already exist and be attached to the designated switch control units.

Specified serial numbers or descriptions are also copied to the switch control units and switch device definitions.

3. After you press the Enter key, HCD redisplays the updated Switch List panel.
   - Connect the switch control units to the processor (which also connects the switch devices to the processor). To specify additional parameters use the ***Change*** action on the Control Unit List panel. For details, see "Defining Processor Attachment Data" on page 124.
   - Connect the switch devices to the operating system. Use the ***Change*** action on the I/O Device List panel. For details, see "Changing Devices" on page 137.

Changing Switch Data



To change the following switch characteristics, you can type over the columns on the Switch List panel, or you can use the ***Change*** action from the context menu (or action code **c**) on the Switch List panel:

- Switch type
- Serial number and description

When you change the type, serial number, or description of the switch, the control units, and devices attached to the switch are also updated.

```
                    Change Switch Definition

 Specify or revise the following values.

 Switch ID  . . . . . . . . . . : 01
 Switch type  . . . . . . . . . 2032          +
 Switch address . . . . . . . . 21            +

 Serial number  . . . . . . . . 10145      +
 Description  . . . . . . . . . Switch 01

  F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
 F12=Cancel
```

Figure 50. Change Switch Definition

Priming Switch Data



You can prime your I/O configuration in a work IODF with the switch serial number for the active processor. For the prerequisites for this function see "Prerequisites" on page 9

To prime, select the action ***Prime serial number*** from the context menu (or action code **i**) on the Switch List panel.

The Confirm Priming Switch List panel shows the selected switches with the sensed data for the switch types, serial numbers, switch control units, and switch device numbers, and their corresponding definitions in the IODF.

Note: Only one defined switch control unit and one defined switch device is shown even if several have been defined. If the sensed switch control unit and device is one that has been defined, it will be displayed. Otherwise the defined switch control unit and device with the lowest control unit number will be displayed.

An update of the switch serial number also updates the serial number of the corresponding switch control units and switch devices.

The sensed data for the switch serial numbers are shown on the Confirmation panel, and can be accepted, or rejected before being incorporated into the IODF. If a value is blanked out, the defined IODF value is not changed. If you use the F12=Cancel key, none of the sensed values is used.

```
                    Confirm Priming Switch Data List
                                                                  Row 1 of 2
Command ===> ___________________________________________ Scroll ===> CSR

Press Enter to confirm priming, or Cancel to leave the list. A blank value
will not change the IODF definition.

Sw ---------- Type ----------- --- Serial Number --- CU Number Dev Number
ID actual        defined       sensed     defined    act  def  act  def
00 9033-1        9033          10139                 9033 9033 9000 9000
01 9032-3        9032-3        20290                 9032 9032 9001 9001
**************************** Bottom of data ******************************



 F1=Help        F2=Split       F3=Exit        F5=Reset       F7=Backward
 F8=Forward     F9=Swap       F12=Cancel
```

Figure 51. Example of a Confirm Priming Switch Data List panel

Moving Ports



When selecting ***Move Ports***, HCD offers the possibility of moving control unit, channel path or switch port connections on the same switch or from other switches to the selected target switch.

To perform this action, select the target switch for a port move action on the Switch List panel (see Figure 47 on page 157). The panel Actions on selected switches appears and the action ***Move Ports*** can be selected. You can also reach this panel directly by typing in the action code **x** next to the appropriate switch in the Switch List menu. This brings up the following panel Move Ports to a Target Switch.

```
──────────────────────── Move Ports to a Target Switch ────────────────────────
                                                                   Row 1 of 256
Command ===> ____________________________________________ Scroll ===> PAGE

Specify ports to be moved to the specified target.

------- Source -------  ---- Target ----
         Port Range            Starting
Switch + Start + End +  Switch  Port +
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __
__       __      __     AA      __

 F1=Help        F2=Split       F3=Exit        F4=Prompt       F5=Reset
 F7=Backward    F8=Forward     F9=Swap       F12=Cancel      F22=Command
```

Figure 52. Example of a Move Ports to a Target Switch panel

This panel contains data entry fields for the ports to be moved. It is also possible to move a range of ports from a switch to the target switch occupying subsequent port addresses starting with the target port address specified. The target switch field in this panel has been preset and cannot be changed.

Depending on the context, HCD performs the following as part of the ***Move Ports*** action:

- Copies the attributes of the source port to the target port (and set the target port to installed, if necessary).
- Disconnects all source ports from the connected units.
- Connects all target ports to the units previously connected to the source ports.
- Copies existing port configurations of the source port if the move is on the same switch and port configurations exist. The source port configurations will be set to default, i.e., all dynamic and dedicated connections are reset.
- Changes the dynamic switch of the connected channel path to the target switch if the source switch serves as a dynamic switch and the target switch is different from the source switch.

- Changes the link address to the target port if the source port serves as a link address to a channel path connection for a control unit and is connected to a control unit or another switch.

Note: HCD does not perform any checks on whether the user also moves implied ports as well. For example, if a channel path is moved to another switch, the control units that are connected to the channel path must also be moved. Moving a control unit may imply that connected channel paths must be moved as well. If not all implied ports are moved, the configuration may become invalid and a validation error will be shown either during the ***Move Ports*** action or later during the ***Build Production IODF*** action.

Note: If the target switch has switch configurations defined and the port move occurs between different switches, then the switch configurations must be adapted after the port move action.

The ***Move Ports*** action is especially of value when consolidating switches or installing new switches.

Deleting Switches



You can delete the complete definition of a switch or switch configuration by using the ***Delete*** action from the context menu (or action code **d**) on the Switch List panel or Switch Configuration List panel. This also deletes the connections from the ports to channel paths, control units, and other switches. The link address and dynamic switch definitions for a channel path are not deleted.

The Confirm Delete Switch panel shows all the switch control units and devices that will be deleted with the switch. If you don't want them to be deleted with the switch, disconnect the control units from port FE of the switch, before you delete the switch.

```
                          Confirm Delete Switch
                                                                  Row 1
Command ===> ____________________________________________ Scroll ===> PAGE

Scroll forward to view the complete list of switches to be deleted, with
switch control units and devices where shown. Press ENTER to confirm
delete request. Press F12 to cancel delete request.

ID Type          Description                      CU Number Device Number
A1 9032                                           0001      0001
                                                  0011      0011
                                                  0111      0111
                                                  1111      1111
**************************** Bottom of data ******************************



 F1=Help        F2=Split       F3=Exit        F7=Backward    F8=Forward
 F9=Swap       F12=Cancel     F22=Command
```

Figure 53. Example of a Confirm Delete Switch panel

Working with Connections to Switches

In this section, you will learn about how to define connections to switches, for example channel paths, control units, other switches, how to prime switch port data, and what kind of additional actions is offered on the port list panel.

Defining Connections to Switches

You can connect the following objects to a switch starting from the Switch List panel:

- Channel paths
- Control Units
- Other switches

You can also define connections from the objects to the switch when defining the object themselves. See Chapter 6, “How to Define, Modify, or View a Configuration” on page 85 for a description how to define the objects.

Connecting a Channel Path



The following procedure describes how to define a connection between a channel path and a switch starting from the Switch List panel.

1. On the Switch List panel, select the switch and the ***Work with ports*** action from the context menu (or action code **p**). The Port List panel is displayed.

Ports which show value Y in column O indicate that they are occupied by a processor, control unit or switch that is not defined in the accessed IODF.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                                Port List                          Row 1 of 61
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more ports, then press Enter.

Switch ID . . . . . . . : 99   Address :      Switch AB

                                  ---------------Connection---------------
/ Port H Name +                      Unit ID           Unit Type         O
_ C0   Y ______________________                                           N
_ C1   Y ______________________                                           N
_ C2   Y ______________________                                           N
_ C3   Y ______________________ PR CTC01    CHPID 34 9672-R21             N
_ C4   Y ______________________                                           N
_ C5   Y ______________________                                           N
_ C6   Y ______________________                                           N
_ C7   Y ______________________                                           N
_ C8   Y ______________________                                           N
_ C9   Y ______________________                                           N
_ CA   Y ______________________                                           N
 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F12=Cancel   F13=Instruct F22=Command
```

Figure 54. Port List Panel

2. Select a port and the ***Connect to channel path*** action from the context menu (or action code **p**).

   Occupied ports cannot be connected. However, you may change the Occupied status of a port by overwriting the Occupied indicator.

   On the resulting Connect to Channel Path panel specify the target processor ID and channel path ID.

```
 ──────── Connect to Channel Path ────────


  Specify the following values.

  Switch ID  : 99  Port . . . : C4

  Processor ID . . . . ________  +
  Channel path ID  . . __   +

   F1=Help     F2=Split    F3=Exit
   F4=Prompt   F5=Reset    F9=Swap
  F12=Cancel
```

3. Repeat defining connections for all channel paths connected to the switch.

Connecting a Control Unit



The following procedure describes how to define a connection between a control unit and a switch starting from the Switch List panel.

1. On the Switch List panel, select the switch and the ***Work with ports*** from the context menu (or action code **p**). The Port List panel is displayed (see Figure 54 on page 164).
2. Select a port and the ***Connect to control unit*** action from the context menu (or action code **u**).

```
                    Connect to Control Unit

 Specify the following values.

 Switch ID  . . . . : 99  Port . . . . . . . : C4

 Control unit numbers . . 00E1  ____  ____  ____  ____  ____  ____  ____  +

  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

   You can enter up to eight control unit numbers each time the panel is displayed.
3. Repeat defining connections for all control units connected to the switch.

Connecting Another Switch



The following procedure describes how to define a connection between a switch and another switch.

1. On the Switch List panel, select the switch and the ***Work with ports*** action from the context menu (or action code **p**). The Port List panel is displayed (see Figure 54 on page 164).
2. Select a port and the ***Connect to switch*** action from the context menu (or action code **w**).

```
          Connect to Switch

 Specify the following values.

 Switch ID  : 99  Port . . . : C4

 Switch ID  . . . . . 98  +
 Port . . . . . . . . C1  +

  F1=Help     F2=Split    F3=Exit
  F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

3. Repeat defining connections for all other switches connected to the selected switch.

Priming Switch Port Data



You can prime your I/O configuration in a work IODF with the switch port names, and connections for the active processor. For the prerequsites for this function refer to “Prerequisites” on page 9.

To prime, select the action ***Prime port name and connections*** from the context menu (or action code **i**) on the Port List panel.

The Confirm Priming Port Data List panel lists the selected ports with the sensed data for the port names, and for the connected control units, or switches, or the connections to channel paths of the active processor. Their corresponding definitions in the IODF are shown in the line below the sensed data on the panel.

You get sensed data for connected channel paths only if the processor definition in the IODF contains a serial number that matches the serial number of the active processor.

The sensed port names and connection data can be confirmed before being taken into the IODF. If a value is blanked out, the defined IODF value is not changed. If you use the F12=Cancel, or the F3=Exit key, none of the sensed values is used.

```
                    Confirm Priming Port Data List
                                                                Row 1 of 4
Command ===> ___________________________________________ Scroll ===> CSR

Press Enter to confirm priming, or Cancel to leave the list. A blank value
will not change the IODF definition.

Switch ID . . : 01
Port --- Sensed Port Name ---   --------- Sensed Connection --------
     -- Defined Port Name ---   -------- Defined Connection --------
A1   200A-E                     CU   200A              3990-6         1
     200A-E                     ____________________________________
A2   400B-CG                    ____________________________________  2
     400B-CG                    CU   520B              3990-3
A3   ______________________     CU   360A              9343-DC4       3
     360A-00                    CU   360A              9343-1
A4   VMA(32)                    ____________________________________  4
     VMA(32)                    PR   VMABASIC CHPID 32 9672-R61
***************************** Bottom of data ******************************
 F1=Help        F2=Split       F3=Exit        F5=Reset       F7=Backward
 F8=Forward     F9=Swap       F12=Cancel
```

1 No defined data is available for the port connection on the active system. The sensed and defined port names are the same.

2 The sensed and defined port names are available. The port connection is defined in the IODF, but no sensed data is available on the active system.

3 No sensed port name data is available on the active system. The port connection shows differences of the switch type, but the sensed data is not taken in the IODF.

4 No sensed data is available for the port connection on the active system. The sensed and defined port names are the same.

Additional Actions on the Port List Panel

Besides connecting channel paths, control units, and other switches to a switch, you can perform additional actions on the Port List panel. Most of these actions are also possible on the Port Matrix panel, this panel offers an alternative procedure. The following panel shows data after connecting a channel path, a control unit, and another switch as described in the previous sections.

```
  Goto  Options  Filter  Backup  Query  Help
-------------------------------------------------------------------------------
                                 Port List                        Row 22 of 128
Command ===> ___________________________________________ Scroll ===> CSR

Select one or more ports, then press Enter.

Switch ID . . . . . . . : 71   Address :      Switch 71
Switch configuration ID : SW71

                                 -------------Connection-------------   DED
/ Port H Name +                     Unit ID           Unit Type     O B CON +
_ 95   Y SUBC6F-A2                                                   N N _
_ 96   Y SUBC91-A0                                                   N N _
_ 97   Y ______________________                                      N N _
_ 98   Y ______________________                                      N N _
_ 99   Y SUBC6F-C0               CU BA80              3990          N N _
# 99                             CU BD80              3990
_ 9A   Y SUBC91-A2                                                   N N _
_ 9B   Y N40-50                                                      N N _
_ 9C   Y SUBC2D                                                      N N
_ 9D   Y SUBC6F-C2                                                   N N
_ 9E   Y SUBC6F-H0                                                   N N
_ 9F   Y SUBC6F-H2                                                   N N
_ A0   Y JE0-25                  PR CB89     CHPID 25 9672-E08      N N
_ A1   Y JE0-26                  PR CB89     CHPID 26 9672-E08      N N
```

A disabled marker # in the action entry field indicates that the field is nonselectable and the whole row is disabled for processing. This occurs if more than one object is attached to one port, for example, when multiple control units are connected to the same port. Except for the first object attached to the port, all other objects are flagged with the # sign. For example, if the port is connected to more than one unit, a disconnect action specified in the selectable row of that port will lead to the display of another panel where you can select the unit(s) to be disconnected.

Changing Ports to Installed or Uninstalled

The H column indicates whether the ports are installed (Y for Yes) or not (N for No). If you did not specify a range of ports to be set to installed while adding a switch, HCD automatically sets the minimum range of ports to installed at switch definition time.

You can set the port to installed or uninstalled by just typing over the Y or N value in the H column.

Changing Ports to Occupied or Not Occupied

The O column indicates whether a port is occupied (Y for Yes) or not (N for No) by a system external to the IODF.

You can change the port to Occupied or Not Occupied by just typing over the Y or N value in the O column.

Establishing Dedicated Connections and Blocking Ports

If no switch configurations are defined for a switch, the `B` and `Ded Con` columns for blocked indicator and port of dedicated connection are not shown. If switch configurations are defined, data of the first switch configuration (in alphabetical order) is displayed. To display this data for other switch configurations, use ***Select other switch configurations*** from the ***Option*** action bar choice.

You can change the blocked indicator and dedicated connections for the switch configuration displayed in the panel header by just typing over the values in the appropriate column. See also "Establishing Dedicated Connections" on page 169 and "Blocking Ports" on page 170 for detailed explanations.

Note: You cannot establish dedicated connections for an FC switch.

Working with Switch Configurations

In this section you can learn about defining switch configuration data, changing the switch configuration IDs, and deleting switch configurations.

Defining Switch Configuration Data



After defining the switch, you can define the switch configuration, that is the "inside" of the switch.

1. On the Switch List panel, select the switch and the ***Work with switch configurations*** action from the context menu (or action code **S**). HCD displays the Switch Configuration List containing all currently defined configurations for that particular switch.

```
  Goto  Backup  Query  Help
--------------------------------------------------------------------------------
                         Switch Configuration List                 Row 1 of 1

Select one or more switch configurations, then press Enter. To add, use F11.

Switch ID  . . . . : 99        First switch

  Switch       Default
/ Config. ID   Connection + Description
_ NIGHT        Allow        ______________________________
```

2. Use F11=Add to add a new switch configuration. The data-entry fields are shown below, with sample data:

```
──────────────── Add or Repeat Switch Configuration ────────────────

Specify or revise the following values.

Switch ID . . . . . : 99

Switch configuration ID . BASIC___

Description . . . . . _____________________________

Default connection  . . . _1  1.  Allow
                              2.  Prohibit
```

The `Default connection` field sets the default connection for all ports, either allowed or prohibited. Individual port connections can be reset on the Port Matrix panel described in the next step.

3. On the Switch Configuration List panel, select the switch configuration and the ***Work with port matrix*** action from the context menu (or action code **s**). HCD displays the Port Matrix panel showing all ports currently installed on the switch.

```
  Goto  Backup  Query  Help
-------------------------------------------------------------------------------
                         Port Matrix                Row 1 of 28 More:       >

Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more ports, then press Enter.

Switch ID  . . . . . . . . : 99
Switch configuration ID  . : BASIC      Default connection : Allow

                                   Ded   --Dynamic Connection Ports Ex--
/ Port Name +                   B  Con + 0 1 2 3 4 5 6 7 8 9 A B C D E F
_ E0   ________________________ N  __    \ * * * * * * * * * * * * * * *
_ E1   ________________________ N  __    * \ * * * * * * * * * * * * * *
_ E2   ________________________ N  __    * * \ * * * * * * * * * * * * *
_ E3   ________________________ N  __    * * * \ * * * * * * * * * * * *
_ E4   ________________________ N  __    * * * * \ * * * * * * * * * * *
```

Scroll to the right to view further ports.

Establishing Dedicated Connections

You can establish a dedicated connection between two ports by specifying the number of a port to which a dedicated connection is defined in the `Ded Con` column. After pressing the Enter key HCD completes the definition by mirroring the definition. For example, if you specify a dedicated connected in the row of port E0 to port E4, HCD establishes the same dedicated connection in the row of E4 to port E0.

A dedicated connection acts like a physically cabled connection between two ports. Establishing a dedicated connection is not the same as prohibiting all but one connection to a port. Dedicated connections are required to support communication through an ESCD with an ESCON Converter (ESCC), and to support chained ESCDs.

If you maintain switch configurations with HCD, you must define the required dedicated connections before you connect a CVC or CBY channel path to a switch port.

If you have alternate required dedicated actions in a configuration (for example, for backup purposes), you must define alternate switch configurations.

Blocking Ports

You can block or unblock a port by just specifying a `Y` for Yes or `N` for No in the `B` column.

Dynamic Connection Ports

In our example the default switch connection is set to allowed. To prohibit a switch connection from, for example, EA to FA, scroll down until you see port EA and scroll right until you see port FA. Then type over the `*` symbol with a `p` below the heading `Dynamic Connection Ports`. After pressing the Enter key HCD automatically mirrors the entries on the diagonal of the matrix. That means, HCD applies the same entry not only to the matrix element EA/FA but also to FA/EA.

To ensure a correct mirroring of the entries, press the Enter key each time you changed one complete row.

The following symbols can be shown below the heading `Dynamic Connection Ports`:

A Indicates that the dynamic connection is allowed.
P Indicates that the dynamic connection is prohibited.
***** Indicates that the dynamic connection is set to the default connection attribute (shown in the instruction area on the top of the panel).
\ Indicates the intersection of a port's column and row.
- Indicates that one of the dynamic connection ports is not installed or supported.

To allow you a more comfortable scrolling in the matrix, use the FIND command. For example, type:

```
FIND EA, FA
```

to find the row of port EA and the column of port FA.

Changing the Switch Configuration ID



To change the ID of a switch configuration, perform the following steps:

1. On the Switch List panel select the switch and select the ***Work with switch configuration*** action from the context menu (or action code **s**). HCD displays the Switch Configuration List.
2. On the Switch Configuration List panel select the switch configuration and the ***Repeat (copy) switch configurations*** action from the context menu (or action code **r**). The Repeat Switch Configuration panel is displayed.

```
──────────────── Add or Repeat Switch Configuration ────────────────

Specify or revise the following values.

Switch ID . . . . . : 99

Switch configuration ID . _______

Description . . . . . _______________________________

Default connection  . . . 1   1.  Allow
                              2.  Prohibit

 F1=Help    F2=Split   F3=Exit    F5=Reset   F9=Swap   F12=Cancel
```

3. Specify the new identifier for the switch configuration and press the Enter key. HCD displays the Switch Configuration List panel now showing the new switch configuration.
4. Delete the old switch configuration by selecting the switch configuration and the ***Delete*** action from the context menu (or action code **d**). HCD displays a confirmation panel before showing the updated Switch Configuration List.

Generating a Switch Matrix



When selecting ***Generate Matrix***, HCD will define the content of the switch matrix according to the logical paths defined and the existing matrix will be replaced.

This is useful, if channel path - control unit connections have been added or changed and you want to define a switch configuration which considers all defined logical paths running through the selected switch.

To generate a matrix, perform the following steps:

1. On the Switch List panel select the switch and select the ***Work with switch configuration*** action from the context menu (or action code **s**). HCD displays the Switch Configuration List.
2. On the Switch Configuration List panel select a configuration (or action code **g**). HCD will issue an informational message requiring you to confirm your action. The successful generation of the matrix is confirmed by HCD.

When generating the switch configuration, all defined logical paths will be analyzed by HCD. In the case of chained connections, all possible paths of chaining switches will be determined by their respective switch configurations. Therefore, it is necessary, that you select a switch configuration for each chained switch, for which more than one switch matrix has been defined. In this case, the following panel

```
                    Select Active Switch Configurations              Row 1 of 2
Command ===> ___________________________________________ Scroll ===> PAGE

For each switch select one to be used as context to generate a switch
matrix.


Switch ID: 01 Configuration ID: SC1

/ Switch  Configuration Description
_ 02      SC1
_ 02      SC2
****************************** Bottom of data ************************
```

will be displayed allowing selection of the related switch configurations which are considered for the ***Generate matrix*** action.

The following rules are applied when generating a matrix:

- The default connection for the switch configuration will be set to prohibited.
- A logical definition between a channel path using the switch as a dynamic switch and a control unit will lead to a dynamically allowed connection between the channel path entry port and the port serving as the link address.
- A logical definition between a channel path without a dynamic switch and a control unit, or connections via a chaining switch, will lead to a dedicated connection.

  HCD will define a dedicated connection in all the cases where there is only one connection possibility left between the control unit and the channel path entry port. For dedicated connections, HCD considers only those ports, which have not yet been used for dynamic connections. In the case of chained connections, the selected switch configurations of chaining switches are used to determine the possible paths.
- Connections between ports connected to a channel path type, which make a specific port configuration necessary, will be set accordingly. For example, connections between ports serving as entry ports for FCV channels will be defined as explicitly dynamically prohibited.
- In addition to generating the matrix, HCD issues informational messages for all cases in which a path was not completely defined or where different paths conflict with each other. If HCD is not able to determine port connections unambiguously, it will leave those definitions to the user.

Deleting Switch Configurations



To delete a switch configuration, perform the following steps:

1. On the Switch List panel select the switch and select the ***Work with switch configuration*** action from the context menu (or action code **s**). HCD displays the Switch Configuration List.
2. On the Switch Configuration List panel select the switch configuration and the ***Delete*** action from the context menu (or action code **d**). The Confirm Delete Switch Configuration panel is displayed.

```
Confirm Delete Switch Configuration
                                                        Row 1 of 1
Command ===> ________________________________ Scroll ===> PAGE

Scroll forward to view the complete list of switch
configurations to be deleted. Press ENTER to confirm delete
request. Press F12 to cancel delete request.

Switch ID . . . . . . . : 03

Switch Config. ID  Description
SWCON1
************************ Bottom of data *************************
```

3. Press the Enter key to confirm deletion of the switch configuration, or use the F12=Cancel key to cancel the delete request.
4. The updated Switch Configuration List panel is displayed.

Migrating Existing Switch Configurations

HCD allows to migrate a switch configuration from three sources into the IODF:

- An ISPF table containing a switch configuration as stored by I/O Operations
- An active switch
- A saved switch file

Prerequisites

To migrate from an ISPF table, the I/O Operations ISPF table data set name escm.SINGITBL has to be concatenated in the table library chain in your HCD start-up procedure, where “escm” is the high-level qualifier for your I/O Operations installation, or any other ISPF table data set containing ISPF tables saved by I/O Operations.

For additional information, see “Prerequisites” on page 9.

Migration Steps

1. On the primary task selection panel select ***Migrate configuration data***.
2. On the resulting panel select ***Migrate switch configuration data***.

```
──────────── Migrate Switch Configuration Data ────────────

Migrate switch configuration definitions to:

Switch ID . . . . . 98       +
Switch configuration ID . . . . . A98BC___ +


From one of the following:

__  1.  ISPF table
    2.  Active Director
    3.  Saved Director file
──────────────────────────────────────────────────────────
```

Specify the switch ID and the switch configuration ID of the empty switch configuration in the IODF to which you want to migrate the data.

If you have not previously defined the switch and the switch configuration, a panel appears that lets you define them (see "Defining Switches" on page 156).

Select the source from which you want to migrate the switch configuration.

3. A panel appears on which you can define the source:
   - From ISPF tables:
     - Specify the name of the ISPF table that contains the configuration.
   - From an active director:
     - Specify the device number of the switch.
   - From a saved director file:
     - Specify the name of the switch file.
     - Specify the device number of the switch from which the switch file is to be taken.

The following panel is displayed when you are migrating from a saved switch file.

```
──────── Migrate from Saved Director File ────────

Specify the following values.

Director file name . . . . ________
Director device number . . ____
──────────────────────────────────────────────────
```

Note: The source of the switch configuration as specified in the switch device number field does not have to be the switch as specified in the Switch ID field on the Migrate Switch Configuration Data panel. It is possible to take a switch configuration from any switch and save it with HCD for another switch. However, the description of each port connection is saved with the switch configuration, and has to be updated to reflect the real channel path and control unit connections of the target switch.

Changing Port Names

In HCD, port names are saved with the ports, because the port names reflect the connections of a port. When migrating switch configurations with different port names to HCD, the IODF reflects the port names defined in the switch configuration that were migrated last.

Changing Hardware Status of a Port

If the migration source contains ports set to installed and the existing IODF contains the same ports set to uninstalled, the hardware status after the migration depends on the kind of source:

Migration Source	Hardware Status of Ports after Migration
Active switch	Changed to installed
Saved director file	Uninstalled, migrated values ignored
ISPF table	Uninstalled, migrated values ignored

Activating Switch Configuration Data

You can activate a switch configuration, which has been defined or changed with HCD, for a switch. Thus, change and maintenance in a configuration controlled by I/O Operations is simplified by the possibility to use the same user interface.

Prerequisites

- The IODF has to be a production IODF.
- A switch control unit must be defined for each switch.
- A switch device must be defined for each switch control unit.
- The switch control unit must have at least one channel path connected using the switch.
- For activation and saving, an ESCON Manager lock of another user must not exist.

For additional information, see “Prerequisites” on page 9.

Activation Steps

1. On the primary task selection panel, select ***Activate and process configuration data*** and from the resulting panel, select ***Activate switch configuration***. The Activate Switch Configuration panel is displayed.

```
Activate Switch Configuration

Specify the following values, and select how to handle an existing ESCON
Manager lock.

IODF name  . . . . . . . . . : 'BPAN.IODF01'

Switch ID  . . . . . . . . . . ____+
Switch configuration ID  . . BASIC     +

ESCON Manager lock . . 1  1.  Break another user's ESCON Manager lock
                          2.  Preserve another user's ESCON Manager lock
```

2. You may choose between two different kinds of switch activation:

Single Switch Activation

For single switch activation, use the Activate Switch Configuration panel to:

- Specify the switch ID and the switch configuration ID that is to be written to the switch.
- Select how to handle an existing ESCON Manager lock if it is in use by another user.

  I/O Operations uses a locking mechanism to serialize connectivity changes across multiple users and systems. This lock allows only one user (or program) to control I/O Operations command processing at a time. If more than one user at your installation is given the ability to enter I/O Operations commands, they must synchronize their usage of I/O Operations to avoid delays or contention for I/O Operations resources.

Multiple Switch Activation

For multiple switch activation, use the Activate Switch Configuration panel to:

- Specify only the switch configuration ID and no Switch ID. A panel is displayed showing all switches that have a configuration under the specified name.

```
                        Switch Activation List
                                                                Row 1 of 2
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more switches for activation.

Switch configuration ID  . . : BASIC

                                                      CU    Dev
/ ID Type          Description                        Num.  Num.  More?
_ 98 9033          First switch                       0098  0098
_ 99 9033          Second switch                      0099  0099
*************************** Bottom of data ****************************
```

  Switches that are not connected to any switch device are marked with a disabled marker # in the action column, and cannot be selected for activation. The panel shows 'YES' in the 'More?' column if there are more than one control unit and one device. If there is only one control unit and one device, the 'More?' column is left blank. HCD uses the switch devices that are connected to the active system.

- Select the switches that will be activated simultaneously.

  When you have finished your selection, press the Enter key. A confirm panel is displayed. On this panel you have to confirm if you want the active switch configuration of all switches shown in the list to be updated.

  Note: In case a switch activation fails, no switch will be activated, the rule is "none or all".

  For activating switch configuration data, refer to *System Automation for OS/390 Planning and Installation*.

Saving Switch Configuration Data

Use the Save switch configuration data function to save an existing switch configuration definition in a switch file. For information on prerequisites to save a switch configuration, see "Activating Switch Configuration Data" on page 175.

1. On the primary task selection panel, select ***Activate and process configuration data***, and from the resulting panel, select ***Save switch configuration***. The Save Switch Configuration Data panel is displayed.

```
──────────────────────── Save Switch Configuration Data ────────────────────────


 Specify the following values.

 Save switch configuration:
 Switch ID  . . . . . . . . . . 65  +
 Switch configuration ID  . . . FICON65   +

 In Director file:
 File name  . . . . . . . . . . CONF65
 File description . . . . . . . as of 11/2000

 Select how to handle any existing:

 ESCON Manager lock . . 2   1.  Break another user's ESCON Manager lock
                            2.  Preserve another user's ESCON Manager lock

 Director file  . . . . 2   1.  Overwrite
                            2.  Do not overwrite
```

2. Use the Save Switch Configuration Data panel to:
   - Specify the switch ID and the switch configuration ID for the configuration data that is to be saved in the switch file
   - Specify the name of the switch file used to store the switch configuration data
   - Select how to handle an existing ESCON Manager lock
   - Indicate whether to overwrite an existing switch file with the file name you specified.

Chapter 8. How to Activate or Process Configuration Data

Overview

This chapter describes how to:
- Build a production IODF
- Build an IOCDS
- Build S/390 microprocessor IOCDSs
- Manage S/390 microprocessor IPL attributes
- Build an IOCP input data set
- Create JES3 Initialization Stream Checker data
- Build an OS configuration data set
- Verify an I/O configuration
- Activate a configuration dynamically
- Activate a configuration sysplex wide
- Build a CONFIGxx member
- Process the Display M=CONFIG(xx) command
- Switch IOCDS for next POR
- Specify an IODF for IPL

Before the channel subsystem and the operating system can use the configuration that you have defined with HCD, you must build a production IODF from the work IODF.

With the production IODF, you can perform the following tasks in preparation for IPL or dynamic activation.
- Build an input/output configuration data set (IOCDS) from the production IODF for processors not configured in an S/390 microprocessor cluster. The configuration can then be used by the channel subsystem.
- Build IOCDSs of central processor complexes (CPCs) configured in an S/390 microprocessor cluster.
- Manage IPL attributes of central processor complexes (CPCs) configured in an S/390 microprocessor cluster.
- Build an input data set for the input/output configuration program (IOCP) from the production IODF.
- Create data for input to the JES3 Initialization Stream Checker. This checker program ensures that the data used by MVS is consistent with the data used by JES3. (This task can also be done with a work IODF.)
- Build an OS configuration data set from the production IODF. For VM this is an HCPRIO input data set.
- Verify the configuration described in an IODF against a system.
- Activate the configuration dynamically using the activate function (locally or sysplex wide).
- Build a CONFIGxx member for a system from the I/O definitions in an IODF.
- Compare the information in the CONFIGxx member of a system of the sysplex with the existing configuration on that system.
- Switch the IOCDS for the next POR

© Copyright IBM Corp. 1994, 2002

Finally, you can use HCD to:

- Specify which IODF is to be used for IPL.

Build a Production IODF

Although HCD validates configuration data as it is entered, a complete validation may not be performed, because data may not be defined at this time. Therefore, a "post-validation" is performed at "Build Production IODF" time. This validation might issue messages you have to deal with, according to their severity. The production IODF is not created if any errors with a severity higher than 'warning' are produced.

During the validation HCD invokes the IOCP program to perform checking of the channel packaging rules. Therefore, note that the correct version of the IOCP program must be accessible.

Depending on what is defined in the configuration, the work IODF must contain a definition for at least one operating system, *or* one processor, *or* one switch.

- For an MVS operating system, the IODF must contain at least one EDT and one device.

  For a VM operating system, the IODF must contain at least one device as console.
- For a processor, the IODF must contain a definition for at least one channel path, one control unit, and one device. If only receiving CF channel paths are defined for a processor, the control unit and device definitions can be omitted.

Note

A production IODF must have a single extent. If the production IODF has multiple extents, the IPL process results in a WAIT state (wait state code '0B1', reason code '002'). HCD issues error message CBDA009I if a production IODF cannot be built in a single extent.

To build a production IODF, perform the following steps:

1. On the primary task selection panel, select ***Activate or process configuration data***.

```
──────── Activate or Process Configuration Data ────────


Select one of the following tasks.

__  1.  Build production I/O definition file
    2.  Build IOCDS
    3.  Build IOCP input data set
    4.  Create JES3 initialization stream data
    5.  View active configuration
    6.  Activate or verify configuration
        dynamically
    7.  Activate configuration sysplex-wide
    8.  Activate switch configuration
    9.  Save switch configuration
    10. Build OS configuration data set
    11. Build and manage S/390 microprocessor
        IOCDSs and IPL attributes

 F1=Help     F2=Split    F3=Exit     F9=Swap
F12=Cancel
```

Figure 55. Example of an Activate or Process Configuration Data Panel

2. From the resulting panel select ***Build production I/O definition file***. HCD validates the configuration data in the work IODF.
3. If you initially requested activity logging, a panel like the one shown in "Activity Logging" on page 62 is displayed. Enter the activity logging details your installation requires. The Build Production I/O Definition File panel is displayed.

```
──────────────── Build Production I/O Definition File ────────────────


Specify the following values, and choose how to continue.

Work IODF name . . . : 'DOCU.IODF01.WORK'

Production IODF name . 'DOCU.IODF01'
Volume serial number . DATA01  +

Continue using as current IODF:
2   1.  The work IODF in use at present
    2.  The new production IODF specified above



 F1=Help    F2=Split   F3=Exit    F4=Prompt  F9=Swap   F12=Cancel
```

Figure 56. Example of a Build Production I/O Definition File Panel

The selection of option `Continue using as current IODF` controls which IODF is in access after the production IODF has been built. In addition, if you select option 1, `The work IODF in use as present`, the content of the currently built production IODF is copied to the work IODF. This ensures that the work IODF contains the latest configuration tokens of the IODF, and you can continue to use the work IODF for further updates. If you select option 2, `The new production IODF specified above`, the content of the production IODF is not

mapped into the work IODF. In that case, you should start from the newly built production IODF when performing further changes to the I/O configuration.

4. Specify the name and volume serial number (if applicable) for the production IODF. "IODF Naming Convention" on page 49 describes the syntax of a production IODF name. If you choose a name without complying to the prescribed syntax of a production IODF name, that IODF can not be used for the IPL and dynamic activate. Moreover, to perform a dynamic activate, the high-level qualifier of the production IODF has to be the same as the one of the IODF used for the previous IPL or dynamic activate.

   If the data set name for the production IODF does not adhere to the naming convention for a production IODF, the Confirm Production IODF Name panel is displayed, and you must confirm the IODF name.

```
                    Confirm Production IODF Name

 The data set name you specified does not follow the naming
 convention for production IODFs.  You will not be able to IPL
 or ACTIVATE a system configuration from an IODF with this data
 set name.

 Confirm the specified IODF name . . 1_  1.  Yes
                                         2.  No

  F1=Help      F2=Split     F3=Exit      F9=Swap     F12=Cancel
```

Figure 57. Example of a Confirm Production IODF Name Panel

If you use the same name for the new IODF as for an existing IODF, you can replace the existing IODF. In that case, the Confirm Delete I/O Definition panel is shown. Select `yes`, to confirm deletion of the IODF. Be careful, not to delete the active IODF. If you have specified the name of the active IODF, another confirmation panel is shown that warns you once more about the effect of the chosen name.

```
──────────────── Confirm Delete I/O Definition File ────────────────


To confirm delete request, select Yes. To cancel delete request,
select No.

Delete request confirmed . . . __  1.  Yes
                                   2.  No

Creation date  . . : 1997-06-10
Last update  . . . : 1997-09-10  14:19
Volume . . . . . . : SMS012

Description  . . . : IODF for raised floor 710
                     For systems D0, D2, D4 and D6
                     incl. sensed data and mig. SW data


 F1=Help    F2=Split   F3=Exit    F9=Swap   F12=Cancel
```

Figure 58. Example of a Confirm Delete I/O Definition File Panel

5. After pressing Enter, the Define Descriptor Fields panel appears.

```
──────────────────── Define Descriptor Fields ────────────────────


Specify or revise the following values.

Production IODF name  . : 'DOCU.IODF01'

Descriptor field 1  . . . DOCU
Descriptor field 2  . . . IODF01

 F1=Help   F2=Split   F3=Exit   F5=Reset   F9=Swap   F12=Cancel
```

Figure 59. Example of a Define Descriptor Fields Panel

   Specify the `descriptor field 1, 2`, or leave the default values. The descriptor fields describe the IODF and will be part of the HSA token. If you specify asterisks (**) for the IODF suffix in LOADxx, z/OS MVS uses the descriptor fields to find the current IODF (for further details refer to *z/OS HCD Planning*). After the production IODF is built, HCD displays a message.
6. If the work IODF has an activity log file defined for the work IODF, it is copied. After the production IODF has been built, HCD informs you that the production IODF has been created.

You can also create a production IODF using the HCD batch facility (for details see "Build a Production IODF" on page 290).

Build an IOCDS

When a production IODF has been created, you can build an IOCDS (it can be built only from a production IODF). Processors may have varying numbers of IOCDSs. A particular IOCDS is used at POR time to make the configuration data known to the CSS.

For the processor IBM ES/4381, you cannot build an IOCDS with HCD. You have to build an IOCP input data set and then run the stand-alone IOCP program to build an IOCDS from that input data set.

The following procedure is only recommended for processors that do *not* have an SNA address defined, including processors configured in an S/390 microprocessor cluster. For processors in an S/390 microprocessor cluster *with* an SNA address defined, use the procedure described under "Build S/390 Microprocessor IOCDSs" on page 186.

While building IOCDSs HCD internally calls the IOCP program. Therefore, note that HCD must be installed in an APF-authorized library.

1. On the primary task selection panel, specify the name of a production IODF and select ***Activate or process configuration data***.
2. From the resulting panel select ***Build IOCDS***. HCD displays the Processor List panel.
3. On the Processor List panel, select the processor and press the Enter key. HCD displays the IOCDS List panel.
   The IOCDS list shows those IOCDSs that are built using the currently accessed

```
                          IOCDS List
  Goto  Backup  Query  Help
-------------------------------------------------------------------
                                                        Row 1 of 4

Select one or more IOCDSs, then press Enter.

Processor ID . . : P101

                          --Last IOCDS Update--
/ IOCDS  Name     Format  Date         Time
_ A0
_ A1     IODF05   BASIC   1995-05-26   14:27:38
_ A2     IODF03   BASIC   1995-07-17   16:41:19
_ A3
```

Figure 60. IOCDS List

   production IODF.
4. Whenever the IOCDS list is invoked, HCD tries to get actual IOCDS data (e.g. date and time of last update) for processors with SNA addresses directly from the support element (SE) and displays it.

   IODF data is shown only if the SE does not provide information or where an SNA address is not defined.

   A production IODF is updated with data retrieved from the SE if discrepancies between that data and the stored IODF data are detected.
5. On the IOCDS List panel, select the IOCDSs that you want to update and select ***Update IOCDS*** from the context menu (or action code **u**). HCD displays the Build IOCDS panel.

```
                              Build IOCDS


 Specify or revise the following values.

 IODF name . . . . . . . . . : 'SYS1.IODF02'
 Processor ID  . . . . . . . : PROC2        IOCDS  : A0

 Title1  . ____________________________________________________________
 Title2  : SYS1.IODF02 - 1999-12-12 14:52

 Dualwrite  . . . . . . . . . . . . . . . No     (Yes or No)
 Switch IOCDS for next POR  . . . . . . . No     (Yes or No)
 Write IOCDS in preparation of upgrade  No     (Yes or No)

 Job statement information
 //WIOCDS  JOB (ACCOUNT),'NAME'
 //*
 //*
 //*
 //*
 //*
  F1=Help     F2=Split    F3=Exit     F5=Reset    F9=Swap    F12=Cancel
```

On this panel you can:

- Enter identification information you want to be written on the first header line of the IOCP input data set in the `Title1` field.
- Specify the `Dualwrite` option that describes whether the IOCDS is to be updated on both sides of a physically partitioned processor.
- Specify the `Switch IOCDS for next POR` option, that means whether you want to make this IOCDS the active one for the next power-on reset (POR).
- Specify whether to `Write IOCDS in preparation of upgrade`. This specifies whether an IOCDS is to be written regardless of processor type. This is useful to prepare for a processor upgrade.

  If `Yes` is specified, an IOCDS for the selected processor is written regardless of the processor type. For a list of processors that support writing an IOCDS, in preparation for a processor upgrade, or for which such an IOCDS can be written, see "Supported Hardware Report" on page 373.

  Note: If, as a result of a processor upgrade, an IOCDS download is not possible you can, after having built the production IODF, create an IOCP input data set that can be used with the stand-alone IOCP to generate an IOCDS for use with POR.
- Change the job statement information to meet the installation needs. Note that a batch job to build an IOCDS must run on the processor on which the IOCDS is to be updated. (See "Job Statement Information Used in Panels" on page 84 for a description of the job control information that you need to specify when you build an IOCDS.)

  In a multiprocessor JES environment, be sure to specify the JES command and/or job class to ensure that the job runs on the correct processor(s).

  The recommended region size is 2 MBytes more than the IOCP needs. For the region size required by IOCP, refer to the *IOCP User's Guide* for your processor.

6. When an IOCDS is built, a record is written for the processor configuration. If you build a new IODF from an existing IODF, the records are copied to the new IODF. When you build IOCDSs from this new IODF, the IOCDSs from the

old IODF are also shown on the IOCDS list. Because the batch job requires exclusive use of the production IODF for processors that have *no* SNA address specified, you have to either leave the HCD session or change the currently accessed IODF to run the submitted job.

You can also invoke the ***Build IOCDS*** task in batch mode, see "Build an IOCDS or an IOCP Input Data Set" on page 292.

Notes:

1. Unlike writing an IOCDS using the IOCP program, the HCD process generates no IOCP report when using the ***Build IOCDS*** function.
2. When a processor has been upgraded in the IODF, the old IOCDS status data in the IODF is deleted.

Using this Procedure for Processors with an SNA Address

If you use this procedure for processors in an S/390 microprocessor cluster *with* an SNA address defined, HCD does the following:

- HCD writes the IOCDS for that processor to the support element with the designated SNA address (remote IOCDS build).
- If you run the job under MVS/ESA SP Version 5, OS/390, or z/OS, HCD writes the IOCDS for that processor to the support element with the designated SNA address.

To run the batch job, you do not have to leave the HCD session. If the processor has defined an SNA address, HCD assumes that it is part of an S/390 microprocessor cluster. In this case, the job can immediately start without the need to free the currently accessed IODF.

HCD tries to update the IOCDS record but is not able to because the IODF is still allocated by the HCD dialog. This results in an error message on the console log. To avoid this error message, HCD offers the profile option of bypassing the IODF information update (see "Bypass IODF Information Update" on page 44).

Build S/390 Microprocessor IOCDSs

The following procedure describes how to build an IOCDS for processors in an S/390 microprocessor cluster *with* an SNA address defined.

To build IOCDSs within an S/390 microprocessor cluster:

- The SNA address has to be defined for a CPC configured in an S/390 microprocessor cluster
- Specific RACF authority has to be attained (for details on required access authority, refer to "Security-Related Considerations" on page 315).
- The operating system must not be running as a guest under VM.

Perform the following steps:

1. On the primary task selection panel, select ***Activate or process configuration data*** and from the resulting panel select ***Build and manage S/390 microprocessor IOCDSs and IPL attributes***. The S/390 Microprocessor Cluster List panel is displayed:

```
  Goto    Query    Help
------------------------------------------------------------------------------
          S/390 Microprocessor Cluster List               Row 1 of 9

Select one or more CPCs, then press Enter.

  --------------CPC---------------  IODF
/  SNA Address         Type    Model  Processor ID
_ NET00001.CPC01       9672    E08    CPC01
_ NET00001.CPC02       9672    E08    CPC02
_ NET00001.CPC03       9672    E08    CPC03
_ NET00001.CPC04       9672    E08    CPC04
_ NET00001.CPC05       9672    E08    CPC05
_ NET00001.CPC06       9672    E08    CPC06   ..
_ NET00001.CPC07       9672    E08    CPC07
# NET00001.CPC08       9672    E08
# NET00001.CPC09       ____    ___    _____
```

Figure 61. S/390 Microprocessor Cluster List

This panel shows all CPCs configured in an S/390 microprocessor cluster. They are identified by the SNA address of their support element and displayed together with their Type and Model as well as the Processor ID in the IODF. The SNA address has been specified in the processor definition task for the IODF processor definitions and enables the relation to the configured CPCs.

A disabled sign (#) in the action entry field can be due to:

- SNA address not defined in the IODF. In this case, the IODF Processor ID shows no value. Either define the SNA address for a corresponding processor in the accessed IODF or use another IODF.
- SE (support element) of CPC did not respond. In this case, the CPC Type and Model fields show no values.

A processor ID followed by two dots (**..**) indicates that this SNA address has been defined for several processors in the IODF. The first processor ID (in alphabetical order) with the SNA address is displayed. If you want to apply any of the group actions on another processor, use ***Select other processor configuration*** from the context menu (or action code **p**).

2. On the S/390 Microprocessor Cluster List panel, select the CPCs for which you want to build and manage the IOCDSs and ***Work with IOCDSs*** from the context menu (or action code **s**). HCD displays the IOCDS List panel (shown with sample data):

```
Goto  Query  Help
 ------------------------------------------------------------------------------
                                   IOCDS List          Row 1 of 8 More:  >

 Select one or a group of IOCDSs, then press Enter.
                                             -----Token Match-----  Write
 / IOCDS     Name     Type    Status     IOCDS/HSA IOCDS/Proc.  Protect
 _ A0.CPC01  AQIOCDS1 LPAR    POR        Yes       Yes          Yes-POR
 _ A0.CPC02  AQIOCDS1 ESA390  POR        No        Yes          Yes-POR
 _ A0.CPC03  AQIOCDS1 ESA390  POR        No        Yes          Yes-POR
 _ A1.CPC01  AQIOCDS2 LPAR    Alternate  No        No           No
 _ A1.CPC02  AQIOCDS2 ESA390  Alternate  Yes       No           Yes
 _ A1.CPC03  AQIOCDS2 ESA390  Alternate  No        No           No
 _ A2.CPC01                   Invalid
 _ A2.CPC02                   Invalid
```

Figure 62. IOCDS List

On the IOCDS List panel all applicable IOCDSs of the selected CPCs are displayed and arranged in ascending order by IOCDS names (starting, for example, with *A0*-IOCDSs, *A1*-IOCDSs). This list enables you to apply the IOCDS functions as group actions against one or several IOCDSs for all selected processors.

The data displayed is retrieved directly from the support elements. If, however, the support element does not answer, HCD displays the data saved in the IODF and issues a message accordingly.

A production IODF will be updated with data retrieved from the support element if discrepancies between that data and the stored IODF data are detected. A work IODF will remain unchanged.

The `Type` field contains one of the following types of power-on reset modes to be used with the I/O configuration defined in the IOCDS: S/370, ESA/390, or LPAR.

The `Status` field indicates the status of the IOCDS:

`Alternate` not to be used at the next POR
`POR` to be used at the next POR
`Invalid` IOCDS is opened for update

The `Token Match-IOCDS/HSA` field indicates whether the IOCDS token matches the current HSA token. If `Yes` is shown, it means that the IOCDS has been built by HCD, and that it matches the current I/O configuration - either because this IOCDS was used for the last POR, or the matching configuration has been activated dynamically.

The `Token Match-IOCDS/Proc.` field indicates whether the IOCDS token matches the processor token in the IODF, currently used in the HCD dialog. If `Yes` is shown, the IOCDS has been built from the IODF currently used in the HCD dialog.

3. On the IOCDS List panel, you can select the following actions from the context menu:
   - Use the ***Update IOCDS*** action (or action code **u**) to build or update the selected IOCDSs with the I/O configuration data from the currently accessed production IODF. See step 4 on page 189 on how to proceed.

- Use the ***Switch IOCDS*** action (or action code **s**) to mark an IOCDS as the IOCDS that is used for the next POR. The `Status` field will be set accordingly.

  You can only switch to an IOCDS that has an IOCDS/HSA token match or to an IOCDS of a processor that is not activated ('POR-required' status).
- Use the ***Enable write protection*** or ***Disable write protection*** action (or action codes **e** and **w**) to allow or prohibit updating the selected IOCDSs of the designated CPCs. The Write Protect field will be set accordingly.

Use the F20=Right key to move the work area to the right to see information such as date and time of the last IOCDS update and the IOCDS configuration token.

4. If you select the ***Update IOCDS*** action, HCD displays the Build IOCDSs panel.

```
                         Build IOCDs                      Row 1 of 3

Specify or revise the following values.

IODF name . . . . . . . . . : 'SYS1.IODF02'

Title1 . ____________________________________________________________
Title2 : SYS1.IODF02 - 1999-12-12 14:52

                            Write IOCDS in
IOCDS        Switch IOCDS   preparation of upgrade
A0.CPC01     No             No
A0.CPC02     No             No
A0.CPC03     Yes            No
```

On this panel you can:

- Enter identification information you want to be written on the first header line of the IOCP input data set in the `Title1` field.
- Specify the `Switch IOCDS` option, if you want to make this IOCDS the active one for the next power-on reset (POR).
- Specify whether to `Write IOCDS in preparation of upgrade`. This specifies whether an IOCDS is to be written regardless of processor type. This is useful to prepare for a processor upgrade.

  If `Yes` is specified, an IOCDS for the selected processor is written regardless of the processor type. For a list of processors that support writing an IOCDS, in preparation for a processor upgrade, or for which such an IOCDS can be written, see "Supported Hardware Report" on page 373.

  Note: If, as a result of a processor upgrade, an IOCDS download is not possible you can, after having built the production IODF, create an IOCP input data set that can be used with the stand-alone IOCP to generate an IOCDS for use with POR.

5. After pressing the Enter key on the Build IOCDSs panel, the Job Statement Information panel is displayed. Specify the information for the batch job that HCD generates to build the IOCDSs.

   The recommended region size is 2 MBytes more than the IOCP needs. For the region size required by IOCP, refer to the *IOCP User's Guide* for your processor.

Manage S/390 Microprocessor IPL Attributes

For IPL operations for CPCs configured in an S/390 microprocessor cluster, you can:

- Display the IPLADDR and IPLPARM attribute values of the last and for the next IPL.
- Modify IPLADDR and IPLPARM attribute values to be used for next IPL.

Perform the following steps:

1. On the primary task selection panel, select ***Activate or process configuration data*** and from the resulting panel select ***Build and manage S/390 microprocessor IOCDSs and IPL attributes***. The S/390 Microprocessor Cluster List panel is displayed (see Figure 61 on page 187).
2. On the S/390 Microprocessor Cluster List panel select the CPCs for which you want to view and modify IPL attributes.
3. Select the ***Work with IPL attributes*** action from the context menu (or action code **i**). HCD displays the IPL Attribute List panel.

```
──────────────────── IPL Attribute List ────────────────────────────────

                                                     Row 1 of 5 More: >

Update the values to be used for the next IPL and press ENTER. To view
the values used for the last IPL, scroll to the right.

                                  ----------Next IPLPARM ------------
Processor Partition  Next IPLADDR  IODF    LOADxx  Prompt/Msg  Nucleus
ID        Name       IPL Device    Device  Suffix  Option      Suffix

CPC01     MVS1       0D00          0D00    12      M           0
CPC01     MVS2       0D00          0D00    37      M           0
CPC01     MVS3       0D00          0D00    56      M           0
CPC01     CF01       0D00          ____    __      _           _
CPC04     ________   0A00          0A00    54      _           1
 ************************ BOTTOM OF DATA ****************************
```

   The IPL Attribute List panel displays the IPLADDR and IPLPARM attribute values for all selected processor definitions and their partitions (if defined in LPAR mode) that are obtained from the support element of the associated CPCs.
4. On the IPL Attribute List panel view or modify by typing over the attribute values for IPLADDR and IPLPARM.

   Use the F20=Right key to move the work area to the right to view the IPL attributes used for the last IPL.

   The `Next IPLADDR` column shows the LOAD address and specifies the number of the IPL device used for next IPL.

   The `Next IPLPARM` column shows the LOAD parameter used for MVS and is a concatenation of the following attributes: IODF Device, LOADxx Suffix, Prompt/Message Option, and Nucleus Suffix. The `Next IPLADDR` and/or the `Next IPLPARM` value for the next IPL are taken, when 'Use dynamically changed IPL address' and/or 'Use dynamically changed IPL parameter' are selected on a LOAD profile that is used to initiate an IPL, or to activate an operating system. This enables you to change the values of IPLADDR and IPLPARM without updating the profile.

Build an IOCP Input Data Set

Sometimes it is necessary to build an IOCP input data set (only possible from a production IODF):

- If you have to use the stand-alone IOCP program, which does not support direct access to the production IODF.
- If you want to create a backup on tape in case you need to recover the contents of the IOCDS in the service processor.
- If you need an IOCP input data set for a processor on which there is no HCD running (e.g. a new processor). Also, if you upgrade a processor to a model that results in a new IOCP SYSTEM value and the processor does not support an IOCDS write in preparation for a processor upgrade, you have to run the stand-alone IOCP program.

How to Build an IOCP Data Set

1. On the primary task selection panel, specify the name of a production IODF and select ***Activate or process configuration data***.
2. On the resulting panel select ***Build IOCP input data set***. HCD displays the Available Processors panel.
3. On the Available Processors panel, select the processor for which you want to build the IOCP input data set. HCD displays the Build IOCP Input Data Set panel.

```
                        Build IOCP Input Data Set

 Specify or revise the following values.

 IODF name . . . . . . . . . : 'BOKA.IODF08'
 Processor ID  . . . . . . . : CF01
 Title1 : ____________________________________________________________
 Title2 : BOKA.IODF08 - 1999-07-02 15:42

 IOCP input data set
 ____________________________________________________
 Input to Stand-alone IOCP?  Yes  (Yes or No)

 Job statement information
 //WIOCP   JOB (5765),'BOKA',NOTIFY=BOKA,CLASS=A,MSGCLASS=X,REGION=5M
 //JOBLIB     DD   DSN=HCDTEST.IZPIOCP.FALC,DISP=SHR
 //GO.HCDPROF DD   DSN=HCDTEST.PROFILE(MIGENH51),DISP=SHR
 //*
```

4. On this panel you can:
   - Enter the identification information you want to be written on the first header line of the IOCP input data set in the `Title1` field.
   - Specify the name of the IOCP input data set. The IOCP input data set will automatically be allocated (record length 80, record format fixed block). If the data set already exists, you will be asked to confirm replacing it with the new one.
   - Specify whether to build the IOCP data set for stand-alone IOCP.

     Yes
     This is the default. The generated IOCP statements can be used as input to stand-alone IOCP program.

Note: You may not be able to use such a generated IOCP input data set for the migration function of HCD because, for example, the unit name of control units and device types can be truncated due to IOCP restrictions.

No
The IOCP input data set is built using the IOCP changes described in "IOCP Enhancements" and generating the extended migration parameters and statement (if the profile statement MIGRATE_EXTENDED is set to YES) as described in "IOCP Input Data Sets Using Extended Migration". Note that if you try to process these IOCP statements with the stand-alone IOCP program, you may run into problems, because the program may not accept the generated syntax.

- Change the job statement information to meet the installation needs. With JCL overwrite statements you can modify the EXEC procedure that is invoked. You can, for example, specify the HCD profile using the job step name GO. (See "Job Statement Information Used in Panels" on page 84 for a description of the job control information that you need to specify when you build an IOCP input data set.) Ensure that the batch job runs in a region with at least 4 Mbytes.

You can also invoke this task in batch mode. See "Build an IOCDS or an IOCP Input Data Set" on page 292.

IOCP Enhancements

The generated IOCP data set contains control unit and device types of 8 characters and a device model of up to 4 characters. Such an IOCP input data set can be processed by IOCP (with APAR OW13343) and remigrated to HCD without the need to correct the control unit and device types that exceed the 5 character UNIT and 2 character MODEL value limitation.

It also now contains an all-character readable token which allows the user to preserve the dynamic capability when performing a stand-alone IOCP run on a S/390 microprocessor cluster CPC using IOCP input from diskette.

IOCP Input Data Sets Using Extended Migration

As described in "Updating Parts of a Configuration by Migrating Input Data Sets" on page 267, HCD introduces an extended migration to allow you to define your complete configuration without using the ISPF front end dialog.

The extended migration allows you to, for example, define a switch with its ports or define serial numbers and descriptions for devices and control units by editing your input data sets and migrating them into HCD.

Analogously, when building an IOCP input data set from an IODF, information is generated that describes the additional parameters of the configuration objects (if the prerequisites under "Prerequisites to Exploit the Extended Migration" on page 193 are met). Within the generated IOCP input data set, the additional parameters and control statements are shown as comments with special HCD tags so that they can be processed by the IOCP program. When re-migrating such an IOCP input data set to HCD, the tagged comments are identified by HCD and migrated correspondingly.

If you want to use the input data set for both, IOCP processing and HCD migration, the new records must apply to the following rules, so that they can be processed by both programs:

- The new parameters start with the string `*$HCDC$` in column 1.
- The new SWITCH statement starts with the string `*$HCD$` in column 1.
- The IOCP control statement does not have any comment.
- The additional HCD tagged records follow immediately the last record of the corresponding IOCP control statement.
- The first keyword starts at column 16.
- The last operand is not followed by a comma.
- There is no comment to the right of the operand.

Prerequisites to Exploit the Extended Migration

To generate the additional keywords during IOCP data set build, note the following prerequisites:

- Specify the following entry in the HCD profile:

  ```
  MIGRATE_EXTENDED = YES
  ```

  When you specify `MIGRATE_EXTENDED = NO` (which is default), the additional keywords are not generated during IOCP build. In addition, when remigrating the IOCP input data sets, the migration function ignores the commented '*$HCDC$' and '*HCD' tags.

  The HCD profile is explained in "Defining an HCD Profile" on page 41.
- When building IOCP input data sets, you have to set the option `Input to Stand-alone IOCP` to `No` on the Build IOCP Input Data Set panel. See "Build an IOCP Input Data Set" on page 191 for a description of the new option.

Example of an IOCP Input Data Set

Figure 63 on page 194 shows you an example of a generated IOCP input data set with the new parameters. Note that each new parameter starts with an `*$HCDC$` in column 1. The new switch control statement starts with `*$HCD$` in column 1.

```
         ID    MSG1='EXAMPLE',MSG2='BOKA.IODF03 - 95-07-21 16:00',     *
               TOK=('TWO',00000001900096721600570400952 02F00000000,0000*
               0000,'95-07-21','16:00:57','BOKA','IODF03')
*$HCDC$        DESC='Cluster(099) test floor'
*$HCDC$        SERIAL='1044009672'
*$HCDC$        SNAADDR=(USIBMSC,TWO)
         RESOURCE PARTITION=((CF001,3),(MVSSMAL,2),(PRIME,1))
*$HCDC$        DESCL=('Coupling facility','MVS 5.2.0 System1','Producti*
               on CF image')
         CHPID PATH=(10),PARTITION=((CF001),(CF001)),TYPE=CFR
*$HCDC$        DESC='Receiver'
         CHPID PATH=(13),PARTITION=((PRIME),(PRIME)),TYPE=CFS
*$HCDC$        TPATH=(TWO,10,FFFE,FFFE)
*$HCDC$        DESC='Sender'
         CHPID PATH=(20),PARTITION=((MVSSMAL),(MVSSMAL)),SWITCH=AB,    *
               TYPE=CNC
*$HCDC$        SWPORT=((AA,C0))
*$HCDC$        DESC='Channel for DASD'
         CHPID PATH=(21),PARTITION=((MVSSMAL),(MVSSMAL)),TYPE=CNC
*$HCDC$        DESC='Channel for DASD'
         CHPID PATH=(25),PARTITION=((PRIME),(PRIME)),TYPE=CNC
*$HCDC$        SWPORT=((AB,80))
*$HCDC$        DESC='Switch connection'
         CHPID PATH=(26),PARTITION=((MVSSMAL),(MVSSMAL)),TYPE=CNC
*$HCDC$        SWPORT=((AA,C5))
*$HCDC$        DESC='Switch connection'
         CNTLUNIT CUNUMBR=0005,PATH=(25),UNITADD=((00,001)),UNIT=9032-3
*$HCDC$        SWPORT=((AB,FE))
*$HCDC$        SERIAL='1021-CU511'
*$HCDC$        DESC='SWITCH AB'
         CNTLUNIT CUNUMBR=0006,PATH=(26),UNITADD=((00,001)),UNIT=9033
*$HCDC$        SWPORT=((AA,FE))
*$HCDC$        SERIAL='1021-CU510'
*$HCDC$        DESC='SWITCH AA'
         CNTLUNIT CUNUMBR=000F,PATH=(20,21),UNITADD=((08,008)),        *
               LINK=(A1,A2),CUADD=3,UNIT=3995-151
*$HCDC$        SWPORT=((AA,C3),(AB,82))
*$HCDC$        SERIAL='5512003330'
*$HCDC$        DESC='DASD on Q4-B3'
         CNTLUNIT CUNUMBR=FFFE,PATH=(13),UNIT=CFS
         IODEVICE ADDRESS=(080,004),MODEL=151,UNITADD=08,              *
               CUNUMBR=(000F),STADET=Y,UNIT=3995
         IODEVICE ADDRESS=110,MODEL=3,UNITADD=00,CUNUMBR=(0005),       *
               STADET=Y,UNIT=9032
*$HCDC$        SERIAL='1021-CU511'
*$HCDC$        DESC='SWITCH AB'
         IODEVICE ADDRESS=120,UNITADD=00,CUNUMBR=(0006),STADET=Y,      *
               UNIT=9033
*$HCDC$        SERIAL='1021-CU510'
*$HCDC$        DESC='SWITCH AA'
         IODEVICE ADDRESS=(FFFE,002),CUNUMBR=(FFFE),UNIT=CFS
*$HCD$   SWITCH   SWID=AA,SERIAL='1021-CU510',DESC='SWITCH AA',        *
               PORT=((C0,CE),(FE,FE)),SWPORT=((CA,AB,C6)),UNIT=9033
*$HCD$   SWITCH   SWID=AB,SERIAL='1021-CU511',DESC='SWITCH AB',        *
               PORT=((80,F0),(FE,FE)),SWPORT=((C6,AA,CA)),MODEL=3,     *
               UNIT=9032
```

Figure 63. Example of Input Data Set for Migration Enhancements

Create JES3 Initialization Stream Checker Data

Because JES3 does not access the IODF directly, it has to be checked whether JES3 I/O and MVS I/O definitions are the same. It is essential that these definitions are consistent. Each time you run this task, the JES3 initialization stream checker data is stored in a data set, thus allowing JES3 to check the above mentioned definitions and to detect inconsistencies among them.

You can start the task from a work IODF as well as from a production IODF. However, it is recommended to use a production IODF to ensure that the same information is used for IPL.

1. On the primary task selection panel, select ***Activate or process configuration data***.
2. On the resulting panel select ***Create JES3 initialization stream data***. HCD displays the Create JES3 INISH Stream Checker Data panel.

```
──────────── Create JES3 INISH Stream Checker Data ──────────────


Specify or revise the following values.

JES3 initialization stream checker data set name
_____________________________________________________

MVS configuration ID . . . . . OPSYS01   +
EDT identifier . . . . . . . . A1  +
```

3. Specify the required values.

   The output data set will automatically be allocated (record length 80, record format fixed block). Depending on whether you specify the data set name as sequential or partitioned, the data set will be either sequential or partitioned. It is recommended to specify a partitioned data set (PDS), because this is required by the JES3 initialization stream checker.

   If the data set already exists, you will be asked to confirm replacing it with the new one.

You can also invoke this task in batch mode. See "Build I/O Configuration Statements" on page 295 for a description of the job control information that you need to specify when you build JES3 initialization stream checker data.

Build an OS Configuration Data Set

You can use HCD to create the OS configuration data set, HCPRIO statements for VM or OS configuration statements for MVS.

1. On the primary task selection panel, select ***Activate or process configuration data***.
2. From the resulting panel select ***Build OS configuration data set***. HCD displays the Build OS Configuration Data Set panel.

```
──────────────────── Build OS Configuration Data Set ────────────────────


Specify or revise the following values.

IODF name  . . . . . : 'HCDI.IODF00.WORK'
OS config ID . . . . . ________  +
OS config data set . . ____________________________________________

 F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
F12=Cancel
```

3. Specify the identifier of the OS configuration to be used and a name for an input data set to contain the OS configuration statements according to the type of OS configuration specified. The data set will be automatically allocated (record length 80, record format fixed block).

   If the data set already exists, you will be asked to confirm replacing it with the new one.

You can also invoke this task in batch mode. See "Build I/O Configuration Statements" on page 295 for a description of the job control information that you need to specify when you build an OS configuration data set of type MVS. For HCPRIO use the HCPRIO batch utility described in "Build an HCPRIO Input Data Set" on page 295.

Verify a Configuration

HCD allows you to check the definitions in your IODF against the actual configuration as sensed from the active system. See "Prerequisites" on page 9 for the prerequisites for the verify function.

The verify function results in a list of all sensed paths in comparison to the defined paths. Using a filter, this usually extensive list can be reduced to the data of interest. The list can be saved and/or printed. The verification can also be carried out as a batch job resulting in an I/O Path Report (see the example 372 in section "Print Configuration Reports" on page 299).

Verifying a Configuration Against the Local System

1. To verify the I/O configuration of the local system select ***Activate or process configuration data*** from the primary task level. From the resulting panel select ***Activate or verify configuration dynamically.*** The Activate or Verify Configuration panel is displayed.

   Note: For the verify function on the Activate or Verify Configuration panel to be available, the processor configuration from which the active IOCDS was built must match the configuration in the IODF used for IPL (token match).

2. Select the ***Verify active configuration against system*** task to compare the system against the active IODF. Select the ***Verify target configuration against system*** task to compare the system against the accessed IODF. The Identify System I/O Configuration panel is displayed.

```
Identify System I/O Configuration


Specify or revise the following values. Press ENTER to
continue.

IODF to be used . . . . . : IODFST.IODF4F
   Processor ID . . . . . FR38LPAR  +
   Partition name . . . . F38H      +
   OS configuration ID  . B710      +

I/O Cluster name  . . . . ________  + (only for Build CONFIGxx)
```

Figure 64. Identify System I/O Configuration Panel

3. Specify the processor ID and OS configuration ID. If the specified processor is in LPAR mode, you must also specify a partition name.

Verifying a Configuration Against a System in the Sysplex

1. Select ***Activate or process configuration data*** from the primary task level. From the resulting panel select ***Activate configuration sysplex-wide.*** The Active Sysplex Member List is displayed, listing all active systems of the Sysplex as stored in the sysplex couple data set of the system.
2. After selecting the system to be verified a context menu with two verification actions is displayed. Select the ***Verify active configuration against system*** task (action code **k**) to compare the system against the active IODF. Select the ***Verify target configuration against system*** task (action code **l**) to compare the system against the accessed IODF.

   The Identify System I/O Configuration panel is displayed (see Figure 64).
3. Specify the processor ID and OS configuration ID. If the specified processor is in LPAR mode, you must also enter a partition name.

The I/O Path List

The I/O Path List is the output of the verify function available on the Active Sysplex Member List and the Activate or Verify Configuration Dynamically panel (see "Verifying a Configuration Against the Local System" on page 196 and "Verifying a Configuration Against a System in the Sysplex"). The list compares the configuration in the accessed or the active IODF with the actual configuration as sensed from the system.

The report extends over two pages and can be scrolled horizontally.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------
                              I/O Path List         Row 1 of 473 More: >
Command ===> ___________________________________________ Scroll ===> PAGE

Accessed IODF: IODFST.IODF11
Active IODF  : IODFST.IODF11                            System . : CB88
Processor  . : CB88       Partition :                   OS config: B710

----I/O Path----- ----------Sensed Data--------- ----IODF Data-------- D
CHP CU   DEV      STAT CHT   CUTYPE   DEVTYPE  O CHT CUTYPE   DEVTYPE
10  FFFE FFFE,2        CFS   9674-C04 CFS        CFS CFS      CFS      C
11  FFFD FFFC,2        CFS   9674-C04 CFS        CFS CFS      CFS      C
12  FFFE FFF6,2        CFS   9674-C04 CFS        CFS CFS      CFS      C
13  FFFD FFF2,2        CFS   9674-C04 CFS        CFS CFS      CFS      C
20  0040 0040,32       CVC_P ****     ****                             *
21  EFD2 EFD2,4        CNC_S 9672-E02 9672-CTC   CNC SCTC     SCTC
21  EFD2 EFD6          CNC_S 9672-E02 9672-CTB   CNC SCTC     BCTC
21  EFE2 EFE2,4        CNC_S 9672-E02 9672-CTC   CNC SCTC     SCTC
21  EFE2 EFE6          CNC_S 9672-E02 9672-CTB   CNC SCTC     BCTC
21  FF74 FF74          CNC_S 9032-2   9032-2     CNC 9032     9032
22  0A00 0A00,64       CNC_S ****     ****     Y CNC 3990     3380     *
22  0A80 0A80,2        CNC_S 3990-6   3390-A38 Y CNC 3990     3390
22  0A80 0A82          CNC_S 3990-6   3390-A38   CNC 3990     3390
22  0A80 0A83          CNC_S 3990-6   3390-A38 Y CNC 3990     3390
22  0A80 0A84          CNC_S 3990-6   3390-A38   CNC 3990     3390
 F1=Help      F2=Split     F3=Exit      F7=Backward  F8=Forward   F9=Swap
F10=Actions  F12=Cancel   F20=Right    F22=Command
```

Data Shown on the I/O Path List

For each channel path sensed and/or defined in the accessed IODF the list contains a row showing the I/O path and the sensed and defined channel path, control unit, and device information. If a switch is included in the path, the right page shows the corresponding switch information.

Any discrepancies between the defined and the sensed data are indicated in column `D` on the right. For channel paths for which column `D` is blank, the defined and sensed data are consistent. The following values may appear:

Symbol	Meaning
`*`	Defined and sensed I/O paths differ
`C`	Defined only to processor but not to OS
`O`	Defined only to OS but without a path to the processor
`@`	A combination of * and C

On the display column `D` is highlighted.

Columns `STAT` and `O` indicate the status of the I/O path and the connected device, respectively. An empty field means that the corresponding I/O path or device is online. Offline I/O paths are marked with OFFL and offline devices with Y. If the system is unable to sense the status of an I/O path, it is marked UNKN.

Asterisks (`*`) in the CHT (channel type), CUTYPE (control unit type), or DEVTYPE (device type) columns indicate that I/O paths are returned but the values for the corresponding types are blank or invalid.

For certain configurations the I/O path list, although restricted to one processor or partition, can be extensive. Using the `Filter` action you can reduce the list to the entries of interest.

You can save the displayed list by entering SAVE in the command line on the I/O Path List panel.

Note: The LOCATE command is not available for the I/O path list.

Activate a Configuration Dynamically

The system programmer (or other authorized persons) can use the option ***Activate or verify configuration dynamically*** or the ACTIVATE operator command to make changes to a running configuration. That is, the possibility is offered to change from a currently active configuration to some other configuration that is to be made active without the need to POR or IPL the system again.

When activating a configuration dynamically, HCD compares the currently active IODF with the IODF that is to be activated and then processes the difference.

For the IODF that is to be activated, HCD uses the production IODF that is currently in use with the dialog. Use the same high-level qualifier for the currently active IODF and the IODF to be activated.

The manual *z/OS HCD Planning* gives a detailed description of how to dynamically activate a configuration. It describes the prerequisites for a dynamic activation, explains when hardware and software changes or software-only changes are allowed, and describes the actions necessary to change your I/O configuration dynamically. The following sections describe how to use the HCD dialog.

Before activating a configuration dynamically, you may want to view information about the IODF that has been used for IPL or the last dynamic activation.

View Active Configuration

HCD allows you to view the name and status of the IODF that has been used for IPL or for last dynamic activation. The operating system configuration and EDT identifier and, if applicable, the configuration token, which is currently active in the HSA (hardware system area), are shown. Use the ***View active configuration*** function for an overview of the actual status for dynamic activation, indicating whether hardware and software changes are allowed.

1. On the primary task selection panel, select ***Activate or process configuration data*** and then ***View active configuration***.

   The View Active Configuration panel with sample data is shown below:

```
──────────────────── View Active Configuration ────────────────────


Currently active IODF . . : SYS1.IODF01
   Creation date  . . . . : 1995-08-18
   Volume serial number . : SYSPAG

Configuration ID  . . . . : MVSVM       MVS Testsystem on VM
EDT ID  . . . . . . . . . : 00

HSA token . . . . . . . . : LMIF9672 96-08-02 13:22:50 SYS1     IODF50

Activation scope:
Hardware changes allowed .: Yes
Software changes allowed .: Yes

ENTER to view details on the activation scope.
```

2. Press the Enter key to display detailed information on limitation(s) to the activation scope. A Message List panel is displayed containing the messages about the reasons for the restrictions.

How to Activate if Hardware and Software Changes are Allowed

The following procedure describes how to activate a configuration dynamically if both hardware and software changes are allowed. Refer to *z/OS HCD Planning* on information when both hardware and software configuration changes are allowed and when only software configuration changes are allowed.

1. On the primary task selection panel, select ***Activate or process configuration data***, and from the resulting panel select ***Activate or verify configuration dynamically***. HCD displays the Activate or Verify Configuration panel.

```
──────────────── Activate or Verify Configuration ────────────────

The currently active IODF matches the hardware I/O
configuration.  Both hardware and software definitions may be
changed. Select one of the following tasks.

__  1.  Activate new hardware and software configuration.
    2.  Activate software configuration only. Validate
        hardware changes.
    3.  Activate software configuration only.
    4.  Verify active configuration against system.
    5.  Verify target configuration against system.
    6.  Build CONFIGxx member.

 F1=Help      F2=Split     F3=Exit      F9=Swap     F12=Cancel
```

2. Select what you want to activate. The following figure assumes that you selected task `1. Activate new hardware and software configuration`. The panels when you select the other tasks are similar.

```
──────────── Activate New Hardware and Software Configuration ────────────

Specify or revise the values for the IODF activation.

Currently active IODF . : SYS1.IODF01
   Processor ID . . . . : PROC1
   Configuration ID . . : OPSYS01
   EDT ID . . . . . . . : A1

IODF to be activated  . : SYS1.IODF02
   Processor ID . . . . . PROC1     +
   Configuration ID . . . OPSYS01   +
   EDT ID . . . . . . . . A1  +

Test only  . . . . . . . . . . . . . . . . . . . .  Yes  (Yes or No)
Allow hardware deletes (FORCE, FORCE=DEVICE) . . .  No   (Yes or No)
Delete partition access to CHPIDs unconditionally
(FORCE=CANDIDATE)  . . . . . . . . . . . . . . . .  No   (Yes or No)
Write IOCDS  . . . . . . . . . . . . . . . . . . .  No   (Yes or No)
Switch IOCDS for next POR  . . . . . . . . . . . .  No   (Yes or No)
```

Figure 65. Activate New Configuration: Hardware and Software Changes

The panel contains information about the currently active IODF.

If your processor runs in BASIC mode, the option `Allow hardware deletes` and the option `Delete partition access to CHPIDs unconditionally` are not displayed.

3. On the Activate New Hardware and Software Configuration panel you can change the fields that relate to the IODF that is to be activated, and you can specify options as applicable to your requirements. It is recommended that you first specify to test an activation before you dynamically activate a configuration. If the `test only` option is set to `Yes` and if the HCD profile contains the option SHOW_IO_CHANGES=YES, additional information messages are shown that informs you which channel paths, control units and devices are added, deleted, or modified for the Channel Subsystem.

   `Allow hardware deletes` option:

   If logical partitions have been defined for the currently active configuration, you can specify whether you want to allow hardware deletes.

   `Yes` means that the hardware deletes become effective for all partitions.

   `No` (the default) means that, if the changes include requests for deleting hardware, the activation is rejected.

   Note that hardware delete can also be indirectly performed as a result of other changes, for example, a change of a channel path consist of a deletion and an addition of a channel.

   A configuration change is rejected if it includes a hardware delete for an I/O component that is online to the logical partition from which you are making the change, even if you have entered `Yes` in the `Allow hardware deletes` option field. Therefore, you should vary offline any affected I/O component in all logical partitions. For example, when changing a channel path from unshared to shared, you must allow hardware deletes, and you must configure the channel path offline and vary offline the associated I/O devices before you activate the configuration. See *z/OS HCD Planning* for details about preventing disruption when changing the characteristics of I/O components.

   `Delete partition access to CHPIDs unconditionally` option:

   You can also specify how this activation should treat any deletion of a partition from the access or candidate list of a channel path. In the field `Delete partition access to CHPIDs unconditionally` (FORCE=CANDIDATE), enter either `Yes` or `No`. If you specify `Yes`, the access to the channel path will be revoked even if the channel is configured online to the partition; the channel will be configured off-line to the partition, and active I/O operations might be disrupted. If you specify `No` (the default), the activation will be rejected if it includes a deletion of partition access to a channel path that is configured online to that partition.

   Note: You cannot unconditionally delete the partition that is invoking the activate request from the candidate or access list of a channel path if the channel path is currently configured online.

4. If the dynamic activation completed successfully, HCD displays a message.

Configure Channel Path Online to the Partition

When activating a configuration in which a partition is added to the access list of a channel path, you must configure the channel path online to the partition using either the MVS CONFIG command or the processor console CHPID command. PR/SM will configure the channel path to the partition at subsequent activations only after you configure it using the commands above at least once.

When a particular IOCDS is used in a POR for the first time after it has been written, the definitions in that IOCDS are used to determine the assignment of

channel paths to logical partitions according to the channel path access lists that are defined. All previous information about channel configurations associated with this IOCDS is discarded. The exception to this rule is when a newly written IOCDS is first used as part of a dynamic I/O change to the system. For example, the new IOCDS is used as a result of a ***Switch IOCDS for next POR*** or the new IOCDS is the target of the ACTIOCDS= parameter of the MVS ACTIVATE command. When a new IOCDS is used in this manner, the current state of channel configurations is preserved and immediately associated with the newly written IOCDS.

See *z/OS MVS System Commands* for information about the MVS CONFIG command and see the *PR/SM Planning Guide* for information about the CHPID command and for a description of automatic configuration of channel paths to partitions.

If Dynamic Activation Fails

If the activation is rejected, HCD displays a panel that lists the messages and reasons for a failure. From the displayed message list, you can request further information. The message list can also be displayed by using the command SHOWMSG ACTIVATE on any panel that has a command line (except on help panels).

In some cases a dynamic activation may fail and HCD recommends recovery. HCD displays a panel where you can specify whether you want to recover:

- If you confirm recovery by specifying `Yes`, HCD performs *hardware-only changes*.

  You can specify to recover in two ways:
  - To resume activation of the target IODF. That is, HCD tries to continue with the activation.
  - To reset the configuration to the source IODF. That is, HCD activates the configuration that existed before the failure occurred.
- If you do not confirm recovery by specifying `No`, HCD allows you to continue with *software-only changes*. Hardware changes are activated up to the point where the failure occurred.

Detection of Illegal Split/Merge of LCU: If a request for activating a new configuration causes a logical control unit (LCU) to be split or merged illegally, HCD rejects the request. HCD considers an LCU to be:

- Illegally split if a physical control unit (PCU) is removed from the LCU that has devices remaining connected to it.
- Illegally merged if a physical control unit is added to an LCU that has devices connected to it.

HCD detects every split/merge during activation and informs you by message. The message tells between which PCU and which device the split/merge occurred; it also explains how to correct the condition.

For more information on how to recover after a system failure, refer to *z/OS HCD Planning*.

How to Activate if Software-Only Changes Are Allowed

The following procedure describes how to activate a configuration dynamically if only software changes are allowed. Refer to *z/OS HCD Planning* on information when both hardware and software configuration changes are allowed and when only software configuration changes are allowed.

1. On the primary task selection panel, select ***Activate or process configuration data***, and from the resulting panel select ***Activate configuration dynamically***. HCD displays the following panel:

```
──────────────────── Activate Software Configuration Only ────────────────────


Only software changes are allowed.

Specify or revise the values for IODF activation.

Currently active IODF . : SYS1.IODF31
   Configuration ID . . : MVSVM        MVS Testsystems on VM
   EDT ID . . . . . . . : 00

IODF to be activated  . : SYS1.IODF31
   Configuration ID . . . MVSVM     +
   EDT ID . . . . . . . . 00  +

Test only . . . . . . . . Yes    (Yes or No)
```

   The panel contains information about the currently active IODF.
2. On the Activate Software Configuration Only panel, you can change the fields that relate to the IODF that is to be activated. It is recommended that you first test an activation before you actually dynamically activate a configuration.
3. If the dynamic activation completed successfully, HCD displays a message.

If Dynamic Activation Fails

If the activation is rejected, HCD displays a panel that lists the message(s) and reasons for a failure. From the displayed message list, you can request further information. The message list can also be displayed by using the command SHOWMSG ACTIVATE on any panel that has a command line (except on help panels).

Activate a Configuration Sysplex Wide

HCD offers you a single point of control for systems in a sysplex. You can now dynamically activate the hardware and software configuration changes for each system in a sysplex from any other system in the same sysplex. You can:

- Display active sysplex members
- Activate Software Configuration Changes Only
- Activate Software and Hardware Configuration Changes
- Switch IOCDS for the next POR

z/OS HCD Planning gives a detailed description of how to dynamically activate a configuration. It describes the prerequisites for a dynamic activation, explains when hardware and software changes or software-only changes are allowed, and describes the actions necessary to change your I/O configuration dynamically. The following sections describe how to use the HCD dialog for dynamically activating systems in a sysplex.

Displaying Active Sysplex Members

Before you can make any change to a configuration in a sysplex, you must display the active sysplex member list. From this list you then select different actions.

1. On the primary task selection panel, select ***Activate or process configuration data***, and from the resulting panel select ***Activate configuration sysplex-wide***. HCD displays the Active Sysplex Member List.

```
  Goto  Query  Help
------------------------------------------------------------------------------
                          Active Sysplex Member List Row 1 of 16 More:       >

Select one or more systems, then press Enter. To refresh the Activate/Verify
Status, press Enter without selections made.

IODF to be activated: HCDI.IODF00.WORK
Active sysplex  . . : SYSPLEX1

  System   Processor Partition Active          Config.  EDT Act./Verify
/ Name     ID        Name      IODF            ID       ID  Status
_ SYSTEMA  PROCA     PARTA     HCDI.IODF00     MVSA     0A
_ SYSTEMB  PROCB               HCDI.IODF00     MVSB     0B
# SYSTEMC
_ SYSTEMD                      HCDI.IODF00     MVSD     0D
_ SYSTEME  PROCE               HCDI.IODF00     MVSE     0E
_ SYSTEMF  PROCF     PARTF     HCDI.IODF00     MVSF     0F
_ SYSTEM0  PROC0     PART0     HCDI.IODF00     MVS0     00
_ SYSTEM1  PROC1               HCDI.IODF00     MVS1     01
_ SYSTEM2  PROC2               SYS6.IODF05     MVS2     02
_ SYSTEM3  PROC3               SYS6.IODF05     MVS3     03
_ SYSTEM4  PROC4     PART4     HCDI.IODF00     MVS4     04
_ SYSTEM5                      HCDI.IODF00     MVS5     05
_ SYSTEM6  PROC6     PART6     HCDI.IODF00     MVS6     06
# SYSTEM7
_ SYSTEM8  PROC8     PART8     HCDI.IODF00     MVS8     08
_ SYSTEM9  PROC9               HCDI.IODF00     MVS9     09
_
```

Figure 66. Activate Sysplex Member List - Part 1

You can see the system names, and the processor IDs and partition names associated with the system names. You can also see the IODF to be activated, the name of the sysplex, the active IODFs, the configuration IDs and EDT IDs used for IPL, and the Activate status, which is empty initially.

HCD requests the information from the sysplex couple data set and the HSA of every CPC and displays it in a formatted list.

Refreshing the Active Sysplex Member List:

The Active Sysplex Member list will be refreshed whenever you press the Enter key. If a system joins the sysplex, it will be added to the list in alphabetical order. If a system leaves the sysplex, it will be deleted from the list.

Empty Processor ID:

The entry in the Processor ID column is empty when the operating system runs as a VM guest.

This does not mean that you cannot initiate an activation request for that system. It means that you have to specify the correct processor ID later on by yourself, as required.

Empty Partition Name:

The entry in the Partition Name column is empty when the processor runs in BASIC mode.

Disabled System Names:

Pre-MVS 5.1 systems in the sysplex are disabled for any action. That means any activation requests have to be initiated locally on that system using the option ***Activate or verify configuration dynamically***.

2. Scroll the panel to the right to see more information for processors configured in basic mode, such as the currently active hardware configuration token stored in the HSA, and whether the hardware configuration token stored in the HSA matches the processor token stored in the IODF. This information is not shown for processors running in LPAR mode because the information received from the sysplex data set might not reflect the actual state.

```
Goto  Query  Help
--------------------------------------------------------------------------------
                          Active Sysplex Member List Row 1 of 16 More: <     >

Select one or more systems, then press Enter. To refresh the activate status,
press Enter without selections made.

IODF to be activated: BBEI.IODF0A
Active sysplex  . . : SYSPLEX1

  System   -------HSA Configuration Token Information-- Token Match
/ Name     Proc.    Last Update       IODF Descriptors  HSA/Proc.
_ SYSTEMA
_ SYSTEMB  PROCB    21:30:14 95-03-23 BBEI     IODF00   No
# SYSTEMC
_ SYSTEMD
_ SYSTEME  PROCE    17:44:32 95-02-11 BBEI     IODF00   Yes
_ SYSTEMF
_ SYSTEM0
_ SYSTEM1  PROC1    11:23:12 95-01-12 BBEI     IODF00   Yes
_ SYSTEM2  PROC2    23:04:45 95-04-17 SYS6     IODF05   No
_ SYSTEM3  PROC3    08:43:02 95-04-02 SYS6     IODF05   No
_ SYSTEM4
_ SYSTEM5
_ SYSTEM6
# SYSTEM7
_ SYSTEM8
_ SYSTEM9  PROC9    12:08:34 95-01-13 BBEI     IODF00   Yes
_
```

Figure 67. Activate Sysplex Member List - Part 2

3. Again, scroll the panel to the right to see the free space in the HSA for processors configured in basic mode. For processors configured in LPAR mode, select the system name and the ***View the configuration status*** action to receive the equivalent information.

```
  Goto  Query  Help
------------------------------------------------------------------------------
                          Active Sysplex Member List Row 1 of 16 More: <

Select one or more systems, then press Enter. To refresh the activate status,
press Enter without selections made.

IODF to be activated: BBEI.IODF0A
Active sysplex  . . : SYSPLEX1

  System   Processor ---HSA available for config. changes---
/ Name     ID        Physical CUs  Subchannels  Logical CUs
_ SYSTEMA  PROCA
_ SYSTEMB  PROCB       120           217         4112
# SYSTEMC
_ SYSTEMD
_ SYSTEME  PROCE       120           217         4112
_ SYSTEMF  PROCF
_ SYSTEM0  PROC0
_ SYSTEM1  PROC1       120           217         4112
_ SYSTEM2  PROC2       120           217         4112
_ SYSTEM3  PROC3       120           217         4112
_ SYSTEM4  PROC4
_ SYSTEM5
_ SYSTEM6  PROC6
# SYSTEM7
_ SYSTEM8  PROC8
_ SYSTEM9  PROC9       120           217         4112
_
```

Figure 68. Activate Sysplex Member List - Part 3

Activate Software Configuration Changes Only

The following procedure describes how to change the software configuration for one or more systems in a sysplex.

1. Select one or more systems from the Active Sysplex Member list (see Figure 66 on page 204) and the ***Activate software configuration only*** action from the context menu (or action code **o**). The Activate Software Configuration Only panel is displayed.

```
Activate Software Configuration Only
                                                                  Row 1 of 4

Specify or revise the values for activation, then press Enter.

IODF to be activated: BBEI.IODF0A

System   Processor Partition Config.  EDT  Valid. Test  Active
Name     ID +      Name      ID +     ID + HW Ch. Only  IODF
SYSTEMA  PROCA     PARTA     MVSA     0A   Yes    Yes   BBEI.IODF00
SYSTEMB  PROCB               MVSB     0B   No     Yes   BBEI.IODF00
SYSTEMF  PROCF     PARTF     MVSF     0F   Yes    Yes   BBEI.IODF00
SYSTEM0  PROC0     PART0     MVS0     00   Yes    Yes   BBEI.IODF00
**************************** Bottom of data ****************************
```

Figure 69. Activate Software Configuration Only Panel

All systems you have selected are shown together with the associated processor IDs.

Empty Processor ID:

If the *Processor ID* field is empty, prompt for the processor IDs and select the actual one.

Empty Configuration or EDT ID:

If the *Config. ID* and the *EDT ID* fields are empty, it is an indication that the ID of the currently active configuration is not defined in the IODF to be activated. Prompt for the new ID. Updating the *processor ID*, the *Config. ID* or the *EDT ID* fields might be required if your IODF to be activated contains IDs different from those displayed as default IDs.

2. On the Activate Software Configuration Only panel, update the fields of one or more systems. It is recommended that you first test an activation before you actually dynamically activate a configuration.
3. After pressing the Enter key, the Active Sysplex Member list is displayed again, but now the Active Status column shows the status *In progress*. If you refresh the list occasionally, you can see that one system after the other completes the activation request. This is indicated by the status *Messages*.
4. Select a system and the ***View activate messages*** action from the context menu (or action code **m**). The messages returned from that system as the result of the activation request are displayed.

```
                              Message List
  Save  Query  Help
-------------------------------------------------------------------------
                                                                Row 1 of 4

Select one or more messages, then press Enter. To refresh the list, press
ENTER without selections made. To reply to a WTOR message, use the REPLY
command.

System name: SC52

/ Message Text
_  IOS500I ACTIVATE RESULTS 084
#  ACTIVATE COMPLETED SUCCESSFULLY
#  NOTE = 0100,SOFTWARE-ONLY CHANGE
#   COMPID=SC1C3
**************************** Bottom of data ******************************
```

Figure 70. Message Panel with ACTIVATE Messages

5. If you do not need the messages any longer, you can delete them by using the option ***Delete activate messages*** (or action code **d**).

If Dynamic Activation Fails

If the activation is rejected, HCD displays a panel that lists the messages and reasons for a failure.

To get more information you also use the ***View configuration status*** option (or action code **v**). This option provides you the same information as when entering the command D IOS,CONFIG(ALL) at the system console.

```
                                Message List
  Save  Query  Help
-----------------------------------------------------------------------------
                                                                   Row 1 of 12

View configuration status of selected systems.

Message Text
 IOS506I 06.49.55 I/O CONFIG DATA 378
 ACTIVE IODF DATA SET = SYS6.IODF29
 CONFIGURATION ID = L06RMVS1       EDT ID = 01
 TOKEN:  PROCESSOR DATE     TIME     DESCRIPTION
  SOURCE: P101     95-05-09 15:34:56 SYS6     IODF29
          48 PHYSICAL CONTROL UNITS
         547 SUBCHANNELS FOR SHARED CHANNEL PATHS
         548 SUBCHANNELS FOR UNSHARED CHANNEL PATHS
          23 LOGICAL CONTROL UNITS FOR SHARED CHANNEL PATHS
          23 LOGICAL CONTROL UNITS FOR UNSHARED CHANNEL
          PATHS
```

Figure 71. View Configuration Status Panel

HCD offers you two possibilities after an activation failed:

- Select ***Resume activation of target configuration*** (or action code **t**) to force the activation of the system.
- Select ***Reset source configuration*** (or action code **r**) to reset the original configuration.

Activate Software and Hardware Configuration Changes

The following procedure describes how to change the software and hardware configuration for one or more systems in a sysplex.

1. Select one or more systems from the Active Sysplex Member list and the ***Activate software and hardware configuration*** action from the context menu (or action code **a**). The Activate Hardware and Software Configuration panel is displayed.

```
              Activate Hardware and Software Configuration
                                                 Row 1 of 4 More:       >

Specify or revise the values for activation, then press Enter.

IODF to be activated: BBEI.IODF0A

System   Processor Partition Config.  EDT  -FORCE Option- Switch  Test
Name     ID +      Name      ID +     ID + DEVICE CANDID. IOCDS + Only
SYSTEME  PROCE               MVSE     0E   No     No      __      Yes
SYSTEMF  PROCF     PARTF     MVSF     0F   No     No      __      Yes
SYSTEM0  PROC0     PART0     MVS0     00   No     No      __      Yes
SYSTEM1  PROC1               MVS1     01   No     No      __      Yes
**************************** Bottom of data ****************************
```

Figure 72. Activate Hardware and Software Configuration Panel

The systems you have selected are shown together with the associated processor IDs.

Empty Processor ID:

If the `Processor ID` field is empty, prompt for the processor IDs and select the actual one.

Empty Configuration or EDT ID:

If the `Config. ID` and the `EDT ID` fields are empty, it is an indication that the ID of the currently active configuration is not defined in the IODF to be activated. Prompt for the new ID. Updating the `Processor ID`, the `Config. ID` or the `EDT ID` fields might be required if your IODF to be activated contains IDs different from those displayed as default IDs.

Switch IOCDS:

In the `Switch IOCDS` column, you can define the IOCDS name used for the next POR.

2. On the Activate Hardware and Software Configuration panel, update the fields of one or more systems. It is recommended that you first test an activation before you dynamically activate a configuration.

   If you plan to delete a device for a specific system, specify *Yes* in the *FORCE DEVICE* field of that system. If you plan to remove a partition from the access or candidate list of a channel path belonging to a specific system, specify *Yes* in the *FORCE CANDID.* field of that system.
3. After updating the panel, press the Enter key. The Active Sysplex Member list will be displayed again, but now the *Active IODF* fields have changed for the affected systems and now contain the name of the IODF to be activated. If you have defined different processor IDs, configuration IDs or EDT IDs, and you have activated their configurations, these fields also have been changed.
4. Select a system and the ***View activate messages*** action from the context menu (or action code **m**). The messages returned from that system as the result of the activation request are displayed.
5. If you do not need the messages any longer, you can delete them by using the option ***Delete activate messages*** (or action code **d**).

If Dynamic Activation Fails

Refer to "If Dynamic Activation Fails" on page 207 for information on how to proceed, if your activation has been rejected.

Switch IOCDS for the Next POR

In addition to dynamically activating a sysplex, you can also specify the IOCDSs to be used for the next POR from the Active Sysplex Member List.

Refer to "Switch IOCDS for Systems in a Sysplex" on page 213 for a description of how to switch the IOCDS for the next POR.

Build CONFIGxx Member

After dynamic changes have been made to a system it is recommended to update the corresponding CONFIGxx member to reflect these changes. HCD provides a function to build a CONFIGxx member containing the CHP, DEVICE, and SWITCH statements of the local system or of the selected system in a sysplex.

A CONFIGxx member can be built by:

- Selecting the ***Build CONFIGxx member*** action from the Activate or Verify Configuration panel (for the local system)

- Selecting the ***Build CONFIGxx member*** action from the Active Sysplex Member panel (for a system in a sysplex)
- Using a batch utility (see "Build I/O Configuration Statements" on page 295 for details)

After selecting ***Build CONFIGxx member***, the Identify System I/O Configuration panel is displayed (see Figure 64 on page 197). After selecting a system, and an I/O cluster name for managed channel paths, the Restrict Ports Eligible for Dynamic CHPID Management panel is displayed if the configuration contains managed channel paths for the selected I/O cluster. This panel shows all control units known by the selected system and manageable by DCM and their switch ports set to eligible for DCM (indicated by a 'Y'). You can specify ports as ineligible for DCM by overtyping 'Y' with 'N'.

```
──────────── Restrict Ports Eligible for Dynamic CHPID Management ──────────────
                                                                   Row 1 of 39
Command ===> ___________________________________________ Scroll ===> CSR

Type 'N' to restrict ports related to managed CHPIDs from being used by
dynamic CHPID management.

Processor ID: FR38LPAR  Partition: F38H      OS Configuration ID: B710
I/O Cluster name: UTCPLX38

         ---------- Last digit of port address --------
SW.Port  0  1  2  3  4  5  6  7  8  9  A  B  C  D  E  F
65.4     _  _  N  _  _  _  _  _  _  _  _  _  _  _  _  _
65.B     _  _  _  _  _  _  Y  _  _  _  _  _  Y  Y  Y  _
66.4     _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _  _
66.B     _  _  _  _  _  _  Y  _  _  _  _  _  Y  Y  Y  _
67.A     _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _  _
67.B     _  _  _  _  _  _  Y  _  _  _  _  _  Y  Y  Y  _
68.A     _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _  _
68.B     _  _  _  _  _  _  Y  _  _  _  _  _  Y  Y  Y  _
6D.C     _  _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _
6D.D     _  _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _
6E.C     _  _  _  Y  _  _  _  _  _  _  _  _  _  _  _  _
```

Figure 73. Restrict Ports Eligible for Dynamic CHPID Management Panel

The Build CONFIGxx Member panel is then displayed.

```
──────────────────────────── Build CONFIGxx Member ────────────────────────────


Specify or revise the values for the CONFIGxx member. Press ENTER to
continue.

Partitioned data set name . 'SYS1.PARMLIB'
Suffix of CONFIGxx member . __

Volume serial number  . . . ______  + (if data set not cataloged)
 F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
F12=Cancel
```

Figure 74. Build CONFIGxx Member Panel

The initial value for the partitioned data set name is 'SYS1.PARMLIB'.

If the specified CONFIGxx member already exists, the Confirm Update CONFIGxx Member panel is displayed.

```
──────────── Confirm Update CONFIGxx Member ────────────


 Specify or revise the values for the CONFIGxx member.
 Press ENTER to continue.

 Backup CONFIGxx member  . . . . CONFBK01

 Update I/O statements . . . . . 1  1. Update member
                                    2. Replace member

  F1=Help     F2=Split    F3=Exit     F5=Reset    F9=Swap
 F12=Cancel
```

Figure 75. Confirm Update CONFIGxx Member Panel

If you select `Update member`, the CHP, DEVICE, and SWITCH statements are replaced and all other statements remain unchanged. If you select `Replace member`, the content of the CONFIGxx member will be CHP, DEVICE, and SWITCH statements exclusively. All other statements formerly present in the member will be removed.

The following illustrates sample generated statements:

```
* CHP, DEV AND SWITCH STATEMENTS GENERATED BY
* BUILD CONFIGXX UPDATE  REQUEST
* 2001-01-09  13:56:28    IODF: BOKA.IODF38
* PROCESSOR: FR38LPAR  PARTITION: F38H      OS CONFIGURATION ID: B710
* I/O CLUSTER: UTCPLX38
CHP (00,01,04),ONLINE
CHP (05),ONLINE,MANAGED
CHP (06,07,08,09,0A,0B,0C,0D,0E,10),ONLINE
CHP (11),ONLINE,MANAGED
.....
DEVICE (0B00-0B1F),(1C),ONLINE
DEVICE (1400-143F),(0C,22,33),ONLINE
DEVICE (1440-147F),(10,1C,44),ONLINE
....
SWITCH (B565,42),NODCM
SWITCH (B565,B6,BC-BE),DCM
```

The default name for the backup member is CONFBKxx. If the name is blanked out, no backup is saved.

You can also invoke this task in batch mode. See “Build I/O Configuration Statements” on page 295 for a description of the job control information that you need to specify when building a CONFIGxx member.

Process Display M=CONFIG(xx) Command

HCD provides a dialog function to compare the information in the CONFIGxx member for the system in a sysplex with the hardware configuration. The comparison is carried out at the target system and any responses are displayed in a message list.

You can invoke the function from the Active Sysplex Member list by selecting the action ***Process DISPLAY M=CONFIG(xx) command.*** This displays the Process Display M=CONFIG(xx) Command panel.

```
Process DISPLAY M=CONFIG(xx) Command

The DISPLAY M=CONFIG(xx) command is executed on the selected target
system. Specify or revise the suffix for the CONFIGxx member of
SYS1.PARMLIB. Press ENTER to continue.

System  . . . . . . . . : SYSTEMA

Suffix of CONFIGxx member  . . __



 F1=Help    F2=Split   F3=Exit    F5=Reset   F9=Swap   F12=Cancel
```

Figure 76. Process Display M=CONFIG(xx) Command Panel

Here, the suffix for the member to be used must be specified.

The results of this action are displayed in the HCD message panel.

Switch IOCDS for Next POR

HCD allows you to specify an IOCDS that will be used for the next POR either while building IOCDSs or as a separate action without the need to build an IOCDS. Depending on the environment you are working, you have to use different panels to switch the IOCDS:

- Switch IOCDS for processor without SNA address defined
- Switch IOCDS for a processor in an S/390 microprocessor cluster with SNA address defined
- Switch IOCDS for systems in a sysplex

Switch IOCDS for Processor without SNA Address Defined

The following procedure is only recommended for processors that do *not* have an SNA address defined. For a detailed description of the following dialog sequence, refer to "Build an IOCDS" on page 184.

1. On the primary task selection panel, specify the name of a production IODF and select ***Activate or process configuration data***.
2. From the resulting panel select ***Build IOCDS***. HCD displays the Processor List panel.
3. On the Processor List panel, select the processor and press the Enter key. HCD displays the IOCDS List panel (see Figure 60 on page 184).
4. On the IOCDS List panel, select the IOCDSs you want to use for next POR and select ***Switch IOCDS*** from the context menu (or action code **S**).

If the HSA token is available, the HSA token is compared with the processor token. If the HSA token matches the processor token, the ***Switch IOCDS*** action is performed. A warning message is issued, if the date in the IOCDS update record is

an earlier date than the date of the last CSS update. If the HSA token does not match the processor token in the IODF, the action ***Switch IOCDS*** is not performed.

If the HSA token is not available, the serial number of the processor defined in the IODF is compared with the serial number of the active processor. If the serial numbers cannot be found, the types of the processors are compared. If the processor definition in the IODF matches the active processor, the action ***Switch IOCDS*** is performed, otherwise the procedure is not performed.

Switch IOCDS for Processors in an S/390 Microprocessor Cluster with SNA Address Defined

The following procedure describes how to build an IOCDS for processors in an S/390 microprocessor cluster *with* an SNA address defined. For a detailed description of the following dialog sequence, refer to "Build S/390 Microprocessor IOCDSs" on page 186.

1. On the primary task selection panel, select ***Activate or process configuration data*** and from the resulting panel select ***Build and manage S/390 microprocessor IOCDSs and IPL attributes***. The S/390 Microprocessor Cluster List panel is displayed (see Figure 61 on page 187).
2. On the S/390 Microprocessor Cluster List panel, select the CPCs for which you want to switch the IOCDSs and ***Work with IOCDSs*** from the context menu (or action code **s**). HCD displays the IOCDS List panel (see Figure 62 on page 188).
3. Use the ***Switch IOCDS*** action (or action code **s**) to mark an IOCDS as the IOCDS that is used for next POR. The `Status` field will be set accordingly.

   You can only switch to an IOCDS that has an IOCDS/HSA token match or to an IOCDS of a processor that is not activated ('POR-required' status).

Switch IOCDS for Systems in a Sysplex

In addition to dynamically activating a sysplex, you can also specify the IOCDSs to be used for the next POR.

1. Select one or more systems from the Active Sysplex Member list (see Figure 66 on page 204) and the ***Switch IOCDS for next POR*** action from the context menu (or action code **s**). The Switch IOCDS panel is displayed.

```
                              Switch IOCDS
                                                                  Row 1 of 4
Command ===> ___________________________________________ Scroll ===> PAGE

Specify the IOCDS(es) for next POR, then press Enter.

System   Processor Config.  EDT Switch   Active
Name     ID        ID       ID  IOCDS +  IODF
SYSTEMA  PROCA     MVSA     0A  __       BBEI.IODF00
SYSTEMB  PROCB     MVSB     0B  __       BBEI.IODF00
SYSTEMF  PROCF     MVSF     0F  __       BBEI.IODF00
SYSTEM0  PROC0     MVS0     00  __       BBEI.IODF00
*************************** Bottom of data ****************************
```

2. In the column Switch IOCDS, specify the IOCDS that is to be used for the next POR and press the Enter key.

Specify an IODF for IPL

z/OS HCD Planning gives a detailed description of how to specify an I/O configuration at IPL. This chapter summarizes the main aspects you have to consider when specifying an IODF for IPL.

Note

A production IODF must have a single extent. If the production IODF has multiple extents, the IPL process results in a WAIT state (wait state code '0B1', reason code '002'). HCD issues error message CBDA009I if a production IODF cannot be built in a single extent.

IODF Processing at IPL

When you perform an IPL, the production IODF that defines the configuration to the system is selected and used.

On the LOAD parameter, you specify the device containing the IODF for IPL and the identifier for the LOADxx member. In the LOADxx member of SYSn.IPLPARM or SYS1.PARMLIB, you identify the IODF by the IODF statement. The IODF statement consists of an IODF *prefix* and an IODF *suffix*.

- The IODF prefix is an 8-byte high-level qualifier of the IODF data set name. For example, BPAN is the IODF prefix for the IODF data set BPAN.IODF01.
- the IODF suffix is the two-digit hexadecimal number that is part of the IODF name. For example, 01 is the IODF suffix for IODF01. If you do not specify a suffix, MVS searches for an IODF sequentially in a numerically ascending order starting with the IODF suffix 00. If you specify ** as the suffix, MVS uses the descriptor fields to find the current IODF.

During IPL, the system uses the LOADxx member that it finds first when searching in the following order:

1. The system first searches the IODF volume for SYS0.IPLPARM through SYS9.IPLPARM, in that order.
2. If it does not find a SYSn.IPLPARM, it searches the IODF volume for a SYS1.PARMLIB.
3. If it does not find SYS1.PARMLIB on the IODF device, it searches for SYS1.PARMLIB on the IPL device.
4. If it does not find a SYS1.PARMLIB on the IPL device, a coded non-restartable wait state is loaded (WAIT code X'0B1').

Chapter 9. How to Print and Compare Configuration Data

Overview

This chapter describes how to:

- Print configuration reports (channel subsystem, switch, OS configuration data, and CTC connections)
- Print a report of the I/O paths of the actual system compared to the defined I/O configuration
- Print a report of the supported hardware or an I/O definition reference
- Create or view a graphical report of the I/O configuration
- Compare functions (IODFs and CSS/operating system views)
- Print List Panels
- View and print the activity log

Print Configuration Reports

You can use HCD to generate several types of reports about the configuration data in an IODF:

- Channel Subsystem (CSS) Report
- Switch Report
- Operating System (OS) Report
- CTC Connection Report
- I/O Path Report
- Supported Hardware Report
- I/O Definition Reference

In the HCD profile definition, you have the option of printing textual reports in upper case only or defining the number of lines per page (see "Options for Text Reports" on page 42).

Examples of these reports are shown in Appendix B, "Configuration Reports" on page 355.

Channel Subsystem Report

The Channel Subsystem Report contains all configuration data that is used by the channel subsystem. If the IODF contains data for more than one processor or logical partition, you can limit the report to the data for one processor or partition. If you limit the report to one partition, it will generate information only for channel paths, which have the partition in the access list. Channel paths that have that partition in a candidate list will not be taken into consideration.

You can select four types of reports:

- **CSS summary reports** include summary reports about:
  - Processors
  - Partitions
  - IOCDSs
  - Channel paths
  - Control units
  - Devices

  The processor and partition reports are not printed if you limit the CSS summary reports to the data for one processor or partition.

© Copyright IBM Corp. 1994, 2002

- **Channel path detail reports** include reports about:
  - Channel paths
  - CF channel path connectivity
- **Control unit detail report**
- **Device detail report**

Switch Report

The Switch Report contains details about the switch definition, its configurations and the port definitions.

If the IODF contains data for more than one switch, you can limit the report to the data for one switch and the configurations for this switch. In this case, you do not get a switch summary report.

Operating System Report

The Operating System Report contains the configuration data that is used by z/OS or VM/ESA. If the IODF contains data for more than one operating system, you can limit the report to the data for one operating system. You can select three types of reports:

1. The OS device report includes reports about operating systems and OS devices.

   The operating system summary report is not printed if you limit the OS device report to the data for one operating system.
2. OS console report
3. EDT report (MVS-type only)

CTC Connection Report

The CTC Connection Report contains CTC connections of your configuration that are defined through a switch. In case of incorrect definitions, the report also contains a list of messages with diagnostic information.

If the IODF contains more than one processor or logical partition, you can limit the report to the data for one processor or partition.

I/O Path Report

The I/O Path report shows the physically sensed I/O paths (with physical types) of the active system compared with the logical definitions of the paths (also the object types) of a specific IODF.

On the Limit Reports panel (Figure 78 on page 218) the active configuration to sense the configuration from, can be specified by indicating a SYSPLEX and/or SYSTEM name. If nothing is specified, the data is taken from the local system.

For more information, see “Job Statement Information Used in Panels” on page 84.

See “Prerequisites” on page 9 for the prerequisites for the I/O Path report.

Supported Hardware Report

The Supported Hardware Report contains information about the processors, control units, and devices supported in your installation. This report can only be generated using the batch facility as described in “Print Configuration Reports” on page 299.

This report is generated directly from the UIMs. Therefore, it reflects the latest UIM levels installed.

I/O Definition Reference

The I/O Definition Reference contains a description of the parameters to define the device to the Channel Subsystem, and a description of the parameters and features to define the device to the operating system.

This report is generated directly from the UIMs. Therefore, it reflects the latest UIM levels installed.

This report can only be generated using the batch facility as described in "Print Configuration Reports" on page 299.

How to Print a Textual Report

1. On the primary task selection panel, select ***Print or compare configuration data***.
2. On the resulting Print and Compare Configuration Data panel, select ***Print configuration reports***. HCD then displays the following panel:

```
                    Print Configuration Reports


Select the types of report you want, and specify the values below.

IODF name  : 'DOCU.IODF01'

Types of report                 Limit report(s)
_  CSS report                   1   1.  Yes
_  Switch report                    2.  No
_  OS report
_  CTC connection report
_  I/O path report

Job statement information
//         JOB (ACCOUNT),'NAME'
//*
//*
//*
//*
//*

 F1=Help     F2=Split    F3=Exit     F5=Reset    F9=Swap    F12=Cancel
```

Figure 77. Print Configuration Reports Panel

3. Enter the required data.

   When you select a CSS or OS report an additional panel appears on which you can select one or more report types.

   If a data set is pre-allocated the logical record size must be 133. You can allocate the report output data set HCDRPT using the job step name GO.
4. When you select to limit the reports, possible for CSS, Switch, OS and CTC connection reports, the Limit Reports panel appears that allows you to specify a processor ID, partition name, OS configuration ID and a switch ID. When you select an I/O Path report, the Limit Reports panel always appears. This is because limiting an I/O Path report is required. Default values for the processor ID, the partition name (for an LPAR processor) and the OS

configuration ID are then already filled in. These values are based on the active configuration. The system name identifies the system of a sysplex for that the I/O Path report is to be generated. The default is the local system. The sysplex name specifies the sysplex of the system for that the I/O Path report is to be generated. If you specify the sysplex, you must also specify the system name. If you do not specify the sysplex, the system name is the VTAM application name of the host that the I/O Path report is to be generated for. If you selected to print more than one report type, the limitations specified on the Limit Reports panel apply to all of them.

```
                        Limit Reports


To limit the reports, specify the following criteria related
to the IODF in access.

                                     Applicable for:
Processor ID . . . . ________  +  CSS, CTC, I/O path reports
Partition name . . . ________  +  CSS, CTC, I/O path report
OS configuration ID  ________  +  OS, I/O path report
Switch ID  . . . . . __        +  switch report

Specify the sysplex and system name to gather the actual
configuration from.  (Blanks default to the local system.)

Sysplex name . . . . ________     I/O path report
System name  . . . . ________     I/O path report

 F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset
 F9=Swap    F12=Cancel
```

Figure 78. Example of a Limit Reports Panel

The submitted job only starts if the IODF is accessed in read mode. If it is accessed in update mode, the job waits until you access another IODF or exit HCD.

You can also print reports using the batch mode. See "Print Configuration Reports" on page 299 for a description of the job control information that you need to specify when printing a report.

Create or View Graphical Configuration Reports

HCD offers you to print and view a graphical representation of the I/O configuration based on the definitions in the IODF. The reports can be either stored in a data set for printing on an AFP printer (such IBM 3820 or IBM 3800) or via GDDM later on, or displayed on an IBM 3270 terminal with graphical capability.

The graphical report function allows you to print or view five types of reports:

- The **LCU report** shows all logical control units defined for one processor.
- The **CU report** takes a control unit as focal point and shows the connections to the processors and the devices of the IODF. On request, it shows the switches as well.
- The **CHPID report** shows the defined channel paths for a processor and the switches, control units, and devices attached to the CHPID.
- The **Switch report** takes a switch (ESCON director) as focal point and shows the processors, chained switches, and control units with devices attached to the switch.

- The **CF connection report** takes a coupling facility as focal point and shows all connections that exist between the coupling facility and the other processors defined in the IODF.

Prerequisites

For Printing

To process the reports for printing you need one of the following:
- BookMaster Release 3.0 or higher
- DCF/GML Release 4.0
- GDDM Version 2.1 or later

To print the reports you need an AFP printer, such as IBM 3820 or IBM 3800 (not required for GDDM).

To store the output in GDF format, you have to use a terminal with a screen size of 80 columns, for example a 3278-2.

In the HCD profile, specify whether the output of this function can be processed with BookMaster, DCF, GML, or GDF (keyword GCR_FORMAT). BookMaster is the default. To use DCF or GML format, specify a mono- space font using the keyword GCR_FONT. For example, specify `GCR_FONT = X0GT20` (Gothic Text 20-pitch) for a 3820 printer. For more information about the HCD profile, refer to "Defining an HCD Profile" on page 41.

For Viewing

To view the report on an IBM 3270 terminal with graphical capability, GDDM must be installed on your system. Refer to "Setting Up HCD" on page 37 on how to setup the GDDM support.

Use a terminal with a screen size of 80 columns, for example a 3278-2. This display function does not work on terminals (or terminal emulations) with a screen size of 132 columns. HCD uses ISPF to create the GDDM display, which means that terminals running in partition mode or terminals with multiple screen widths, including 3290 and the 3278 Mod 5, are not supported for graphics interface mode.

In the HCD profile, you can specify the colors used for displaying the graphic (see "Defining an HCD Profile" on page 41). If you change the default colors, make sure that foreground and background color match.

How to Create a Graphical Configuration Report

To print or view a configuration, use ***Create or view graphical configuration report.*** on the primary task selection panel. The dialog is described in "Using the Create or View Graphical Configuration Report Option" on page 220.

To view objects in context of their attached objects you can also select an object from an object list panel and use the ***View graphically*** action from the context menu (or action code **h**). The following object lists support this possibility:
- Channel path list
- Control unit list
- I/O device list (only for devices that connect to a control unit)
- Partition list
- Switch list

For example, from the Switch List panel, you can view a switch together with all objects that are attached to the switch. This can help you, for example, to immediately verify your definitions while defining your configuration.

Using the Create or View Graphical Configuration Report Option

1. Select ***Create or view graphical configuration report.*** on the primary task selection panel.
2. The Create or View Graphical Configuration Report panel appears.

```
──────────── Create or View Graphical Configuration Report ────────────


Select the type of report you want, and specify the values below.

IODF name . . . . . . : 'BPAN.IODF00.WORK'

Type of report  . . . . 2_  1.  LCU report
                            2.  CU report
                            3.  CHPID report
                            4.  Switch report
                            5.  CF connection report

Processor ID  . . . . . ________  + (for an LCU or a CHPID report)
Partition name  . . . . ________  + (to limit an LCU or a CHPID report)

Output data set . . . . 'BPAN.IODF00.PRINT'

Output  . . . . . . . . 1   1.  Write to output data set
                            2.  View
```

`Type of report`: Select the type of report you want to create.

`Processor ID` and `Partition name`: Enter the required data for an LCU or a CHPID report.

`Output`: Select whether you want to write the output to an output data set for printing or to display the output on your terminal.

`Output data set`: For BookMaster, GML, or DCF processing, the output data set must be a sequential data set or a member of a partitioned data set. If the PDS or the sequential data set does not exist, it will automatically be allocated (record length 200, record format fixed blocked).

For creating output for GDF, specify a member of a partitioned data set. If the data set does not exist, it will automatically be allocated (record length 400, record format fixed blocked). If the data set already exists, it is overwritten with the new data, you are not asked to confirm replacement. The output is written into different members, one for each segment (see "Printing the Output" on page 221 for a definition what a segment is). The member names are up to eight characters long. They are derived from taking up to seven characters from the member name specified in the output data set field and adding a number. For instance, if the name was specified as `'BPAN.IODF00.PRINT(SWITCHES)'`, the member names would be `SWITCH01, SWITCH02, ... SWITCH10`, and so on.

3. When pressing the Enter key, the Define Report Layout panel appears. The following example shows the panel for a CU report.

```
                          Define Report Layout


Specify the values below for report type: CU

Include index  . . . 1_  1.  Yes     Include partitions . 1_  1.  Yes
                         2.  No                              2.  No

                                     Only for a CU or CHPID report:
Include CTC, CF CUs. 1_  1.  Yes     Include switches . . 1_  1.  Yes
                         2.  No                              2.  No

Show CU  . . . . . . 1_  1.  Serial number
                         2.  Description

To limit a CU report, specify only one of the following:
Range  . . . . . . . ____  -  ____
Type . . . . . . . . ____________  +
Group  . . . . . . . ________  +
```

Select what you want to include in the graphical report. To limit the control units to be shown in a CU report, you can specify either the range, type, or group (for example, DASD) of the control units.

4. After pressing the Enter key the report is written to an output data set or shown on the terminal. See "Printing the Output" and "Viewing the Output" on page 222 on how to proceed.

You can also create graphical reports using the batch mode. See "Create a Graphical Configuration Report" on page 301 for a description of the job control information that you need to specify when printing a report.

Printing the Output

1. Process the output data set using BookMaster, DCF, GML, or GDF. While processing it is recommended that you specify the following parameters:

   Indexing
   To print the index you selected on the Define Report Layout panel specify INDEX for BookMaster and GML processing

   Full page
   To use the full page for the report SYSVAR S is to be set to 1 for DCF processing. Note that in many installations offset is used as default.

   Rotate printout
   Specify a parameter to print the report in landscape format, that means to rotate the printout by 90 degree.

2. Print the report.

HCD tries to display a report on one page. If a report is too large for one page, HCD divides the report into segments and shows each segment on an extra page. If a CU report, for example, shows more than 8 control units, HCD shows the control units of the same type in one segment on an extra page. If a segment is too large for one page, HCD continues the segment on the next page. You can specify the `GCR_COMPACT=YES` keyword in the HCD profile to see more objects on one page.

For an example of a report, see "Graphical Configuration Reports" on page 405.

Viewing the Output

The following figure shows an example of the panel when viewing a report.

```
                                HCD Graphics

                                PROC1
9121-480                                                LPAR

BOEBPN1    BOEBPN1    BOEBPN1    BOEBPN2    BOEBPN2

  DED        REC        DED        DED        DED
  CNC        CVC        CNC        CNC        CNC
  1          1          1          2          2
  9          A          B          E          F

  1          1          1          1          1 1 2 2
  A          A          A          A          9 B E F

 3088       3088       3088       3088        SWCH
 1A00       1A40       1A80       1AC0       1B00

 3088       3088       3088       3088       SWCH
1A00,064   1A40,064   1A80,064   1AC0,064   1B00,001

Command ===>                                                  1 OF 1
  F1=Help      F2=Split     F3=Exit      F4=Jump      F5=Zoom in   F6=Zoom out
  F7=Up        F8=Down      F9=Swap     F10=Previous F11=Next     F12=Cancel
 F19=Left     F20=Right    F22=Command
```

HCD tries to display the entire configuration on one panel. If a report is too large for one panel, HCD divides the report into segments and shows each segment on an extra panel. If a CU report, for example, shows more than 8 control units, HCD shows the control units of the same type in one segment on an extra panel. You can move from segment to segment by using the Next and Previous function keys.

If a segment is too large for the panel, you can scroll upwards, downwards, to the left and to the right.

The following list describes specific function keys while viewing a graphical report.

F4=Jump
This function can only be used when you have displayed the graphical report using the ***Create or view graphical configuration report.*** on the primary task selection panel. It displays the action list of the HCD dialog that contains the object you selected with the cursor. Any change made to the configuration on the action list will not be reflected in the graphical report when you return to it. Use the REFRESH command to reflect the changes made to the objects currently shown on the display (see "Refresh Command" on page 224).

F5=Zoom in
Makes the graphical display bigger, so you can see the details of an object. The position of the cursor identifies the lower left corner of the part you want to enlarge. If the cursor in not positioned, HCD takes the center of the currently displayed report.

F6=Zoom out
Makes the graphical display smaller, so you can see more of a report on one panel.

F7=Up
Scrolls upwards.

F8=Down
Scrolls downwards.

F10=Previous
Moves to the previous segment of a report, if any.

F11=Next
Moves to the next segment of a report, if any.

F19=Left
Scrolls to the left.

F20=Right
Scrolls to the right.

Save Command

You can use the SAVE command to store a graphical configuration displayed on your screen in a member of a partitioned data set (PDS) in GDF format for printing with GDDM.

Before you use this command, the partitioned data set has to be allocated to ddname ADMGDF. The records of this PDS must have a record length of 400.

Specify SAVE (or just SA) and the member name, into which you want to save the data, on the command line. The syntax of the SAVE command is as follows:

SAVE Command

```
►►──┬─SAVE─┬──member_name──────────────────────────────────────────►◄
    └─SA───┘
```

member_name
specifies the name of the member to contain the graphical configuration you want to print. Use a different name for each SAVE command, otherwise the data will be overwritten. The name may be up to eight characters long.

Locate Command

You can use the LOCATE command to center and highlight a specific object of the report. When you locate a partition, channel paths, or coupling facility partition, the connections to the object are highlighted instead of the object itself.

Specify LOCATE (or just L) and the object you want to locate in the command line. For objects that are associated with another object (for example, CHPIDs that are associated with a processor), you have to specify this object as well.

Locating Multiple Objects with the Same ID: The LOCATE command first searches for an object in the currently displayed panel. If the object is not found it starts with the first segment and continues to the right until an object has been found. To find the other objects with the same ID, use the + and − parameter of the LOCATE command. The + parameter searches for the next object to the right, the − parameter to the left.

The syntax of the LOCATE command is as follows:

LOCATE command

```
►►──┬─LOCATE─┬──┬─CF──processor ID──────────────────┬──┬──────────────────►◄
    └─L──────┘  │  ├─CHPID──processor ID──┬──object id──┤  ├─ + ─┤
                │  ├─CU──────────────────┤             │  └─ - ─┘
                │  ├─DEV─────────────────┤             │
                │  ├─PART──processor ID──┤             │
                │  ├─PR──────────────────┤             │
                │  └─SW──────────────────┘             │
```

CF Coupling Facility
CHPID
Channel path
CU Control unit
DEV Device
PART Partition
PR Processor
SW Switch

Example: To locate CHPID 27 of processor SYSA, type

```
L CHPID SYSA 27
```

Refresh Command

When you jump to an action list using F4=Jump and change objects in this list, use the REFRESH command on return to the graphical display to refresh the graphic with the changes made.

REFRESH applies to all objects that were currently shown on the graphical report when pressing the F4=Jump key, that is, added objects or those, for which you changed the ID, will not appear in the refreshed graphic.

Valid abbreviation of the REFRESH command is RE.

Print List Panels

You can use the SAVE command to save the data that is currently displayed on HCD list panels into the data set. The data set can be used for printing.

You can also save and print lists that are filtered. If you use the ***Set Filter*** option from the ***Filter*** action bar choice, you can, for example, print all channels of a processor that are not connected to a control unit.

The command is available on the following list panels:

- Operating system configuration list
  - EDT list
  - Esoteric list
  - Esoteric/device list
  - Generic
  - Generic/device list
  - Console list
- Switch list
  - Port list
  - Switch configuration list
  - Port matrix
- Processor list
  - Channel path list
  - Partition list
- Control unit list
- Device list
- Configuration package list
  - Configuration package object list
- CTC connection list
- I/O path list

On these list panels, perform the following steps:

1. Enter the command

   ```
   SAVE
   ```

2. The Save List panel appears:

   ```
   ------------------------------ Save List ------------------------------
   | Specify the following values.                                        |
   | Output data set  ____________________________________________________|
   | Additional remarks (for example, the filter criteria)                |
   | ____________________________________________________________________|
   | ____________________________________________________________________|
   ----------------------------------------------------------------------
   ```

   The output data set can be a sequential data set or a member of a partitioned data set. If the data set does not exist, it will be automatically allocated (record length 300, record format fixed block). The name of the data set is saved for the next HCD session.

   In addition you can specify two lines of optional comments that will be shown under the header of your report.

3. A result of a printed data set may look like the following example. Note that the column headers the same as shown on the panel itself.

```
BOKA.IODF52.WORK - 2000-11-16  14:00 - Channel Path List 1

with DCM 2

Processor : FR38LPAR 3  Partitions : 1=F38B      2=F38C      3=F38D      4=F38E      5=F38F
                                     6=F38G      7=F38H      8=CFQ1      9=CFQ2      A=F38A
                                     B=          C=          D=          E=          F=

                DynEntry Entry +          I/O Cluster                                 ----------Partitions---------
CHPID Type Mode Switch + Sw Port Con Mngd Name        Description                     1 2 3 4 5 6 7 8 9 A B C D E F 4
-------------------------------------------------------------------------------------------------------------------------
00    CNC  SHR  __       00 20   _   No   ________   ______________________

00    CBP  SHR  __       __ __   Y   No   ________   CFQ1 ICB SENDER CHANNEL        a a a a a a a _ _ a _ _ _ _ _
01    CBP  DED  __       __ __   Y   No   ________   CFQ1 ICB RECEIVER CHANNEL      _ _ _ _ _ _ _ a _ _ _ _ _ _ _
02    CBP  SHR  __       __ __   Y   No   ________   CFQ1 ICB SENDER CHANNEL        a a a a a a a _ _ a _ _ _ _ _
03    CBP  DED  __       __ __   Y   No   ________   CFQ1 ICB RECEIVER CHANNEL      _ _ _ _ _ _ _ a _ _ _ _ _ _ _
04    CNC  SHR  6D       6D FB   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
05    CNC  SHR  6E       6E FB   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
06    CNC  SHR  6F       6F B3   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
07    CNC  SHR  6F       6F C7   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
08    CNC  SHR  70       70 B3   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
09    CNC  SHR  70       70 C7   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0A    CNC  SHR  77       77 EB   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0B    CNC  SHR  77       77 31   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0C    CNC  SHR  89       89 D6   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0D    CNC  SHR  89       89 43   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0E    CNC  SHR  71       71 73   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
0F    CVC  DED  __       __ __   _   No   ________   console for F38C               _ a _ _ _ _ _ _ _ _ _ _ _ _ _
10    CNC  SHR  65       65 A9   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
11    CNC  SHR  66       66 A9   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
12    CNC  SHR  67       67 A9   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
13    CNC  SHR  68       68 A9   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
14    CNC  SHR  6D       6D F7   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
15    CNC  SHR  6E       6E F7   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
16    CNC  SHR  6F       6F AF   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
17    CNC  SHR  6F       6F CB   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
18    CNC  SHR  70       70 AF   _   Yes  UTCPLX38   ______________________________ * * * * * * * _ _ * _ _ _ _ _
19    CNC  SHR  70       70 CB   _   No   ________   ______________________________ a a a a a a a _ _ a _ _ _ _ _
```

Figure 79. Example of a Printed List Panel

1 Header with IODF name, date, time, list name

2 Optional comments specified on Save List panel

3 Identifier of higher-level object, for example the processor name when you print the channel path list

4 Column headers as shown on the panel itself

Compare Functions

Compare IODFs

You can use the ***Compare IODFs*** function to compare two IODFs and report the differences between them. For greater clarity, you can limit the compare reports to certain perspectives of the IODF:

- The ***Processor Compare Report*** shows differences in the properties of partitions, CHPIDs, control units, and devices.
- The ***Switch Compare Report*** shows differences in the properties of switches and switch configurations.
- The ***OS Configuration Compare Report*** shows differences in device parameters, in features, in EDTs, in esoterics, in generics defined for EDTs, and consoles.

To compare IODFs, do the following:

1. Select ***Print or compare configuration data*** on the primary task selection panel .
2. On the Print or Compare Configuration Data panel, select ***Compare IODFs***. The following panel is displayed:

```
                              Compare IODFs

Select the compare reports you want, and specify the following values.

New IODF name : 'DOCU.IODF01'
Old IODF name . ________________________________  +

Select compare reports                  Limit ?
             _  Processor                 _  Yes
             _  Switch                    _  Yes
             _  Operating system          _  Yes

Job statement information
//         JOB (ACCOUNT),'NAME'
//*
//*
//*
//*
//*

 F1=Help     F2=Split  F3=Exit  F4=Prompt   F5=Reset    F9=Swap
F12=Cancel
```

Figure 80. Example of a Compare IODFs Panel

On this panel, select one or more compare report(s). In addition, you can set the limit option. When the limit option is set, the related limiting panels will come up.

On the ***Limit Processor Compare Reports*** panel, you can limit the processor compare reports by one or more of the specific compare reports. In addition, you can limit the reports by specifying a processor ID and a partition name. If you want to limit by processor, you must specify the processor IDs for both IODFs or not at all. If you limit the processor compare report by partition name, you receive the following results:

- Channel path compare will only contain channel paths which have the limiting partition in their access or candidate list.
- Control unit compare will only include the control units related to channel paths which have the limiting partition in their access or candidate list.
- Device compare will only include the devices connected via channel paths which have the limiting partition in their access or candidate list.

```
──────────── Limit Processor Compare Reports ────────────

Select one or more of the processor compare reports.

 _  Processor Compare
 _  Partition Compare
 _  Channel Path Compare
 _  Control Unit Attachment Compare
 _  Device Attachment Compare
 _  Control Unit Compare
 _  Device Compare

To limit the reports, specify the following values.

                         New IODF          Old IODF
Processor ID . . . . . . ________  +       ________  +
Partition name . . . . . ________  +       ________  +

 F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset
 F9=Swap    F12=Cancel
```

Figure 81. Example of a Limit Processor Compare Reports Panel

On the ***Limit Switch Compare Reports*** panel, you can limit the switch compare reports by one or more of the specific compare reports. In addition, you can limit the reports by specifying a switch ID for both, the new and the old IODF.

```
──────────── Limit Switch Compare Reports ────────────


Select one or more of the switch compare reports.

_  Switch Compare
_  Switch Port Compare
_  Switch Configuration Compare
_  Port Configuration Compare

To limit the report, specify the following values:

                 New IODF        Old IODF
Switch ID  . . . __  +           __  +

 F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset
 F9=Swap    F12=Cancel
```

Figure 82. Example of a Limit Switch Compare Reports Panel

On the ***Limit Operating System Compare Reports*** panel, you can limit the operating system compare reports by one or more of the specific compare reports. In addition, you can limit the reports by specifying an operating system ID for both, the new and the old IODF.

```
──────────── Limit Operating Systems Compare Reports ────────────

Select one or more of the operating system compare reports.

_  Operating Systems Compare
_  EDT Compare
_  Generic Compare
_  Generic Update Compare
_  Esoteric Compare
_  OS Console Compare
_  OS Device Compare

To limit the report, specify the following values:

                         New IODF          Old IODF
Operating system ID  . . ________  +       ________  +


 F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset
 F9=Swap    F12=Cancel
```

Figure 83. Example of a Limit Operating System Compare Reports Panel

How to Print a Compare IODFs Report

After you have selected the specific pairs for the compare reports, you can decide what print options to use. The print options are shown on the Select Print Options panel, see Figure 84.

If you do not select an option (by only pressing the Enter key), the default print options are used (`Print inserted data`, and `Print deleted data`).

Examples of these reports are shown in Appendix B, "Configuration Reports" on page 355.

```
──────────── Select Print Options ────────────

Select one or more of the following
options, or ENTER to use the defaults.

/  Print inserted data
/  Print deleted data
_  Print unchanged data
_  Print unchanged item IDs

 F1=Help       F2=Split      F3=Exit
 F5=Reset      F9=Swap      F12=Cancel
```

Figure 84. Example of a Select Print Options (for Compare IODFs Only) Panel

When you do not select any option, HCD prints a report of

- IDs of added or deleted objects, and those objects, that have added or deleted relations
- IDs of added relations
- Attributes of objects that are different in both IODFs

When you select the `Print inserted data` option, HCD prints a report of all attributes, and relations of added objects.

When you select the `Print deleted data` option, HCD prints a report of all attributes, and relations of deleted objects.

When you select the `Print unchanged data` option, HCD prints a report of of all attributes, and relations of unchanged objects.

When you select the `Print unchanged item IDs` option, HCD prints a report of the IDs of unchanged objects. But this applies only, if the `Print unchanged data` option is not selected.

Compare CSS / Operating System Views

You can use the ***Compare CSS / operating system views*** function to compare the device definitions of a selected CSS and OS configuration, showing which devices (their numbers and types) are defined to either the CSS or the OS, or both. By using this function you can find out the differences between a hardware (channel subsystem/CSS) and software (operating system/OS) definition in the currently accessed IODF.

```
                         Compare CSS / OS Views


 Specify the following values.

 IODF name . . : 'DOCU.IODF00.FP.NEW'

 CSS view
 Processor ID . . . . ________  +   Partition name . . ________  +

 OS view
 Configuration ID . . ________  +   2   1.  Print all data
                                        2.  Print different data
 Job statement information
 //         JOB (ACCOUNT),'NAME'
 //*
 //*
 //*
 //*
 //*

  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

Figure 85. Select Print Options (for CSS/OS Compare Only)

When using the ***Compare CSS / operating system views*** function, you are offered the possibility of selecting what to print on the ***Compare CSS / OS Views*** panel, shown in Figure 85. The `Print all data` option prints a report of all devices either defined in the CSS or the OS.

The `Print different data` option prints a report of the devices that differ as follows:
- Defined for the CSS, but not for the OS.
- Defined for the OS, but not for the CSS.
- Defined for both, but of different device type.

If you limit the Compare CSS/OS Views Report for the CSS-side to one partition, it will generate information only for those devices that are attached to the channel paths, that have the limiting partition in the access or candidate list.

View and Print the HCD Activity Log

The HCD activity log is described in "Activity Logging" on page 62.

To look at the activity log for an IODF,

1. Select ***Print or compare configuration data*** from the primary task selection panel.
2. On the Print or Compare Configuration Data panel, select ***View the activity log*** or ***Print the activity log***.

The log has the same format in both cases. For browsing, the log is displayed by the ISPF/PDF browse facility. For printing, the log is written to the ISPF list data set.

Note: HCD maintains an activity log only if this was requested when the IODF data set was created.

Chapter 10. How to Query Supported Hardware and Installed UIMs

Overview

This chapter describes how to view system data about:
- Supported processors
- Supported switches
- Supported control units
- Supported devices
- Supported installed UIMs

Your z/OS system has several tables and modules that contain data about the general characteristics of processors, switches, control units, and devices in the system.

HCD uses this data to validate your configuration definition. You might want to look at it during the definition task; it helps you select the correct characteristics when you define your hardware units. You can also use the supported hardware report as a help when defining your configuration. See "Supported Hardware Report" on page 373 for an example of a supported hardware reportand "I/O Definition Reference" on page 401 for an example of an I/O definition reference.

You can view the system data by selecting ***Query supported hardware and installed UIMs*** from the primary task selection panel or the ***Query*** action from the action bar. Then select the subtask or pull-down choice that you want.

Query Supported Processors

The option `List supported processors` shows which processors are supported by the system. You can also see which features each processor supports, and its capabilities (such as what types of channel paths the processor supports).

© Copyright IBM Corp. 1994, 2002

```
──────────────────────────── Supported Processors ────────────────────────────
                                                   Row 221 of 280 More:       >
Command ===> ____________________________________________ Scroll ===> PAGE

Select one to view more details.

  Processor
  Type-Model Support Level
  9672-RC4   Parallel, ESCON (CBY), CF, OSA channels
  9672-RC5   Parallel, ESCON (CBY), CF, OSA channels
  9672-RX3   Parallel, ESCON (CBY), CF, OSA channels
  9672-RX4   Parallel, ESCON (CBY), CF, OSA channels
  9672-RX5   Parallel, ESCON (CBY), CF, OSA channels
  9672-RY4   Parallel, ESCON (CBY), CF, OSA channels
  9672-RY5   Parallel, ESCON (CBY), CF, OSA channels           2
  9672-RZ5   Parallel, ESCON (CBY), CF, OSA channels
  9672-R11   Parallel, ESCON (CBY), OSA channels               1
  9672-R12   Parallel, ESCON (CBY), CF, OSA channels
  9672-R14   Parallel, ESCON (CBY), CF, OSA channels
 F1=Help        F2=Split       F3=Exit        F7=Backward    F8=Forward
 F9=Swap       F12=Cancel     F20=Right      F22=Command
```

Figure 86. List of Supported Processors

The two lines in Figure 86 marked with **1** and **2** illustrate that processors with different support levels generate more entries in the list of supported processors.

Horizontal scrolling displays additional information on the processors.

```
──────────────────────────── Supported Processors ────────────────────────────
                                                   Row 221 of 280 More: <     >
Command ===> ____________________________________________ Scroll ===> PAGE

Select one to view more details.

  Processor  Supported
  Type-Model Channel Path Types
  9672-RC4   BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA
  9672-RC5   BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA
  9672-RX3   BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA
  9672-RX4   BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA
  9672-RX5   BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA
```

```
──────────────────────────── Supported Processors ────────────────────────────
                                                   Row 221 of 280 More: <     >
Command ===> ____________________________________________ Scroll ===> PAGE

Select one to view more details.

  Processor   Support   Supported
  Type-Model  Level ID  Protocols  Dynamic  PR/SM  EMIF
  9672-RC4    H960703   D,S,S4     Yes      Yes    Yes
  9672-RC5    H970610   D,S,S4     Yes      Yes    Yes
  9672-RX3    H950426   D,S,S4     Yes      Yes    Yes
  9672-RX4    H960703   D,S,S4     Yes      Yes    Yes
  9672-RX5    H970610   D,S,S4     Yes      Yes    Yes
```

```
──────────────────────────── Supported Processors ────────────────────────────
                                                   Row 221 of 280 More: <
Command ===> ____________________________________________ Scroll ===> PAGE

Select one to view more details.

  Processor  --Highest Number for-- ---------Maximum Number of---------
  Type-Model CUs      Devices       Switches CHPIDs CUs  LCUs Partition
  9672-RC4   FFFE     FFFF          256      256    6144 3072 15
  9672-RC5   FFFE     FFFF          256      256    6144 3072 15
  9672-RX3   FFFE     FFFF          256      192    6144 3072 10
  9672-RX4   FFFE     FFFF          256      256    6144 3072 15
  9672-RX5   FFFE     FFFF          256      256    6144 3072 15
```

You can view channel path, control unit, and device information by placing the cursor in front of a processor and pressing the Enter key. As a sample of this type of information, you see the channel path information below:

```
──────────────────────── View Channel Path Information ────────────────────────
                                                                     Row 1 of 9
Command ===> ____________________________________________________________

ENTER to view information about control units.

Processor Type-Model  . . . . . : 9672-RC4
    Parallel, ESCON (CBY), CF, OSA (w/ device sharing)

Supported  Maximum  --Max. Number per CHPID--- ---Supported---- Shared
Type       Number   UA Ranges  Links  Devices  Time-out  STADET
BL         96       64                 256      Yes       Yes    no
BY         96       64                 256      Yes       Yes    no
CBY        256      64                 256      Yes       Yes    no
CFR        16                                                    no
CFS        16                          256      No        No     no
CNC        256      120        120     1024     No        Yes    yes
CTC        256      120        120     512      No        Yes    yes
CVC        256      64                 256      Yes       Yes    no
```

Pressing the Enter key gives you a list of allowed channel path type mixtures. Pressing the Enter key again gives you similar information for control units and devices.

Query Supported Switches

The option `List supported switches` shows the characteristics of each type of switch in the system, such as the port range and the supported channel attachments of each switch.

```
                           Supported Switches

ENTER to continue.

               Port Numbers  Supported
Switch Type    Low - High    Channel Attachments
FCS             00 - FF      FC
2032            00 - FF      FC
9032            C0 - FB      CNC,CTC,CVC,CBY
9032-3          80 - FB      CNC,CTC,CVC,CBY
9032-5          04 - FB      CNC,CTC,CVC,CBY,FCV
9033            C0 - CF      CNC,CTC,CVC,CBY
```

Query Supported Control Units

The option `List supported control units` displays a panel showing a list of available control unit groups, for example the DASD control unit group. Select one control unit group to limit the list of supported control unit types. The Supported Control Units panel appears showing the characteristics of control unit types contained in a group.

```
                        Supported Control Units
                                                Row 2 of 28 More:       >
Command ===> ____________________________________ Scroll ===> CSR

Select a control unit to view the list of device types that can be
attached to the control unit.

                           -------Default for-------
  Control Unit  Supported Protocol  I/O Concurrency
  Type          Protocols Used      Level
  2105          S,S4      S         2
  2835-2        D         D         2
  3380-CJ2      S         S         2
  3830-2        D         D         2
  3830-3        D         D         2
  3851          D         D         2
  3880-1        D,S       S         2
  3880-11       D,S       S         2
  3880-13       D,S       S         2
  3880-2        D,S       S         2
  3880-21       D,S,S4    S         2
  3880-23       D,S,S4    S         2
  3880-3        D,S       S         2
```

Horizontal scrolling displays additional information on supported channel path type attachments.

```
                        Supported Control Units
                                                Row 2 of 28 More: <
Command ===> ____________________________________ Scroll ===> CSR

Select a control unit to view the list of device types that can be
attached to the control unit.


  Control Unit  Supported
  Type          Channel Attachments
  2105          CNC,FC,FCV
  2835-2        BL,CVC,EIO
  3380-CJ2      BL,CVC,EIO
  3830-2        BL,CVC,EIO
  3830-3        BL,CVC,EIO
  3851          BL,BY,CVC,CBY,EIO
  3880-1        BL,CVC,EIO
  3880-11       BL,CVC,EIO
  3880-13       BL,CVC,EIO
  3880-2        BL,CVC,EIO
  3880-21       BL,CVC,EIO
  3880-23       BL,CVC,EIO
  3880-3        BL,CVC,EIO
```

You can view which devices can be attached to a certain control unit type by placing the cursor in front of a control unit and pressing the Enter key. As a sample of this type of information, you see the CU - Device Attachment List below:

```
CU - Device Attachment List
                                                    Row 1 of 2
Command ===> ____________________________ Scroll ===> PAGE

Following device(s) can be attached to control unit type
3990

ENTER to continue.

Device Type
3380
3390
******************** Bottom of data **********************
```

Query Supported Devices

The option `List supported devices` displays a panel showing a list of available device groups, for example the DASD device group. Select one device group to view characteristics of device types contained in this group. You can limit the list of device types to view only the device types supported by a specific operating system type. After selecting a group of devices, the Supported Device Type List panel appears.

```
Supported Device Type List
                                                          Row 13 of 27
Command ===> ___________________________________________ Scroll ===> PAGE

Select a device type to view the list of control unit type(s) to which the
device can be attached.

                          --Support--          -Recommended- -Console-
  Device                  Dyn.  Four- Multi-   Time-  STADET NIP    VM
  Type          MVS  VM         Digit Exposure Out           Elig.  Us
  3370               Yes              No       Yes    Yes           No
  3375          Yes  Yes  Yes   Yes   No       Yes    Yes    No     No
  3380          Yes  Yes  Yes   Yes   No       Yes    Yes    No     No
  3380-CJ2      Yes  Yes  Yes   Yes   No       Yes    Yes    No     No
  3390          Yes  Yes  Yes   Yes   No       Yes    Yes    No     No
```

You can also see what control units each I/O device type can be attached to by placing the cursor in front of a device and pressing the Enter key.

As a sample of this type of information, you can see the Device - CU Attachment List below:

```
Device - CU Attachment List
                                                    Row 1 of 11
Command ===> ____________________________ Scroll ===> PAGE

Following control unit type(s) support the attachment of
device type
3380

ENTER to continue.

Control Unit Type
NOCHECK
3380-CJ2
3880-13
3880-2
3880-23
3880-3
```

Query Installed UIMs

The option `List installed UIMs` shows which UIMs are available in the system and which I/O device types are supported by each UIM.

```
                          Installed UIMs
                                                                Row 1 of 51
Command ===> ___________________________________________ Scroll ===> PAGE

Select one for a list of the devices it supports.

  UIM Name  E Description
  CBDUS001    UIM for 3330, 3333, 3340, 3344, 3350
  CBDUS002    UIM FOR 3375, 3380 ,3390, 3995-151/153, 9345
  CBDUS003    UIM for 3350P and 3351P
  CBDUS004    UIM for 327x devices
  CBDUS005    UIM for Magnetic Tape Devices
  CBDUS011    UIM for 3800
  CBDUS012    UIM for Unit Record devices
  CBDUS013    UIM for 2305-2
  CBDUS014    UIM for CTC Devices
  CBDUS022    UIM for AFP1 and 3820 Printers
  CBDUS023    UIM for 37xx and 7770
  CBDUS024    UIM for 1030, 1050, 1050X, 115A, 2740, 2740C, 2740X, 376
  CBDUS025    UIM for 2741P, 2741C, 83B3, TWX, WTTA
  CBDUS026    UIM for BSC1, BSC2, BSC3
 F1=Help        F2=Split       F3=Exit        F7=Backward    F8=Forward
 F9=Swap       F12=Cancel     F22=Command
```

A `Y` (for Yes) in the `E` (for Error) column indicates that the respective UIM is in error and treated as not existing.

A # sign in front of a UIM name indicates that it cannot be selected because it is flagged in error.

For each of the installed UIMs you can view a list of supported devices by placing the cursor in front of a UIM and pressing the Enter key. As a sample of this type of information, you can see the View Supported Devices list below:

```
                       View Supported Devices
                                                                Row 1 of 7
Command ===> ___________________________________________ Scroll ===> PAGE

This UIM supports the listed device types.

UIM name : CBDUS002
           UIM FOR 3375, 3380 ,3390, 3995-151/153, 9345

ENTER to continue.

              Generic
              -- or --
Device Type   VM D/T   Description
3375          3375     Direct Access Storage Device
3380          3380     Direct Access Storage Device
3380-CJ2      3380     Direct Access Storage Device
3390          3390     Direct Access Storage Device
3995-151      3390     Direct Access Storage Device
3995-153      3390     Direct Access Storage Device
9345          9345     Direct Access Storage Device
 F1=Help        F2=Split       F3=Exit        F7=Backward    F8=Forward
 F9=Swap       F12=Cancel     F22=Command
```

Chapter 11. How to Migrate Existing Input Data Sets

Overview

This chapter describes how to:
- Prepare the input data sets before migrating them
- Migrate the input data sets using the HCD dialog
- Migrate the input data sets using the HCD batch utilities
- Replace existing configuration data through migration
- Change I/O configurations by editing data sets
- Understand and resolve errors that occurred during migration

HCD allows you to migrate existing configuration data that was defined in IOCP, MVSCP, and HCPRIO input data sets to an IODF.

As input, you can use one of the following:
- An IOCP input data set
- An MVSCP input data set
- An HCPRIO input data set

You can also use the migration to create I/O definitions by editing control statements. Data sets containing the statements corresponding to a specific IODF can be generated using a batch utility. Refer to "Build I/O Configuration Statements" on page 295 for details on which data sets can be built and how to run the build process.

When migrating from input data sets, HCD checks the syntax of the input statements and runs a validation process that checks that the definitions being migrated do not conflict with the I/O configuration rules and with existing definitions in the IODF or with other definitions being migrated.

If HCD detects an error in the input data sets, it issues messages after the migration process has ended.

Migration Sequence

If you want to migrate more than one input data set into a single IODF, comply to the following migration sequence:
1. Migrate all IOCP input data sets
2. Migrate all MVSCP or HCPRIO input data sets

LPAR Considerations

If you have a combined IOCP/MVSCP input data set containing definitions for more than one LPAR and the same device number specified for more than one LPAR, migrate this input data set in the following way:

1. Migrate the input data set as IOCP only input data set.

© Copyright IBM Corp. 1994, 2002

2. Remove the duplicate device number definition and repeat the migration as an MVSCP only input data set. In the appropriate IODEVICE statement, specify the control unit number the device attaches to by means of the CUNUMBR parameter.

Preparing Your Input Data Sets for Migration

Before you can successfully migrate IOCP, MVSCP, or HCPRIO input data sets, you may need to change the input because HCD does a more rigorous checking of the input statements than IOCP or MVSCP.

To ensure that the migration is successful and that the resulting IODF accurately reflects the physical configuration, ensure that your input data sets apply to the validation rules described below. For assistance when checking the definitions in the input statements, you can use the following possibilities:

- Select ***Query supported hardware and installed UIMs*** from the primary task selection panel
- Use the ***Query*** action bar choice
- Use the batch facility "Print a Configuration or Supported Hardware Report"

Data Requiring Attention

This section details which data may need to be changed and how to change it to ensure a successful migration.

Control Unit Types

HCD checks whether a specified control unit type is valid. Review your input for invalid control unit types. If applicable, correct the UNIT parameter of the CNTLUNIT statement.

If you do not want to change the type in your input data set, you can edit the HCD profile and specify how a control unit type in the IOCP input data set is mapped to a control unit type in the IODF. Specify one or more of the following keyword:

```
MAP_CUTYPE = xxxxx,yyyy-yy
```

xxxxx
is the control unit type specified in the IOCP input data set

yyyy-yy
is the control unit type and model (optional) to be used in the IODF

For more information about the HCD profile, refer to "Defining an HCD Profile" on page 41.

Control Unit Models

HCD requires, for certain control unit types, the specification of a model. For example, the IBM 3880 control unit requires a model specification. If a control unit type requires a model specification, and if you do not specify one in the input data set, HCD assigns a model to the control unit definitions based on the attached devices and the used control unit protocol. This control unit model is indicated as default model in the UIM (information message CBDA534I is issued). As processing goes on, it can be necessary to change the default model to another model to support the specified protocol (warning message CBDA536I is issued). Or, the default model is changed to attach a device type which is not supported by the default control unit model (warning message CBDA265I is issued).

Note: The sequence of messages is shown in reverse order in the migration log file since the messages are sorted according to decreasing severities. For an example, please see "Errors Detected During Assembly Process" on page 278.

To assign a model to a control unit, change the UNIT parameter of the CNTLUNIT statement in the input data set. Append the model number separated by a dash to the control unit type specification. For example:

```
CNTLUNIT ...,UNIT=3880-23
```

To avoid changing the input data sets, you can also add a model number by using the MAP_CUTYPE parameter in the HCD profile as described under "Control Unit Types" on page 240.

Protocol Support for Control Units

HCD checks the protocols supported by a control unit type. For example, in the source you may have an IBM 3745 with protocol S specified as control unit type 3705. The IOCP program does not check the protocol S specification. To be accepted by HCD as valid input, you have to change the control unit type to 3745.

Device Types

For IOCP Input Data Sets: HCD checks the device types for validity and that they can be attached to the specified control unit. Check your IODEVICE statements in the IOCP input data set and make sure that the device types are valid and reflect the true physical device they are defining. A common error, for example, is the IBM 3745 device type defined as 3705.

For MVSCP Input Data Sets: HCD supports device types that previously had to be defined as "look-alike" devices for MVSCP. For example, for an IBM 3251 graphic device (previously defined as 2250-3), it is mandatory that the correct device type is defined in the UNIT parameter. HCD validates the PCU parameter, which is different for the IBM 3251 and the IBM 2250-3 graphic devices.

A device whose device type supports the dynamic capability may be defined as dynamic or not dynamic by means of the DYNAMIC parameter. However, there are programs, including customer programs, supplier programs and IBM products, that depend on device related data structures such as UCB and EDT, or use existing operating system services which access these data structures, and are unprepared to handle dynamic changes to these structures.

Therefore, HCD considers devices that are not specified with the DYNAMIC parameter in the IODEVICE statement as "installation-static", as it does if DYNAMIC=NO. That means, that the device might support the dynamic capability, but the installation requests that the device is not treated as dynamic.

Installation-static devices can be dynamically added to the software I/O configuration, but can not be deleted or modified while z/OS is running.

When migrating the MVSCP input data sets, HCD shows **no** value as default with the DYNAMIC and the LOCANY parameter, instead of specifying NO.

For HCPRIO Input Data Sets: HCD supports device types that previously had to be defined as "look-alike" devices for HCPRIO. For example, you can define an IBM 6262 printer device (previously defined as an IBM 4248 printer device in the HCPRIO input data set) with a device type of 6262.

The device type support for VM has been brought into line with the MVS type support. However, there might be some differences to HCPRIO device type support (for example, concerning the MODEL parameter).

Esoteric Token

HCD introduces an esoteric token that will be used by allocation to find the appropriate esoteric for a data set that has been cataloged using the esoteric. You no longer have to maintain a chronological order and may delete and add esoterics without getting access problems for data sets that are cataloged using esoterics.

You may use the HCD profile (see "Defining an HCD Profile" on page 41) to tell HCD to assign a token in ascending order to each esoteric when migrating an MVSCP input data set.

If you do not want to assign tokens in ascending order or when you migrate only parts of a configuration using the incremental update function (see "Updating Parts of a Configuration by Migrating Input Data Sets" on page 267), you can use a new parameter on the UNITNAME statement. This parameter lets you specify a token for an esoteric to be migrated to HCD, as follows:

```
UNITNAME=...,TOKEN=nnn
```

nnnn
is a number from 1 to 8999.

You have to specify a token for all esoterics or for none at all. For more information on catalog considerations, refer to "Data Sets Cataloged with an Esoteric Device Group Name" on page 320.

Assembler Statements

HCD generates own macro instructions into the logical input data set before processing. This may cause problems with assembler statements you inserted into your input data sets. For example, coding the ISEQ, CSECT, or RMODE instructions may cause a warning message issued by the assembler. As a consequence the migration will be terminated. To avoid this, remove your assembler statements. The generated HCD instructions look as follows:

```
       PRINT OFF
       COPY CBDZPARS
       TITLE 'xxx LISTING'
CBDTXT CSECT
CBDTXT RMODE ANY
       PRINT ON NOGEN
            .
            .
input data set statements
            .
            .
       PRINT OFF
       HCDEND
       END CBDTXT
```

Preparing Additional Input Data Sets for Migration

This section describes what you have to consider when migrating more than one MVSCP, IOCP, or HCPRIO input data set to one IODF.

When you migrate additional input data sets to an IODF that already contains definitions, these input data sets may contain control units and devices that are already defined in the existing IODF. HCD assumes that control units being added that already exist in the IODF refer to the same physical control unit, and that the

control unit is shared between processors. The following sections describe the rules when a control unit or device is mapped to an existing one and when it is newly defined.

Migrating Additional IOCP Input Data Sets

When migrating additional IOCP input data sets, the mapping of control units and devices depends on whether the attached control units are already defined in the IODF or not.

The same control unit number is already defined in the IODF: The control unit is mapped, if both:

- The control unit type is the same, and
- The number and type of attached devices are the same

If one of these conditions is not fulfilled, the control unit definition is rejected. Figure 87 to Figure 89 on page 244 show examples of how control units are mapped. These examples do not show more than two control units attached to devices, but the same rules also apply if more control units are attached.



Figure 87. IOCP Migration. Control units and devices are mapped, because they already exist in the IODF.



Figure 88. IOCP Migration. Control units and devices are mapped, although the devices also attached to another control unit in the IODF.

The following example shows the same control units in the IODF and IOCP input data set, but the attached devices are shared in the IOCP input data set. In this case, the devices are merged and will be shared after the migration (only if the control units do not connect to the same processor configuration).



Figure 89. IOCP Migration. Control units and devices are mapped (only if the control units do not connect to the same processor configuration).

The same control unit number is not already defined in the IODF: In this case:

- A new control unit is defined.
- A new device is defined, unless
  - The device in the input data set is attached to a control unit, to which it is already attached in the IODF. In this case, the new device is mapped to the existing one and attached to both control units (see Figure 90 on page 245.)

  - or -

  - A device with same device number and type already exists in the IODF and is not attached to any control unit. In this case, the new device is mapped to the existing one and attached to the new control unit (see Figure 91 on page 245).

If none of these conditions is fulfilled, a new device is defined (see Figure 92 on page 246).



Figure 90. IOCP Migration. Devices are mapped, because one attached control unit is already defined in the IODF.



Figure 91. IOCP Migration. Devices are mapped, because the attached control unit is not yet defined in the IODF.



Figure 92. IOCP Migration. Devices are not mapped, because the control unit number does not exist in the IODF.

Migrating Additional MVSCP or HCPRIO Input Data Sets

A device can only be mapped if the device number and device type are the same. If the device number or type is not the same, a new device is defined.

If the device number and type are the same, HCD maps the device according to the following rules:

1. If you specify an associated processor and partition on the Migrate IOCP / MVSCP / HCPRIO Data panel or with the batch migration utility, HCD maps the new device to a device with the same device number and type connected to this processor and partition (provided that such a device exists).
2. If you do not specify an associated processor and partition or the new device does not attach to the specified processor and partition, HCD checks if the device is attached to a control unit. The device in the input data set is mapped, if
   - The device in the IODF is attached to the same control unit.

   - or -
   - The device in the IODF is not attached to any control unit.

   This is illustrated in Figure 93 on page 247.



Figure 93. MVSCP Migration. Devices are mapped, because the devices are not attached to a control unit in the IODF.

3. If the new device is not attached to a control unit, the device is mapped to the first device found with the same device number and type.

   If the IODF contains several devices with the same device number and type, the device of the MVSCP input data set can be erroneously mapped to a wrong device. To avoid this, you can specify the associated processor and partition on the Migrate IOCP / MVSCP / HCPRIO Data panel.



Figure 94. MVSCP Migration. Devices are mapped to the first devices found with the same type and number.

If only a subset of devices in the input data set is already defined in the IODF, this subset is mapped to the existing devices and the remaining new definitions are added.



Figure 95. MVSCP Migration. 32 devices are mapped, the other 32 devices are newly defined.

Considerations for IBM ES/4381 Processors

- HCD recognizes only valid control unit types and models. A control unit type of LCA (documented as a valid control unit type in *IBM ES/4381 Processor Input/Output Configuration Program User's Guide and Reference* is not accepted by HCD. The control unit type must be changed (for example, to 3274).
- HCD derives the channel path identifier (CHPID) from the channel set and channel number. For example, the following CHPID statement results in a CHPID value of `03`:

  ```
  CHPID   PATH=((12,3,0)),TYPE=BL
  ```

  The channel path identifier `12`, specified in the CHPID statement, is used only during the migration function to relate the control units and devices to the channel path. After the migration is complete, the CHPID stored in the IODF will be `03`. Similarly, when building an IOCP input data set, a CHPID number of `03` will result in generating the following CHPID statement:

  ```
  CHPID   PATH=((03,3,0)),...
  ```
- The rules concerning native console devices are not validated by HCD.
- If the DEVNUMBR parameter is specified with an IODEVICE statement, HCD obtains the device number from the DEVNUMBR parameter, and the unit address from the last two digits of the ADDRESS parameter. If, however, the DEVNUMBR parameter is not specified, the ADDRESS parameter value is used as the device number. The unit address is taken from the UNITADD parameter (if present), otherwise from the last two digits of the ADDRESS parameter.

Migrating Input Data Sets Using the HCD Dialog

The following steps describe how to migrate IOCP, MVSCP, or HCPRIO input data sets to an IODF using the HCD dialog.

Step 1: Specify the Work IODF

Before starting the migration, you require a work IODF. You can create a new work IODF or use an existing one.

1. On the primary task selection panel enter the name of the IODF to which you want to migrate your input data sets.
2. Select ***Migrate configuration data***.

   If you create a new work IODF, a panel appears on which you have to enter IODF specifications. (Refer to Figure 11 on page 50.)

3. On the following Migrate Configuration Data panel, select ***Migrate IOCP/OS data***. The Migrate IOCP / MVSCP / HCPRIO Data panel shown in Figure 96 appears.

Step 2: Migrate the Input Data Sets

```
                    Migrate IOCP / MVSCP / HCPRIO Data

Specify or revise the following values.

Processor ID . . . . . . . . . . . . _________  +
OS configuration ID  . . . . . . . . _________  +

Combined IOCP/MVSCP input data set . ____________________________________
           or
IOCP only input data set . . . . . . ____________________________________
MVSCP only or HCPRIO input data set  ____________________________________
           Associated with processor _________  +
                             partition _________  +
Processing mode  . . . . . . . . . . . 2   1.  Validate
                                           2.  Save

Incremental update . . . . . . . . . . 2   1.  Yes
                                           2.  No
MACLIB used  . . . . . . . . 'SYS1.MACLIB'
Volume serial number . . . ______  + (if not cataloged)
```

Figure 96. Migrate IOCP / MVSCP / HCPRIO Data Panel

1. Specify the identifier of the processor or operating system with which the input data sets will be associated.
   - For an IOCP input data set migration, specify a processor ID.
   - For an MVSCP or HCPRIO input data set migration, specify an OS configuration ID.

   If the specified processor or operating system does not exist in the IODF, a panel appears that allows you to define a new processor or operating system in the IODF.
2. Specify the input data set:
   - If you are migrating a combined MVSCP/IOCP input data set, specify the `Combined IOCP/MVSCP input data set` field.
   - If you are migrating an IOCP input data set only, specify the `IOCP only input data set` field.
   - If you are migrating an MVSCP or HCPRIO input data set only, specify `MVSCP only or HCPRIO input data set` field.
   - If you have separate IOCP and MVSCP (or IOCP and HCPRIO) input data sets, but want to migrate both into one IODF, specify both the `IOCP only input data set` and the `MVSCP only or HCPRIO input data set` field.
3. The specification of the `Associated with processor` and `partition` field is only applicable if you migrate MVSCP of HCPRIO input data sets to an IODF.

   Specify a processor and partition with which you want to associate definitions in the input data sets. HCD uses this information to map devices correctly if the IODF contains duplicate device numbers. For more information about this mapping, refer to "Migrating Additional MVSCP or HCPRIO Input Data Sets" on page 246.
4. Specify the processing mode:

- **Validate** causes HCD to check the input and to inform you if errors are discovered. HCD *does not store the input* in the IODF, even if the input data set is free of errors. Only the new processor and/or operating system definitions that you defined are stored.

  The validate mode provides detailed messages how HCD treats control units and devices that already exist in the IODF.
- **Save** causes HCD to check the input, and if free of errors, to store the data in the IODF. If there are errors in the input data set(s), HCD informs you by a message, and depending on the severity of the error, does not write the input to the IODF.

5. If the specified processor or OS configuration already contains definitions, you can add and replace existing objects with the new information defined in the input data sets. For this *partial migration* you have to select the `Incremental update`. Refer to "Updating Parts of a Configuration by Migrating Input Data Sets" on page 267 for more information about the partial migration.
6. If the CBDZPARS macro, which contains the migration parsing macros, is not in SYS1.MACLIB, specify the name of the library that contains it. If the library is not cataloged, specify the volume serial number.

After the input has been accepted, HCD issues a message informing you that the migration of input data sets is in process.

Step 3: Analyze Errors and Upgrade the Input Data Set

During the migration process, HCD first invokes the assembler that parses the input statements. If it detects an error, migration is terminated.

- HCD writes a message to the terminal indicating that migration completed with return code RC=12.
- HCD writes a message to the HCD message list indicating that the assembler completed with a return code other than zero.
- The assembler writes information to the assembly listing that describes the problem in more detail.

If the assembler does not detect any errors, HCD runs a validation check. If it detects an error, HCD writes:

- A message to the terminal indicating that migration completed with a return code higher than 4.
- Error messages to the HCD message list describing the validation problem.

If the return code is 0 or 4, the IODF is updated and saved (if you specified to save the data). It is, however, recommended that you review the message log. HCD may have made assumptions that are contrary to your configuration requirements. Your actions:

1. Review the message list. For explanations and examples refer to "Resolving Migration Errors" on page 277.
2. Edit and correct the IOCP, MVSCP, and HCPRIO input data sets.
3. Migrate your input data sets again.

Step 4: Update Configuration Data

If the protocol or the attached devices specified in the IOCP input data set do not match the supported control unit model, HCD may change the model definitions.

If HCD changes definitions, you are informed by messages. Review the messages, and follow the recommendation provided in the individual message.

If the type/model designated by HCD does not match the real type/model of the control unit, use the HCD dialog to specify the correct type/model.

Also, if this control unit is to be shared with another processor, update the IOCP input data set that is to be migrated accordingly.

Note: The configuration stored in an IODF may not match the IOCP/MVSCP or HCPRIO input. If discrepancies occur, you can make corrections by using the dialog.

The following notes apply only if you do not use the extended migration function as described in "Changing I/O Configurations by Editing Data Sets" on page 252.

For coupling facility migration: After the IOCP input has been accepted, HCD issues messages informing you that the CF control unit and CF device definitions of the IOCP input data set were ignored.

Migrating Input Data Sets Using the Batch Utility

The following steps explain how to migrate your input data sets using the HCD batch utility instead of the HCD dialog. The batch utility is an easy way to migrate your input data sets if you are not familiar with the dialog yet. You have to use it for migrating your input data sets from MVS/XA SP 2.n or MVS/ESA SP 3.n.

Step 1: Create the Work IODF

If an IODF does not yet exist, you first have to create a work IODF into which you want to migrate your MVSCP, IOCP, or HCPRIO data sets. Refer to "Initialize IODF" on page 285 on how to create and initialize an IODF.

Step 2: Migrate Input Data Set

The HCD utility function for migration allows you to migrate the content of MVSCP, IOCP, and HCPRIO input data sets and to store the definitions into an IODF. For a detailed description of the utility function for migration, refer to "Migrate I/O Configuration Statements" on page 287.

Step 3: Analyze Errors and Upgrade the Input Data Set

During the migration process, HCD first invokes the assembler that parses the input statements. If it detects an error, the migration process is terminated.

- HCD writes a message to the data set allocated by HCDMLOG that the migration completed with return code RC=12.
- HCD writes a message to the HCD migration log (HCDPRINT) indicating that the assembler completed with a return code other than zero.
- The assembler writes information to the assembly listing (HCDASMP) that describes the problem in more detail.

If the assembler does not detect any errors, HCD runs a validation check. If it detects an error:

- HCD writes a message to the data set allocated by HCDMLOG that the migration completed with return code higher than 4.

- HCD writes error messages to the HCD migration log (HCDPRINT) describing the validation problem.

If the return code is 0 or 4, the IODF is updated. It is, however, recommended that you review the migration log. HCD may have made assumptions that are contrary to your configuration requirements. Your actions:

1. Review the migration log. For explanations and examples refer to "Errors Detected During Validation Process" on page 279.
2. Edit and correct the IOCP, MVSCP, and HCPRIO input data sets.
3. Migrate your input data sets again.

Step 4: Build Production IODF

Before you can use the IODF to IPL your operating system you have to convert the work IODF into a production IODF. Refer to "Build a Production IODF" on page 290 for an example on how to build a production IODF using the work IODF.

Changing I/O Configurations by Editing Data Sets

With z/OS HCD the extended migration function and the added possibilities for writing and migrating configurations allow defining or changing configuration definitions without using the HCD ISPF dialog front-end.

It is possible to define all configuration objects with their attributes and their connections in I/O configuration statements with IOCP/MVSCP like syntax, in a data set used as input to the migrate function. For example, a switch together with its ports can be defined via this method.

It is also possible to recreate data sets containing I/O configuration statements for the processor, operating system and switch configurations from an IODF.

However, for some tasks, such as deleting certain configuration objects, it is necessary or easier to make the configuration changes directly in the HCD dialog. For more details on the capabilities of the migration function refer to the table in Table 6 on page 268.

Processor configurations
The migrate IOCP function is extended to allow the specification of parameters, additional to IOCP, in the input data set. Analogously, when building an IOCP input data set from the IODF, information is generated which describes the additional parameters of the configuration objects. Processor configuration data sets can be built using the Build IOCP Input Data Set function or the new CONFIG PR batch utility. For details, refer to "Build an IOCP Input Data Set" on page 191 and to "Build I/O Configuration Statements" on page 295.

Operating system configurations
The migrate MVSCP function is extended to allow the specification of all configuration data of an OS configuration, e. g., the device preference values for esoterics or the user parameters for devices. Also, it is possible to generate an OS configuration data set from the IODF using the Build OS Configuration Data Set dialog or the CONFIG OS batch utility. For details, refer to "Build an OS Configuration Data Set" on page 195 and to "Build I/O Configuration Statements" on page 295.

Switch configurations and switch-to-switch connections
It is possible to migrate switch definitions with all ports, switch-to-switch connections and all switch configurations from a data set. Analogously, it is

possible to build such a data set from the IODF using the CONFIG SW batch utility. For details, refer to "Build I/O Configuration Statements" on page 295.

Additional Parameters and Statements

In the following, the configuration objects and their attributes you can define via I/O control statements and migrate into HCD are described. For a detailed description of the IOCP keywords and parameters, refer to the *IOCP User's Guide* for your processor.

Operating system	ID Name Type Description
NIP console	Device number Order
EDT	ID Preference value Description
Esoteric	Name Device numbers Token VIO indication
Generic	Name Preference value VIO indication
Switch	ID Unit Model Description Serial number Installed ports Chained switch connection
Port	Address Name Occupied indication
Switch configuration	ID Switch ID Description Default dynamic connection
Port configuration	ID Allowed dynamic connections Prohibited dynamic connections Dedicated connection Blocked indication
Processor	ID Unit Model Support level Configuration mode SNA address Serial number Description
Partition	Name Number Usage Description

Channel path	ID Type Operation mode Partition access list Partition candidate list OS parameter I/O cluster Dynamic switch Description Coupling facility (CF) connection information Entry switch/port connected to a channel path
Control unit	Number Unit Model Serial number Switch/port connected to a control unit Description Connected channel paths/link addresses Unit address ranges I/O concurrency level Protocol Logical address
Device	Number Unit Model Serial number Volume serial number Connected control units Description Unit address Preferred channel path TIMEOUT indication Status detection indication OS parameters/features

Operating System

An operating system is specified with the IOCONFIG statement. It contains the following parameters:

ID
Specifies the numerical identifier of the OS (mandatory).

This keyword is maintained for compatibility with the MVSCP syntax.

TYPE
Specifies the OS configuration type. This is required only, if the migration is performed using the wildcard * in the parameter string of the batch utility. Otherwise, it is ignored and the OS configuration type is taken from the invocation parameters.

NAME
Specifies the OS configuration ID. This is required only, if the migration is performed using the wildcard * in the parameter string of the batch utility. Otherwise, it is ignored and the OS configuration ID is taken from the invocation parameters.

DESC
Specifies a description of the operating system (optional). The description of the OS configuration is added or updated.

Syntax:

`ID=id`	2 alphanumeric characters

`NAME=os_name`	up to 8 alphanumeric characters
`TYPE=type`	MVS or VM
`DESC='description'`	up to 32 characters

Example: The following example defines an OS configuration named NEWOS01B of type MVS together with the given description.

```
IOCONFIG ID=01,NAME=NEWOS01B,DESC='MVS 5.1 LPAR system',TYPE=MVS
```

NIP Consoles

A NIP console is specified with the NIPCON statement. It contains the DEVNUM keyword.

DEVNUM Specifies a list of device numbers to be used as NIP consoles (mandatory). All devices specified must be defined in your configuration.

NIP tries to use the devices in the order they are listed (left-to-right).

Syntax:

`DEVNUM=(device_number[,device_number]...)`	list of device numbers

Example: In the example the devices with numbers 102E and 102F are assigned to be used as consoles. NIP will try device 102E first.

```
NIPCON DEVNUM=(102E,102F)
```

EDT

An Eligible Device Table is specified with the EDT statement.

Note: If you want to define only one EDT, place the EDT statement ahead of all UNITNAME statements (see "Esoteric" on page 256 and "Generic" on page 256). If multiple EDT statements are written, each statement must preceed the UNITNAME statements defining the corresponding EDT.

The EDT statement contains the following parameters:

ID Specifies the identifier of the EDT. The default is the ID specified on the IOCONFIG statement. If multiple EDT statements are written, the ID parameter is mandatory for all but one statement.

DEVPREF Specifies a list of devices in the order of preference (optional).

This parameter conforms to legacy syntax but is still supported. However, it is recommended to use the DEVPREF parameter with the UNITNAME statement, see "Generic" on page 256, instead.

DESC Specifies a description of the EDT (optional).

Syntax:

`ID=id`	2 hexadecimal characters
`DEVPREF=(generic_name[,generic_name]...)`	list of generic device types, generates the preference value of generics according to the list position
`DESC='description'`	up to 32 characters

Example: The following example defines EDT 01 with the given description.

```
EDT ID=01,DESC='Eligible Device Table 1'
```

Esoteric

An esoteric is specified with the UNITNAME statement. For use with esoterics it contains the following parameters:

NAME Specifies the name of the esoteric (mandatory).

Note: Do not use esoteric names SYSALLDA, SYS3480R, or SYS348XR.

UNIT Specifies a sequence of consecutive device numbers (optional). The numbers specified must be defined in the configuration.

TOKEN Allows controlling the order of esoterics in the EDT (optional). Only relevant if you have data sets that are cataloged using esoterics.

Tokens prevent the order of esoterics from becoming alphabetical after IPL, thus avoiding access problems for data sets that are cataloged using esoterics.

If a token is specified for one esoteric you must also specify tokens for all other esoterics.

VIO States whether or not the devices are eligible for VIO. May only be set to YES if the esoteric contains at least one DASD device type (optional).

Syntax:

`NAME=esoteric_name`	8 alphanumeric characters
`UNIT=((devnum,n)[,(devnum,n)]...)`	4 hexadecimal characters followed by a decimal number
`TOKEN=token_value`	number in the range 1 to 8999
`VIO=value`	YES or NO

Example: The following example assigns 8 device numbers 01D1 through 01D8 and the token value to esoteric device group ES002. The group is not eligible for VIO.

```
UNITNAME NAME=ES002,                        *
         UNIT=((01D1,8)),                   *
         TOKEN=2015,                        *
         VIO=NO
```

Generic

A generic is specified with the UNITNAME statement. For use with generics it contains the following parameters:

NAME Specifies the name of the generic (mandatory; must be a valid generic name).

VIO Specifies whether or not the devices are eligible for VIO (optional). VIO=YES may only be specified if the generic name specifies a DASD device type.

DEVPREF Allocates a position in a preference order of generics (optional).

For default values see the information on MVS devices within the "Supported Hardware Report" on page 373 in Figure 152 on page 394. This parameter value must be unique for the OS configuration.

Syntax:

`NAME=generic_name`	8 alphanumeric characters
`VIO=value`	YES or NO
`DEVPREF=pref_value`	decimal number between 1 and 99999

Example: The following example defines the generic device group 3390 with the preference value 150. The devices are eligible for VIO.

```
UNITNAME NAME=3390,                    *
         VIO=YES,                      *
         DEVPREF=150
```

Switch

A switch is specified with the SWITCH statement. It contains the following parameters:

SWID Specifies an identifier for the switch (mandatory).

UNIT Specifies the switch unit (mandatory).

MODEL Specifies the switch model (optional).

DESC Specifies a description of the switch (optional).

SERIAL Specifies a serial number (optional).

PORT Specifies the installed ports (default from UIM, optional).

Specify only ports that are supported by the switch type. At least the minimum installed port range is set to installed. If the switch already exists with an installed port range that differs from the specified installed port range(s), only the new specified ports are set to installed if possible. That means, any existing installed port that does not hold a connection to a channel path or control unit is set to not installed if not specified with the PORT parameter.

SWPORT Specifies the chained switch connections (optional). If operand exceeds 255 characters, repeat the SWITCH statement with the remaining values.

If the switch already exists, all existing connections to other switches are broken. The connections to other switches are established as specified by the SWPORT parameter.

ADDRESS Specifies the switch address for a FICON switch (optional).

The corresponding switch control unit and device are specified by corresponding CNTLUNIT and IODEVICE statements.

Syntax:

`SWID=id`	2 hexadecimal characters
`UNIT=switch_unit`	like CU type
`MODEL=switch_model`	like CU model

`DESC='description'`	up to 32 characters
`SERIAL=serial_no`	up to 10 characters
`PORT=((low_port_id,high_port_id),...)`	up to 8 port ranges
`SWPORT=((from_port,to_switch,to_port),...)`	up to 8 switch-to-switch connections

Example: In the following example, switch 02 with an installed port range 80 to FB is chained to port D1 of switch 01 via port C0.

```
SWITCH SWID=02,UNIT=9032,MODEL=3,                                  *
            PORT=((80,FB)),                                        *
            DESC='Aspen switch, installed 10/09/94',               *
            SERIAL=55-8888,                                        *
            SWPORT=(C0,01,D1)
```

Note: Put the serial numbers in quotes, if you use characters such as blanks or commas as part of your serial numbers.

Port

A switch port is specified with the PORT statement. It contains the following keywords:

ID Port address identifying the port (mandatory).

NAME Specifies a port name (optional).

To be accepted within I/O Operations (ESCON Manager) commands the port name must not include commas, asterisks, or blanks. It must not contain X'FF' or any extended binary-coded decimal interchange code (EBCDIC) character less than X'40'. It must also not begin with a left parenthesis and end with a right parenthesis.

OCC Indicates that the port has an external connection (optional).

External means a connection to a processor, switch, or control unit.

Syntax:

`ID=port_id`	2 hexadecimal characters
`PORTNM='portname'`	up to 24 characters
`OCC`	no value assigned

Example: In the following example port D5 is named 'connected_to_CU_7230' and indicated as occupied.

```
PORT ID=D5,                                  *
     PORTNM='connected_to_CU_7230',          *
     OCC
```

Switch Configuration

A switch configuration is specified with the SWCONF statement. It contains the following parameters:

ID Specifies the switch configuration ID (mandatory).

SWID Identifies the switch owning the configuration (mandatory).

DESC Specifies a description of the switch configuration (optional).

DEFCONN Specifies whether the default port connections are set to allowed or prohibited (mandatory).

Syntax:

`ID=switch_configuration_id`	8 characters
`SWID=switch_id`	2 hexadecimal characters
`DESC='description'`	up to 32 characters
`DEFCONN=dynamic_default_connection`	A (allowed) or P (prohibited)

Example: In the following example the default connection for switch configuration BASECONF of switch 01 is set to allowed.

```
SWCONF ID=BASECONF,                                *
       SWID=01,                                    *
       DESC='basic configuration',                 *
       DEFCONN=A
```

Port Configuration

A port configuration is specified with the POCONF statement.

The POCONF statement is an optional extension to the switch configuration. With POCONF, port connections are defined explicitly and existing defaults are overridden. In all, the statement may be a maximum of 255 characters long. To express longer statements the POCONF may be repeated. POCONF includes the following parameters:

ID Port address identifying the port (mandatory).

PORTCF Specifies the type of connections to target ports (mandatory).

In the PORTCF operand

- **A** sets the dynamic connection to the succeeding list of target port IDs to allowed
- **P** sets the dynamic connection to the succeeding list of target port IDs to prohibited
- **D** sets a dedicated connection to the succeeding target port ID
- **BLOCKED** blocks the port

Syntax:

`ID=port_id`	2 hexadecimal characters
`PORTCF=(A,(id1,...,idn),`	list of ports in installed range (connection allowed)
`P,(id1,...,idm),`	list of ports in installed range (connection prohibited)
`D,(id),`	port with dedicated connection
`BLOCKED)`	BLOCKED attribute

Example: In the following example port D2 has allowed dynamic connections to ports B1 and B3, and prohibited dynamic connections to B5 and B7. Port D4 has a dedicated connection to port C0.

```
POCONF ID=D2,                                      *
       PORTCF=(A,(B1,B3),P,(B5,B7))
POCONF ID=D4,                                      *
       PORTCF=(D,(C0))
```

Processor

A processor is specified with the ID statement. If specified, it must preceed all other statements in the configuration data set. It contains the following keywords:

NAME Specifies the processor ID. If the ID does not exist, it is created (1).

MSG1 Specifies the identification information that is printed on the ID1 line of the heading in IOCP configuration reports (optional). Only supported for compatibility with IOCP.

MSG2 Specifies the identification information that is printed on the ID2 line of the heading in IOCP configuration reports (optional). Only supported for compatibility with IOCP.

SYSTEM Specifies the machine limits and rules that IOCP will enforce for a deck verification. The system parameter includes a specification of the processor machine type number and, optionally, a machine limits number (optional). Only supported for compatibility with IOCP.

UNIT Specifies the processor unit (1).

MODEL Specifies the processor model (1).

LEVEL Specifies the processor support level (1). For further information on support levels refer to "'support_level_ID'" on page 289.

MODE Specifies the processor configuration mode as LPAR or BASIC (1).

SNAADDR Specifies the SNA address (network name, system name) for a processor in an S/390 microprocessor cluster (optional).

SERIAL Specifies the processor serial number (optional).

DESC Specifies a description for the processor (optional).

Note (1): Processed only if the migration is performed using the wildcard * in the parameter string of the batch utility.

Syntax:

`NAME=processor_id`	8 characters
`MSG1='message'`	up to 64 characters
`MSG2='message'`	up to 64 characters
`SYSTEM=(processor_unit[,limits_number]`	4 characters followed by a decimal number
`UNIT=processor_unit`	8 characters
`MODEL=processor_model`	4 characters
`LEVEL=support_level`	8 characters
`SNAADDR=(network_name,system_name)`	list of 2 entries, each up to 8 characters
`MODE=processor_mode`	BASIC or LPAR
`SERIAL=serial_number`	up to 10 characters
`DESC='description'`	up to 32 characters

Example: In the following example processor ASYLPAR of type 9021, model 982 is defined with the serial number 0518719021, in LPAR mode, support level 236420.

```
ID NAME=ASYLPAR,UNIT=9021,MODEL=982,                        *
      DESC='8-way Processor',SERIAL=0518719021,             *
      MODE=LPAR,LEVEL=236420
```

Partition

A partition is specified with the RESOURCE statement. It contains the following keywords:

PART or PARTITION
Specifies a list of partition names with an optional addition of the corresponding partition numbers (mandatory).

DESCL Specifies a list containing descriptions for the defined partitions (optional).

USAGE Specifies a list describing the partition usage type for each partition.

Note: If the partition type is missing, it is set automatically depending on which types of channel paths are assigned to the partition and the capability of the processor.

Syntax:

`PART=((name[,part_number])...)`	name of up to 8 alphanumeric characters 1 hexadecimal character part. number
`PARTITION=((name[,part_number])...)`	name of up to 8 alphanumeric characters 1 hexadecimal character part. number
`DESCL=('desc1','desc2','desc3',...)`	description for each partition up to 32 characters per description
`USAGE=(usage1,usage2,usage3,...)`	usage of each partition (CF, OS, or CF/OS)

Example: In the following example partitions LP1, LP2, and CF1 are defined and described.

```
RESOURCE PART=((LP1,1),(LP2,2),(CF1,3)),                    *
      DESCL=('Logical Partition 1',                         *
      'System 3',                                           *
      'Coupling Facility'),                                 *
      USAGE=(CF/OS,OS,CF)
```

Channel Path

A channel path is specified with the CHPID statement. It contains the following keywords:

PATH Specifies the CHPID number of the channel path (mandatory).

TYPE Specifies the channel path type of I/O operation for the channel path (mandatory).

SHARED Specifies that the channel path on the CHPID statement is shared (optional).

PART, PARTITION, or NOTPART
PART and PARTITION specify the access list of logical partitions that will have the channel path configured online after POR, and the candidate list identifying the logical partitions which can access the device.

NOTPART specifies the access list of logical partitions that will not have the channel path configured online after POR, and the list of logical partitions which cannot access the device.

REC REC in the PART or PARTITION keyword allows the channel path to be dynamically moved between partitions after POR.

OS Specifies channel path data that is used by the operating system. For example, OS=01 indicates that the channel path is managed by DCM. Or, OS=40 indicates that the maximum frame size for an IQD channel is 24K.

I/O CLUSTER Specifies an I/O cluster name. An I/O cluster is a sysplex that owns a managed channel path for an LPAR processor configuration.

SWITCH Specifies a number for a switch (ESCON Director) which is used as a dynamic switch for all paths from the channel path (CHPID) to the connected control units (required for dynamic connections through a switch).

DESC Specifies a description of the channel path (optional).

TPATH Specifies a connected CF channel path (optional).

The TPATH parameter can be specified for a CF channel path, either CF receiver, CF sender, or CF peer channel path.

For a CF sender or CF receiver channel path, the TPATH parameter must contain:
- the target processor and
- the target channel path ID

When specified with a CF sender channel path id, the TPATH parameter must also contain:
- the CF sender control unit and device numbers used for the CF connection. This information is optional for a CF receiver channel path.

For a CF peer channel path, the TPATH parameter contains the following items for the source and target channel paths of the CF connection:
- processor name
- channel path ID
- control unit number (only if this is a sending CF channel, i.e., the channel path connects to a target CF logical partition)
- starting device number (only if this is a sending CF channel)

A CF connection uses two (CF sender channel) or seven (sending CF peer channel) devices. Only the starting one can be specified (with four digits). The remaining devices are automatically assigned to the next consecutive device numbers.

Any CF control units and CF devices specified via CNTLUNIT and IODEVICE statements are ignored.

The connection can only be established if the target channel path exists. If the target channel path is already connected, the existing connection is broken and a new connection is established.

SWPORT Specifies an entry switch port (optional).

Syntax:

`PATH=chpid_number`	2 hexadecimal characters

`TYPE=type`	valid channel path type
`SHARED`	no value assigned
`PART=((access_list)[,(cand_list)][,REC])`	up to 2 lists of partitions, optional addition of REC
`PARTITION=((access_list)[,(cand_list)] [,REC])`	up to 2 lists of partitions, optional addition of REC
`NOTPART=((access_list)[,(cand_list)])`	up to 2 lists of partitions
`OS=xx`	2 hex character OS parameter
`IOCLUSTER=sysplex`	8 character sysplex name for managed CHPID
`SWITCH=number`	2 hexadecimal characters
`DESC='description'`	up to 32 characters
`TPATH=(proc,chpid<,CFS CU,CFS device>)` (for legacy CF channel path only)	target CHPID for connected CHPID pairs (CF connection): 8 character processor name, 2 hex character CHPID, 4 hex character CU number, 4 hex character device number
`TPATH=((proc,chpid<,CFP CU,CFP device>), (proc,chpid<,CFP CU,CFP device>))` (for CF peer channel path only)	pair of source and target CHPIDs (CF peer connection): 8 character processor name, 2 hex character CHPID, 4 hex character CU number, 4 hex character device number
`SWPORT=(swid,port)`	switch and port to which the CHPID connects

Example: In the following example channel path 35 of type CNC is connected to port FB of switch 03, which is used as a dynamic switch. Channel path 35 is defined as shared with all partitions of the processor in its access list.

Channel path 10 of type CFS, defined to partition LP4, is connected to CFR channel 11 of processor PROC1 using control unit FFFE and devices FFF0,2 for the coupling facility connection.

Channel path 12 of type CFR, defined as dedicated to partition C1, is connected to CF sender channel 70 of processor PROC2. (The used coupling facility devices and control units are defined with CHPID 70 of processor PROC2.)

```
CHPID PATH=(35),SWITCH=03,TYPE=CNC,                          *
      SWPORT=((03,FB)),SHARED,                               *
      DESC='Chpid connected to switch'
CHPID PATH=(10),TYPE=CFS,PART=((LP4),(LP4)),                 *
      TPATH=(PROC1,11,FFFE,FFF0)
CHPID PATH=(12),TYPE=CFR,PART=((C1),(C1)),                   *
      TPATH=(PROC2,70)
```

Control Unit

A control unit is specified with the CNTLUNIT statement. It contains the following keywords:

CUNUMBR Specifies a number assigned to the control unit (mandatory). The number assigned to each control unit must be unique within an IODF.

UNIT Specifies the type of control unit (mandatory).

SERIAL Specifies a serial number (optional).

SWPORT Specifies switch ports to which the control unit is connected (optional). If operand exceeds 255 characters, repeat the CNTLUNIT statement with the remaining values.

DESC Specifies a description of the control unit (optional).

PATH Specifies the channel paths attached to the control unit (mandatory).

LINK Specifies the link address to which the control unit is attached (optional).

The order in which the link addresses are specified corresponds to the order in which the channel paths are specified in the PATH keyword.

UNITADD Specifies the unit address ranges that are recognized by the control unit (mandatory).

CUADD Specifies the logical address for the control unit (optional).

SHARED Specifies the level of concurrency of I/O requests that the parallel channel path allows for the control unit (optional).

PROTOCOL Specifies the interface protocol that the parallel control unit uses when operating with the channel paths specified in the PATH keyword (optional).

Syntax:

`CUNUMBR=number`	4 hexadecimal characters
`UNIT=type`	valid control unit type
`SERIAL=serial_number`	up to 10 characters
`SWPORT=((swid1,port1),(swid2,port2),...)`	list of up to 8 sublists (switch ID,port ID) 2 hex character switch ID 2 hex character port ID
`DESC='description'`	up to 32 characters max.
`PATH=(chpid[,chpid]...)`	2 hexadecimal characters for each static CHPID '**' for each managed CHPID
`LINK=(link_addr[,link_addr]...)`	two or four hexadecimal characters for the link address of each CHPID '**' if not specified
`UNITADD=((address[,number]),...)`	2 hexadecimal characters for each unit address followed by a decimal number
`CUADD=address`	1 or 2 hexadecimal characters
`SHARED=value`	Y or N
`PROTOCOL=value`	D, S, or S4

Example: In the following example control unit 0CC0 of type 3995-151 is connected to channel path 20 using link address E4. The control unit is connected to port E4 of switch AA.

```
CNTLUNIT CUNUMBR=0CC0,PATH=(20),UNITADD=((00,256)),LINK=(E4), *
      UNIT=3995-151,SWPORT=((AA,E4)),                         *
      SERIAL=0123456789,DESC='Building 12'
```

Note: Put the serial numbers in quotes, if you use characters such as blanks or commas as part of your serial numbers.

Device

A device is specified with the IODEVICE statement. It contains the following keywords:

ADDRESS Specifies the device number and how many devices are to be defined (mandatory).

UNIT Specifies the device type (mandatory).

MODEL Specifies the model number of the device, if available (optional).

PART, PARTITION or NOTPART

PART and PARTITION specify the candidate list identifying the logical partitions which can access the device (optional).

NOTPART specifies the logical partitions which cannot access the device (optional).

Note: You may specify not more than one of these keywords in any one IODEVICE statement.

SERIAL Specifies the serial number of the device (optional).

VOLSER Specifies the volume serial number (optional).

CUNUMBR Specifies the number(s) of the control unit(s) the device is attached to (mandatory).

DESC Specifies a description of the device (optional).

UNITADD Specifies the unit address that is transmitted on the channel path to select the I/O device (optional). If not specified, the last two digits of the device number are used.

PATH Specifies the preferred channel path (optional).

TIMEOUT Specifies whether the I/O interface timeout function is to be active (optional).

STADET Specifies whether the Status Verification Facility is to be enabled or disabled (optional).

OS Parameters/Features: In the following section device specific parameters and features are described. To find out which parameters, private parameters, and features are available to you for a particular device run your Supported HW Report and I/O Definition Reference. (See "Print Configuration Reports" on page 299 for details on how to run the report function.) Examples of a Supported HW Report and of an I/O Definition Reference are shown in "Supported Hardware Report" on page 373 and in "I/O Definition Reference" on page 401, respectively.

USERPRM Allows the specification of OS private parameters.

To locate the private parameters available to you for a particular device refer to your Supported HW Report. The OS private parameters are listed in column `SUPPORTED PARAMETERS / FEATURES`, following PRIVATE: and extending to the slash (/). For example, device 3590 listed in the sample Supported Hardware Report in Figure 152 on page 394 supports the private parameters LIBRARY and AUTOSWITCH.

FEATURE If included in the device specific parameters, FEATURE allows device specific features to be assigned. The features available depend on your UIMs.

To locate the features available to you for a particular device type refer to your Supported HW Report. The features are listed in column `SUPPORTED PARAMETERS / FEATURES`, following the slash (/). For example, device 3590 listed in the sample Supported Hardware Report in Figure 152 on page 394 supports the features SHARABLE and COMPACT.

ADAPTER Specifies either the terminal control or transmission adapter used to connect a telecommunications line to a transmission control unit, or the type of channel adapter that connects a communications controller to a channel path (optional).

DYNAMIC Specifies if the device is eligible for dynamic I/O configuration (optional).

LOCANY Specifies if UCB can reside in 31 bit storage (optional).

NUMSECT Specifies the number of guaranteed 256-byte buffer sections in a 2840 display-control buffer allocated to a device 2250-3 (optional).

OFFLINE Specifies if the device is considered online or offline at IPL (optional).

OWNER Specifies the subsystem or access method using the device (optional).

PCU Only applicable to a display device 2250-3 attached to a control unit 2840-2 (optional)

Identifies the 2840-2 control unit the 2250-3 is attached to. For all 2250-3 attached to the same control unit the same value is specified.

If coded, no separate IODEVICE statement `UNIT=2840` must be used.

SETADDR Specifies which of the 4 set address (SAD) commands is to be issued to the transmission control unit for operations on the line specified by the ADDRESS operand (optional).

TCU Specifies the transmission control unit for a telecommunications line (optional).

Syntax:

`ADDRESS=(device_number,number_of_units)`	4 hexadecimal characters followed by a decimal number in the range 1 to 4095
`UNIT=device_type`	up to 8 alphanumeric characters
`MODEL=model_number`	up to 8 alphanumeric characters
`PART=(name1[,name2]...)`	list of names with up to 8 alphanumeric characters
`PARTITION=(name1[,name2]...)`	list of names with up to 8 alphanumeric characters
`NOTPART=(name1[,name2]...)`	list of names with up to 8 alphanumeric characters
`SERIAL=serial_number`	up to 10 numeric characters

`VOLSER=volume_serial_number`	up to 6 characters
`CUNUMBR=(number1[,number2]...)`	up to 8 hexadecimal numbers of 4 characters
`DESC='description'`	up to 32 alphanumeric characters
`UNITADD=unit_address`	2 hexadecimal characters
`PATH=chpid`	2 hexadecimal characters
`TIMEOUT=value`	Y or N
`STADET=value`	Y or N
`USERPRM=((param1,value1)[,(param2,value2)]...)`	list of device specific parameter/value pairs
`FEATURES=(feature1[,feature2]...)`	list of device specific features
`ADAPTER=adapter`	up to 5 alphanumeric characters
`DYNAMIC=value`	Y or N
`LOCANY=value`	Y or N
`NUMSECT=number`	decimal number
`OFFLINE=value`	Y or N
`OWNER=value`	VTAM or OTHER
`PCU=number`	decimal value in the range 1 to 4095
`SETADDR=value`	0, 1, 2, or 3
`TCU=value`	2701, 2702, or 2703

Example: In the following example device numbers 0A90 to OA9F of type 3490 are defined with unit addresses 00 to 0F. Each device is attached to control unit 0A00. It is sharable between systems, data is compacted, it is considered off-line at IPL, and supports dynamic configuration. The device does not support auto tape library nor is it automatically switchable and its UCB cannot reside above 16 MB.

```
IODEVICE ADDRESS=(0A90,16),UNIT=3490,UNITADD=00,                *
         FEATURE=(SHARABLE,COMPACT),OFFLINE=YES,DYNAMIC=YES,    *
         LOCANY=NO,USERPRM=((LIBRARY,NO),(AUTOSWITCH,NO)),      *
         CUNUMBR=0A00,DESC='VIRTUELL TAPE',SERIAL=033401
```

Note: Put the serial numbers in quotes if you use characters such as blanks or commas as a part of your serial numbers.

Updating Parts of a Configuration by Migrating Input Data Sets

The HCD incremental update function allows you to modify objects in your IODF by specifying the objects with I/O control statements in data sets, e. g. IOCP, MVSCP, or HCPRIO input data sets, and migrating these input data sets into your existing IODF.

Possible Actions on Objects Using the Incremental Update

Table 6 on page 268 shows what actions you can perform on objects by using the HCD incremental update function. The meaning of the markup is as follows:

x Action possible, you can make the change.

— Action not possible, you cannot make the change with the batch migration utility but must use the HCD dialog.

(x) Action possible. These attributes are deleted when the object itself is deleted.

(—) Action not possible. These attributes cannot be deleted because the object itself cannot be deleted.

See the notes below the table for further instructions on how to add, delete, or change certain objects, their attributes and connections.

Table 6. Actions on IODF Objects

Object/Attributes	Add	Delete	Change
Processor			
ID	x	—	—
Type/model	x	(—)	—
Support level	x	(—)	—
Configuration mode	x	(—)	—
Serial number	x	—	x
Description	x	—	x
SNA address	x	—	x
Partition			
Name	x	x 1)	x 11)
Image number	x	(x)	x11)
Usage type	x 10)	(x)	x
Description	x	x	x
Channel path			
ID	x	—	—
Type	x	(—)	x 5)
Operation mode	x	(—)	x 5)
Access list	x	x	x 5)
Candidate list	x	x	x 5)
Dynamic switch	x	x	x 5)
Switch connection	x	x	x 5; 15)
CF connection	x	x	x 5)
Description	x	x	x 5)
OS parameter	x	x	x 5)
I/O cluster	x	x	x 5)
Control unit			
Number	x	x 2)	x 4)
Unit/model	x	(x)	x
Description	x	x	x
Serial number	x	x	x
Switch connection	x	x	x 15)
Channel paths	x	(x)	x
DLA	x	x	x
Logical address (CUADD)	x	x	x
Unit addresses	x	(x)	x
Protocol	x	x	x
IOCL	x	x	x
Device			
Number	x	x 3)	x 4)
Unit/model	x	(x)	x
Description	x	x	x
Serial number	x	x	x
Volume serial number	x	x	x
Control units	x	(x)	x
Processor connect	x	(x)	x
Unit address	x	(x)	x
Preferred CHPID	x	x	x
TIMEOUT	x	x	x

Table 6. Actions on IODF Objects (continued)

Object/Attributes	Add	Delete	Change
STADET	x	x	x
Candidate list	x	x	x
OS connect	x	—	x
Parameters	x	x	x
Features	x	x	x
User parameters	x	x	x
Operating system			
ID	x	—	—
Type	x	(—)	—
Description	x	—	x
EDT			
ID	x	—	—
Description	x	—	x
Esoteric			
Name	x	—	—
VIO	x	(—)	x
Device list	x	x 6)	x 7)
Token	x	—	x
Generic			
VIO	x	(—)	x
Preference value	x	(—)	x
Console			
Device list	x	x 9)	x 13)
Order	(x)	(x)	x
Switch			
ID	x	—	—
Unit/model	x	(—)	x
Ports (installed range)	x	(—)	x 8)
Serial number	x	—	x
Description	x	—	x
Switch connection	x	x 14)	x 15)
Address	x	—	x
Ports			
ID	x	—	—
Name	x	(—)	x
Occupied indicator	x 15)	x 15)	n.a.
Switch configuration			
ID	x	—	—
Description	x	—	x
Default connection	x	—	x
Port configuration			
Allowed connection	x	—	x
Prohibited connection	x	—	x
Dedicated connection	x	—	x
Blocked indicator	x	x	n.a.

References to IOCP and MVSCP in the following notes refer to data sets with extended syntax as described in "Changing I/O Configurations by Editing Data Sets" on page 252.

Notes:

1. To delete a partition, specify all connected channel paths (defined via access or candidate lists) together with their attached I/O units without referring to the partition and without repeating the partition in the RESOURCE statement.
2. A control unit is implicitly deleted, if its channel paths are respecified in the IOCP input data set together with their attached I/O units (except the control unit) and it no longer has any connection to a processor.
3. A device is implicitly deleted, if its attaching control units are implicitly deleted using the incremental update specification, and there is no additional connection left to any control unit or operating system.
4. To change control unit and device attributes, specify the entire logical control unit(s) (LCU) the control unit or device is part of.
5. To change channel path attributes, specify all logical control units the channel path is connected to in the IOCP input data set. Otherwise, the channel path is disconnected from the corresponding control units.
6. To delete an esoteric device list, specify all device definitions in the MVSCP input data set, but do not connect them to the esoteric name.
7. To add a device to an esoteric device list, specify the esoteric with the device number.

   To delete a device from the esoteric device list, specify the device in an IODEVICE statement) but do not specify the device number for the esoteric device list.
8. An installed port can be set to uninstalled only if it does not belong to the minimum installed port range and does not hold a connection to a channel path or control unit.
9. To delete a console list, specify all contained devices using the IODEVICE statement but do not include the devices in a NIPCON statement.
10. If the usage type is not specified and you add a partition, the usage type is automatically defined: if the IOCP input data set contains a CF receiver channel path with the partition in its access or candidate list, the usage type is set to CF/OS, if not, the usage type is set to OS.
11. To change the partition name or partition number specify the whole partition configuration including all channel paths with attached I/O units which have the partition in their access and candidate lists.
12. (No longer used.)
13. To change a complete console device list, use the NIPCON statement.

    To remove a single device from the console list, specify the corresponding IODEVICE statement and omit the NIPCON statement.
14. To delete a switch-to-switch connection, specify a switch via a SWITCH statement and omit the switch-to-switch connection in the SWPORT parameter.
15. When updating switch ports new connections always overwrite a previous connection or status. To be updated with an occupied status the port must currently not be connected.

How to Invoke the Incremental Update

1. Specify your objects with IOCP, MVSCP, or HCPRIO control statements. Note that you can add additional parameters and SWITCH statements to exploit the extended migration as describes under "Changing I/O Configurations by Editing Data Sets" on page 252).

2. Select ***Migrate configuration data*** on the primary task selection panel and on the resulting panel the ***Migrate IOCP/OS data*** option.
3. On the following Migrate IOCP / MVSCP / HCPRIO Data panel (see Figure 96 on page 249), enter the required data and change the incremental update to Yes.
4. After the input has been accepted, HCD issues a message informing you that the migration of input data sets is in process.

Example 1: Adding a Partition

In this example, you specify a partition in your input data set that does not yet exist in the IODF. The attached control units and devices are already defined in the IODF for another processor.

The following figure illustrates the result after the incremental update:



Figure 97. Partial Migration of an IOCP Input Data Set. A new partition is added. Control units and devices are mapped.

The partition is added and the control unit and devices are mapped. For a detailed description when control units and devices are mapped, refer to "Migrating Additional IOCP Input Data Sets" on page 243.

Example 2: Replacing a Channel Path and Attached Control Unit

In this example, you specify a channel path with attached control unit and devices in an IOCP input data set. The channel path, the control unit, and one device already exist in the IODF.

The following figure illustrates the result after the incremental update:




```
CHPID    PATH=01,TYPE=CNC,PART=PART1
CNTLUNIT CUNUMBR=100,UNIT=3990,PATH=01,...
IODEVICE ADDRESS=(5C0,32),UNIT=3390,
         CUNUMBR=100
```

Figure 98. Partial migration of an IOCP input data set. The whole logical control unit (control unit 100 and 200 and connected devices) are replaced by control unit 100 and its connected devices.

The logical control unit in the IOCP input data set replaces the whole logical control unit in the IODF.

Example 3: Replacing a Channel Path with a New Control Unit

In this example, you specify channel paths with control unit and device in the input data set. The channel paths are already defined in the IODF, but connect to another control unit.

The following figure illustrates the result after the incremental update:




```
CHPID    PATH=01,TYPE=BL
CHPID    PATH=02,TYPE=BL
CNTLUNIT CUNUMBR=200,UNIT=3880,PATH=(01,02),..
IODEVICE ADDRESS=(7C0,32),UNIT=3380,
         CUNUMBR=200
```

Figure 99. Partial migration of an IOCP input data set. CHPIDs are defined as in the IOCP input data set

The channel paths in the IODF are deleted and newly defined as they are defined in the IOCP input data set.

Example 4: Replacing a Control Unit that Attaches to Two Processors

In this example, you want to replace existing control units and devices by another type. The control units and devices are attached to two processors.

The incremental update must be done in several steps:

1. Specify another control unit number in your IOCP input data set than the one in the existing IODF. Specify the CHPID, CNTLUNIT, and IODEVICE control statements.
2. Migrate your input data set for the first processor.



Figure 100. Partial migration of an IOCP input data set. Control unit defined for two processors is migrated to the first processor.

3. Migrate your input data set again for the second processor.



Figure 101. Partial Migration of an IOCP Input Data Set. Control unit defined for two processors is migrated to the second processor.

Example 5: Updating an Operating System

In this example, you update an operating system by adding and changing EDTs, generics, esoterics, and console devices.

```
            IODF                                    MVSCP Input Data Set
                                                IODEVICE ADDRESS=(800,8),UNIT=...,MODEL=...

EDT ID=01                                       EDT ID=01
UNITNAME=POOL1,UNIT=((700,8),(900,8))           UNITNAME=POOL1,UNIT=((800,8)),VIO=YES
UNITNAME=POOL2,UNIT=((100,16))                  UNITNAME=POOL3,UNIT=((0270,16))
UNITNAME=TAPES,UNIT=((A80,4))                   UNITNAME=9345,VIO=YES

NIPCON DEVNUM=(40,41,42)                        EDT ID=02
                                                UNITNAME=TAPES,UNIT=((180,4))

                                                NIPCON DEVNUM=(40,50,60)


                       Resulting IODF
               IODEVICE ADDRESS=(800,8),UNIT=...,MODEL=...

               EDT ID=01
               UNITNAME=POOL1,UNIT=((700,8),(800,8),(900,8)),VIO=YES
               UNITNAME=POOL2,UNIT=((100,16))
               UNITNAME=POOL3,UNIT=((0270,16))
               UNITNAME=TAPES,UNIT=((A80,4))
               UNITNAME=9345,VIO=YES

               EDT ID=02
               UNITNAME=TAPES,UNIT=((180,4))

               NIPCON DEVNUM=(040,050,060)
```

Figure 102. Partial Migration of an MVSCP Input Data Set

You can either migrate the changes with a combined input data set or with an MVSCP only input data set. With a combined input data set, you can make CSS and operating system changes at the same time.

If you migrate an MVSCP only input data set, specify a processor and partition, with which device definitions in the input data sets will be associated in the IODF, on the Migrate IOCP / MVSCP /HCPRIO Data panel. HCD uses this information to map devices correctly if the IODF contains duplicate device numbers. For more information about this mapping, refer to "Migrating Additional MVSCP or HCPRIO Input Data Sets" on page 246.

The result after the migration is as follows:

- The definition of EDT input statements replaces the definition in the IODF, new definitions are added. That means in the example above, EDT 01 is replaced and EDT 02 is added.
- Devices are added. To add devices, you also have to newly define the esoterics to which the devices are to be assigned.
- Devices in a UNITNAME statement are added to the devices already defined for the esoteric.
- The list of consoles is replaced.

Note: If an EDT statement is missing or specified without EDT ID, the EDT ID for esoterics and generics is taken from the ID of the IOCONFIG statement. If the IOCONFIG statement is also not available, the EDT ID will be assumed as '00'.

Resolving Migration Errors

If HCD detects an error when you migrate using the HCD dialog, it displays a message list when the migration has been completed.

Figure 103 is an example of such a message list. It lists all the messages that were issued during the process. The list shows the statement number of the input statement for which the message was issued. You can now:

- Get explanations of messages in the list. To get explanations, use the ***Explain message*** action from the context menu or action code **e** .
- Delete messages that are of no further interest. That is, delete those messages that you do not want to appear in the *HCD migration log*.

```
──────────────────────────── Message List ────────────────────────────────────
 Query  Help
-----------------------------------------------------------------------------
                                                                   Row 1 of 6

Select one or more messages, then press Enter.

 /  Statement Orig Sev Message Text
 -  9         1    E   Duplicate unit address F0 on channel path 01 of
 #                     processor BOEHCD.
 -  5         2    W   Type of control unit 0131 assumed as 3800-13 to
 #                     attach device 01F0.
                   I   No output written to IODF. VALIDATE processing
 #                     forced due to errors.
```

Figure 103. Message List Example

When you exit the message list or when you migrated your input data sets using the batch utility, HCD writes the error messages to the HCD migration log.

You can display the HCD migration log through ISPF. The name of the HCD migration log data set is developed from the name of the input data set, without high-level qualifier, and your user ID as follows:

userid.*yyy*.*zzz*.MESSAGES

where the input data set, without high-level qualifier, is:

yyy.zzz

or

yyy(zzz)

Errors Detected During Assembly Process

During migration, HCD invokes the assembler to parse the input statements. If it encounters an error, it writes a message to the message list. This message points to an assembler listing for more details.

The name of the assembly listing data set is developed from the name of the input

```
 Query  Help
-----------------------------------------------------------------------
                              Message List                        Row 1 of 2

Select one or more messages, then press Enter.

 /  Statement Orig Sev Message Text
 -                 T   Assembler processing returns with return code    =
 #                     8. See BPAN.CDS.CSYSIO.LISTING for details.
```

Figure 104. Message List Containing an Assembler Message

data set, without high-level qualifier, and your user ID as follows:

userid.yyy.zzz.LISTING

where the input data set, without high-level qualifier, is:

yyy.zzz

or

yyy(zzz)

At the bottom of the assembly listing, you find the statement numbers where errors were detected. If you locate the statement numbers in the listing, you see the IOCP statement in error followed by the error message. The following examples show IOCP statements and the assembly messages issued.

Example 1

In this example an entry in the IOCP input data set is commented out, but the continuation character $ is left in column 72.

```
7493 *        CNTLUNIT CUNUMBR=02E,PATH=(02,06),SHARED=N,UNIT=3990,       91A$
7494 *              UNITADD=((E),32)),PROTOCL=S4
```

The assembler listing shows the following message:

```
IEV144   *** ERROR ***  BEGIN-TO-CONTINUE COLUMNS NOT BLANK
```

Example 2

This example shows a line with only 87A being included in the IOCP input data set.

```
7493 *        CNTLUNIT CUNUMBR=234,PATH=24,SHARED=N,UNIT=3880,            87A
7494 *              UNITADD=(30,16),PROTOCL=S4                            87A
7495                                                                      87A
7496 *IOCP                                                                87A
```

The assembler listing shows the following message:

```
IEV144   *** ERROR ***  OPERATION CODE NOT COMPLETE ON FIRST CARD
```

Example 3

This example shows a wrong channel path type in the CHPID statement.

```
CHPID PATH=((00)),TYPE=CMC
```

The assembler listing shows the following message:

```
IEV144   *** MNOTE ***  8,003 TYPE=CMC  IS  INVALID
```

Errors Detected During Validation Process

During the validation process, HCD checks that the definitions being migrated do not cause any conflicts with existing definitions in the IODF and with other definitions being migrated. HCD also checks that the contents of the input data sets is valid. The errors are shown in the message list and migration log.

Figure 105 shows error messages in the migration log.

```
I/O Configuration Migration                Time: 11.39    Date: 94-11-26    Page:    1
MVS/ESA HCD V 5.2

(1) DSN=BBEI.IOCP01.CTL     1
(2) DSN=BBEI.MVSCP01.CTL

Statement  Orig  Sev  Msgid   Message Text

      9    (1)  E  CBDA230I  Duplicate unit address F0 on channel path 01 of processor BOEHCD.

      5    (2)  W  CBDA265I  Type of control unit 0131 assumed as 3880-13 to attach device 01F0.

                I  CBDA516I  No output written to IODF. VALIDATE processing forced due to errors.

Total Messages   Terminating   Error   Warning   Informational
          3           0          1         1             1

Return Code was   8
```

Figure 105. Example: HCD Migration Log

The messages are sorted according to their severity, and within a certain severity level according to their occurrence.

The value in the **Orig** column points to the input data set that caused this error. At the top of the migration log you find a reference list that shows the values with the names of the input data sets (see the line marked **1**).

In Figure 105 the first message line means, that the statement number 9 in the input data set 1 (data set BBEI.IOCP01.CTL) is the cause of the error message.

The following examples show common validation errors and explain their causes.

Example 1

```
Statement Orig Sev  Msgid   Message Text

      7    (1)  E  CBDA154I  Channel path type CNC is not supported by channel
                             path ID 3A.
```

This message is issued, because an ESCON channel is defined although the support level was defined in the IODF as having only parallel channels installed for the specified CHPID. To resolve this, either change the channel type in the IOCP input data set, or change the processor type or support level in the IODF.

Example 2

```
Statement Orig Sev  Msgid   Message Text

      4    (1)  E  CBDA234I  Unknown type 38823 of control unit 0000
                             specified.
```

This message is issued, because HCD does not know the control unit type 38823. Select the ***Query supported hardware and installed UIMs*** from the primary task selection panel or use the ***Query*** action bar choice for information on valid control unit and device types.

Example 3

```
Statement Orig Sev  Msgid   Message Text

    228   (1)   W  CBDA265I  Type 3800-3 assumed for control unit DD32
                             to attach the device 0828.
    227   (1)   I  CBDA534I  Control unit DD32 is assumed as 3800-1.
```

These messages are issued, because HCD has to choose the control unit type among several models.

The control unit model 3800-1 is indicated as default model in the UIM (information message CBDA534I is issued). As processing goes on, it is necessary to change the default model (3800-1) to another model (3800-3) to attach a device type which is not supported by the default control unit model (warning message CBDA265I is issued).

Note: The sequence of messages is shown in reverse order in the migration log file since the messages are sorted according to decreasing severities. To resolve this, either include the model in the IOCP input data set, map the control unit types via HCD profile entries, or update the IODF using the HCD dialog, if HCD has made an incorrect assumption.

Insufficient Data Set Sizes

HCD dynamically allocates the data sets required for migration. It can happen that the default data set sizes are insufficient for the migration of the existing data. During the migration process, the system informs you by a message which data set needs to be enlarged. In that case, the data set needs to be preallocated with a larger size before invoking the HCD migration task again.

HCD uses, by default, the following ddnames and data set sizes:

- HCDPRINT

  Used for the HCD migration log.

  The data set name is built from the input data set name — if two input data sets are specified from the IOCP input data set name — qualified with 'MESSAGES'. If the input is a member of a partitioned data set, an additional qualifier - the name of the member - is inserted before 'MESSAGES'. The high-level qualifier of that data set name is replaced by the TSO prefix (user ID).

  The minimum allocation (also used as default allocation if the data set does not exist) is: RECFM=FBA, LRECL=133, BLKSIZE=2926, SPACE=(TRK,(1,10)), exclusive access.

- HCDASMP

  Contains the assembler SYSPRINT data set, which contains the assembly listing (input statements with sequence numbers and messages).

The data set name is built from the input data set name qualified with 'LISTING'. If the input is a member of a partitioned data set, an additional qualifier - the name of the member - is inserted before 'LISTING'. The high-level qualifier of that data set name is replaced by the TSO prefix (user ID).

The minimum allocation (also used as default allocation if the data set does not exist) is as follows: RECFM=FBA, LRECL=121, BLKSIZE=1573, SPACE=(TRK,(15,150)), exclusive access.

- HCDUT1

  Used by the assembler as a work data set (UNIT=SYSALLDA, LRECL=80, BLKSIZE=3200, SPACE=(TRK,(15,150)), exclusive access).

- HCDUT2

  Used as output data set for the modified input stream and by the assembler as SYSIN data set (UNIT=SYSALLDA, LRECL=80, SPACE=(TRK,(10,15)), exclusive access).

- HCDUT3

  Used by the assembler as punch data set (SYSPUNCH).

  Used by the loader as input data set (UNIT=SYSALLDA, LRECL=80, SPACE=(TRK,(10,30)), exclusive access).

Notes:

1. The sizes of the output data sets HCDUT2, HCDASMP, and HCDPRINT depend on the size of the input and on the number of messages produced. The space given above should be taken as minimum allocation values.
2. For HCDASMP and HCDPRINT, HCD checks whether data sets with the default names exist. If so, the space allocations of these existing data sets are used if they exceed the minimum allocation values. Correspondingly, the space of the HCDUT2 data set is made dependent on the input data set(s). This rule is only applicable if the ddnames have not been previously allocated.
3. Preallocate HCDASMP and HCDPRINT if:
   - You want to have them on a different data set than the default one
   - You want to place these data sets on a specific volume
   - The default size is not large enough

Chapter 12. How to Invoke HCD Batch Utility Functions

Programming Interface information

You can invoke HCD batch utility functions:

- With an input parameter string. The diagram below shows how to invoke an HCD batch utility function. For formats of the input parameter strings and sample batch jobs see "Input Parameter String" on page 284.

HCD Batch Invocation

```
►►──EXEC──PGM=CBDMGHCP,──PARM='─┤ Input Parameter String ├─'──────────────►◄
```

- By using an ATTACH or LINK module programming statement to invoke the module CBDMGHCP.

  When you invoke the module, register 1 must contain the address of a two-word parameter list.

  Word 1
  Address of input parameter (see "Input Parameter String" on page 284), preceded by a two byte length field.

  Word 2
  Address of a list of alternate DD names. If not used, the address must be binary zero. For the list format of alternate DD names see "List of Alternate DD Names" on page 314.

You may overwrite standard DD names listed in Figure 106 on page 313 as desired before invoking HCD.

If you specify the UIMs and UDTs in a library other than SYS1.NUCLEUS, you have to add the following statement to your batch jobs:

```
//HCDPROF DD DSN=BPAN.HCD.PROF,DISP=SHR
```

In the HCD profile (in our example BPAN.HCD.PROF) specify the following keyword:

```
UIM_LIBNAME=libname
```

If the keyword is omitted, SYS1.NUCLEUS is assumed. If you specify an asterisk (*) as data set name, HCD assumes that the UIM data set is part of the ISPF load library concatenation chain, contained in the JOBLIB/STEPLIB concatenation chain, or specified in the active LNKLSTxx member. For more information, see "Defining an HCD Profile" on page 41.

Running jobs in a sysplex environment:

If you want to execute a job on a specific system in a sysplex, you must specify in your batch job which system is to be used. If you do not specify the exact system of a sysplex for which the batch job is planned to execute on, the job executes on the system that has the free space to run on.

© Copyright IBM Corp. 1994, 2002

The output from some of the HCD functions depend very much on where the job was executed; for example, downloading IOCDSs and requesting the I/O Path report.

How to Read Syntax Diagrams

For details on this subject see "How to Read Syntax Diagrams" on page xv.

Note: Trailing commas in the parameter string can be omitted.

Input Parameter String

Input Parameter String

```
►►──┬──────────┬──┬─ Start the dialog ──────────────────────────────────────────►◄
    └─TRACE,───┘  ├─ Initialize a VSAM data set into an IODF ──┤
                  ├─ Upgrade an IODF ──────────────────────────┤
                  ├─ Migrate I/O configuration statements ─────┤
                  ├─ Build a production IODF ──────────────────┤
                  ├─ Build a work IODF from a production IODF ─┤
                  ├─ Build an IOCDS or an IOCP input data set ─┤
                  ├─ Build an HCPRIO input data set ───────────┤
                  ├─ Build I/O Configuration statements ───────┤
                  ├─ Copy an IODF ─────────────────────────────┤
                  ├─ Print a configuration report ─────────────┤
                  ├─ Create a graphical configuration report ──┤
                  ├─ Compare IODFs or CSS/OS views ────────────┤
                  ├─ Import an IODF ───────────────────────────┤
                  └─ Export an IODF ───────────────────────────┘
```

TRACE
When specified, the HCD trace will be activated.

Input Parameter String
You will find a detailed description of the input parameter strings in the following sections.

You can also activate tracing by adding the TRACE command in the HCD profile. This allows you to specify the trace parameters in more detail. In this case, you must allocate DD name HCDPROF to the HCD profile when invoking the batch utility. For more information, see "Defining an HCD Profile" on page 41, and "TRACE Command" on page 437.

Function Parameter Strings

Start the Dialog

This utility function starts the HCD (ISPF) Dialog session. The HCD primary task selection panel is displayed.

This function is invoked by passing the following parameter string.

Start the dialog

```
├──DIALOG──┬──────────┬──────────────────────────────────────────┤
           │   ┌─E─┐  │
           └─,─┴─J─┴──┘
```

E | **J** is a one-character code for national language support in help panels and messages. Specify one of the following (if omitted, the default is E):

E for English

J for Japanese

Initialize IODF

This utility function initializes a defined VSAM DIV file into an IODF. Each IODF contains as first record a header record, called the IHR (IODF Header Record). This record contains, among other information, the size of the IODF, an optional description of up to 128 characters, as well as an option whether activity logging is enabled or disabled. HCD rejects any data set that does not contain such a header record.

The VSAM DIV file must be preallocated using DD name HCDIODFT. You can add an optional IODF description using DD name HCDCNTL.

This function is invoked by passing the following parameter string.

Initialize a VSAM data set into an IODF

```
├──INITIODF──SIZE=nnnn──┬──────────────────────────┬──┬──────────┬──┤
                        │              ┌─YES─┐     │  └─,FORCE─┘
                        └─,ACTLOG=─────┴─NO──┴─────┘
```

SIZE=*nnnn*

nnnn specifies the size of the IODF in 4K blocks. This value must not be greater than the number of records specified with the IDCAMS Define Cluster control statement.

ACTLOG=(YES | NO)

specifies enabling of activity logging. If omitted, the default is YES.

FORCE

indicates that reinitialization of an existing IODF is allowed.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFT	IODF to be initialized
HCDCNTL	Up to 128 characters used as description for the IODF.

DD name	Description
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

The following example shows the IDCAMS control statements necessary to define a VSAM DIV file.

```
DEFINE CLUSTER (NAME (SYS1.IODF01.CLUSTER) -
       LINEAR -
       RECORDS (1024) -
       VOLUMES (DATA02) -
       ) -
       DATA (NAME (SYS1.IODF01))
```

For an example see the batch job on page 310.

Notes:

1. This batch job issues a job message IEC161I, which can be ignored.
2. The VSAM DIV file consists of a data and a cluster file. According to the IODF naming convention (see "IODF Naming Convention" on page 49), the name of the data file is the IODF name (in this example SYS1.IODF01), and .CLUSTER is appended to the data file for a cluster file. To define your VSAM DIV file, you must append .CLUSTER to the IODF name in the DEFINE CLUSTER statement (in this example SYS1.IODF01.CLUSTER).

Upgrade IODF

This utility function upgrades a back-level IODF (from HCD Release 2, or HCD Release 3) to be accessible with the current HCD release.

You have to allocate:
- The IODF you want to upgrade with DD name HCDIODFS
- The IODF into which the I/O definitions are to be upgraded with DD name HCDIODFT

This function is invoked by passing the following parameter string.

Upgrade an IODF

```
├──UPGRADE──────────────────────────────────────────────────────────────┤
```

Notes:

1. The target data set must be large enough to hold the source IODF.
2. The target IODF may be created using the utility ***Initialize IODF*** (described in "Initialize IODF" on page 285).
3. Both data sets must be valid IODFs.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Back-level IODF to be upgraded
HCDIODFT	IODF into which IODF definitions are to be upgraded (if not specified, the IODF is upgraded in place)
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* UPGRADE IODF
//*
//UPGRADE  EXEC PGM=CBDMGHCP,PARM='UPGRADE'
//HCDIODFS DD   DSN=BWIN.IODFR2.WORK,DISP=SHR
//HCDIODFT DD   DSN=BWIN.IODF00.WORK,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

For considerations concerning the size when upgrading a back-level IODF, refer to Table 3 on page 62.

Migrate I/O Configuration Statements

This utility function allows you to migrate the data set containing I/O configuration statements, e. g. an IOCP, MVSCP, or HCPRIO input data set and store the definitions into an IODF.

You have to allocate:

- The IODF into which the I/O definitions are to be migrated with DD name HCDIODFT
- The I/O configuration input data set with DD name HCDIN
- The MACLIB containing the parsing macros with DD name HCDLIB

This function is invoked by passing the following parameter string.

Migrate I/O configuration statements

```
├─MIGR─,─┬─┬─I──┬─┬─┤ processor parameters ├─┬──────────────────────┬─┤
        │ │ IP─┘ │ └─,─*──────────────────┘ │                      │
        │ ├─O──┬─┤ OS parameters ├──┬──────┬─┤                      │
        │ │ OP─┘ │                  └─┤ association ├─┘            │
        │ │      └─,─*──────────────────────────────┘              │
        │ ├─B──┬─┤ OS parameters ├─┤ processor parameters ├─┤      │
        │ │ BP─┘                                                   │
        └─S─,─*──────────────────────────────────────────────────┘
```

processor parameters:

```
├─,─procid─,─proctype─,─┬──────────────┬─┬──────────────────────┬─┤
                       └─┤ procmode ├─┘ └─,─support_level_ID─┘
```

OS parameters:

```
├─,─osid─,─ostype──────────────────────────────────────────────┤
```

association:

```
├─,─asproc─┬──────────┬──────────────────────────────────────┤
           └─,─aspart─┘
```

procmode:

```
├─┬─BASIC─┬──────────────────────────────────────────────────┤
  └─LPAR──┘
```

I | IP | O | OP | B | BP | S

Function indicator:

I	Migration of processor configuration statements (e. g. IOCP data sets)
IP	Partial migration of processor configuration statements
O	Migration of OS configuration statements (e. g. MVSCP or HCPRIO data sets)
OP	Partial migration of OS configuration statements
B	Combined migration of processor and OS configuration statements
BP	Partial combined migration of processor and OS configuration statements

S Switch migration

Processor related variables and keywords:

procid Processor ID (up to 8 characters)

proctype Processor type and model separated by a hyphen, for example 9672-E08

procmode Processor mode

BASIC
If the processor operates in BASIC mode (default).

LPAR If the processor operates in LPAR mode.

support_level_ID
Support level ID associated with the processor. This parameter is required if the processor does not already exist and several support level IDs are installed for a supported processor type. The support level ID can be obtained by the ***List supported processors*** function or by the supported hardware report described in "Print Configuration Reports" on page 299. For an example of a supported hardware report refer to "Supported Hardware Report" on page 373.

If you do not specify a support level, the highest support level will be used for the processor.

Note: The support level ID is unique to HCD and does not correspond to the EC level of the processor.

***** Allows multiple processor configurations to be migrated. Scans the input data set to determine which processor configurations are to be processed. For successful migration the configurations must include the ID statement described in "Processor" on page 260.

OS related parameters:

osid Operating system ID (up to 8 characters)

ostype OS type (MVS or VM)

asproc Associated processor. For more information, see "Migrating Additional MVSCP or HCPRIO Input Data Sets" on page 246

aspart Associated partition. For more information, see "Migrating Additional MVSCP or HCPRIO Input Data Sets" on page 246

***** Allows multiple OS configurations to be migrated. Scans the input data set to determine which OS configurations are to be processed. For successful migration the configurations must include the IOCONFIG statement described in "Operating System" on page 254.

Switch related wildcard:

***** Allows switch configurations of multiple switches to be migrated. Scans the input data set to determine which switch configurations are to be processed. For successful migration the configurations must include the SWCONF statement described in "Switch Configuration" on page 258.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFT	IODF into which I/O definitions are to be migrated
HCDIN	I/O configuration input data set
HCDLIB	MACLIB containing the parsing macros (CBDZPARS)
HCDMLOG	HCD Message Log data set
HCDPRINT	Data set for migration log (see "Insufficient Data Set Sizes" on page 280)
HCDASMP	Data set for assembly listing (see "Insufficient Data Set Sizes" on page 280)
HCDPROF	HCD profile (when using extended migrate function)
HCDTRACE	Trace data set (if trace is activated)

For defaults of HCDPRINT and HCDASMP, for preallocating additional migration data sets, and for viewing the migration log see "Resolving Migration Errors" on page 277. **Example:**

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* MIGRATE AN IOCP DECK
//*
//MIGRATE  EXEC PGM=CBDMGHCP,
//            PARM='MIGR,I,PROC1,9672-E08,LPAR'
//HCDIODFT DD   DSN=BWIN.IODF03.WORK,DISP=OLD
//HCDIN    DD   DSN=BWIN.IOCP.DECK,DISP=SHR
//HCDLIB   DD   DSN=SYS1.MACLIB,DISP=SHR
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//HCDPRINT DD   DSN=BWIN.IOCP.MESSAGES,DISP=OLD
//HCDASMP  DD   DSN=BWIN.IOCP.LISTING,DISP=OLD
//
```

Build a Production IODF

This utility function creates a production IODF using the work IODF. The work IODF has to be specified with DD name HCDIODFS, the target production IODF with DD name HCDIODFT. First, the target production IODF has to be created by defining a VSAM DIV file and initializing it using the utility Initialize IODF (see "Initialize IODF" on page 285).

After the production IODF has been built, it is copied back to the work IODF. Thus, the work IODF contains the new tokens and can be used for further updates. Since the production IODF may be larger than the original work IODF, the work IODF may be automatically enlarged to accommodate the contents of the production IODF.

This function is invoked by passing the following parameter string.

Build a Production IODF

```
├─PRODIODF──┬──────────────────────────────────┬──────────────────────────┤
           ├─DESC1=descriptor1────────────────┤
           ├─DESC2=descriptor2────────────────┤
           └─DESC1=descriptor1,DESC2=descriptor2─┘
```

DESC1=*descriptor 1*
: Default is the first qualifier of the production IODF name (up to 8 characters).

DESC2=*descriptor 2*
: Default is the second qualifier of the production IODF name, which is IODFxx (up to 8 characters).

The descriptor fields describe the IODF and will be part of the HSA token. If you specify asterisks (**) for the IODF suffix in LOADxx, the operating system uses the descriptor fields to find the current IODF.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Work IODF
HCDIODFT	Production IODF
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* BUILD PRODUCTION IODF
//*
//PROD     EXEC PGM=CBDMGHCP,
//             PARM='PRODIODF DESC1=BWIN,DESC2=IODF03'
//HCDIODFS DD   DSN=BWIN.IODF03.WORK,DISP=OLD
//HCDIODFT DD   DSN=BWIN.IODF03,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Build a Work IODF from a Production IODF

This utility function creates a work IODF using an existing production IODF. The production IODF has to be specified with DD name HCDIODFS, the target work IODF with DD name HCDIODFT. First, the work IODF has to be created by defining a VSAM DIV file and initializing it using the utility Initialize IODF (see “Initialize IODF” on page 285).

This function is invoked by passing the following parameter string.

Build a Work IODF

```
├──WORKIODF──────────────────────────────────────────────────────────────┤
```

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Production IODF
HCDIODFT	Work IODF
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* BUILD WORK IODF
//*
//WORK     EXEC PGM=CBDMGHCP,PARM='WORKIODF'
//HCDIODFS DD   DSN=BWIN.IODF03,DISP=SHR
//HCDIODFT DD   DSN=BWIN.IODF03.WORK,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Build an IOCDS or an IOCP Input Data Set

This utility function builds the IOCDS or the IOCP input data set using the definitions of a production IODF. This function is invoked by passing the following parameter string.

Build an IOCDS or an IOCP input data set

```
►►─IOCDS─,─┬──────┬─,─procid─,─┤ ind ├──────────────────────►◄
           └─iocds─┘
```

ind

```
                ┌─SA──┐
├─┬─D─,─┬──────┤     ├──────────────────────────────────────┤
  │     │      └─NOSA─┘
  ├─I─┬──────────────┤
  │   └─,NOCHKCPC────┘
  ├─W─┬──────────────┤
  │   └─,NOCHKCPC────┘
  ├─S──────────────────┤
  └─T──────────────────┘
```

iocds is a two-character IOCDS identifier, if building an IOCDS

procid Processor ID

D | I | W | S | T
One-character request code:

D Build an IOCP input data set

SA
The generated IOCP statements can be used for the stand-alone IOCP program (default).

NOSA
Depending on the HCD profile option MIGRATE_EXTENDED=YES, the generated IOCP statements have additional information that can be used for the extended migration. This information is shown as comments to IOCP.

Note: An IOCP input data set generated with operand NOSA may not be accepted by the stand-alone IOCP program, because of differences between the IOCP program running in z/OS and the stand-alone IOCP program.

I Build an IOCDS

W Build an IOCDS with dual-write option

NOCHKCPC
Write an IOCDS regardless of the type of the receiving processor. Refer to "Supported Hardware Report" on page 373 for a list of processor types that can receive an IOCDS in preparation for a processor upgrade and for processor types for which such an IOCDS can be written.

S Build an IOCDS and set the IOCDS active for next POR

T Build an IOCDS with dual-write option and set the IOCDS active for next POR

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Source IODF
HCDDECK	IOCP data set (if build IOCP input data set is requested)
HCDCNTL	Control data set for specifying the MSG1 IOCP parameter
SYSPRINT	SYSPRINT data set for IOCP output listing (requested for build IOCDS)
SYSIN	Temporary work file used as IOCP input deck
HCDMLOG	HCD Message Log data set
HCDPROF	HCD profile (when generating additional information for extended migration)
HCDTRACE	Trace data set (if trace is activated)

Example 1:

The following example shows a ***Build IOCDS*** job.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=5M
//*
//* BUILD IOCDS (WITH DUAL-WRITE OPTION)
//*
//IOCDS    EXEC PGM=CBDMGHCP,
//            PARM='IOCDS,A0,PROC1,W'
//HCDIODFS DD   DSN=BWIN.IODFA3,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//SYSPRINT DD   DSN=&&IOCPOUT,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650),
//             SPACE=(CYL,(1,1)),DISP=(NEW,PASS,DELETE),UNIT=SYSALLDA
//SYSIN    DD   DSN=&&TEMP,DISP=(NEW,DELETE),SPACE=(CYL,(1,1)),
//             DCB=(RECFM=FB,LRECL=80,BLKSIZE=6080),UNIT=SYSALLDA
//HCDCNTL  DD   *
MSG1
/*
//* EXECUTED ONLY IF RETURN CODE HIGHER THAN 0
//PRINT    EXEC PGM=IEBGENER,COND=(0,EQ,IOCDS)
//SYSUT1   DD   DSN=&&IOCPOUT,DISP=(OLD,DELETE)
//SYSUT2   DD   SYSOUT=*
//SYSIN    DD   DUMMY
//SYSPRINT DD   DUMMY
//*
//CLEANUP  EXEC PGM=IEFBR14,COND=(0,NE,IOCDS)
//SYSUT    DD   DSN=&&IOCPOUT,DISP=(OLD,DELETE)
//
```

Example 2:

The following example shows a ***Build IOCP input data set*** job.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=5M
//*
//* BUILD IOCP DECK
//*
//IOCP     EXEC PGM=CBDMGHCP,
//            PARM='IOCDS,,PROC1,D,SA'
//HCDIODFS DD   DSN=BWIN.IODFA3,DISP=SHR
//HCDDECK  DD   DSN=BWIN.IOCP3.DECK,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
```

```
//HCDCNTL  DD   *
MSG1
/*
//
```

Note: MSG1 specifies the identification information printed on the first ID line of the heading of the IOCP input data set. Specify the text without any keyword and quotation-marks.

Build an HCPRIO Input Data Set

This utility function creates an HCPRIO input data set using the definitions of a VM operating system in a production IODF.

The IODF from which I/O definitions are extracted has to be specified with DD name HCDIODFS, and the HCPRIO input data set with DD name HCDDECK.

This function is invoked by passing the following parameter string.

Build an HCPRIO input data set

```
├──VMBUILD──,──H──,──osid──────────────────────────────────────────────┤
```

H Function indicator for HCPRIO input data set

osid
VM operating system ID (up to 8 characters)

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	IODF from which I/O definitions are extracted
HCDDECK	VM I/O configuration data set
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* BUILD AN HCPRIO INPUT DATA SET
//*
//HCPRIO   EXEC PGM=CBDMGHCP,PARM='VMBUILD,H,VM1'
//HCDIODFS DD   DSN=BWIN.IODF03,DISP=SHR
//HCDDECK  DD   DSN=BWIN.HCPRIO3.DECK,DISP=OLD
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Build I/O Configuration Statements

This utility function allows you to build I/O configuration statements from an IODF and to store them in a data set. The statements describe:

- Operating system configurations
- Processor configurations
- Switch configurations

The data sets created can be edited and re-migrated into the IODF.

In addition, you can build:
- JES3 initialization stream checker data
- CONFIGxx members (from production IODF only)

You invoke this function by passing the following parameter string:

Build I/O Configuration Statements

```
├─CONFIG─,─┬─OS─,─┬─osid─┬──────────────────────────────┤
          │      │  └─*─┘                              │
          ├─PR─,─┬─procid─┬──────────────────────────────┤
          │      │  └─*───┘                              │
          ├─SW─,─┬─swid─┬──────────────────────────────┤
          │      │  └─*─┘                              │
          ├─JES─,─osid─,─edt_id──────────────────────────┤
          └─XX─,─┤ CONFIGxx_parameters ├──────────────────┘
```

CONFIGxx_parameters:

```
├─xx─,─procid─,─┬──────────────┬─,─osid─,─┬─U─┬─,─┬──────────┬─,─┬──────────┬──┤
               └─partition_id─┘           └─R─┘   └─backup────┘   └─sysplex───┘
```

OS | PR | SW | JES | XX
Function indicator:

OS Build OS configuration statements
osid OS configuration ID (up to 8 characters)
***** If you specify * in place of an OS configuration ID, HCD searches for a list of OS configuration IDs in a data set allocated to HCDCNTL. If no data set has been allocated to DD name HCDCNTL, statements are built for all operating systems in the IODF.

PR Build processor configuration statement
procid processor ID (up to 8 characters)
***** If you specify * in place of a processor ID, HCD searches for a list of processor IDs in a data set allocated to HCDCNTL. If no data set has been allocated to DD name HCDCNTL, statements are built for all processors in the IODF.

If only the coupling facility partition and CF receive channels are to be generated for a particular processor, the respective processor ID in the list has to be qualified by the keyword CF, according to the following syntax:

```
├─procid──┬──────────┬──────────────────────────────────────┤
          └─,─CF─────┘
```

SW Build switch configuration statements

swid Switch ID (2 hexadecimal characters)

***** If you specify * in place of a switch ID, HCD searches for a list of switch IDs in a data set allocated to HCDCNTL. If no data set has been allocated to DD name HCDCNTL, statements are built for all switches in the IODF.

JES Build JES3 initialization stream checker data

osid OS configuration ID (up to 8 characters)

edt_id EDT ID (2 hexadecimal characters)

XX Build CONFIGxx members

xx Suffix of the CONFIGxx member to be built

procid Processor ID (up to 8 characters)

partition_id
Partition name; required entry, if the processor is in LPAR mode (up to 8 characters).

osid OS configuration ID (up to 8 characters)

U/R `U` updates the current CONFIGxx member. The CHP and DEVICE statements are replaced and all other statements remain unchanged. This is the default.

`R` deletes the current CONFIGxx member and generates new CHP and DEVICE statements.

backup
Name for the backup copy of the current CONFIGxx member (up to 8 characters).

sysplex
Name of the sysplex used for setting managed channel paths to ONLINE.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Source IODF
HCDDECK	Generated output data set For CONFIGxx this must be a data set name of a partitioned data set.
HCDMLOG	HCD Message Log data set
HCDCNTL	Optional for specifying a list of operating systems, processors, or switches Not applicable for building CONFIGxx member or JES3 inish data set
HCDTRACE	Optional for capturing the trace if trace is activated.

Example 1:

The following example shows a job to build a configuration data set containing processor configuration PROC1 including its CF connections to processor PROC2.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* BUILD Processor configuration statement
//*
//BUILD  EXEC PGM=CBDMGHCP
          PARM='CONFIG,PR,*'
//HCDIODFS DD   DSN=BWIN.IODF03,
//HCDDECK  DD   DSN=BWIN.IODF.03.DECKS(PROC1),DISP=SHR
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//HCDCNTL  DD   *
PROC1
PROC2,CF
/*
//
```

Example 2:

The following example shows a job to update CONFIG03 in data set SYS1.PARMLIB from processor configuration PROC1, partition LPAR1 and OS configuration MVS1 while saving the existing member under the name CONFBK03.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* BUILD CONFIGxx
//*
//BUILD  EXEC PGM=CBDMGHCP
          PARM='CONFIG,XX,03,PROC1,LPAR1,MVS1,U,CONFBK03'
//HCDIODFS DD   DSN=BWIN.IODF03,DISP=OLD
//HCDDECK  DD   DSN=SYS1.PARMLIB,DISP=SHR
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
/*
//
```

Copy IODF

This utility function copies the content of the IODF, addressed by DD name HCDIODFS, into another data set, addressed by DD name HCDIODFT.

This function is invoked by passing the following parameter string.

Copy an IODF

```
├─COPYIODF──────────────────────────────────────────────────────────┤
```

Notes:

1. The target data set must be large enough to hold the source IODF.
2. The target IODF can be created by defining a VSAM DIV file and by initializing it using the utility ***Initialize IODF*** (described in "Initialize IODF" on page 285).
3. Both data sets must be valid IODFs.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Source IODF
HCDIODFT	Target IODF
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

For an example see the batch job on page 310.

Print Configuration Reports

This HCD batch utility function allows you to print reports about:

- The hardware definitions stored in the specified IODF.
- The I/O paths of an actual system compared to the definitions in the IODF.
- The processors, control units, and devices supported in your installation.

This function is invoked by passing the following parameter string.



C | P | U | D | S | M | E | N | T | I | X | Y

Type of the report. Specify one or more of the following codes in any order, with no separating characters:

C CSS report - CSS summary report only
P CSS report - channel path detail report
U CSS report - control unit detail report
D CSS report - device detail report
S Switch report
M OS report - OS devices
E OS report - EDTs
N OS report - NIP/VM consoles

T CTC report
I I/O Path report
X Supported hardware report
Y I/O definition reference

procid Processor ID to limit a CSS, CTC connection or I/O path report to a specific processor. If not specified for an I/O path report, the ID of the active processor configuration is taken (=default).

partnm
Partition name to limit a CSS, CTC connection or I/O path report to a specific logical partition. The processor ID must also be specified; otherwise, the partition name is ignored for the CSS and CTC connection report. For the I/O path report, the partition name is defaulted to a partition that contains a device common to the specified or defaulted OS configuration.

osid Operating system configuration ID to limit an OS report or an I/O path report to a specific operating system configuration. If not specified for an I/O path report, the ID of the active operating system configuration is taken (=default).

swid Switch identifier to limit a Switch report to a specific switch

system
If the sysplex name is also specified, the system name (1 - 8 alphanumeric characters) identifies the system of a sysplex for that the I/O Path report is to be generated. If the sysplex is not specified, the system name is the VTAM application name of the host for that the I/O Path report is to be generated. The default is the local system.

sysplex
Sysplex name (1 - 8 alphanumeric characters) to specify the sysplex of the system for that the I/O Path report is to be generated. If you specify the sysplex, you must also specify the system name.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
STEPLIB	SYS1.SCBDHENU (required for I/O definition reference)
HCDIODFS	Source IODF (not required when printing the supported hardware report, and I/O definition reference)
HCDRPT	Output data set: record size 133, record format fixed block
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example 1:

```
//BWINJOB   JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//************************************************************
//*  PRINTS A CSS SUMMARY REPORT FOR PARTION PART1 OF PROCESSOR
//*                              PROC1,
//*         A SWITCH REPORT FOR SWITCH 00,
//*         AN OS REPORT FOR DEVICES, EDT AND NIP CONSOLES OF
//*                              OS CONFIGURATION MVS1
//************************************************************
```

```
//REPORT1   EXEC PGM=CBDMGHCP,
//             PARM='REPORT,CSMEN,PROC1,PART1,MVS1,00'
//HCDIODFS  DD   DSN=BWIN.IODF03.WORK,DISP=SHR
//HCDRPT    DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//HCDMLOG   DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Example 2:

```
//BWINJOB   JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//              MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//************************************************************
//*  PRINTS A SUPPORTED HARDWARE REPORT AND
//*         AN I/O DEFINITION REFERENCE
//************************************************************
//REPORT2   EXEC PGM=CBDMGHCP,
//               PARM='REPORT,XY'
//STEPLIB   DD   DSN=SYS1.SCBDHENU,DISP=SHR
//HCDRPT    DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//HCDMLOG   DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Example 3:

```
//BWINJOB   JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//              MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//************************************************************
//*  PRINTS AN I/O PATH REPORT OF THE ACTIVE CONFIGURATION
//*  COMPARED TO THE DEFINITIONS IN IODF SYS1.IODF00
//************************************************************
//REPORT3   EXEC PGM=CBDMGHCP,
//               PARM='REPORT,I'
//HCDIODFS  DD   DSN=SYS1.IODF00,DISP=SHR
//HCDRPT    DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//HCDMLOG   DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Example 4:

```
//BHEIREP  JOB (DE03243,,RZ-29),'HEISSER',CLASS=A,REGION=4M,
//        MSGLEVEL=(1,1),NOTIFY=BHEI,MSGCLASS=Q
//*****************************************************************
//*EXAMPLE OF A BATCH JOB THAT IS CREATED FROM THE DIALOG AND THAT
//*PRINTS AN I/O PATH REPORT OF THE ACTIVE CONFIGURATION OF THE
//*SYSTEM HCDTST3 COMPARED TO THE DEFINITIONS FOR THE PROCESSOR
//*VMABASIC AND THE OPERATING SYSTEM MVSVM IN BHEI.IODF01.WORK
//*****************************************************************
//REP0    EXEC PROC=CBDJRPTS,
//             RPARM='REPORT,I,VMABASIC,,MVSVM,,HCDTST3,LOCAL'
//             IODF='BHEI.IODF01.WORK'
//
```

Note: For generating the I/O Path Reports which are printed in examples 3 and 4, System Automation for OS/390 (I/O Operations) or the ESCON Manager is required.

Create a Graphical Configuration Report

This utility function allows you to produce a graphical representation of the I/O configuration based on the definitions in the IODF.

This function is invoked by passing the following parameter string.

Create a graphical configuration report

```
├──GRAPHIC──TYPE=──────────────────────────────────────────────►

►──┬─CU──────────────────────────────────────────────┬──┬──────────┬──┤
   ├─SWITCH────────────────────────────────────────┤  └─ Options ─┘
   ├─CF────────────────────────────────────────────┤
   ├─CHPID──,──PROC=──procid──┬──────────────────┬┤
   │                          └─,──PART=──partname─┘│
   └─LCU──,──PROC=──procid────┬──────────────────┬┘
                              └─,──PART=──partname─┘
```

Options

```
                  ┌─,──────┐
                  ▼        │
├──,──OPT=──(──┬──┬─EP──┬──┬──────────┬──)──────────────────────┤
              │  ├─ES──┤  ├─,──DCF──┤
              │  ├─EC──┤  └─,──GML──┘
              │  ├─SD──┤
              │  └─EI──┘
              └─┬─DCF─┬──────────────┘
                └─GML─┘
```

TYPE Type of the report. Specify one of the following codes:

CU	CU report
SWITCH	Switch report
CF	CF connection report
CHPID	CHPID report
LCU	LCU report
Procid	Processor ID for which the LCU or CHPID report is produced.
Partname	Partition name to limit an LCU or CHPID report to one partition.

OPT Options of the report. Specify one or more of the following codes in any order, separated by a comma:

EP	Exclude partition
ES	Exclude switch
EC	Exclude CTC control units
SD	Show control unit description (instead of serial number)
EI	Exclude index
DCF	DCF output format
GML	GML output format

Notes:

1. If no output format is specified, the specification in the HCD profile is used. If the HCD profile does not specify a formatting type either, the default BookMaster format is used.
2. The output format GDF is not supported in batch mode.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	Source IODF
HCDRPT	Output data set: record size 200, record format FB. **Note:** This must be a cataloged data set.
HCDMLOG	HCD Message log data set
HCDPROF	HCD profile data set (if profile contains keywords concerning the graphical report)
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINGCR1 JOB (DE3259,,71034-83),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//* -------------------------------------------------------
//* Graphical Configuration Report
//* -------------------------------------------------------
//GCREP  EXEC PGM=CBDMGHCP,
//           PARM='GRAPHIC TYPE=CHPID,PROC=TEST3'
//HCDIODFS DD DSN=USER.IODF00.DBR4,DISP=SHR
//HCDRPT   DD DSN=USER.IODF00.DBR4.REPORT,
//            DCB=(RECFM=FBA,LRECL=200,BLKSIZE=6400),
//            SPACE=(TRK,(50,50)),DISP=(NEW,KEEP),UNIT=SYSALLDA
//HCDMLOG  DD DSN=USER.HCD.LOG,DISP=OLD
//HCDPROF  DD DSN=USER.HCD.PROF,DISP=SHR
//
```

Compare IODFs or CSS/OS Reports

This utility function allows you to compare two IODFs and report the differences. You can compare the IODFs from the CSS, OS, and switch perspective.

In addition, you can limit the CSS, OS, and switch perspective by single compare reports, and the CSS perspective by LPARs.

You have to allocate the new IODF with DD name HCDIODFS, and the old IODF with DD name HCDIODFT for comparing IODFs. If you compare the CSS to the OS definition, you always compare within one IODF that must be allocated to HCDIODFS.

You invoke this function by passing the following parameter string.

Note: This parameter string must not exceed 100 characters.

Compare IODFS or CSS/OS Reports

```
├─COMPARE─,─┬─┤ IODF Compare ├─┬──────────────────────────────────┤
           └─┤ CSS/OS Compare Report ├─┘
```

IODF Compare:

```
├─┬─┬─┬─A─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─┬─►
  │ │ │ │ B │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │
  │ │ │ │ C │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │
  │ │ │ │ D │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │ │
  │ │ │ │
```

A Print added data
B Print deleted data
C Print unchanged data
D Print unchanged item IDs

CL | C | OL | O | SL | S
Type of the report. Specify one or more of the following codes in any order, with no separating characters:

CL Limit the CSS compare report by single compare reports and LPARs

PR Processor compare
PA Partition compare
CP Channel path compare
CA Control unit attachment compare
DA Device attachment compare
CU Control unit compare
DV Device compare

procid1
New processor ID

partn1 Partition name of the new processor ID

procid2
Old processor ID

partn2 Partition name of the old processor ID

C Indicates CSS compare report

procid1
New processor ID

procid2
Old processor ID

OL Limit OS compare report by single compare reports

OS Operating system compare
ED EDT compare
GE Generic compare
GU Generic update compare
ES Esoteric compare
NI OS console compare
OD OS device compare

osid1 New operating system ID

osid2 Old operating system ID

O Indicates OS compare report

osid1 New operating system ID

osid2 Old operating system ID

SL Limit switch compare report by single compare reports

SW Switch compare
PO Switch port compare

SC Switch configuration compare
PC Port configuration compare

swid1 New switch ID

swid2 Old switch ID

S Indicates SWITCH compare report

swid1 New switch ID

swid2 Old switch ID

Print option
If no selection is made, only devices are printed that are
- Defined for the CSS, but not for the OS
- Defined for the OS, but not for the CSS
- Defined for both, but of different device type

C Print all devices

D Indicates CSS/OS compare

procid Processor ID

partn Partition name. This is a required parameter, if the processor runs in LPAR mode. For more information, see "Compare CSS / Operating System Views" on page 230.

osid Operating system ID

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
STEPLIB	SYS1.SCBDHENU (required for OS device compare)
HCDIODFS	New IODF
HCDIODFT	Old IODF (only for IODF compare)
HCDMLOG	HCD Message Log data set
HCDRPT	Report data set; record size 133, record format fixed block
HCDTRACE	Trace data set (if trace is activated)

Example 1:

The following example shows a job to ***compare two IODFs***.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* COMPARE IODFs WITH ADDED AND DELETED DATA
//* DEVICE, DEVICE ATTACHMENT AND OS DEVICE COMPARE
//* LIMITED TO LPAR PROC2.LPAR1 ON BOTH AND OS PROD17
//*
//COMPARE1 EXEC PGM=CBDMGHCP,
//            PARM='COMPARE,AB,CL,DVDA,PROC2,LPAR1,PROC2,LPAR1,
//            OL,PROD17,PROD17'
//STEPLIB  DD   DSN=SYS1.SCBDHENU,DISP=SHR
//HCDIODFS DD   DSN=BWIN.IODF06.WORK,DISP=SHR
//HCDIODFT DD   DSN=BWIN.IODF03,DISP=SHR
//HCDRPT   DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Example 2:

The following example shows a job to ***compare CSS/OS reports***.

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* COMPARE CSS/OS CONFIGURATION BETWEEN
//* DEVICES CONNECTED TO PROC1, PART1 ON CSS SIDE
//*         DEFINED TO OS MVS1
//*
//COMPARE2 EXEC PGM=CBDMGHCP,
//            PARM='COMPARE,AB,D,PROC1,PART1,MVS1'
//HCDIODFS DD   DSN=BWIN.IODF06.WORK,DISP=SHR
//HCDRPT   DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Import an IODF

This utility function allows you to import configuration data (previously exported from another system) into an IODF. It is assumed that the mentioned configuration data has been received outside HCD, for example, using the TSO RECEIVE command, and stored in a sequential data set.

The data set containing IODF data to be imported has to be specified with DD name HCDIN.

This function is invoked by passing the following parameter string.

Import an IODF

```
├──IMPORT──,──IODF name──,──┬──────────┬──,──┬──────────┬──────────────────────┤
                            └─volume───┘     └─REPLACE──┘
```

IODF name Specifies the name of the target IODF (fully qualified).

volume Specifies the volume serial number of the IODF destination. This parameter is neglected if the target IODF already exists and REPLACE is specified, or, if the data set is SMS managed.

REPLACE Specifies that an IODF with the same name will be replaced by the received IODF. If REPLACE is not specified, the IODF is not replaced.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIN	The data set containing IODF data to be imported
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

Example:

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//             MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* IMPORT AN IODF
//*
//IMPORT   EXEC PGM=CBDMGHCP,
//            PARM='IMPORT,BWIN.IODF08,DATA04'
//HCDIN    DD   DSN=BWIN.EXPORTED.IODF03,DISP=SHR
//HCDMLOG  DD   DSN=BWIN.HCD.LOG,DISP=OLD
//
```

Export an IODF

This utility function allows you to send an IODF to another system.

You have to preallocate the IODF you want to export with DD name HCDIODFS.

If you want to send an IODF to an unattended z/OS system, you have to allocate a data set with DD name HCDCNTL. From this data set, HCD extracts information to set up the JCL to run on the unattended target system. You have to modify or adapt the JOB statement, JES routing statement(s), and JOBLIB information in this data set before you call the export utility.

This function needs to be executed in an TSO environment, for example, by invoking HCD under control of the TSO terminal monitor program IKJEFT01.

This function is invoked by passing the following parameter string.

Export an IODF

```
├─EXPORT─,─user id─,─┬──────────┬─,─┬──────────────┬─,─┬──────────┬──────────►
                    └─node id──┘   └─IODF name────┘   └─volume───┘

►─,─┬─────────┬─,─┬──────────┬──────────────────────────────────────────┤
    └─ACTLOG──┘   └─NOREPLACE─┘
```

user id Specifies the user ID of the target, or a nickname (nickname only if the IODF is not sent to an unattended z/OS system).

node id Specifies the node ID of the target system, but only if the IODF is not sent to an unattended target system (otherwise it is ignored in favor of information provided by the JCL).

IODF name Specifies the name of the target IODF. Default is the name of the source IODF prefixed with the specified target user ID. This parameter is only applicable if the IODF is sent to an unattended z/OS system, otherwise it is ignored.

volume Specifies the volume serial number of the DASD on which the target IODF is created if it does not exist. This parameter is only applicable if the IODF is sent to an unattended z/OS system, and the IODF data set is not managed by SMS, otherwise it is ignored.

ACTLOG Specifies that the appropriate Activity Log file should also be sent. If this parameter is missing, or the target is an unattended MVS system, it is not sent.

NOREPLACE For unattended exports, this keyword provides overwrite protection for an IODF at the target system with the same name as the IODF to be exported.

Batch Invocation

A data set must be allocated to the following DD names when invoking the batch utility.

DD name	Description
HCDIODFS	IODF to be exported
HCDCNTL	JCL data set containing the JOB statement, the JES routing statement(s) and the JOBLIB information for sending the IODF to an unattended z/OS system.
SYSTSPRT	Print dataset
SYSTSIN	SYSIN dataset
HCDMLOG	HCD Message Log data set
HCDTRACE	Trace data set (if trace is activated)

You can also find the following examples in the data set SYS1.SAMPLIB.

Example 1:

The following example shows a job to export an IODF to an attended system.

```
//BWINEX1 JOB (3259,7030-83),'BWIN',CLASS=A,USER=BWIN,
//        MSGLEVEL=(1,1),NOTIFY=BWIN,MSGCLASS=Q,REGION=4M
/*
//EXPORT1 EXEC PGM=IKJEFT01
//SYSPRINT DD SYSOUT=*
//HCDIODFS DD DSN=BWIN.IODF52.WORK,DISP=SHR
//HCDMLOG  DD DSN=BWIN.HCD.LOG,DISP=OLD
//SYSTSPRT DD SYSOUT=*
//SYSTSIN  DD *
     CALL 'SYS1.LINKLIB(CBDMGHCP)',      +
     'EXPORT,BMGN,BOETST1'
/*
//
```

Example 2:

The following example shows a job to export an IODF to an unattended z/OS system.

```
//BWINEX2 JOB (3259,7030-83),'BWIN',CLASS=A,USER=BWIN,
//        MSGLEVEL=(1,1),NOTIFY=BWIN,MSGCLASS=Q,REGION=4M
//*************************************************************
//* MODIFY AND ADAPT DATA SET ALLOCATED WITH DDNAME HCDCNTL
//* BEFORE YOU SUBMIT THIS JOB.
//*   USE HCDCNTL2 FOR A JES2 SYSTEM
//*   USE HCDCNTL3 FOR A JES3 SYSTEM
//*************************************************************
//EXPORT1 EXEC PGM=IKJEFT01
//SYSPRINT DD SYSOUT=*
//HCDIODFS DD DSN=BWIN.IODF52.WORK,DISP=SHR
//HCDMLOG  DD DSN=BWIN.HCD.LOG,DISP=OLD
//HCDCNTL  DD DSN=SYS1.SAMPLIB(HCDCNTL2),DISP=SHR
```

```
//SYSTSPRT DD SYSOUT=*
//SYSTSIN  DD *
      CALL 'SYS1.LINKLIB(CBDMGHCP)',      +
      'EXPORT,BMGN,,BMGN.IODF11.WORK,DATA05'
/*
//
```

Example 2.1:

The following example shows the JCL statements that may be specified in a data set allocated with DD name HCDCNTL for a JES3 system.

```
//BWINEX1 JOB (3259,7030-83),'BWIN',CLASS=A,NOTIFY=BWIN,
//            MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//*
//* JCL STATEMENTS SPECIFIED WITH DDNAME HCDCNTL
//*
//*ROUTE  XEQ  BOETST1
//BBMGNIM NJB (3259,7030-83),'BMGN',CLASS=A,
//            MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M,
//            USER=BMGN,PASSWORD=password
//OUT1    OUTPUT JESDS=ALL,DEFAULT=YES,DEST=BOEVS01.BWIN
//
```

Example 2.2:

The following example shows the JCL statements that may be specified in a data set allocated with DD name HCDCNTL for a JES2 system.

```
//BMGNIM  JOB (3259,7030-83),'BMGN',CLASS=A,
//            MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M,
//            USER=BMGN,PASSWORD=password
/*ROUTE  XEQ  BOETST1
//
```

Note: You can replace the /*ROUTE statement by the /*XMIT statement.

```
/*XMIT XEQ BOETST1 DLM=xx
```

When you use the DLM parameter with the /*XMIT statement, you specify a two-character delimiter to terminate the data being transmitted. (For the end of the records to be transmitted, the default is /* in the input stream.)

Batch IODF Copy Example

You may want to use the batch initialize and copy IODF functions when performing system maintenance. For example, these functions can be used when copying all the data sets from one volume (that contains IODFs) to another volume.

The following sample jobs show how to copy multiple IODFs to an alternate volume. In the example it is assumed that the following IODFs exist: SYS1.IODF00 and SYS1.IODF03. The first sample job allocates corresponding data sets on volume DATA02. The second sample job initializes these data sets into IODFs, and copies the source IODFs into the newly created IODFs. Jobs similar to these are contained in member CBDSALIO and CBDSCPIO in SYS1.SAMPLIB.

```
//* JOB TO DEFINE IODF
//DEFIODF JOB REGION=4M,...
//*
//* DEFINE NEW IODF DATASETS SYS2.IODF00, SYS2.IODF03
//*
//ALLOC    EXEC PGM=IDCAMS
```

```
//SYSPRINT DD   SYSOUT=*
//SYSIN    DD   *

     DEFINE CLUSTER (NAME (SYS2.IODF00.CLUSTER) -
                     LINEAR                     -
                     RECORDS (1024)             -
                     VOLUMES(DATA02)            -
                     )                          -
            DATA (NAME (SYS2.IODF00))

     DEFINE CLUSTER (NAME (SYS2.IODF03.CLUSTER) -
                     LINEAR                     -
                     RECORDS (1024)             -
                     VOLUMES(DATA02)            -
                     )                          -
            DATA (NAME (SYS2.IODF03))

//* JOB TO COPY IODF
//INITIODF JOB REGION=4M,...
//*
//* INITIALIZE AND COPY SYS1.IODF00 to SYS2.IODF00
//*
//INIT1    EXEC PGM=CBDMGHCP,PARM='INITIODF SIZE=1024,ACTLOG=NO'
//HCDCNTL  DD *
This IODF is a copy of SYS1.IODF00
/*
//HCDIODFT DD   DSN=SYS2.IODF00,DISP=OLD
//HCDMLOG  DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//*
//COPY1    EXEC PGM=CBDMGHCP,PARM='COPYIODF'
//HCDIODFS DD   DSN=SYS1.IODF00,DISP=SHR
//HCDIODFT DD   DSN=SYS2.IODF00,DISP=OLD
//HCDMLOG  DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//*
//* INITIALIZE AND COPY SYS1.IODF03 to SYS2.IODF03
//*
//INIT2    EXEC PGM=CBDMGHCP,PARM='INITIODF SIZE=1024,ACTLOG=NO'
//HCDCNTL  DD *
This IODF is a copy of SYS1.IODF03
/*
//HCDIODFT DD   DSN=SYS2.IODF03,DISP=OLD
//HCDMLOG  DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//*
//COPY2    EXEC PGM=CBDMGHCP,PARM='COPYIODF'
//HCDIODFS DD   DSN=SYS1.IODF03,DISP=SHR
//HCDIODFT DD   DSN=SYS2.IODF03,DISP=OLD
//HCDMLOG  DD   SYSOUT=*,DCB=(RECFM=FBA,LRECL=133,BLKSIZE=6650)
//
```

Notes:

1. This batch job issues job message IEC161I, which can be ignored.
2. The VSAM DIV file consists of a data and a cluster file. According to the naming convention, the name of the data file is the IODF name (in this example SYS1.IODF01), and .CLUSTER is appended to the data file for a cluster file. Append .CLUSTER to the IODF name in the DEFINE CLUSTER statement (in this example SYS1.IODF01.CLUSTER).

When designating the number of records to be allocated in an IODF (specified on the DEFINE CLUSTER statement and as a PARM value on the INITIODF job step), it is important that the target IODF be allocated at least as big as the source IODF. While using the HCD dialog, you can use the SHOWIODF command from the command line, or the View action bar choice to display the number of records allocated in the source IODF.

Note: Remember to also copy the associated LOADxx members. For information on the LOADxx members, see *z/OS MVS Initialization and Tuning Reference* and *z/OS MVS Initialization and Tuning Guide*.

List of Standard DD Names

Standard DD names are used in the job control statements that define the data sets used by HCD. These names are shown in Figure 106 on page 313. If you want to change these names, you must create a list of alternate DD names, using the standard format for such a list.

	DD name	HCD Task	Data Set Contents
1	not used		
2	not used		
3	not used		
4	HCDLIB	Migration	Assembler macro library
5	HCDIN	Migration	Migration input
6	HCDPRINT	Migration	Migration log (messages)
7	not used		
8	HCDUT1	Migration	Assembler work file
9	HCDUT2	Migration Activity Log	Modified IOCP, MVSCP, and HCPRIO input to assembler Target activity log during copy
10	HCDUT3	Migration	Assembler output (object) data
11	not used		
12	HCDTERM	Migration	Assembler and loader messages
13	not used		
14	not used		
15	not used		
16	not used		
17	HCDRPT	Query/print	HCD reports
18	HCDALOG	All	Activity log
19	HCDJES3	All	JES3 initialization stream checker data
20	HCDASMP	Migration	Assembler output listing
21	HCDDECK	Activation	IOCP and HCPRIO input data set (output)
22	HCDIODFP	All	First IODF
23	HCDIODFS	Maintain IODF	Source IODF (for COPY, for example)
24	HCDIODFT	Maintain IODF	Target IODF
25	HCDPROF	Tailor HCD defaults	HCD profile definitions
26	HCDMLOG	All	Message log
27	HCDTRACE	All	Trace data set (if trace is activated)
28	HCDCNTL	Activation Maintain IODF	Control file for Build IOCDS Control file for Build IOCP input data set JCL data set for Import/Export IODF IODF description List of configurations for Build I/O Configuration Statements

Figure 106. Standard DD names Used by HCD

List of Alternate DD Names

If used, this optional list, must start on a halfword boundary that is not also a fullword boundary.

- The first two bytes must contain a binary count of the number of bytes in the rest of the list.
- The rest of the list specifies alternate DD names that you wish to use in place of the standard DD names.
  - DD names in the alternate list must appear in the same sequence as they appear in the standard list.
  - Each name must be eight characters long. If a name contains fewer than eight characters, pad it with blanks. If you omit an alternate DD name, set that entry in the alternate DD names list to binary 0.
  - Entries in the alternate DD names list that correspond to empty entries in the standard DD names list must be set to binary 0.

End of Programming Interface information

Chapter 13. Security and Other Considerations

Overview

This chapter contains:

- Security-related considerations
- Catalog-related considerations
- Considerations concerning data sets cataloged with an esoteric device group name
- SMS-related considerations
- ISPF and TSO/E aspects that you need to consider
- VM-related considerations

Various additional information on topics that directly relate to HCD, but are not part of the actual definition process, is contained in this chapter.

Security-Related Considerations

An appropriate resource-level security facility, such as Resource Access Control Facility (RACF*) 1.9 or an equivalent security product, is required to control access to the data sets used by HCD. You perform the access control in two steps:

1. Define the necessary RACF profiles
2. Give users access authority

Note: If no security product is installed, you cannot perform the ***activate*** function from HCD.

For additional RACF definitions necessary to run the HCD LDAP Backend against IODF data, see Chapter 14, "LDAP Support" on page 325.

Defining RACF Profiles

You define three types of profiles:

1. Data Set Profiles

   Define data set profiles for all data sets used by HCD.

2. OPERCMDS Class Profile:

   Define the profile MVS.ACTIVATE to invoke the dynamic reconfiguration function under HCD or to use the MVS operator command ACTIVATE from an MVS console. (For a description of the command syntax, see *z/OS MVS System Commands*.)

   If you issue the ACTIVATE command, the I/O supervisor calls jobname IEASYSAS stepname IOSAS to assist in the activate procedure. IOSAS requires read access to the IODF data sets. Because the default entry for IOSAS in the Program Properties Table (PPT) is PASS, RACF checking occurs. ICH408I is the result of an ACTIVATE IODF=XX command. To ensure the successful completion of the activate process, you have to choose one of the following alternatives:

   - Place the IOSAS task into the RACF started task table (ICHRIN03) and indicate that the user is authorized.

© Copyright IBM Corp. 1994, 2002

- Define the IODF data sets to RACF with UACC=READ.
- Add IOSAS as an entry in the Started Procedures Table with a valid user ID. This user ID must have read access to the SYS1.NUCLEUS and the IODF data sets.

The ACTIVATE command needs UPDATE access, regardless whether the TEST option is specified or not.

You also have to define the profile MVS.DISPLAY.IOS with read access if you wish to work from the sysplex member list to view the active configuration status or to process a CONFIGxx member.

3. FACILITY Class Profiles:

   Define the following two profiles:
   - CBD.CPC.IPLPARM to query and update the IPLADDR and IPLPARM attribute values of the last IPL, and to be used for next IPL.
   - CBD.CPC.IOCDS to query and update IOCDS control information.

Giving Users Access Authority

The access authority you can give to a user depends on the profile.

Access to Data Set Profiles

You can give READ, UPDATE, or ALTER access to IODFs in general or to a specific IODF.

Access to Profile MVS.ACTIVATE

You can give UPDATE access to allow the user to activate a configuration change. You can give READ access if you want to restrict the ***activate*** function to the test option.

Access to Profile CBD.CPC.IPLPARM

NONE The user is not allowed to query or change the IPLADDR and IPLPARM attribute values. This is also the case if profile CBD.CPC.IOCDS is not defined or RACF is not installed,

READ Allows the user to query the IPLADDR and IPLPARM attribute values; however changing the IPLADDR and IPLPARM attribute values is not allowed.

UPDATE Allows the user to update the IPLADDR and IPLPARM attribute values.

Figure 107 on page 317 shows the relationship between HCD IPL attribute management functions and the CBD.CPC.IPLPARM access authority. Option 2.11 in the figure refers to option 2 on the primary selection panel and option 11 on the resulting panel.

Option	HCD IPL Attribute Management Functions	RACF Authority
2.11	List S/390 microprocessor cluster	READ (or READ authority in CBD.CPC.IOCDS)
2.11	View IPL attributes	READ
2.11	Update NEXT IPL attributes	UPDATE

Figure 107. CBD.CPC.IPLPARM Access Authority and HCD IPL Attribute Management Functions

Access to Profile CBD.CPC.IOCDS

If profile CBD.CPC.IOCDS is not defined or RACF is not installed, the local IOCDS functions (that is for processors with no SNA address specified) work as before, that is, the operator will be requested to approve the write-IOCDS request.

The new remote IOCDS functions (that is for processors with an SNA address specified) require RACF authorization.

NONE The user is not allowed to query or change IOCDS control information, or to write an IOCDS (neither by HCD nor IOCP).

READ Allows the user to query IOCDS control information. Changing IOCDS control information or writing an IOCDS is not allowed (neither by HCD nor IOCP).

UPDATE Allows the user to write IOCDSs (by HCD or IOCP), or to change and view IOCDS control information. If profile CBD.CPC.IOCDS is defined, then the operator will not be requested to approve the writing of an IOCDS. (That is, only users with update access to profile CBD.CPC.IOCDS are allowed to write an IOCDS.)

Figure 108 on page 318 shows the relationship between IOCDS management functions and the CBD.CPC.IOCDS access authority. The first column in the table refers to the options you have to select to get to the HCD functions, that is, you start with option 2 on the primary selection panel and select options 2, 6, or 11 on the resulting panel.

Option	HCD IOCDS Management Functions	RACF Authority
2.11	List S/390 microprocessor cluster	READ (or READ authority in CBD.CPC.IPLPARM)
2.11	View IOCDS control information	READ
2.11	Update IOCDS control information (switch IOCDS, enable or disable write protection)	UPDATE
2.2 or **2.6**	Build IOCDS (SNA address not defined for processor ***or*** batch IOCP job runs on SP 4.3 system)	UPDATE [1] or Profile not defined to RACF [2]
2.2 or **2.6** or **2.11**	Build IOCDS (SNA address defined for processor ***and*** batch IOCP job runs on SP 5.1 system)	UPDATE [1]
--	Direct invocation of IOCP	UPDATE [1] or Profile not defined to RACF [2]

[1] The build IOCDS function does not require authorization by the system operator, that is, no WTOR message is written.

[2] A WTOR message will be issued to the operator to authorize the build IOCDS function.

Figure 108. CBD.CPC.IOCDS Access Authority and HCD IOCDS Management Functions

For more information on security considerations for IOCDS management, refer to the *IOCP User's Guide*.

Providing Additional Security for Devices

If your system has stringent security requirements and includes Resource Access Control Facility (RACF), you can ensure that only certain programs can allocate unit record, communication, or graphics devices. These programs include Print Services Facility (PSF) for printers, Advanced Communication Facility/Virtual Telecommunications Access Method (ACF/VTAM) for communication or graphics devices, and JES2 or JES3 for unit record, communication, or graphics devices.

When a user attempts to allocate a device, the system uses SAF (the system authorization facility) to issue an authorization check. If RACF is installed, it checks a profile in the DEVICES class to determine whether the user can access the device. If the user does not have authority to access the device, the allocation fails. (Note that the system does not retry an allocation request that fails because the user is not authorized to access the device.)

Work with your RACF security administrator to set up profiles in the DEVICES class:

1. Determine your exact security requirements. Consider questions such as these:
   - Are there some devices that only a few users can use?
   - Are there some devices that all users can use?
   - Do some devices share the same security requirements?
2. Work with your RACF security administrator to assign profile names for the devices to be protected. Assign a discrete profile name to each device that has a

unique security requirement. Assign a generic profile name to each device group that shares security requirements. For devices, RACF profile names include the following information:

sysid Is the system identifier, which is defined on the SYSNAME keyword in the IEASYSxx member of SYS1.PARMLIB.

Note: The system identifier is necessary only if different devices with the same device class, unit name, and device address can be attached to multiple systems and they have different security requirements. In most cases, you should specify an asterisk (*) for this qualifier.

device-class
Is one of the following UCB device classes:

TP	Teleprocessing or communications devices
UR	Unit record devices
GRAPHIC	Graphic devices. These device classes are consistent with the class names used on the DISPLAY U operator command.

unit-name
Is a generic name (such as 3800) that identifies the device or devices.

For more details, see *z/OS Security Server RACF Security Administrator's Guide*.

Catalog Considerations

One IODF can contain configuration data mirroring multiple processor or logical partition system images, but being a VSAM data set, it can be cataloged in only one catalog. Therefore, if you wish to share an IODF data set among multiple systems and each system is using a separate master catalog, you must define (in the master catalog of each system) an alias that relates to the user catalog on the DASD that is shared among the systems. Define aliases and the user catalog *before* using HCD to define IODF data sets. Figure 109 on page 320 shows the recommended catalog structure.



Figure 109. Recommended IODF Catalog Structure. (When several OSs share one IODF)

Note: It is useful to catalog the IODF in a user catalog which resides on the same volume as the IODF. That way if the volume fails and must be restored, the catalog/IODF connection is always preserved across the restore. The catalog is used to reference the IODF during HCD definition activities and during dynamic I/O reconfiguration, *not* during IPL.

Data Sets Cataloged with an Esoteric Device Group Name

When using HCD, data sets that were previously cataloged with an esoteric device group name (for example, SYSDA) by use of the DEFINE NONVSAM, or IMPORT CONNECT command of the Integrated Catalog Facility, or the IEHPROGM utility, can cause unpredictable results if such a data set is accessed through the catalog. The reason is that the catalog entry contains the EDT-index pointing to the esoteric. The order of the esoteric in the EDT is no longer determined by the order in which the esoterics are defined, because HCD arranges the esoterics alphabetically.

To avoid this problem, you can do one of the following:

- Specify a token for the esoterics.

  The esoteric token will be used by allocation to find the appropriate esoteric for a data set that has been cataloged using the esoteric. You no longer have to maintain a chronological order and may delete and add esoterics without getting access problems for data sets that are cataloged using esoterics. Tokens for system built esoterics (for example, SYSALLDA) are generated by allocation and always have the same value (for SYSALLDA 9999 decimal, for example). You cannot control the token for system built esoterics. To circumvent the problem, define a new user esoteric with a token that corresponds to the EDT index in the catalog entry and that contains the same device list as SYSALLDA.

To get to the EDT index:
  - Use the LISTCAT command, or,
  - If you have your MVSCP deck, count the UNITNAME statements for esoterics up to the statement that defines the esoteric name to get to the number for the token.
- Re-catalog the data sets with a generic device type name (for example, 3380), before using HCD to migrate IOCP/MVSCP data.

To determine if you have any data sets that have been cataloged with an esoteric, use the scan utility that is provided in the SYS1.SAMPLIB member IEFESOJL. This utility scans a catalog and lists the data sets that were cataloged with esoteric device group names. The prologue of this SAMPLIB member contains information on the modifications you have to make to the JCL to run the job in your installation.

SMS-Related Considerations

In a system managed by Storage Management Subsystem (SMS) you have to make sure that either:

- The IODF data set name is not managed by SMS. You can then specify the IODF volume serial number when creating an IODF; or
- The Access Control System (ACS) routines are set up to automatically place the IODFs on the IODF volume. In this case the volume serial number is ignored.

Note: These considerations are important only for a production IODF that is used for IPL.

You also have to consider that HCD dynamically allocates some data sets (with fixed naming conventions). These data sets are:

- The data set used for the activity log. For more information see "Activity Logging" on page 62. If an ACTLOG data set does not yet exist, HCD dynamically allocates one, using ESOTERIC system defaults (ALLOCxx of SYS1.PARMLIB, respectively the UADS entry). You have to make sure that the entries in your ACS routines do not conflict with the SMS provided defaults. For example, if your ACTLOG data set name is *not* managed by SMS, whereas your default ESOTERIC defines an SMS managed volume, an allocation error might result. If you want to use a specific volume, specify a volume serial number to allocate a new activity log in the HCD profile (see "Defining an HCD Profile" on page 41).
- The data sets used by HCD for the migration of IOCP/MVSCP/HCPRIO data (HCDPRINT, HCDASMP, HCDUT1, HCDUT2, HCDUT3). For detailed information refer to "Insufficient Data Set Sizes" on page 280.
- The data sets used when building an HCPRIO or IOCP input data set (both named HCDDECK), and the data set used when creating JES3 Initialization Stream Checker data (named HCDJES3).

ISPF-Related Considerations

The usual ISPF facilities are available for the HCD dialog. For example, you can:

- Suppress the display of function key assignments.
- Display panel identifiers.
- Change the position of the command line.

HCD supports the ISPF split-screen facility with the F2=Split and F9=Swap keys. So, if necessary, you can perform other ISPF operations during an HCD session. HCD cannot be used in two parallel ISPF sessions.

Compared to traditional ISPF applications, HCD enables system programmers to control a great number of hardware configuration objects by their related actions.

VM-Related Considerations

HCD allows the definition of VM operating systems and their devices including their VM-specific parameters. This is triggered by the "operating system type - VM" when defining an operating system. Figure 110 shows the panel where you can enter the operating system type.

```
──────────────── Add Operating System Configuration ────────────────


 Specify or revise the following values.

 OS configuration ID  . . . . . OPSYS02_
 Operating system type  . . . . VM        +

 Description  . . . . . . . . . VM operating system

  F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
 F12=Cancel
```

Figure 110. Define a VM operating system

When you attach a device to a VM operating system, the Define Device Parameters / Features panel displays the operating system-specific parameters. See Figure 111 for an example of attaching a device to a VM operating system.

```
──────────────── Define Device Parameters / Features ─────────────────
                                                              Row 1 of 3

Specify or revise the values below.

Configuration ID . : OPSYS02      VM operating system
Device number  . . : 0100         Number of devices  : 1
Device type  . . . : 3370

Parameter/  Value  P Req.  Description
Feature
OFFLINE     No             Device considered online or offline at IPL
SHARED      ________       Device shared between multiple real systems
UIRATE      DEFAULT        Hot I/O Recovery Rate
```

Figure 111. Define Device Parameters/Features for VM Device

The VM specific functions of HCD consist of:

- Defining an operating system of type VM.
- Defining devices to a VM operating system.
- Defining VM consoles.

- Migrating an HCPRIO input data set to an IODF. For more details refer to Chapter 11, "How to Migrate Existing Input Data Sets" on page 239.
- Creating an HCPRIO input data set from a production IODF. See "Build an OS Configuration Data Set" on page 195 for a description how to create an HCPRIO input data set based on the definitions in the IODF.
- Issuing VM device reports (including VM console report).

In a mixed environment, running an MVS-type system in one partition and VM in another partition, any change of the VM definitions (for example, add a device) can be done without POR the processor. The ***Dynamic I/O Reconfiguration*** function for the hardware can be used to add this device to the Channel Subsystem (CSS). In a second step (prior to VM/ESA Version 1 Release 2), you have to build a new nucleus, and then the VM partition has to be IPLed using the HCPRIO input data set you recently created, unless the new device has been "over-generated" in the present NUCLEUS. Starting with VM/ESA Version 1 Release 2, a device can be set online dynamically. You do not have to IPL the VM system image. For more details refer to *VM/ESA Planning and Administration*

If you are running an MVS-type system and VM on separate processors, you can configure your VM/ESA system with HCD, and produce IOCP and HCPRIO input data sets, which can be used on the VM system.

Chapter 14. LDAP Support

Overview

This chapter describes:
- LDAP structure
- HCD LDAP Backend structure
- Integrating the HCD LDAP Backend into the z/OS LDAP Server
- Customizing the HCD LDAP Backend
- Accessing the IODF information
- HCD LDAP Backend operational behavior
- Handling the LDAP requests as transactions

Before reading this section we strongly recommend you have a copy of *z/OS Security Server LDAP Server Administration and Use* and *z/OS SecureWay Security Server LDAP Client Programming* available to refer to.

Together with the z/OS Security Server LDAP Server and SDBM backend the HCD LDAP Backend can be used to access and update IODF data via the standardized Lightweight Directory Access Protocol (LDAP) based on TCP/IP.

The HCD LDAP Backend is optional. The HCD functionality is not limited if the HCD LDAP Backend is not used. If you do not want to use the HCD LDAP Backend, then you do not need to read this chapter and you do not need to take any further actions.

All operations on IODFs are performed on behalf of user IDs which have to be explicitly permitted for the HCD LDAP Backend. This does not affect your system security because the HCD LDAP Backend only supports LDAP clients who are bound to the SDBM backend using a user ID and the appropriate password.

The HCD LDAP Backend supports a subset of LDAP search requests and a subset of LDAP add, delete, and modify requests.

The HCD LDAP Backend is able to perform sequences of update requests as transactions. The LDAP client has to support LDAP V3 controls in order to use this transaction feature.

Updates to an IODF are performed via HCD. Thus, it is ensured that the HCD validation rules are applied.

Only existing IODFs can be used with the HCD LDAP Backend. The HCD LDAP Backend cannot be used to create or delete IODFs. It cannot be used, for example, to build a production IODF or perform dynamic activation.

© Copyright IBM Corp. 1994, 2002

Introduction to LDAP

The following is a brief introduction to the LDAP structure and function. For more information refer to *z/OS Security Server LDAP Server Administration and Use*.

LDAP is an Internet Protocol Standard based on the TCP/IP protocol. LDAP stands for Lightweight Directory Access Protocol.

LDAP is a protocol which makes directory information accessible. A directory can be considered to be a type of yellow pages. New entries can be added, existing entries can be altered or deleted, and it is possible to search for all matching entries using wildcards.

The LDAP directory is represented hierarchically in a so-called *Directory Information Tree* (DIT). The nodes of this tree are called *entries*. Every entry is an instance of an *object class*. An object class is a name which is associated with a collection of *attributes*.

Every attribute is either mandatory (required) or optional and either single valued or multi valued. Required attributes must have one or more values, optional attributes can have zero or more values. One required single valued attribute of every object class is `objectclass`: This attribute specifies the object class of which the entry is an instance.

Each entry has a *relative distinguished name* (RDN) which is specified when the entry is created. The RDN must identify the entry uniquely among its siblings (not necessarily in the whole tree); it consists of one or more attribute-value pairs. The *distinguished name* (DN) of an entry is the sequence of the RDNs starting from the entry itself and ending with the RDN of the root entry. The DN identifies a node uniquely within the whole DIT.

An example for a DN of a partition within a DIT for HCD IODFs would be the following:

```
hcdPartitionId=PART00,hcdProcessorConfigId=PROC00,
hcdIodfId=SYS1.IODF00,cn=localhost
```

This is illustrated in the following figure.



Figure 112. Sample DIT portion of the HCD LDAP Backend

An LDAP server program owns a DIT which can be accessed by a client via the LDAP protocol. In the case of the z/OS LDAP Server, the task of storing the DIT is delegated to several so-called *backends*. Each backend holds a certain subtree portion and is responsible for carrying out the client's requests on this portion. The DN of the root entry of a backend is called a *suffix*. When the z/OS LDAP Server receives a request concerning an entry it extracts the suffix from the DN of that entry in order to determine which backend is responsible for the request.

HCD supports the z/OS Security Server LDAP Server by providing a backend which makes IODFs accessible via the LDAP protocol.

HCD LDAP Backend: Structure and Mode of Operation

The HCD LDAP Backend is plugged into the z/OS LDAP Server like other backends (for instance SDBM). It is configured using the LDAP server configuration file (typically called `slapd.conf`).

The HCD LDAP Backend is similar to the RACF backend SDBM. As with SDBM, the main function of the HCD LDAP Backend is to mediate between the LDAP server and an external component, in this case HCD. HCD retains control over the IODFs; update requests are validated, processed, and the results stored by HCD in the appropriate IODF. Since it is HCD that processes the requests, updates through the z/OS LDAP Server preserve the integrity of the IODFs.

It follows from this, that the HCD portion of the DIT must reflect the data structure of HCD exactly. For this reason, rather strict rules (as compared to the DB2 backend RDBM) have to be observed when requesting an update of IODF data through the z/OS LDAP Server.

Access control to the HCD LDAP Backend is based on RACF permissions for user IDs, not (as is the usual practice) on LDAP Access Control Lists (ACLs). The HCD

LDAP Backend performs all services on behalf of a user ID. It accepts a service request only on condition that the associated user ID has previously been bound to (authenticated by) SDBM. If this condition is fulfilled, the HCD LDAP Backend switches to this user ID and tries to perform the request using only the RACF access rights granted to the user ID in question. In this way, access to IODFs through the LDAP interface and through the ISPF interface are both controlled by the same security mechanism. Note that this will have some consequences for the configuration of the z/OS LDAP Server.

The HCD LDAP Backend uses several instances of HCD to perform operations on IODFs. Each of these instances serves exactly one request at a time on behalf of a user ID. This strategy provides an easy method of handling the validation of modified configuration data and serialization of client requests. The HCD instances are managed according to the following principles:

1. After starting up, the HCD LDAP Backend opens a (configurable) minimum number of address spaces each of which contains exactly one HCD instance for handling requests.
2. When the HCD LDAP Backend receives a legitimate request on behalf of a user ID, it assigns this request to an HCD instance. This instance is then tied to the user in question, that is, all subsequent requests from this user will be routed to this same HCD instance.
3. If the number of available instances is not sufficient, the HCD LDAP Backend will open a new instance provided that a (configurable) maximum number of instances is not exceeded.
4. In order that instances tied to a user can be switched to another user after having been idle for a certain time, two (configurable) timeout values can be defined:
   - The lower value specifies the time after which an instance can be switched to a user who requests a service and has not yet been tied to an HCD instance.
   - The higher value specifies the time after which the connection between an HCD instance and a user is dissolved in any case.

   The lower value provides additional flexibility: As long as there is no need to switch to a new user, the current connection can be maintained until the second timeout is reached.

A special feature of the HCD LDAP Backend is that it supports transactions. A transaction is a sequence of requests which is only executed as a whole. If one of the individual requests fails, the whole transaction is not carried out. This provides additional protection against inconsistency of data. Note, however, that transactions are only supported in conjunction with LDAP V3, not with LDAP V2.

Integrating the HCD LDAP Backend into the z/OS LDAP Server

The HCD LDAP Backend performs its services on behalf of user IDs and uses only the RACF access rights of these user IDs to determine the legitimicy of a request. This presupposes that the backend runs under a user ID which is entitled to switch to the user ID of the respective bind request. Since the backend takes as its user ID that of the z/OS LDAP Server, the HCD LDAP Backend can only be plugged into the z/OS LDAP Server, if the latter runs as a started task under a user ID which is permitted to switch to another user ID. For more details on this switch, see the section "Threads and Security" of the *z/OS UNIX System Services Planning* book.

The further setup depends on which security level you choose for the LDAP server. There are two options:

- UNIX security
- z/OS UNIX security

With UNIX security, the z/OS LDAP Server must run under the superuser. The superuser has on this security level total authority over the system; in particular, he is automatically entitled to assume the identity of any other user. With z/OS UNIX security on the other hand, the right to switch user IDs must be explicitly granted, even to the superuser.

z/OS UNIX security is more secure than UNIX security, and we recommend that you choose this option. However, you must be aware that this is a global decision which may have consequences for every server on your system. For this reason, the steps required for both options are described below in detail. Warnings are issued whenever a step has repercussions for your system configuration.

For both options you must issue a number of RACF commands. In the example commands shown in the following descriptions, typical assumptions about the system configuration have been made. As these do not necessarily conform with your particular system configuration, you may need to modify the commands as required.

If you have already been using the z/OS LDAP Server and are adding the HCD LDAP Backend, check whether your setup conforms to the requirements of the HCD LDAP Backend. If it does not (for instance, you are not running the LDAP server as a started task), then you must change your setup.

Performing the Setup

We suggest that you divide the setup process into two parts. The first part consists of setting up the LDAP server so that it is able to run with the HCD LDAP Backend. The second part consists of setting up the HCD LDAP Backend.

Setting Up the LDAP server

This section describes how to set up the z/OS LDAP Server so that it can run with the HCD LDAP Backend. There is a sample REXX procedure CBDSLCLS in SYS1.SAMPLIB that contains the RACF commands listed in this section for the z/OS UNIX security level.

To set up the z/OS LDAP Server, perform the following steps:

1. *Define the user ID under which the LDAP server runs*. This first step depends on the security level you have chosen:
   - **z/OS UNIX security**. In this case, you may specify any free UID for the user ID of the z/OS LDAP Server. Issue the following RACF command:

     ```
     ADDUSER LDAPSRV DFLTGRP(OMVSGRP) OMVS(UID(i) HOME('/u/ldapsrv')
     PROGRAM('/bin/sh')) NOPASSWORD
     ```

     Here *i* is an arbitrary free UID.
   - **UNIX security**. On this security level you must define the user ID of the z/OS LDAP Server as a superuser. Issue the following:

     ```
     ADDUSER LDAPSRV DFLTGRP(OMVSGRP) OMVS(UID(0) HOME('/u/ldapsrv')
     PROGRAM('/bin/sh')) NOPASSWORD
     ```

   This example command is based on the following assumptions (which may not hold for your system!):

a. The user ID of the LDAP server is `LDAPSRV`.
b. There exists a group `OMVSGRP`.
c. There exists an HFS directory `/u/ldapsrv`.

2. *Create a started task procedure*. For this first part of the setup process, just tailor the sample procedure which is shipped with the z/OS LDAP Server. In the second part (see "Setting Up the HCD LDAP Backend" on page 332), you will have to make some further additions to it.
3. *Connect the user ID to the started task procedure by adding the started task to the RACF class STARTED*. Issue:

   ```
   RDEFINE STARTED LDAPSRV.* STDATA(USER(LDAPSRV) TRUSTED(NO))
   ```

   This example command is based on the following assumptions (which may not hold for your system!):
   a. The RACF class STARTED has been activated.
   b. GENERIC is enabled for the RACF class STARTED.
   c. There is no profile in that class with the name `LDAPSRV.*`.
   d. The cataloged procedure for the task is named `LDAPSRV`.
4. *Define SDBM for LDAP*. The HCD LDAP Backend requires the z/OS LDAP Server to run with the RACF backend. Therefore, SDBM must be included in the configuration file. In the second part of the setup process (see "Setting Up the HCD LDAP Backend" on page 332) you will have to make further additions to the configuration file.

Up to this point the setup of the z/OS LDAP Server for z/OS UNIX Security and the setup for UNIX security run in parallel. The setup of the LDAP server for UNIX security is completed with step 4; the steps 5 through 7 on page 331 only apply to z/OS UNIX security. If you have chosen UNIX security, continue with step 8 on page 331.

5. *Define libraries to program control*. Under z/OS UNIX security, every program that is loaded into a server address space must be marked as controlled (see section "Defining Modules to Program Control" of the *z/OS UNIX System Services Planning* book).

   When using the HCD LDAP Backend, the libraries containing the following load modules must be defined to program control:

Load Modules	**Typical Library**
HCD LDAP Backend	SYS1.LINKLIB on SYSRES
HCD	SYS1.LINKLIB on SYSRES
UIMs	SYS1.NUCLEUS on SYSRES
C++ RTL	CEE.SCEERUN on SYSRES
z/OS LDAP Server	SYS1.SGLDLNK *and* SYS1.LPALIB on SYSRES

Figure 113. Load Module Libraries

   Note that if you use load modules from other libraries you have to define these libraries to program control as well.

   To define these libraries to program control, issue the following RACF commands:

   ```
   RDEFINE PROGRAM ** UACC(READ)
   RALTER PROGRAM ** UACC(READ) ADDMEM('SYS1.LINKLIB'/'******'/NOPADCHK)
   RALTER PROGRAM ** UACC(READ) ADDMEM('SYS1.NUCLEUS'/'******'/NOPADCHK)
   ```

```
RALTER PROGRAM ** UACC(READ) ADDMEM('CEE.SCEERUN'/'******'/NOPADCHK)
RALTER PROGRAM ** UACC(READ) ADDMEM('SYS1.SGLDLNK'/'******'/NOPADCHK)
RALTER PROGRAM ** UACC(READ) ADDMEM('SYS1.LPALIB'/'******'/NOPADCHK)
SETROPTS WHEN(PROGRAM) REFRESH
```

The first command defines a profile named ** to the class PROGRAM. The other commands, except the last, define the libraries containing the load modules to program control. The last command refreshes the in-storage copy of the PROGRAM profiles.

The example commands are based on the following assumptions (which may not hold for your system!):

a. The RACF class PROGRAM has been activated.
b. GENERIC is enabled for the RACF class PROGRAM.
c. There is no profile in that class with the name **.
d. The load modules needed reside in their typical libraries as listed above.

Warning!
Changing profiles in RACF class PROGRAM can cause severe system problems if not done in a manner suitable for the system. If you are unsure ask your RACF administrator.

6. *Define BPX.SERVER*. By defining BPX.SERVER you switch to z/OS UNIX security. Issue the following RACF commands (the second command updates the in-storage copy of the FACILITY profiles):

```
RDEFINE FACILITY BPX.SERVER UACC(NONE)
SETROPTS RACLIST(FACILITY) REFRESH
```

The example commands are based on the following assumptions (which may not hold for your system!):

a. The RACF class FACILITY has been activated.
b. There is no profile in that class with the name `BPX.SERVER`.

Warning!
Defining a profile named BPX.SERVER in the RACF class FACILITY switches system security from UNIX security to z/OS UNIX security. Other applications may be affected by this switch.

7. *Give the user ID under which the LDAP server runs access to BPX.SERVER*. In order to enable the user ID to perform server functions it must be given access to BPX.SERVER. Issue the following commands (the second command updates the in-storage copy of the FACILITY profiles):

```
PERMIT BPX.SERVER CLASS(FACILITY) ID(LDAPSRV) ACCESS(UPDATE)
SETROPTS RACLIST(FACILITY) REFRESH
```

Note that the access must be `UPDATE`.

The example commands are based on the following assumption (which may not hold for your system!):

The user ID of the LDAP server is `LDAPSRV`.

8. *Run the z/OS LDAP Server*. Check whether the RACF backend (SDBM) is working correctly by issuing an LDAP request against SDBM. You can use the LDAP operation utilities to do this. For this purpose, enter a command according to the following template:

```
ldapsearch -h ldaphost -p ldapport -D binddn -w passwd
-b "racfid=UserID,profiletype=user,sysplex=name" "objectclass=*"
```

See *z/OS Security Server LDAP Server Administration and Use* for more information on LDAP operation utilities and SDBM.

If the request returns a plausible result, SDBM is working correctly.

Setting Up the HCD LDAP Backend

This section describes how to set up the HCD LDAP Backend. There is a sample REXX procedure CBDSLCUS in SYS1.SAMPLIB that contains the RACF commands listed in this section for the z/OS UNIX security level.

To set up the HCD LDAP Backend, perform the following steps:

The first step is only required for z/OS UNIX security. If you have chosen UNIX security, continue with step 2.

1. *Authorize the HCD LDAP Backend to act on behalf of other user IDs*. With UNIX security the LDAP server runs under a superuser (with UID 0) who is permitted to act on behalf of any user ID. Under z/OS UNIX security, the HCD LDAP Backend (which receives no password from the z/OS LDAP Server) can only perform a service for a client user ID when it has been explicitly authorized to act on behalf of that user ID (see the section "Defining Servers to Process Users without Password" of *z/OS UNIX System Services Planning*).

   In order to authorize the user ID of the server to act on behalf of another user ID, you must do the following:

   a. Define a surrogate profile for the prospective client by issuing the following RACF commands (the second command updates the in-storage copy of the SURROGAT profiles):

      ```
      RDEFINE SURROGAT BPX.SRV.userID UACC(NONE)
      SETROPTS RACLIST(SURROGAT) REFRESH
      ```

   b. Authorize the user ID of the LDAP server for this profile by the following commands (the second command updates the in-storage copy of the SURROGAT profiles):

      ```
      PERMIT BPX.SRV.userID CLASS(SURROGAT) ID(LDAPSRV) ACCESS(READ)
      SETROPTS RACLIST(SURROGAT) REFRESH
      ```

   These example commands are based on the following assumptions (which may not hold for your system!):

   a. The RACF class SURROGAT has been activated.
   b. There is no profile in that class with the name `BPX.SRV.`*`userID`*, where *`userID`* is the user ID of the prospective client.
   c. The user ID of the LDAP server is `LDAPSRV`.

The following steps apply to both security levels.

2. *Tailor the started task procedure*. This includes:

   - You have to ensure that the POSIX runtime environment is active for the started task; you can do this by adding `POSIX(ON)` to the runtime options PARM string. For the EXEC statement of the sample procedure shipped with the z/OS LDAP Server, the result of this addition would look as follows:

     ```
     //GO  EXEC PGM=GLDSLAPD,REGION=&REGSIZE,TIME=1440,
     //    PARM=('POSIX(ON)/&PARMS >DD:SLAPDOUT 2>&1')
     ```

- The HCD instances that have been started by the HCD LDAP Backend have the same region size as the LDAP server started task. So, you may need to adjust the region size of the LDAP server started task according to the region size suitable for the HCD instances.
- You have to ensure that the z/OS LDAP Server and the HCD LDAP Backend are able to find the load modules in Figure 113 on page 330 by using the z/OS search order. If the libraries containing these load modules are not searched by z/OS on your system, you must insert a `STEPLIB DD`, which contains the missing libraries, into the started task procedure.

3. *Tailor the z/OS LDAP Server configuration file*. You must include the definition of the HCD LDAP Backend in the configuration file `slapd.conf`. A sample is provided in `/usr/lpp/hcd/examples/slapd.conf`. For this purpose you must do the following (the examples are taken from the sample file):
   - Include options for the HCD schema files `schema.hcd.at` and `schema.hcd.oc` (in that sequence) directly after the `include` statements for the z/OS LDAP Server and the SDBM (RACF) backend. These could look as follows:

     ```
     include /usr/lpp/hcd/etc/schema.hcd.at
     include /usr/lpp/hcd/etc/schema.hcd.oc
     ```

     You must not modify the schema files `schema.hcd.at` and `schema.hcd.oc` themselves. They should be included directly from the installation location. This is usually `/usr/lpp/hcd/etc`.

     Note: The schema files will not create any DB2 tables if used together with the RDBM backend. Hence, the object classes and attributes defined within the HCD schema cannot be used in the RDBM backend.
   - Insert a database option to declare the HCD LDAP Backend as follows:

     ```
     database hcd CBDMLBCK
     ```
   - Insert a suffix line in the HCD LDAP Backend database section; the suffix must not be used for any other backend. For example:

     ```
     suffix "cn=localhost"
     ```
   - Customize the HCD LDAP Backend. The options that are recognized by the HCD LDAP Backend are described in "Configuration File Parameters" on page 334. The following would be acceptable values:

     ```
     MinHcdInstances          1
     MaxHcdInstances          3
     AllowSwitchTime          30
     ForceSwitchTime          600
     TransactionRollbackTime  3600
     Trace                    off
     Profile                  off
     TraceDsnSuffix           HCD.TRACE
     ProfileDsnSuffix         HCD.PROFILE
     TransformAttributeValues off
     ```
4. *Run the HCD LDAP Backend*. To verify that your setup is working issue an LDAP request against the HCD LDAP Backend. You can use the LDAP operation utilities to do this. For this purpose, enter a command according to the following template:

   ```
   ldapsearch -h ldaphost -p ldapport -D binddn -w passwd -s base
   -b "hcdIodfId=IodfName,suffix" "objectclass=*"
   ```

   This command performs a search on the specified IODF on behalf of the user ID specified by *binddn*. *binddn* must be a DN from within the SDBM name space representing a user ID, and *passwd* the appropriate password. *IodfName*

must be the name of an existing IODF dataset. *suffix* would be `cn=localhost` if you have kept the default value specified in the sample configuration file `slapd.conf`.

If the request returns a plausible result, the HCD LDAP Backend is working correctly.

Customizing the HCD LDAP Backend

The HCD LDAP Backend can be customized in the following ways:

- Parameters which are recognized by the HCD LDAP Backend can be set in the LDAP server's configuration file.
- LDAP debug levels can be set for the LDAP server and apply to the HCD LDAP Backend also.
- HCD LDAP Backend can be run in English or Japanese.

Configuration File Parameters

Configuration file parameters that apply to the HCD LDAP Backend are set in the database section of the HCD LDAP Backend in the LDAP server configuration file `slapd.conf`. Any parameter which is not known by the LAPD server itself is handed over to the HCD LDAP Backend. The following list shows the supported parameters:

MinHcdInstances *int*

Specifies the minimum number of HCD instances started during startup of the HCD LDAP Backend.

Default: `1`
Range: `1-10`
Constraints: Must be less than or equal to the numerical value of `MaxHcdInstances`

For example, `MinHcdInstances 1` causes the HCD LDAP Backend to start exactly one initial HCD instance.

MaxHcdInstances *int*

Specifies the maximum number of HCD instances which can be used simultaneously by the HCD LDAP Backend. The HCD LDAP Backend will start new HCD instances dynamically if they are needed and if the maximum number has not already been reached.

Default: `3`
Range: `1-10`
Constraints: Must be greater than or equal to the numerical value of `MinHcdInstances`

For example, `MaxHcdInstances 3` will allow the HCD LDAP Backend to use a maximum of three HCD instances simultaneously.

AllowSwitchTime *int*

Specifies the idle time in seconds after which the user ID of an HCD instance may be changed.

Default: `30`
Range: `1-120`
Constraints: Must be less than the numerical value of `ForceSwitchTime`.

For example, `AllowSwitchTime 30` will ensure that an HCD instance must be idle for at least thirty seconds before the HCD LDAP Backend is allowed to switch the HCD instance to a different user ID.

ForceSwitchTime *int*
Specifies the idle time in seconds after which the user ID of an HCD instance is unconditionally reset. If a new request on behalf of this user ID arrives, this or any other free HCD instance has to be switched to that user ID.
Default: `600`
Range: `60-3600`
Constraints: Must be greater than the numerical value of `AllowSwitchTime`.
Exception: If the value specified for `ForceSwitchTime` is `0`, a forced reset of the user ID will not be performed.

For example, `ForceSwitchTime 600` will ensure that the user ID of an HCD instance is reset by the HCD LDAP Backend after an idle time of 600 seconds (10 minutes) of the HCD instance

TransactionRollbackTime *int*
Specifies the idle time (in seconds) of an LDAP client after which a transaction, running on behalf of this LDAP client is rolled back automatically.
Default: `3600`
Range: `10-3600`

For example, `TransactionRollbackTime 3600` will ensure that the HCD LDAP Backend automatically rolls back a transaction which is still open on behalf of an LDAP client which has been idle for 3600 seconds (one hour).

Trace on|off Determines whether the HCD instance running on behalf of the HCD LDAP Backend generates an HCD trace (see "HCD Trace Facility" on page 434). Each HCD instance generates its own trace.
Default: `off`

TraceDsnSuffix *name*
Specifies the suffix of the dataset names where the traces of the HCD instances are to be written to. The effective name of the trace dataset of one particular HCD instance is determined by concatenating the user ID associated with the HCD instance with the suffix.
Default: `HCD.TRACE`
Constraints: Only valid dataset names with a maximum of 35 characters can be used. Note that the suffix must not be empty.

For example, assume you have set the `TraceDsnSuffix` to `LDAP.HCD.TRACE` and that you have specified `Trace on`. If an HCD instance now performs an LDAP request on behalf of user ID `TEST` and is, therefore, switched to this user ID, it will open the trace dataset with name `'TEST.LDAP.HCD.TRACE'` and `DISP=OLD`. This dataset is then used for tracing the operations of the HCD instance.

Profile on|off Determines whether the HCD instances running on behalf of the HCD LDAP Backend will use an HCD profile on startup or user

ID switch (see "Defining an HCD Profile" on page 41). Each HCD instance uses its own profile, depending on the user ID which the HCD instance is currently related to.
Default: `off`

ProfileDsnSuffix *name*
Specifies the suffix of the profile dataset name used by the HCD instances. The effective name of the profile dataset of one particular HCD instance is determined by concatenating the user ID associated with the HCD instance with the suffix.
Default: `HCD.PROFILE`
Constraints: Only valid dataset names with a maximum of 35 characters can be used. Note that the suffix must not be empty.

For example, assume you have set `ProfileDsnSuffix` to `LDAP.HCD.PROFILE` and you have specified `Profile on`, If an HCD instance now performs an LDAP request on behalf of user ID `TEST` and is thus switched to this user ID, it will open the profile dataset with name `'TEST.LDAP.HCD.PROFILE'` and `DISP=SHR`. The contents of the dataset will be read and the HCD instance will be set up accordingly.

TransformAttributeValues on|off
Specifies whether the values of the attributes `hcdIodfDescription` and `hcdDescription` are interpreted as being in IBM-939 or not. In general, these values are interpreted as being in IBM-037. It is important to have the correct setting because the z/OS LDAP Server communicates with LDAP clients using UTF-8 representation and the HCD LDAP Backend has to convert attribute values appropriately.
Default:
`off`

LDAP Debug Level

For a description of the debug levels see "LDAP Problem Determination" on page 441.

Message Translation

The HCD LDAP Backend supports English and Japanese messages. To obtain English messages with the character representation IBM-1047, choose one of the following values for the environment variable `LANG`:

- `C`
- `En_US`
- `En_US.IBM-1047`

To obtain Japanese messages with the character representation IBM-939, choose one of the following values for the environment variable `LANG`:

- `Ja_Jp`
- `Ja_Jp.IBM-939`

For the values of `LANG` supported by the z/OS LDAP Server and for more information on how to specify the value of `LANG`, see the *z/OS Security Server LDAP Server Administration and Use*.

Note: The settings of the environment variable `LANG` do not control the language of the HCD messages which HCD LDAP Backend returns to LDAP clients upon their requests. In fact, all HCD messages returned to LDAP clients will always be in English.

Accessing IODF Information

The HCD LDAP backend provides access to IODF information via the LDAP protocol. You can, for instance, add or delete devices and control units, or modify operation system settings. It is also possible to automate complex updates, for instance a whole I/O configuration, by communicating with the z/OS LDAP Server through an application (see *z/OS SecureWay Security Server LDAP Client Programming*).

The IODF Directory Information Tree

In order to make HCD IODF information accessible via the LDAP protocol, the HCD LDAP Backend realizes a one-to-one mapping between the IODF data structure and the structure of the LDAP directory information tree (DIT). It is this one-to-one mapping that makes the update of IODFs through the z/OS LDAP Server possible.

The resulting HCD portion of the DIT has some special constraints as compared to an all purpose backend like RDBM:

- One important difference between the HCD portion and RDBM concerns the relation between object class and position in the (sub)tree. In RDBM, every object class can occur on every position. The HCD subtree, on the other hand, must correspond to the structure of the IODF. Accordingly, the object class of every entry managed by the HCD LDAP Backend uniquely determines the object class of its parent entry.

  Note, however, that this parent relation cannot be understood as in object oriented programming: Thus the object class `hcdPartition` has as its parent the object class `hcdProcessorConfig`, but `hcdPartition` is certainly not derived from `hcdProcessorConfig`.
- In addition, there are a number of HCD specific dependencies between entries that reside on different branches of the HCD subtree. In some cases, the HCD LDAP Backend takes these dependencies into account by automatically adding or deleting certain entries when certain other entries are added or deleted. In other cases you must ensure yourself that your request conforms with these interrelationships. For details, see "Restrictions for Search and Update Requests" on page 339 and Appendix F, "IODF Data Model" on page 475.
- The schema of the HCD portion of the DIT is fixed. It cannot be extended or modified.

The object classes required for the IODF DIT and their interrelationships (parent relation and branch crossing interrelationships) are described in Appendix F, "IODF Data Model" on page 475. This appendix also contains descriptions of all the attributes that are needed for these object classes.

Performing LDAP Requests on IODFs

In order to request a service from the HCD LDAP Backend you must always perform two steps:

1. *Authenticate yourself to the RACF Backend*. For authentication, you have to specify a so-called *bind* DN and a password. The authentication (called *binding* in LDAP terminology) is successful when the bind DN identifies an entry of the

backend to which the suffix of the bind DN is assigned, and when the specified password is in fact associated with this entry. The HCD LDAP Backend does not perform this identity check itself, but uses the RACF Backend (SDBM) for that purpose. Thus, you must specify a user ID in the bind DN, and the bind DN must have the following structure:

```
"racfid=user_ID,profileType=user,sysplex=Your_Sysplex,..."
```

Here `sysplex=Your Sysplex` is the first element of the suffix. Note that `group` is not allowed as the value of the `profileType` attribute.

If the binding to the RACF Backend fails, the HCD LDAP Backend will not support the subsequent requests.

2. *Access an IODF*. If you want to access an IODF with the dataset name `IodfDsn`, the DN in your LDAP request must have the following form:

```
"...,hcdIodfId=IodfDsn,suffix_of_HCD_LDAP_Backend"
```

Note that only IODFs that can be reached by the z/OS LDAP Server are accessible with the HCD LDAP Backend.

If you have issued your request as described, the HCD LDAP Backend will take the following actions:

- The user ID is extracted from the initial bind request.
- The IODF dataset name is extracted from the LDAP request.
- A prepared address space is switched to the user ID, and HCD is started.
- HCD loads the specified IODF and performs the requested operations.
- The results are sent back to you.

Operational Behavior

The operational behavior of the HCD LDAP Backend is basically the same as that for the RACF backend with some small differences. Information about the RACF Backend can be obtained from the *z/OS Security Server LDAP Server Administration and Use*.

The following gives an overview of the functional behavior of the HCD LDAP Backend:

1. The HCD LDAP Backend does not participate in extended group membership searching on a client request.
2. It is possible to run several HCD LDAP Backends on one z/OS LDAP Server simultaneously.
3. The root of a subtree (see Figure 112 on page 327) is denoted by a suffix in the LDAP server configuration file. It is only possible to specify one suffix per HCD LDAP Backend.
4. The HCD LDAP Backend does not support Access Control Lists (ACLs) which are normally used to protect information stored in an LDAP directory from unauthorized access. The reason for this is that the DIT portions managed by the HCD LDAP Backend are based on IODF datasets for which all access control is performed by RACF.
5. The HCD LDAP Backend does not support the following LDAP request types and will answer these requests with the return code "Unwilling to Perform":
   - Bind
   - ModifyDN (also called ModifyRDN, or ModRdn)
   - Compare

- Abandon
- Extended Request

6. The following LDAP request types are supported by the HCD LDAP Backend:
   - Add
   - Delete
   - Modify
   - Search

   The following table shows how the HCD LDAP backend behaves during these LDAP operations:

Target DN	Search	Add	Delete	Modify
suffix	Error: Inappropriate Matching	Error: Inappropriate Matching	Error: Inappropriate Matching	Error: Inappropriate Matching
hcdIodfId= *IodfDsn,suffix*	Perform the appropriate search. See "Search"	Error: Inappropriate Matching	Error: Inappropriate Matching	Perform the appropriate modify. See "Modify" on page 341
...,hcdIodfId= *IodfDsn,suffix*	Perform the appropriate search. See "Search"	Perform the appropriate add. See "Add" on page 340	Perform the appropriate delete. See "Delete" on page 341	Perform the appropriate modify. See "Modify" on page 341

7. Multi-server or replication is not supported by the HCD LDAP Backend

Restrictions for Search and Update Requests

This section describes the restrictions which the HCD LDAP Backend imposes on the search, add, delete and modify capabilities of LDAP. Many of these restrictions derive from the fact that the structure of HCD portion of the DIT is much more rigidly controlled than, for instance, the RDBM subtree.

In the following subsections, `suffix` stands for the suffix of the HCD LDAP Backend.

Search

Searching is restricted as follows:

- Only search bases ending with `hcdIodfId=Iodf_dataset_name,suffix` are supported. This implies that only one IODF can be searched at a time.
- The only search filters that are supported by the HCD LDAP Backend are `objectclass=*` and `objectclass=name`, where `name` has to be the name of an object class that is defined for the HCD LDAP Backend.
- Time or size limits are not supported.
- Controls are not supported.
- It is not possible to restrict the attributes of the matching entries that will be displayed. Every attribute that has at least one value will be shown in the search results.

Examples:

Following are two examples for retrieving information from an existing IODF with the command line search utility of LDAP.

The command

```
ldapsearch -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-s base -b "hcdIodfId=TEST.IODF00.WORK,suffix" "objectclass=hcdIodf"
```

retrieves the top entry of object class `hcdIodf` belonging to the IODF named TEST.IODF00.WORK on behalf of user ID TEST. The result may look as follows:

```
hcdIodfId=TEST.IODF00.WORK,suffix
objectClass=hcdIodf
hcdIodfId=TEST.IODF00.WORK
hcdIodfType=W
hcdIodfDescription=Testing purposes
hcdBlocksAllocated=20
hcdBlocksUsed=2
hcdCreationDate=1999-10-04
hcdLastUpdateDate=1999-12-16
hcdLastUpdateTime=09:25:50
1 matches
```

The same result could be obtained with the search filter `"objectclass=*"`.

The command

```
ldapsearch -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-s one -b "hcdIodfId=TEST.IODF00.WORK,suffix" "objectclass=hcdDevice"
```

retrieves all entries of object class `hcdDevice` belonging to the IODF named TEST.IODF00.WORK, again on behalf of user ID TEST. One of the retrieved entries may look as follows:

```
hcdDeviceNumber=000D,hcdIodfId=TEST.IODF00.WORK,suffix
objectClass=hcdDevice
hcdDeviceNumber=000D
hcdUnit=2540P
hcdModel=1
hcdDescription=Virt. Puncher
```

Add

Adding an entry is restricted as follows:

- Entries can only be added below `hcdIodfId=...,suffix`, that is, add is not supported on DN `hcdIodfId=...,suffix` or DN *suffix*.
- Since every object class of the HCD LDAP Backend except `hcdIodf` has a uniquely determined parent class, ensure that the object class of the new entry and that of the entry to which the new entry is appended are related as child and parent. Exactly one value must be specified for the objectclass attribute. See Appendix F, “IODF Data Model” on page 475 for parent-child relationships between object classes.
- If the RDN of the entry to be added is `attribute=value`, `value` must be specified as a value of `attribute` inside the entry.
- The attributes which are contained in the entry’s RDN are determined by the object class of an entry. See Appendix F, “IODF Data Model” on page 475.
- There must be no entry in the DIT with the same DN as the entry to be added.
- If an add request fails because of a missing parent, the HCD LDAP Backend does not update the matched DN field of the result.
- Check Appendix F, “IODF Data Model” on page 475 to see which object classes can be added.
- Adding an entry may cause other entries to be created automatically using default values. See Appendix F, “IODF Data Model” on page 475.

- Two controls are supported for the LDAP add request. See "Transactions" on page 343 for details.

Example:

A new entry of the object class `hcdControlUnit` of type 3990 with a control unit number of 0100 can be appended to the entry `hcdIodfId=TEST.IODF00.WORK,`*`suffix`* as follows.

First create a dataset member named `TEST.LDIF(ADDCU100)` with the content

```
dn:hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix
changetype:add
objectclass:hcdControlUnit
hcdControlUnitNumber:0100
hcdUnit:3990
```

Then call the LDAP command line utility `ldapadd` with the following parameters:

```
ldapadd -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-f //'TEST.LDIF(ADDCU100)'
```

The entry will be added on behalf of the user ID `TEST`.

You can then verify that the entry was created correctly by issuing

```
ldapsearch -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-s base -b "hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix"
"objectclass=*"
```

The search result should look like:

```
hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix
objectClass=hcdControlUnit
hcdControlUnitNumber=0100
hcdUnit=3990
1 matches
```

Delete

Deleting an entry is restricted as follows:

- Only entries below DN `hcdIodfId=...,`*`suffix`* can be deleted. Delete on DN `hcdIodfId=...,` *`suffix`* or DN *`suffix`* is not supported.
- Check Appendix F, "IODF Data Model" on page 475 to see which object classes can be deleted.
- Deleting one entry may cause other entries to be deleted automatically. See Appendix F, "IODF Data Model" on page 475.
- Two controls are supported for the LDAP delete request. See "Transactions" on page 343 for details.

Example:

To delete the entry added in the example shown in "Add" on page 340 you can call the LDAP command line utility `ldapdelete` with the following parameters:

```
ldapdelete -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
"hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix"
```

The entry will be deleted on behalf of the user ID `TEST`.

Modify

Modifying an entry is restricted as follows:

- Only the entry DN `hcdIodfId=...,suffix` and below can be modified. Modification of DN *suffix* is not supported.
- Check Appendix F, "IODF Data Model" on page 475 to see which object classes can be modified.
- The HCD LDAP Backend only supports the delete and replace subcommands of modify. The add subcommand is NOT supported.
- The value of the `object class` attribute cannot be deleted or replaced.
- The value(s) of the attributes which are contained in the entry's RDN cannot be deleted or replaced.
- One modify request to a single entry can contain a sequence of delete and replace subcommands. This sequence can be considered as atomic: Either the whole sequence is performed or nothing is performed.
- One attribute can only be referenced once in the whole modify request. It can only be deleted once, replaced once, and only *either* be deleted *or* replaced.
- Modify delete only supports the deletion of all values of an attribute. For this reason, you must not specify values in the modify delete request. If a value is specified, the whole modify request is rejected by the HCD LDAP Backend.
- Attributes described as mandatory in an object class must not be deleted
- Modify replace replaces all existing values of the given attribute with the new values listed, creating the attribute if it did not already exist. A replace with no value will delete the entire attribute if it exists, and is ignored if the attribute did not exist.
- All values must conform with the type specified in the attribute definition.
- Modifying an entry may cause other entries to be modified automatically. See Appendix F, "IODF Data Model" on page 475.
- Two controls are supported for the LDAP modify request. See "Transactions" on page 343 for details.

Example:

The entry created in "Add" on page 340 can be modified by adding the attribute `hcdDescription` as follows.

First create a dataset member named `TEST.LDIF(REPCU100)` with the content

```
dn:hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix
changetype:modify
replace:x
hcdDescription:New description
```

Then call the LDAP command line utility `ldapmodify` with the following parameters:

```
ldapmodify -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-f //'TEST.LDIF(REPCU100)'
```

If the modify request completes successfully, the entry will look like:

```
hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix
objectClass=hcdControlUnit
hcdControlUnitNumber=0100
hcdUnit=3990
hcdDescription=New description
```

This `hcdDescription` can now be deleted again with the delete subrequest of modify. To do this, first create a dataset member named `TEST.LDIF(DELCU100)` with the content

```
dn:hcdControlUnitNumber=0100,hcdIodfId=TEST.IODF00.WORK,suffix
changetype:modify
delete:hcdDescription
-
```

Then issue the following command:

```
ldapmodify -D "racfid=TEST,profiletype=user,sysplex=sysplex1" -w "passwd"
-f //'TEST.LDIF(DELCU100)'
```

Transactions

Transactions is a concept in which individual LDAP requests are handled collectively as a single unit such that if one of the requests within the transaction should fail, then the whole transaction with all its requests is not carried out. In this way, you do not have a situation where some requests are performed and others are not. This may otherwise involve your having to undo individual requests of a logical sequence because one or more of the requests failed. Transactions can be helpful if you want to perform complex tasks which consist of LDAP request sequences. For example, if you want to define a coupling facility (which would require adding two entries of object class `hcdChannelPath`) you can perform the necessary LDAP requests within a transaction.

In general, arbitary sequences of at least two update requests (i.e. add, delete, modify) can be performed as a transaction. A transaction cannot consist of a single update request as a single request by definition behaves like a transaction.

Prerequisites and Method of Functioning

The LDAP client marks a request for the HCD LDAP Backend as being part of a transaction by specifying an LDAP V3 control for the request. For this reason, transactions in the HCD LDAP Backend can only be used with LDAP clients supporting LDAP V3 controls.

LDAP V3 controls represent additional information which can be included with a request to, or to a response from the LDAP server.

In order to use transactions offered by the HCD LDAP Backend, the following two LDAP V3 controls, both of which are supported by the HCD LDAP Backend, are required. Both controls must always be used with a valid value which determines how the HCD LDAP Backend will react to the control.

Examples of how to use these controls are shown on page 345

1. **hcdTransactionControl**:

   Name: hcdTransactionControl

   Description: This control is used on the first and last request of a transaction, to indicate either the start (via value NEW) and finish (via value COMMIT or ROLLBACK) of a transaction request sequence.

   Assigned Object Identifier: 1.3.18.0.2.10.3

   Target of Control: Server

   Control Criticality: Critical

   Values: Value is exactly one char 0 terminated string in UTF-8 encoding representing exactly one of the strings (words):

   ```
   NEW
   COMMIT
   ROLLBACK
   ```

These strings are not case sensitive. The following byte values (shown as two digit hexadecimal numbers) represent these strings:

```
Value      Byte sequence

NEW      = 4E 45 57 00
COMMIT   = 43 4F 4D 4D 49 54 00
ROLLBACK = 52 4F 4C 4C 42 41 43 4B 00
```

2. **hcdTransactionId**:

   Name: hcdTransactionId

   Description: This control is used on all requests of a transaction except the first request. The value of this control indicates which particular transaction a request belongs to.

   If an LDAP client initiates a new transaction with an appropriate request, the HCD LDAP Backend answers the request with an LDAP response containing control `hcdTransactionId`. The LDAP client has to extract this control's value from the response and must specify the value for `hcdTransactionId` on all following requests belonging to the transaction.

   Assigned Object Identifier: 1.3.18.0.2.10.4

   Target of Control: Server

   Control Criticality: Critical

   Values: Value is exactly one char 0 terminated string in UTF-8 encoding representing a non-negative, non-zero long int value in decimal format which is the transaction ID. Only values previously received from the HCD LDAP Backend are allowed - all others are rejected.
   Example: Assuming a transaction has an ID of 238. Then, the following byte values (shown as two digit hexadecimal numbers) represent the appropriate `hcdTransactionId` control value:

   ```
   32 33 38 00.
   ```

   The 10 decimal digits have the following character representation in UTF-8 (shown as two digit hexadecimal numbers):

   ```
   0 = 30, 1 = 31, 2 = 32, 3 = 33, ..., 9 = 39.
   ```

In order to perform a transaction containing a sequence of LDAP requests R_1, R_2, ..., R_n, the LDAP client has to do the following:

1. Send the LDAP requests R_1, R_2, ..., R_n of the transaction one after another to the LDAP server and wait for a response to each request before sending the next.
2. To initiate a new transaction (containing the requests R_1, R_2, ..., R_n) extend the first request R_1 with control `hcdTransactionControl` and specify `NEW` as value for this control. Control `hcdTransactionId` must not be used on the first request R_1. If the HCD LDAP Backend is able to open the new transaction, it will respond by returning the control `hcdTransactionControl` and the control `hcdTransactionId` with a transaction ID as *value*. In the case of failure neither controls will be returned.
3. Send all subsequent requests R_2, ..., R_n of the current transaction, with the control `hcdTransactionId` containing the valid transaction ID issued by the HCD LDAP Backend as a response to the first request R_1.
4. Commit (or if necessary rollback) the whole transaction using the control `hcdTransactionControl` and the *value* `COMMIT` (or `ROLLBACK`). This must be added to the last request (R_n) of the transaction. If, however, any request in between fails, you can use the `hcdTransactionControl` to initiate an immediate `ROLLBACK`. The control `hcdTransactionId` with the appropriate value must, of course, also be specified.

Note: Only update requests (i.e. add, delete and modify) can be part of a transaction.

All operations belonging to a transaction must act on the same IODF and must have been issued by the same LDAP client with the same LDAP handle bound to the same user ID.

The following section shows you how to initiate a transaction, to add further LDAP requests to a transaction and to close a transaction.

How is a Transaction Initiated and Closed?

To use the transaction facility, you have to:

- Set up and run the z/OS LDAP Server and the HCD LDAP Backend as described previously in this chapter.
- Provide an LDAP V3 client program which uses the appropriate controls of the HCD LDAP Backend.

Refer to *z/OS Security Server LDAP Server Administration and Use*, *z/OS SecureWay Security Server LDAP Client Programming*, and the IBM redbook *Understanding LDAP* for examples of LDAP client programs.

The following shows some examples of how to use the previously introduced controls on LDAP requests to take the following actions:

- Initiate a transaction
- Submit further transaction requests
- End a transaction

All the following examples written in C, are provided for the LDAP add request (here, we use the LDAP request `ldap_add_ext()` from the LDAP client API in C), but of course, the modify and delete request could also have been chosen for the examples.

Please note that you have to chose the version of the LDAP client API function which allows you to specify server controls. See the *z/OS SecureWay Security Server LDAP Client Programming* for more information on the functions themselves, as well as on the parameters which have to be passed for particular requests.

Example 1: Initiate a new transaction

A transaction is initiated using the `hcdTransactionControl` with `NEW` as value. This control can be defined the following way:

```
static LDAPControl hcdTransactionControl_new =
      {
          "1.3.18.0.2.10.3",  /* -- hcdTransactionControl -- */
          { 3, "\x4E\x45\x57\x00" }, /* -- NEW ------------- */
          LDAP_OPT_ON         /* -- critical --------------- */
      } ;
static LDAPControl *hcdTC_new[2] = {  &hcdTransactionControl_new, NULL };
```

Note, as mentioned before, the value NEW (and also the values COMMIT and ROLLBACK, shown in example 3) have to be specified using UTF-8 encoding.

All controls to be passed to the LDAP server are stored in an array. In this case, only one control is in the NULL-terminated array.

This array is now be passed to the function which sends the appropriate request to the LDAP server. For example, `ldap_add_ext()` is used to request an add operation as follows:

```
rc = ldap_add_ext( ld, dn, pmods, hcdTC_new, NULL, &msgidp);
```

Here, the control `hcdTC_new` is used where the *value* `NEW` was specified in UTF-8.

If this request was successful and if a new transaction was started, the HCD LDAP Backend sends back the control `hcdTransactionId` which contains the transaction ID. Such control looks like the following control which is provided only for demonstrational purposes (see also Example 2):

```
static LDAPControl hcdTransactionId =
       {
          "1.3.18.0.2.10.4",  /* -- hcdTransactionId ------ */
          { 1, "\x31\x00" },  /* -- TXN Id ---------------- */
          LDAP_OPT_ON         /* -- critical -------------- */
       };
static LDAPControl *hcdTC_Id[2] = { &hcdTransactionId, NULL };
```

In the above example, for the control `hcdTransactionId` the value indicates a transaction ID of 1.

Note, you should never generate a value for this control on your own. Instead, call the LDAP client API functions `ldap_result()` and `ldap_parse_result()` on the response of the first request to obtain the valid transaction ID.

After having issued `ldap_add_ext()`, calling `ldap_parse_result()` parses the results which were previously obtained by `ldap_result()`. Here, among other parameters, the LDAP control containing the transaction ID is provided.

The following code example demonstrates how to use both ldap requests:

```
rc = ldap_result(ld, msgidp, 0, NULL, &LDAP_TXN_Msg);
rc = ldap_parse_result(ld, LDAP_TXN_Msg, &errcodep, &matcheddnp,
                      &errmsgp, &referralsp, &servctrlsp, freeit);
```

The interesting parameter as far as controls are concerned is `servctrlsp`. This pointer locates an array such as `hcdTC_new`. The appropriate values of the control have to be copied into the `hcdTransactionId` control which can be done in the following way (assuming that `servctrlsp[0]` contains the `hcdTransactionId` control and the control `servctrlsp[0]` is not freed):

```
hcdTransactionId.ldctl_value.bv_val = (servctrlsp[0])->ldctl_value.bv_val;
hcdTransactionId.ldctl_value.bv_len = (servctrlsp[0])->ldctl_value.bv_len;
```

After these values have been copied, the correct transaction ID can be provided for further LDAP requests which are part of this transaction. This is shown in Example 2 below.

Example 2: Submit further LDAP requests of the transaction.

After a transaction was successfully initiated, further LDAP requests can be added to the transaction. Here, the user must provide an `hcdTransactionId` control where *value* contains the correct transaction ID. As stated before, this control is provided by the HCD LDAP Backend and must be used for further requests belonging to this specific transaction.

If we assume for demonstrational purposes, that, for the transaction we just initiated, the transaction ID number is 1, then, the control which was provided by the HCD LDAP Backend would be as follows:

```
static LDAPControl hcdTransactionId =
       {
          "1.3.18.0.2.10.4", /* -- hcdTransactionId ------ */
          { 1, "\x31\x00" }, /* -- TXN Id ---------------- */
          LDAP_OPT_ON        /* -- critical -------------- */
       };
static LDAPControl *hcdTC_Id[2] = { &hcdTransactionId, NULL };
```

In general, the values 1 and `"\x31\x00"` have to be replaced by the correct values of the control that is provided by the call of `ldap_parse_result()` (see example 1).

After the correct values for this transaction have been copied into the above control, further LDAP requests can be added to the transaction using this control. The call of such an LDAP requests is just the same as in example 1 with the only exception that the controls have been exchanged as follows:

```
rc = ldap_add_ext( ld, dn, pmods, hcdTC_Id, NULL, &msgidp);
```

As the transaction ID does not change for a specific transaction, all further requests belonging to this transaction must use the same `hcdTransactionId` control.

Example 3: End a transaction

Here, two different cases must be considered. As stated before, a transaction can be commited for execution, or it can be aborted by the user using a rollback request.

It is recommended that you explicitly rollback a transaction if a single LDAP request returns a bad return code. The reason for this is that, transactions are intended to represent logical units of requests which belong together. In principal, both the actions - commit and rollback - are the same from an implementational point of view. The only difference is, which control is to be specified for the LDAP request that finishes the transaction. If the user wants to commit a transaction, the following control must be defined:

```
static LDAPControl hcdTransactionControl_commit =
       {
          "1.3.18.0.2.10.3",    /* -- hcdTransactionControl -- */
          { 6, "\x43\x4F\x4D\x4D\x49\x54\x00" },/* - COMMIT -- */
          LDAP_OPT_ON           /* -- critical --------------- */
       };
static LDAPControl *hcdTC_commit[3] = { &hcdTransactionControl_commit,
                                        &hcdTransactionId, NULL };
```

If the user want to rollback a transaction, the following control must be defined:

```
static LDAPControl hcdTransaction_rollback =
       {
          "1.3.18.0.2.10.3",    /* -- hcdTransactionControl -- */
          { 8, "\x52\x4F\x4C\x4C\x42\x41\x43\x4B\x00" }, /*ROLLBACK*/
          LDAP_OPT_ON           /* -- critical --------------- */
       };
static LDAPControl *hcdTC_rollback[3] = { &hcdTransactionControl_rollback,
                                          &hcdTransactionId, NULL };
```

Using these controls, the final request will, in the case of commit, now be:

```
rc = ldap_add_ext(ld, dn, pmods, hcdTC_commit, NULL, &msgidp);
```

and in the case of a rollback:

```
rc=ldap_add_ext(ld, dn, pmods, hcdTC_rollback, NULL, &msgidp);
```

If you have a look at the previous definition of `hcdTC_commit` and `hcdTC_rollback`, both parameters are control arrays that contain the commit or rollback control itself, and which, in addition, contain also the control `hcdTC_Id` for submitting the next request. Hence, one control indicates the end of the transaction, and the other control identifies the transaction on the basis of its ID. Once a transaction is closed, no further requests can be added to this control.

Appendix A. Navigating Through the Dialog

This appendix illustrates the flow from the options on HCD primary task selection panel and the various actions that can be taken from each option. The panels that appear for option 1 have a Common User Access* (CUA*) action bar at the top and a context menu for each object. Figure 116 on page 350 shows the general action bar valid for the action list panels. Some action list panels offer special action bar choices that are not shown in the figure (for example the ***Show/Hide*** action bar choice on the Device List panel invoked from the Operating System List panel). Figure 117 on page 351 to Figure 121 on page 353 shows the options on the context menu and the navigation possibilities to other panels. Almost all of the options on the context menu can be directly selected by entering the action code next to the item in the list to be selected. Available action codes are shown in parentheses below the "Options Available" heading.



Figure 114. HCD Primary Task Selection Panel



Figure 115. HCD - Define, Modify, or View Configuration Data - Option 1

© Copyright IBM Corp. 1994, 2002



Figure 116. HCD - Generic Action Bar Options



Figure 117. HCD - Define Operating System - Option 1.1



Figure 118. HCD - Define Switch - Option 1.2

```
Task          Options Available
Menu

                                                  (r) Repeat (copy)
                                                  (x) Transfer (move) partition configs
                                                  (c) Change
                                                  (d) Delete
                                                  (v) View attached channel paths
                                                  (s) View attached control units
                                                  (u) View attached devices
                                                  (k) View related CTC connections
                                                  (h) View graphically
                 (a) Add like
                 (r) Repeat (copy) proc confgs.
                 (c) Change
                 (i) Prime serial number
1.3              (d) Delete
Define           (p) Work with partitions.....
 Proc &          (s) Work with att channel p..
 CHPID           (u) Work with att devices....
   Data          (k) View related CTC connect.
                 (v) View processor definition
                                                  (a) Add like
                                                  (c) Change
                                                  (f) Connect CF channel paths
                                                  (g) Aggregate channel paths
                                                  (d) Delete
                                                  (s) Work with attached CUs ...
                                                  (v) View channel path definition
                                                  (w) View connected switches
                                                  (k) View related CTC connections
                                                  (h) View graphically
                                                  (a) Add like
                                                  (c) Change
                                                  (g) CSS group change
                                                  (o) OS group change
                                                  (t) Device type group change
                                                  (i) Prime serial number and VOLSER
                                                  (d) Delete
                                                  (v) View device definition
                                                  (l) View logical CU information
                                                  (k) View related CTC connections
                                                  (h) View graphically
                                                                  (p) Connect to CF channel path
                                                                  (n) Disconnect
                                                                  (v) View source channel path def.
                                                                  (t) View dest channel path definition
                                                                  (s) View CF CUs and devices
                                                                  (a) Add like
                                                                  (c) Change
                                                                  (n) Disconnect from processor
                                                                  (i) Prime serial number
                                                                  (d) Delete
                                                                  (s) Work with attached devices ....
                                                                  (v) View CU definition
                                                                  (l) View logical CU information
                                                                  (k) View related CTC connections
                                                                  (h) View graphically
```

Figure 119. HCD - Define Processor and Channel Path - Option 1.3

```
Task          Options Available
Menu

                 (a) Add like
                 (c) Change
                 (i) Prime serial number
1.4              (d) Delete
Define           (s) Work with attached devices
 Control         (v) View CU definition
  Unit           (l) View logical CU information
                 (k) View related CTC connections
                 (h) View graphically
                                                  (a) Add like
                                                  (c) Change
                                                  (g) CSS group change
                                                  (o) OS group change
                                                  (t) Device type group change
                                                  (i) Prime serial number and VOLSER
                                                  (d) Delete
                                                  (v) View device definition
                                                  (l) View logical CU information
                                                  (k) View related CTC connections
                                                  (h) View graphically
```

Figure 120. HCD - Define Control Unit - Option 1.4

```
Task          Options Available
Menu

                 ------------------------------
                 (a) Add like
                 (c) Change
 1.5             (g) CSS group change
 Define          (o) OS group change
  I/O        --> (t) Device type group change
   Device        (i) Prime serial number and VOLSER
    Data         (d) Delete
                 (v) View device definition
                 (l) View logical CU information
                 (k) View related CTC connections
                 (h) View graphically
                 ------------------------------
```

Figure 121. HCD - Define I/O Device - Option 1.5



Figure 122. HCD - Utility Functions - Options 2 - 7

Appendix B. Configuration Reports

This appendix shows examples of the configuration reports that can be produced by HCD.

- Textual configuration reports
- Graphical configuration reports
- IODF compare reports

Textual Configuration Reports

This section shows examples for textual configuration reports. "Print Configuration Reports" on page 215 lists the different report types available and describes how to produce them.

Channel Subsystem Reports

Processor Summary Report

```
                                        PROCESSOR SUMMARY REPORT                    TIME: 11:52  DATE: 1997-03-02  PAGE A-   1
PROCESSOR                   CONFIG.  SERIAL                                    ------ SNA ADDRESS -------
   ID     TYPE     MODEL    MODE     NUMBER     DESCRIPTION                    NETWORK NAME     CPC NAME
--------- -------- -------- -------- ---------- -------------------------------  --------------------------
PROC1     9021     900      LPAR     1234569021 This is the main processor
PROC2     9021     720      BASIC    2345679021 This is the second processor
```

Figure 123. Example of a Processor Summary Report

CONFIG. MODE — Indicates the operation mode in which a processor may operate. These modes are:

BASIC The processor is not logically partitioned.

LPAR The processor is logically partitioned. Several operating systems may run concurrently in different partitions of the processor.

SNA ADDRESS — The SNA Address consists of Network name and CPC name and associates the CPC and the processor definition in the IODF.

Partition Report

```
                                          PARTITION  REPORT                     TIME: 11:52  DATE: 1997-03-02  PAGE B-   1
  PROCESSOR ID  PROC1        TYPE  9021       MODEL 900        TOKEN: PROC1    92-07-03 15:36:27 HCD      IODF01
   PARTITION NAME  NUMBER  USAGE   DESCRIPTION
   --------------  ------  -----   --------------------------------
   PROD1           1       OS      First production partition
   PROD2           2       OS      Second production partition
   TEST1           3       OS      First test system
   TEST2           4       OS      Second test system
   TEST3           5       CF      CF partition
   TEST4           6       CF/OS   CF/OS partition
```

Figure 124. Example of a Partition Report

NUMBER — Is the partition number. This information is printed only for EMIF capable processors.

USAGE — Specifies the usage type of a partition: CF indicates a partition supporting coupling facility. OS indicates a partition running an operating system. CF/OS indicates a partition supporting coupling facility or running an operating system.

© Copyright IBM Corp. 1994, 2002

Note: This report and the following channel subsystem reports show the processor token only if the IODF is a production IODF.

IOCDS Report

```
                                        I O C D S   REPORT                    TIME: 12:34  DATE: 2000-11-24  PAGE C-   1
PROCESSOR ID  FR38LPAR     TYPE  2064      MODEL 109
              IOCDS      NAME      FORMAT      DATE        TIME

              A0       MNGDBASC    LPAR     2000-09-29    19:24
              A1       MNGDLPAR    LPAR     2000-09-29    19:29
              A2       FR38LPAR    LPAR     2000-08-28    11:34
              A3       vmnomgd     LPAR     2000-08-24    18:31
```

Figure 125. Example of an IOCDS Report

NAME	Represents the user-defined name of the IOCDS (derived from the MSG1 parameter)
FORMAT	IOCDS format (BASIC or LPAR)
DATE/TIME	Time stamp of IOCDS creation time (if the processor has no SNA address defined)

Channel Path Summary Report

```
                                        CHANNEL PATH SUMMARY REPORT                    TIME: 15:37 DATE:  2001-09-06 PAGE  D-   1
PROCESSOR ID  FR38LPAR TYPE  2064     MODEL  109      CONFIGURATION MODE: LPAR
            MFS       I/O      DYNENT  SWITCH                          PARTITION NUMBERS
 CHPID TYPE KB  MNGD CLUSTER   SWITCH    ID   PORT  SIDE  MODE  |1|2|3|4|5|6|7|8|9|A|            DESCRIPTION
 ____ ____ ___ ____ ________  ______  _____ ____  ____  ____  _____________________________  ______________________________
  00   OSA      NO                                      SHR   |A|A|A|A|A|A|A| | |A|            CHP 00 OSA Card
  01   OSA      NO                                      SHR   |A|A|A|A|A|A|A| | |A|            CHP 01 OSA Card
  03   IQD  40  NO                                      SHR   |A|C| | | | | | | |A|            iQDIO channel with MFS 40
  04   CNC      NO              6D      6D    FB        SHR   |A|A|A|A|A|A|A| | |A|
  05   CNC      YES  UTCPLX38   6E      6E    FB        SHR   | | | | | | | | | |
  06   CNC      NO              6F      6F    B3        SHR   |A|A|A|A|A|A|A| | |A|
  07   CNC      NO              6F      6F    C7        SHR   |A|A|A|A|A|A|A| | |A|
  08   CNC      NO              70      70    B3        SHR   |A|A|A|A|A|A|A| | |A|
  09   CNC      NO              70      70    C7        SHR   |A|A|A|A|A|A|A| | |A|
  0A   CNC      NO              77      77    EB        SHR   |A|A|A|A|A|A|A| | |A|
  0B   CNC      NO              77      77    31        SHR   |A|A|A|A|A|A|A| | |A|
  0C   CNC      NO              89      89    D6        SHR   |A|A|A|A|A|A|A| | |A|
  0D   CNC      NO              89      89    43        SHR   |A|A|A|A|A|A|A| | |A|
  0E   CNC      NO              71      71    73        SHR   |A|A|A|A|A|A|A| | |A|
  0F   CVC      NO                                      DED   | |A| | | | | | | |            console for F38C
  10   CNC      NO              65      65    A9        SHR   |A|A|A|A|A|A|A| | |A|
  11   CNC      YES  UTCPLX38   66      66    A9        SHR   | | | | | | | | | |
  12   CNC      NO              67      67    A9        SHR   |A|A|A|A|A|A|A| | |A|
  13   CNC      YES  UTCPLX38   68      68    A9        SHR   | | | | | | | | | |
  14   CNC      YES  UTCPLX38   6D      6D    F7        SHR   | | | | | | | | | |
  15   CNC      NO              6E      6E    F7        SHR   |A|A|A|A|A|A|A| | |A|


     PARTITION
   NUMBER    NAME
   ______    ________
     1       F38B
     2       F38C
     3       F38D
     4       F38E
     5       F38F
     6       F38G
     7       F38H
     8       CFQ1
     9       CFQ2
     A       F38A


   LEGEND FOR PARTITION NUMBERS FIELD:
   ___________________________________
    A     - PARTITION IS IN CHPID'S ACCESS LIST
    C     - PARTITION IS IN CHPID'S CANDIDATE LIST ONLY
    BLANK - PARTITION IS NOT IN CHPID'S ACCESS OR CANDIDATE LIST
```

Figure 126. Example of a Channel Path Summary Report

MNGD	Indicates whether the channel path is managed.
I/O CLUSTER	The I/O cluster name for managed channel paths.
DYNENT SWITCH	Designates the switch holding the dynamic connection.
SWITCH ID	Designates the switch the channel is physically plugged in (entry switch).
PORT	Designates the entry port on the entry switch.
SIDE	Refers to the side of the processor the channel path belongs to.
MODE	Operation mode of the channel path.
MFS	Designates the maximum frame size in KB.

Channel Path Detail Report

The Channel Path Detail Report lists the channel paths defined per processor with their attributes and attachment information.

In addition, the switch connections on the path between the CHPID and the control unit are shown if they can be determined by HCD. The entry switch and port of the CHPID are always shown.

For an entry switch of a CHPID which is defined as a dynamic switch, the control unit port is shown if it is compatible with the link address defined for the CHPID. For an entry switch of the CHPID which is defined as a dedicated switch, the control unit port or the ports connecting the switches are only shown if switch configurations are defined which allow HCD determining a valid path between CHPID and control unit.

In case of chained switches, the first print line for a channel path shows the switch the channel path is physically plugged in. The second print line shows the switch the control unit is connected to. In addition, the first print line shows the ID of the switch with the dynamic connection.

Each attached control unit of a specific channel path is separated by a line.

The first print line for an attached control unit shows the first unit address range defined for the control unit. If there are more unit address ranges defined for a control unit, these are shown in the following print lines. Together with the unit address range(s) of the control unit the attached devices of the control unit are shown grouped according to device types and consecutive numbers and unit addresses. The report shows the starting device number and range of the device group. The unit address describes the address of the first device in the range.

For FICON switches, the dynamic switch ID is empty. The control unit port ID is shown as a two-byte port address (the port ID prefixed by the switch address) when used in a cascaded switch environment, or as a one-byte port address otherwise. For cascaded FICON switches, only the channel path port ID and the control unit port ID are shown, but no connection between the switches.

Note: For a Coupling Facility control unit, all CF devices attached to this control unit are listed, not only those devices that are defined for the connected coupling facility channel path described in the row. To view exactly those devices that are defined for the coupling facility channel path, print the CF Channel Path Connectivity Report.

```
                                    CHANNEL PATH DETAIL REPORT                  TIME: 14:46  DATE: 2000-11-14  PAGE E-   2
PROCESSOR ID FR38     TYPE 2064     MODEL 109      CONFIGURATION MODE: LPAR
                           --- SWITCH ----                                   UNIT ADDR                 UNIT
                           ID  PR  CU  DYN  --- CONTROL UNIT ---  CU-          RANGE    -- DEVICE --  ADDR   DEVICE
CHPID  TYPE    SIDE  MODE      PN  PN  ID   NUMBER  TYPE-MODEL    ADD  PROTOCOL  FROM  TO   NUMBER,RANGE  START  TYPE-MODEL
 00    ICP          SHR                       FFFE   CFP                                        FFF9,7           CFP
 01    ICP          SHR                       FFFD   CFP                                        FFEB,14          CFP
 02    ICP          SHR                       FFFD   CFP                                        FFEB,14          CFP
 03    ICP          SHR
 10    CBP          DED                       FFFC   CFP                                        FFE4,7           CFP
 11    CBP          DED                       FFFB   CFP                                        FFDD,7           CFP
```

Figure 127. Example of a Channel Path Detail Report

`SWITCH ID` Designates the entry switch the channel path is physically plugged in. For chained ESCON switches or cascaded FICON switches, a second line is shown with the ID of the switch to which the control unit is connected.

`SWITCH PR PN` Designates the entry port of the entry switch. In case of an ESCON chained switch, it designates the entry port of the chained switch.

SWITCH CU PN	Designates the port the control unit is connected to. In case of an ESCON chained switch, it designates the port of the entry switch to which the chained switch is connected. For a cascaded FICON switch, the port ID is prefixed by the switch address.
SWITCH DYN ID	For an ESCON environment, it designates the switch holding the dynamic connection.

CF Channel Path Connectivity Report

```
                                CF CHANNEL PATH CONNECTIVITY REPORT                 TIME: 14:46  DATE: 2000-11-14  PAGE F-   2
 PROCESSOR ID FR38     TYPE 2064     MODEL 109      CONFIGURATION MODE: LPAR
--------------- SOURCE ------------- ------------------------- DESTINATION ------------------------ --- SOURCE ---- - DESTINATION -
                 ACCESS   CANDIDATE PROCESSOR                                  ACCESS   CANDIDATE CNTRL DEVICE    CNTRL DEVICE
CHPID TYPE MODE O LIST     LIST          ID    TYPE-MODEL        CHPID TYPE MODE LIST     LIST      UNIT  NUM,RANGE UNIT  NUM,RANGE
_____ ____ ____ _ _______  _________ _____ _____________________ _____ ____ ____ _______  _________ _____ _________ _____ _________
00    ICP  SHR  N ZCF0A             FR38      2064-109          01    ICP  SHR  ZCF0B             FFFE  FFF9,7    FFFD  FFF2,7
                  ZOS01                                                        ZOS02
-----------------------------------------------------------------------------------------------------------------------------------
01    ICP  SHR  N ZCF0B             FR38      2064-109          00    ICP  SHR  ZCF0A             FFFD  FFF2,7    FFFE  FFF9,7
                  ZOS02                                                        ZOS01
-----------------------------------------------------------------------------------------------------------------------------------
02    ICP  SHR  N ZOS01             FR38      2064-109          03    ICP  SHR  ZCF0A             FFFD  FFEB,7
-----------------------------------------------------------------------------------------------------------------------------------
03    ICP  SHR  N ZCF0A             FR38      2064-109          02    ICP  SHR  ZOS01                           FFFD  FFEB,7
-----------------------------------------------------------------------------------------------------------------------------------
10    CBP  DED  N ZOS01             FRCF      2064-100          10    CBP  DED  SACF01            FFFC  FFE4,7
-----------------------------------------------------------------------------------------------------------------------------------
11    CBP  DED  N ZOS02             FRCF      2064-100          11    CBP  DED  SACF02            FFFB  FFDD,7
```

Figure 128. Example of a CF Channel Path Connectivity Report

SOURCE/DESTINATION CHPID	The identifier of the source/destination channel path.
SOURCE/DESTINATION TYPE	Is the type of the source/destination channel path.
SOURCE/DESTINATION MODE	Is the operation mode of the source/destination channel path.
SOURCE O	CHPID is identified as occupied
SOURCE/DESTINATION ACCESS LIST	Shows those partitions the source/destination channel path has in its access list.
SOURCE/DESTINATION CANDIDATE LIST	Shows those partitions the source/destination channel path has in its candidate list.
DESTINATION PROCESSOR ID	Is the name of the processor the destination channel path is defined for.
DESTINATION TYPE-MODEL	Is the type-model of the destination processor.
SOURCE CNTRL UNIT	Is the number of the CF control unit used for the source CF channel path connection.
SOURCE DEVICE NUM,RANGE	Is the number of the starting CF device and range of a device group used for the source CF channel path connection.
DESTINATION CNTRL UNIT	Is the number of the CF control unit used for the destination CF channel path connection.
DESTINATION DEVICE NUM,RANGE	Is the number of the starting CF device and range of a device group used for the destination CF channel path connection.

Note: This report lists exactly the devices that are defined for the CF channel path connection described in the row.

Control Unit Summary Report

```
                                  CONTROL UNIT SUMMARY REPORT                    TIME: 13:23  DATE: 1997-03-02  PAGE G-   1
  CONTROL UNIT         SERIAL
NUMBER  TYPE-MODEL     NUMBER       DESCRIPTION                                CONNECTED SWITCH ID.PORT NUMBER
---------------------  ----------   -------------------------------  |--.--|--.--|--.--|--.--|--.--|--.--|--.--|--.--|
 0098   9033           55-9999      First switch                      98.FE
 0099   9032           55-8888      Second switch                     99.FE
 00C1   3480                         First tape control unit
 00C2   3480                         Backup tape control unit
 00D1   3990-3                       DASD control unit                 98.C2 99.E1
 00D2   3990-1
 00E1   3274                         Terminal control unit
 00E2   3174                         Terminal control unit             99.E4
 00E3   3174                                                           99.EF
 FFFE   CFS
```

Figure 129. Example of a Control Unit Summary Report

`CONNECTED SWITCH ID PORT` Describes where the CU is physically connected to (switch and port)

Control Unit Detail Report

The Control Unit Detail Report lists all control units defined in the currently accessed IODF, with their attributes and attachment information.

For each control unit all processors are shown, where the control unit is attached to. For each of those processors, all control units, that are part of the "logical control unit" the currently printed control unit belongs to, are printed. Also, the currently shown control unit is listed again to show information about switch connection, channel path attachment, and attached devices. The information about each logical control unit the currently printed control unit belongs to, is separated by a dotted line.

The switch connection information is shown in the Control Unit Detail Report even if no switch configuration is defined. For example:

If a control unit is connected to a switch, but no complete path is defined through the switch (that means, no valid path is defined through the switch, which allows a dynamic connection) the complete switch connection information with SWITCH ID, CU PN, and PR PN can be determined.

In case of chained switches, the first information in a print line is shown for the switch the control unit is connected to. The second set of switch information is for the switch that the channel path is connected to. Note that this is different from the Channel Path Detail report.

To get information about the switch with the dynamic connection (in case of chained ESCON switches), the Channel Path Detail Report has to be produced.

For each control unit belonging to a logical control unit, the channel path it is attached to, is printed together with the link address (if applicable).

For FICON cascade switching, the link address will be shown as a two-byte number. If a path from the control unit is via cascaded FICON switches, the link between the FICON switches is not shown. Instead, the control unit port of the switch connected to the control unit and the CHPID port of the switch connected

to the channel path are shown. If no port connections are defined, switch data is extracted from the dynamic switch and the link address. Port IDs are shown as one-byte port addresses.

The last column of the report shows the devices which are attached to the control unit printed under column CNTL UNITS IN LOG CNTL UNIT. If the control unit is attached to more than one channel path, the information about the attached devices is printed together with the last printed channel path. The devices attached to a control unit are grouped according to consecutive number. The report shows the starting device number and range of the device group.

Note: For a Coupling Facility control unit, all CF devices attached to this control unit are listed, not only those devices that are defined for the connected coupling facility channel path described in the row. To view exactly those devices that are defined for the coupling facility channel path, print the CF Channel Path Connectivity Report.

```
                                    CONTROL UNIT DETAIL REPORT                  TIME: 14:40  DATE: 2001-09-11  PAGE H-   1
                                                                          -CHAINED/CASC-
  CONTROL UNIT        PROCESSOR   CNTL UNITS IN        CU-   SWITCH  CU  PR   SWITCH  CU  PR   CHPID .     -- DEVICE --
 NUMBER  TYPE-MODEL      ID       LOG CNTL UNIT  IOCL  ADD    ID    PN  PN    ID    PN  PN   LINK ADDR   NUMBER,RANGE
 ___________________  ________   _____________  ____  ___   ______ __  __   ______ __  __   ________   ___________

  1000   2105         PROCA          1000        2           23    15         20        04   10 . 4315
                                                             22    15         21        04   11 . 4215     1000,58
                      ---------------------------------------------------------------------------------------------
                      PROCB          1000        2           21    15  05                   10 . 4115     1000,58
                      ---------------------------------------------------------------------------------------------
                      PROCC          1000        2           23    15         21        06   10 . 15       1000,58
 ---------------------------------------------------------------------------------------------------------------------
  2800   2105         FR38LPAR       2800             3      77    34  08                   4B . 34
                                                             78    F8  82                   4C . F8       2800,256
                                                                                            6  (*)
 ---------------------------------------------------------------------------------------------------------------------
```

Figure 130. Example of a Control Unit Detail Report

CNTL UNITS IN LOG CNTRL UNIT	Designates which CUs belong to the logical CU.
SWITCH ID	Designates the switch the CU is connected to.
CU PN	Designates the port the CU is physically connected to.
PR PN	Designates the entry port of the channel (except in the case of chained switches)
CHAINED/CASC (SWITCH ID, CU PN, PR PN)	Designates a possible second switch the CHPID is connected to.
IOCL	Designates I/O concurrency level (same as SHARED in IOCP). Specifies the level of concurrency of I/O requests that the parallel channel path allows for the control unit (CU). **1** One I/O request at a time. (SHARED=Y) **2** Multiple I/O requests at a time. (SHARED=N) **3** IOCL 1 until dedicated allegiance. (SHARED=Y)
CHPID . LINK ADDR	Designates the channel path and the one- or two-byte link address to which the control unit is connected. *n*(*) in this column indicates that the control unit is connected to *n* managed channel paths.

Device Summary Report

The Device Summary Report gives you an overview of the devices defined in the currently accessed IODF and their attaching control units. The devices are grouped according to the same characteristics. The report shows the starting device number and the range of the group.

For multi-exposure devices, the base devices are grouped separately from the non-base exposure devices.

```
                                  DEVICE SUMMARY REPORT                        TIME: 16:59  DATE: 1997-10-28  PAGE I-   1
--- DEVICE ---    DEVICE                                                  SERIAL
 NUMBER,RANGE    TYPE-MODEL            ATTACHING CONTROL UNITS            NUMBER       DESCRIPTION                        VOLSER
_____________   _____________  |___|___|___|___|___|___|___|___|  __________  ______________________________   ______
   0080,16      3174           0080                                             Merian SNA Connection
   0090,2       RS6K           0110
   0092,2       RS6K           0112
   0094,2       RS6K           0114
   0096,2       RS6K           0116
   0110,2       RS6K           0110
   0112,2       RS6K           0112
   0114,2       RS6K           0114
   0116,2       RS6K           0116
   01C0         3270-X         01C0                                             Console Real and Virt.
   01C1,31      3270-X         01C0                                             Terminal
   0200,64      3390           200A 200B
   0300,32      9345           300A 300B
   0320,32      9345           320A 320B
   0340,32      9345           340A 340B                                        Real Dasd (9345 340-35f)         MVSLIB
   0360,32      9345           360A 360B                                        Real Dasd (9345 360-37f)         TSO001
```

Figure 131. Example of a Device Summary Report

Device Detail Report

The Device Detail Report lists all devices defined in the currently accessed IODF, with their attributes and attachment information. Each device is shown with the processors to which it is attached. The device - processor attachment attributes are also listed.

For each processor the device is attached to, the CUs for the attachment to the processor, as well as the channel path(s) the CU is attached to, are also listed.

The starting device number and the range of subsequent device numbers are shown in one row. A range value of 1 is omitted.

The Device Detail Report shows a partition matrix which indicates whether a logical partition of a corresponding processor has access to the device either via the channel path access list or the channel path candidate list, and whether a partition is excluded or included via the device candidate list.

At the end of the report the totals for the following items are listed for each processor:
- CHPIDS
- SUBCHANNELS
- PHYSICAL CONTROL UNITS
- LOGICAL CONTROL UNITS

For the CHPID total, the report lists separate values for the total shared and the total unshared. For the physical CU total, HCD reports the total shared (those attaching to shared channel paths) and the total unshared.

For the subchannel and logical CU totals, the report lists separate values for the shared, unshared, and additional unshared counts that are, respectively, assigned and unassigned to a logical partition. The shared count is the total number assigned to shared channel paths. The generated for LPAR unshared count is the total that would have been generated for a basic IOCDS. The additional unshared count contains the unshared values that were generated for the LPAR IOCDS.

The TOTAL value is the total that would have been contained in the generated IOCDS. The HSA TOTAL is the total that will exist in the HSA after POR. At the completion of POR, the HSA may contain more subchannels and logical CUs than does the IOCDS.

```
1                                   DEVICE DETAIL REPORT                        TIME: 14:40  DATE: 2001-09-11  PAGE J-   1
- DEVICE       DEVICE        PROCESSOR  UNIT TIME STATUS  PREFERRED      CNTL UNIT     CHPID.          PARTITION NUMBERS
  NUMBER      TYPE-MODEL       ID      ADDR OUT? DETECT?   CHPID    PROT NUMBER CUADD LINK     |1|2|3|4|5|6|7|8|9|A|B|C|D|E|F|  SIDE
  _________   ___________   ________   ____ ___ _______ ________   ____ ______ _____ __.____   _______________________________  ____
   001A       9032          P201        00  NO   YES                      001A       20.FE    |A|C| | | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
   001B       9032          P201        00  NO   YES                      001B       21.FE    |A|A|A| | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
   0CC0,4     3390          P201        00  NO   YES                      0CC0       20.E4    |A|C| | | | | | | | | | | |
                                                                                      23.E4    |A|C| | | | | | | | | | | |
                                                                           0CC1       27.E4    |A|C| | | | | | | | | | | |
                                                                                      29.E4    |A|C| | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
   0CC4       3390          P201        04  NO   YES                      0CC0       20.E4    |A|-|+| | | | | | | | | | | |
                                                                                      23.E4    |A|-|+| | | | | | | | | | | |
                                                                           0CC1       27.E4    |A|-|+| | | | | | | | | | | |
                                                                                      29.E4    |A|-|+| | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
  ...........................................................................................................................
   5160,4     SCTC          P201        00  NO   YES                      5160    4  23.EA    |A|C|+| | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
   5168,4     SCTC          P201        04  NO   YES                      4160    4  25.CB    |A|A|A| | | | | | | | | | | |
  ---------------------------------------------------------------------------------------------------------------------------
   1000,8     3390B         PROCA       00  NO   YES                      1000       10.4315
                                                                                      11.4215
                            PROCB       00  NO   YES                      1000       10.4115
                            PROCC       00  NO   YES                      1000       10.15
  ---------------------------------------------------------------------------------------------------------------------------


      PARTITION       PROCESSOR: P201
    NUMBER    NAME
    ______    _______
      1       A1
      2       A2
      3       A3
      4       A4


    TOTALS FOR CHPIDS, SUBCHANNELS AND CONTROL UNITS FOR PROCESSOR: P201

                                                ADDITIONAL
                                                UNSHARED      IOCDS      HSA       HSA
                                  SHARED   UNSHARED   GENERATED    TOTAL     TOTAL     LIMIT
                                  ______   ________  __________   _____     _____     _____
      CHPIDS _________________      18        0         N/A        18       N/A       N/A
      PHYSICAL CONTROL UNITS _      37        0         N/A        37       N/A       N/A
      SUBCHANNELS ____________     354        0           0       354      1416     40960
      LOGICAL CONTROL UNITS __      35        0           0        35       140      5120


    LEGEND FOR PARTITION NUMBERS FIELD:
    ___________________________________
     A     - PARTITION IS IN CHPID'S ACCESS LIST
     C     - PARTITION IS IN CHPID'S CANDIDATE LIST ONLY
     BLANK - PARTITION IS NOT IN CHPID'S ACCESS OR CANDIDATE LIST
     -     - PARTITION IS IN CHPID'S ACCESS OR CANDIDATE LIST BUT PARTITION IS EXCLUDED FROM DEVICE'S CANDIDATE LIST
     +     - PARTITION IS NOT IN CHPID'S ACCESS OR CANDIDATE LIST BUT PARTITION IS INCLUDED IN DEVICE'S CANDIDATE LIST
```

Figure 132. Example of a Device Detail Report

TIME OUT	Indicates whether the I/O interface time-out function is active or not for channel-initiated I/O operations to the device.
STATUS DETECT	Indicates whether the illegal status detection facility is enabled or disabled.
CUADD	Indicates the logical address of the corresponding CU.
CHPID. LINK	Designates the channel the CU is connected to.
SIDE	Refers to the side of the processor.

Switch Reports

Switch Summary Report

```
                              SWITCH SUMMARY REPORT                              TIME: 14:54  DATE: 2001-09-11  PAGE K-   1
SWITCH                              SERIAL                                        CU        DEVICE    INSTALLED
  ID       TYPE             ADDR    NUMBER        DESCRIPTION                     NUMBER    NUMBER    PORTS
_____     _____________    _____    __________    ___________________________     ______    ______    _________
  21       2032             41                     switch address 41 fabric a                                 33
  98       9033                      55-9999       First switch                     0098      0098       9
                                                                                    0198      0198
                                                                                    0298      0298
  99       9032                      55-8888      Second switch                     0099      0099      29
```

Figure 133. Example of a Switch Summary Report

CU NUMBER — Shows all switch control units attached to the switch CU port of the switch.

DEVICE NUMBER — Shows all switch devices defined for a switch.

ADDR — Shows the switch address, if available.

Switch Detail Report

```
                                    SWITCH DETAIL REPORT                        TIME: 10:53  DATE: 1997-10-09  PAGE L-   3
   SWITCH ID  01   TYPE  9032-3
                                                 ------------- CONNECTION -----------------
   PORT     PORT NAME                           UNIT  UNIT ID            UNIT TYPE           OCCUPIED
   ____     _________________________________   ____  ___________________________________   ________
    AE                                           CU   053E               3490                NO
   ---------------------------------------------------------------------------------------------------
    AF      CHAIN_FROM_99                        SW   99       PORT  F0  9033                NO
   ---------------------------------------------------------------------------------------------------
    B0                                           PR   X9672    CHPID 31  9021-9X2            NO
                                                 CU   0800               SCTC
   ---------------------------------------------------------------------------------------------------
    B1      CU_400                               CU   0400               3190                NO
   ---------------------------------------------------------------------------------------------------
    B2      PROCA_CP18                                                                       YES
   ---------------------------------------------------------------------------------------------------
    B3      PROCA_CP19                                                                       YES
   ---------------------------------------------------------------------------------------------------
    B4                                           CU   0900               3990                NO
   ---------------------------------------------------------------------------------------------------
```

Figure 134. Example of a Switch Detail Report

CONNECTION UNIT — Specifies the type of the unit the port is connected to. PR = Processor CU = Control Unit SW = Switch

OCCUPIED — Indicates a port connection external to the IODF.

Switch Configuration Summary Report

```
                                  SWITCH CONFIGURATION SUMMARY REPORT            TIME: 17:24  DATE: 1997-03-02  PAGE M-   1
SWITCH         SWITCH         CONFIG      DEFAULT
  ID            TYPE            ID        CONNECTION     CONFIGURATION DESCRIPTION
------     --------------    --------     ----------     --------------------------------
  98       9033             BASIC        ALLOW          night-shift configuration
  99       9032             BASIC2       ALLOW
```

Figure 135. Example of a Switch Configuration Summary Report

`DEFAULT CONNECTION` Indicates what state a potential dynamic connection may have (allow or prohibit).

Switch Configuration Detail Report

The Switch Configuration Detail Report lists all supported ports of a switch with their dynamic connection attributes. The first row for a port shows whether the port is installed or not. If the port is installed, the port name is also displayed. Further the row shows if the port is blocked or not, and whether a dynamic or dedicated connection is defined for that port. The next rows show information, whether a dynamic connection from that port to all other installed ports is allowed or prohibited:

- 'p' indicates, that the dynamic connection is prohibited
- 'a' indicates, that the dynamic connection is allowed
- '\' indicates, that this is the intersection point
- A blank indicates, that one of the two ports is not installed

For example, the connection between port C0 and port C6 is prohibited.

```
                                    SWITCH CONFIGURATION DETAIL REPORT                TIME: 17:24  DATE: 1997-03-02  PAGE N-   1
   SWITCH      SWITCH       CONFIGURATION   DEFAULT      INSTALLED
     ID         TYPE              ID        CONNECTION   PORTS
   ------   -------------   -------------   ----------   ---------
     98     9033              BASIC         ALLOW             9
PORT    INSTALLED   PORT NAME                 BLOCKED    CONNECTION TYPE   DEDICATED PORT
   ALLOWED / PROHIBITED MASK
C0         YES                                 YES        DYNAMIC
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  \   p   p   p   p   p   p   p
C1         YES       PROC1CHPID20              NO         DEDICATED            C2
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   \   a   a   a   a   a   a
C2         YES                                 NO         DEDICATED            C1
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   \   a   a   a   a   a
C3         YES                                 NO         DYNAMIC
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   a   \   a   a   a   a
C4         YES                                 NO         DEDICATED            C5
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   a   a   \   a   a   a
C5         YES       CHAIN_FROM_99             NO         DEDICATED            C4
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   a   a   a   \   a   a
C6         YES                                 NO         DYNAMIC
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   a   a   a   a   \   a
C7         YES       PROC1CHPID25              NO         DYNAMIC
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
  p   a   a   a   a   a   a   \
C8         NO
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF

C9         NO
 C0  C1  C2  C3  C4  C5  C6  C7  C8  C9  CA  CB  CC  CD  CE  CF
```

Figure 136. Example of a Switch Configuration Detail Report

Operating System Reports

Operating System Summary Report

```
                                OPERATING SYSTEM SUMMARY REPORT                TIME: 13:37  DATE: 1997-03-02  PAGE O-   1
OPERATING
SYSTEM ID   TYPE        DESCRIPTION
--------    --------    --------------------------------
OPSYS01     MVS         MVS operating system
OPSYS02     VM          VM operating system
```

Figure 137. Example of an Operating System Summary Report

MVS Device Report

The MVS Device Report gives an overview of the devices defined to an MVS-type operating system in the currently accessed IODF.

The devices are grouped according to same characteristics. The report shows the starting device number and the range of a group.

```
                                    MVS DEVICE REPORT                              TIME: 14:40  DATE: 1997-10-24  PAGE P-   1
   OPERATING SYSTEM CONFIGURATION ID:  OPSYS01
 DEV#,RANGE  TYPE-MODEL    BASE  UCB-TYPE  ERP-NAME  DDT-NAME  MLT-NAME  OPT  UIM-NAME  ATI  AL  SH  SW  MX  MI
 ---------- -------------  ----  --------  --------  --------  --------  ---  --------  ---  --  --  --  --  --
 0001       3278-3               12001009  IGE0010E  IECVDDT4  IEAMLT05       CBDUS004   1C
 0098       9033                 0000083A  IGE0004E  IRDVDDT   IRDMLT51       CBDUS051   4C
 00C1       3480                 78008080  IGE0001E  DDTR3480  IEAMLT08       CBDUS005   00           Y
 01D1,8     3390                 3010200F  IECVDERP  IGGDDTA1  IEAMLT02       CBDUS002   40
                                    MVS DEVICE REPORT                              TIME: 14:40  DATE: 94-10-24  PAGE P-   2
         KEY            KEY DESCRIPTION
         ---            ---------------
         DEV#,RANGE  -  DEVICE NUMBER, COUNT OF DEVICES (DECIMAL)
         TYPE-MODEL  -  DEVICE NAME
         BASE        -  BASE DEVICE NUMBER FOR MULTIPLE EXPOSURE DEVICES
         UCB-TYPE    -  UCB TYPE BYTES
         ERP-NAME    -  ERROR RECOVERY PROGRAM
         DDT-NAME    -  DEVICE DESCRIPTOR TABLE
         MLT-NAME    -  MODULE LIST TABLE
         OPT         -  OPTIONAL MLT INDICATOR
         UIM-NAME    -  UNIT INFORMATION MODULE SUPPORTING THE DEVICE
         ATI         -  ATTENTION TABLE INDEX (UCBATI)
         AL          -  ALTERNATE CONTROL UNIT (UCBALTCU)
         SH          -  SHARED UP OPTION (UCBSHRUP)
         SW          -  DEVICE CAN BE SWAPPED BY DDR (UCBSWAPF)
         MX          -  DEVICE HAS MULTIPLE EXPOSURES (UCBMTPXP)
         MI          -  MIH PROCESSING SHOULD BE BYPASSED (UCBMIHPB)
         O           -  MLT IS OPTIONAL
         Y           -  DEVICE SUPPORTS THIS FEATURE
         BLANK       -  DEVICE DOES NOT SUPPORT THIS FEATURE

                 TOTAL NUMBER OF DEVICES BY CLASS
                 --------------------------------
         CLASS NAME             CLASS TYPE    DEVICE COUNT
         ----------             ----------    ------------
         TAPE                       80               1
         COMMUNICATION DEVICES      40               0
         C-T-C                      41               0
         DASD                       20               8
         GRAPHICS                   10               1
         UNIT RECORD                08               1
         CHARACTER READERS          04               0
         TOTAL NUMBER OF I/O DEVICES DEFINED BY THIS I/O CONFIGURATION       11
```

Figure 138. Example of an MVS Device Report

MVS Device Detail Report

```
                                    MVS DEVICE DETAIL REPORT                    TIME: 14:40  DATE: 1997-10-24  PAGE Q-   1
OPERATING SYSTEM CONFIGURATION ID:  OPSYS01
--- DEVICE ---      DEVICE
 NUMBER,RANGE    TYPE - MODEL     PARAMETER                                  FEATURE
--------------   -------------    -------------------------------------      ----------------------------------------
   0001          3278-3           OFFLINE=NO,DYNAMIC=YES                     DOCHAR
-----------------------------------------------------------------------------------------------------------------------
   0098          9033             OFFLINE=YES,DYNAMIC=YES
-----------------------------------------------------------------------------------------------------------------------
   00C1          3480             OFFLINE=NO,DYNAMIC=YES,LIBRARY=NO
-----------------------------------------------------------------------------------------------------------------------
   01D1,8        3390             OFFLINE=NO,DYNAMIC=YES
-----------------------------------------------------------------------------------------------------------------------
```

Figure 139. Example of an MVS Device Detail Report

PARAMETER
: Shows the parameter values specified for the devices. If you do not specify "Yes" or "No" for devices that support the dynamic capability, the DYNAMIC parameter will not be displayed.

FEATURE
: Shows the features given to these devices.

Eligible Device Table Report

```
                                          E D T   REPORT                        TIME: 14:40  DATE: 1997-10-24  PAGE R-   1
OPERATING SYSTEM CONFIGURATION ID:  OPSYS01
EDT IDENTIFIER: A1   DESCRIPTION: special
                                        AFFINITY  ALLOCATION   ASSOCIATED
NAME        NAME TYPE  VIO  TOKEN  PREF   INDEX    DEVICE TYPE  GENERICS                DEVICE NUMBER LIST
---------   ---------  ---  -----  ----  --------  -----------  ----------  ---------------------------------------------
3390        GENERIC                 280    FFFF     3010200F                01D1-01D8
-----------------------------------------------------------------------------------------------------------------------
3480        GENERIC                1100    0008     78008080                00C1
-----------------------------------------------------------------------------------------------------------------------
3277-2      GENERIC                3800    FFFF     12001009                0001
-----------------------------------------------------------------------------------------------------------------------
SWCH        GENERIC                0500    FFFF     0000083A                0098
-----------------------------------------------------------------------------------------------------------------------
ES001       ESOTERIC               3800    FFFF     12001009    3277-2      0001
-----------------------------------------------------------------------------------------------------------------------
ES002       ESOTERIC                280    FFFF     3010200F    3390        01D1-01D8
                                   1100    0008     78008080    3480        00C1
-----------------------------------------------------------------------------------------------------------------------
3400-9      G/GENERIC              1100    0008     78008080    3480        00C1
-----------------------------------------------------------------------------------------------------------------------
SYSALLDA    G/ESOTERIC              280    FFFF     3010200F    3390        01D1-01D8
-----------------------------------------------------------------------------------------------------------------------
SYS3480R    G/ESOTERIC             1100    0008     78008080    3480        00C1
```

Figure 140. Example of an Eligible Device Table Report

VIO
: Eligible for virtual I/O, designates temporary data sets that exist in paging storage only.

PREF
: Preference value, indicates the order the system should follow when attempting allocation.

AFFINITY INDEX
: This index is used by the system allocation programs to determine which devices have affinity to each other. Devices have affinity if either of the following statements are true:

- The devices have the same affinity index.
- The affinity index for one of the devices is a subset of the other devices' affinity index.

An affinity index is a subset of another if both of the following statements are true:

- Neither index has a value of X'FFFF'.
- One or more bits in one index are set to a binary "one" and one or more corresponding bits in the other index are set to a binary "one".

ALLOCATION DEVICE TYPE	UCB device table for allocation entry.
ASSOCIATED GENERICS	Indicates the relation of a device type to generics.
DEVICE NUMBER LISTS	Lists the devices that are included in the group. The devices are grouped according to subsequent device numbers. The report shows the range of the device group.

NIP Console Report

```
                                 N I P C O N   REPORT                          TIME: 13:37  DATE: 1997-03-02  PAGE S-   1
OPERATING SYSTEM CONFIGURATION ID:  OPSYS01
                              NIP CONSOLE DEVICES
                              -------------------
                      DEVICE #        TYPE-MODEL
                      --------       -------------
                      0001           3278-3
```

Figure 141. Example of a NIP Console Report

VM Device Report

The VM Device Report gives an overview of the devices defined to a VM operating system in the currently accessed IODF.

The devices are grouped according to same characteristics. The report shows the starting device number and the range of a group.

```
                                   VM  DEVICE REPORT                              TIME: 15:06  DATE: 1997-10-24  PAGE P-   1
   OPERATING SYSTEM CONFIGURATION ID:  OPSYS02
 DEV#,RANGE   TYPE-MODEL       BASE     CLASS                      VIRT   UIM-NAME   MX   DO   US
 ----------   ----------       ----     ----------------           ----   --------   --   --   --
 0001         3278-3
 0002         3279-2                                                Y
 01D1,4       3390
                                   VM  DEVICE REPORT                              TIME: 15:06  DATE: 94-10-24  PAGE P-   2
        KEY            KEY DESCRIPTION
        ---            ---------------
        DEV#,RANGE  -  DEVICE NUMBER, COUNT OF DEVICES (DECIMAL)
        TYPE-MODEL  -  DEVICE TYPE AND MODEL
        BASE        -  BASE DEVICE NUMBER FOR MULTIPLE EXPOSURE DEVICES
        CLASS       -  VM DEVICE CLASS
        VIRT        -  DEVICE IS NOT DEFINED TO CHANNEL SUBSYSTEM
        UIM-NAME    -  UNIT INFORMATION MODULE SUPPORTING THE DEVICE
        MX          -  DEVICE HAS MULTIPLE EXPOSURES
        DO          -  DEVICE IS SUPPORTED DEDICATED-ONLY
        US          -  DEVICE IS UNSUPPORTED
        Y           -  DEVICE SUPPORTS THIS FEATURE
        BLANK       -  DEVICE DOES NOT SUPPORT THIS FEATURE

                TOTAL NUMBER OF DEVICES BY CLASS
                --------------------------------
        CLASS NAME                          DEVICE COUNT
        ----------                          ------------
        TERMINAL                                    0
        GRAPHIC                                     0
        REMOTE GRAPHIC                              0
        SPOOL                                       0
        TAPE                                        0
        DASD                                        0
        SPECIAL                                     0
        TOTAL NUMBER OF I/O DEVICES DEFINED BY THIS I/O CONFIGURATION       0
```

Figure 142. Example of a VM Device Report

VM Device Detail Report

```
                                        VM  DEVICE DETAIL REPORT                    TIME: 15:06  DATE: 1997-10-24  PAGE Q-   1
   OPERATING SYSTEM CONFIGURATION ID:  OPSYS02
   --- DEVICE ---      DEVICE
    NUMBER,RANGE    TYPE - MODEL     PARAMETER                                    FEATURE
   --------------   -------------    -------------------------------------------  ------------------------------------------
      0001          3278-3           OFFLINE=NO,OFFLINE=NO
   ------------------------------------------------------------------------------------------------------------------------------
      0002          3279-2           OFFLINE=NO,OFFLINE=NO
   ------------------------------------------------------------------------------------------------------------------------------
      01D1,4        3390             OFFLINE=NO,OFFLINE=NO,OFFLINE=NO
   ------------------------------------------------------------------------------------------------------------------------------
```

Figure 143. Example of a VM Device Detail Report

PARAMETER Shows the parameter values specified for the devices.

FEATURE Shows the features given to these devices.

VM Console Report

```
                                   VM CONSOLE REPORT                              TIME: 13:45  DATE: 1997-03-02  PAGE S-   1
OPERATING SYSTEM CONFIGURATION ID:  OPSYS02
                                 VM CONSOLE DEVICES
                                 -------------------
                       DEVICE #        TYPE-MODEL
                       --------       -------------
                       0002           3279-2         PRIMARY SYSTEM CONSOLE
```

Figure 144. Example of a VM Console Report

CTC Connection Report

```
                                        CTC CONNECTION REPORT                       TIME: 17:42  DATE: 1997-08-03  PAGE U-   1


       ------------------------- SIDE 1 ----------------------- - COMMON -- ------------------------- SIDE 2 -----------------------
       PROC.    PARTITION- DEVICE- --CHPID--- ENTRY ----CU----- --DEVICE--- PROC.    PARTITION- DEVICE- --CHPID--- ENTRY ----CU-----
 LINE  ID       NAME     # NUM  OS ID MOD TYP SW PO ID    LA  # RNG TYPE UA ID       NAME     # NUM  OS ID MOD TYP SW PO ID    LA  #
------ -------- -------- - ---- -- -- --- --- -- -- ---- ---- - --- ---- -- -------- -------- - ---- -- -- --- --- -- -- ---- ---- -

    1* PROC001             0100 N  10 DED CNC 05 E1 1010 F0   0   5 BCTC 00 PROC001A            0500 N  20 DED CTC 05 F0 1020 E1
    2  PROC001             1106 N  10 DED CNC 05 E1 0106 F7       1 SCTC 00 PROC003  PART1    1 1105 N  21 DED CTC 05 F7 0105 E1
 ----- -------- -------- - ---- -- -- --- --- -- -- ---- --   - --- ---- -- -------- -------- - ---- -- -- --- --- -- -- ---- ---- -
    3* PROC001A            0500 N  20 DED CTC 05 F0 1020 E1       5 BCTC 00 PROC001             0100 N  10 DED CNC 05 E1 1010 F0   0
    4* PROC001A            0690 N  20 DED CTC 05 F0 0069 E7       1 SCTC 00
 ----- -------- -------- - ---- -- -- --- --- -- -- ---- --   - --- ---- -- -------- -------- - ---- -- -- --- --- -- -- ---- ---- -
    5* PROC002             0200 N  10 DED CNC       1011 C5       2 SCTC 00
    6* PROC002             0650 N  11 DED CTC 05 E7 0065 E8       1 SCTC 00 PROC002             0660 N  13 DED CNC 05 E8 0066 E7
    7* PROC002             0660 N  13 DED CNC 05 E8 0066 E7       1 SCTC 00 PROC002             0650 N  11 DED CTC 05 E7 0065 E8
    8* PROC002             0680 N  11 DED CTC 05 E7 0068 F0       1 SCTC 00
    9  PROC002             0701 N  12 DED CTC 05 D0 0050 F4   1   1 SCTC 01 PROC003  PART1    1 0301 N  10 SHR CNC 05 F4 1012 D0
   10  PROC002             0800 N  22 DED CTC 05 D7 0060 F3   2   5 SCTC 00 PROC003  PART2    2 0400 N  11 SHR CNC 05 F3 1013 D7
   11* PROC002             0805 N  22 DED CTC 05 D7 0060 F3   2   1 BCTC 05 PROC003  PART2    2 0405 N  11 SHR CNC 05 F3 1013 D7
   12  PROC002             0806 N  22 DED CTC 05 D7 0060 F3   2   3 SCTC 06 PROC003  PART2    2 0406 N  11 SHR CNC 05 F3 1013 D7
   13* PROC002             1108 N  26 DED CNC 05 F8 0108 F7   1   1 SCTC 00 PROC003  PART1    1 1107 N  21 DED CTC 05 F7 0107 F8
   14* PROC002             2400 N  24 DED CTC 04 E0 0024 E0       1 SCTC 00
 ----- -------- -------- - ---- -- -- --- --- -- -- ---- --   - --- ---- -- -------- -------- - ---- -- -- --- --- -- -- ---- ---- -
   15* PROC003  PART1    1 0300 N  10 SHR CNC 05 F4 1012 D0       1 SCTC 00
   16  PROC003  PART1    1 0301 N  10 SHR CNC 05 F4 1012 D0       1 SCTC 01 PROC002             0701 N  12 DED CTC 05 D0 0050 F4   1
   17  PROC003  PART1    1 1105 N  21 DED CTC 05 F7 0105 E1       1 SCTC 00 PROC001             1106 N  10 DED CNC 05 E1 0106 F7
   18* PROC003  PART1    1 1107 N  21 DED CTC 05 F7 0107 F8       1 SCTC 00 PROC002             1108 N  26 DED CNC 05 F8 0108 F7   1
 ----- -------- -------- - ---- -- -- --- --- -- -- ---- --   - --- ---- -- -------- -------- - ---- -- -- --- --- -- -- ---- ---- -
   19* PROC003  PART2    2 0300 N  10 SHR CNC 05 F4 1012 D0       2 SCTC 00
   20  PROC003  PART2    2 0400 N  11 SHR CNC 05 F3 1013 D7       5 SCTC 00 PROC002             0800 N  22 DED CTC 05 D7 0060 F3   2
   21* PROC003  PART2    2 0405 N  11 SHR CNC 05 F3 1013 D7       1 SCTC 05 PROC002             0805 N  22 DED CTC 05 D7 0060 F3   2
   22  PROC003  PART2    2 0406 N  11 SHR CNC 05 F3 1013 D7       3 SCTC 06 PROC002             0806 N  22 DED CTC 05 D7 0060 F3   2


        KEY                 KEY DESCRIPTION
        ---                 ---------------

        LINE NR          -  LINE NUMBER USED TO REFER TO CTC MESSAGES - A MESSAGE IS INDICATED BY AN ASTERIX (*)

        SIDE 1 / SIDE 2
        PROC. ID         -  PROCESSOR ID
        PARTITION NAME   -  PARTITION NAME
        PARTITION #      -  PARTITION IMAGE NUMBER
        DEVICE NUM       -  DEVICE NUMBER
        DEVICE OS        -  INDICATION, IF FIRST DEVICE OF RANGE IS DEFINED TO AN OPERATING SYSTEM
        CHPID ID         -  CHANNEL PATH ID
        CHPID S          -  CHANNEL PATH MODE
        CHPID TYPE       -  CHANNEL PATH TYPE
        ENTRY SW         -  ENTRY SWITCH OF THE CHANNEL PATH
        ENTRY PO         -  ENTRY PORT OF THE CHANNEL PATH
        CU ID            -  CONTROL UNIT NUMBER
        CU LA            -  LINK ADDRESS OF CONTROL UNIT RELATED TO THE CHANNEL PATH
        CU #             -  LOGICAL ADDRESS (CUADD) RELATED TO THE PROCESSOR

        COMMON
        DEVICE RNG       -  DEVICE RANGE FOR DEVICES ON SIDE 1 AND SIDE 2
        DEVICE TYPE      -  DEVICE TYPE COMMON TO DEVICES ON SIDE 1 AND SIDE 2 (IF MESSAGE G751 THEN DEVICE TYPE OF SIDE 1)
        DEVICE UA        -  UNIT ADDRESS OF DEVICES RELATED TO THE PROCESSOR (COMMON TO SIDE 1 AND SIDE 2)
```

Figure 145. Example of a CTC Connection Report

Diagnostic Messages

The following example shows you messages that might be returned with the report. The diagnostic messages are sorted by severity. For each connection, HCD displays only one messages, even if the connection includes several errors. You first have to correct the first error before the next message is displayed. HCD displays the messages according to the priority as described in “Displaying Diagnostic Messages” on page 152.

```
                                    CTC CONNECTION REPORT                    TIME: 17:42  DATE: 1997-08-03  PAGE U-   3

 LINE  SEV MSGID     MESSAGE TEXT

    1   E  CBDG750I  Logical address (CUADD) is specified for CU 1010, but CHPID 20 of processor PROC001A is
                     not defined as shared.

    3   E  CBDG750I  Logical address (CUADD) is specified for CU 1010, but CHPID 20 of processor PROC001A is
                     not defined as shared.


    4   E  CBDG752I  Channel path type error. CHPID 20 of processor PROC001A is connected to a CHPID 11 of
                     processor PROC002 with the same type.

    8   E  CBDG752I  Channel path type error. CHPID 11 of processor PROC002 is connected to a CHPID 20 of processor
                     PROC001A with the same type.

   11   E  CBDG751I  Device type of device 0805 connected to processor PROC002, CHPID 22 does not match with device
                     type of device 0405 on the other side.

   13   E  CBDG750I  Logical address (CUADD) is specified for CU 0108, but CHPID 21 of processor PROC003 is
                     not defined as shared.

   18   E  CBDG750I  Logical address (CUADD) is specified for CU 0108, but CHPID 21 of processor PROC003 is
                     not defined as shared.

   21   E  CBDG751I  Device type of device 0405 connected to processor PROC003, CHPID 11 does not match with device
                     type of device 0805 on the other side.

    6   W  CBDG753I  Wrap around connection detected for processor PROC002 (partition - none -) via CHPID 11 and
                     CHPID 13.

    7   W  CBDG753I  Wrap around connection detected for processor PROC002 (partition - none -) via CHPID 13 and
                     CHPID 11.


   15   W  CBDG754I  HCD cannot determine connection. No control units and devices match to processor PROC003,
                     partition PART1, CU 1012 and device 1012.

   19   W  CBDG754I  HCD cannot determine connection. No control units and devices match to processor PROC003,
                     partition PART2, CU 1012 and device 1012.

    5   I  CBDG757I  HCD cannot determine connection. CHPID 10 of processor PROC002 has no dynamic switch defined.

   14   I  CBDG756I  HCD cannot determine connection. CHPID 24 of processor PROC002 is connected via chained
                     switches.


 Total Messages  Terminating     Error     Warning  Informational
         14                       8          4           2
```

Figure 146. Sample of Diagnostic Messages coming with the CTC connection report

I/O Path Report

The I/O Path report shows the physically sensed I/O paths (with physical types) of the active system compared with the logical definitions of the paths (also the object types) of a specific IODF.

- If the sensed I/O path reports a switch, the verification assumes that this is a dynamic switch. It checks whether the defined I/O path in the IODF contains a dynamic switch, and whether the link address corresponds to the output port of the sensed data. If the IODF contains defined switch data, it is verified whether the defined data correspond to the sensed data. If dedicated switches are defined, the I/O Path report always shows differences in the `D` column.
- When you compare between the sensed and defined data, not all fields are used to determine if there is a difference between the two sides (either an `*`, or `@` is shown in the column `D` of the report). The data that is used are the CHPID, the control unit number, the device number, and the switch information of the defined dynamic switches and the sensed dynamic switches.

The I/O path verification checks if the actual system contains the same paths as in the defined I/O configuration. Differences are indicated in the I/O Path report in column D with the following characters:

1 The * indicates that differences are found between the sensed and the defined I/O path. Either
- only sensed data is available, or
- only defined data in the IODF is available, or
- the sensed and defined switch data differ.

2 The C indicates that the defined and the sensed I/O path are the same, but the defined I/O path is defined to the CSS only.

3 An @ is a combination of * and C, and indicates that differences are found between the sensed and the defined I/O path, and that the I/O path is defined to the CSS only.

4 The O indicates that the defined I/O path in the IODF is defined to the operating system only.

```
                                        I/O PATH REPORT                      TIME: 09:10    DATE: 2001-12-20  PAGE V-   1
 SYSTEM:          SYSPLEX:                                  PROCESSOR: PROCA     PARTITION:          OS CONFIG: ZOS130
<--------------------- Sensed data ---------------------> <------------------------- IODF data -------------------------->   D
--CHP--- DYN.SWITCH CONTROL UNIT- ------DEVICE------- PATH  -CHP-- -SWITCH- CHAINED- DYNSW   -CONTROL UNIT-- -----DEVICE------
ID TYPE  PI SW PO   NUMB TYPE     NUMBER   TYPE     O STAT  ID TYP PI SW PO PI SW PO DS LA   NUMB TYPE     L NUMBER   TYPE
-- ----- -- -- --   ---- -------- -------- -------- - ----  -- --- -- -- -- -- -- -- -- ---- ---- -------- - -------- --------    -
00 OSA              0230 9676     0230,2                    00 OSA                            0230 OSA        0230,2   OSA
00 OSA              0230 9676     023F     9676-2           00 OSA                            0230 OSA        023F     OSAD
                                                            04 CFS                            FFF7 CFS        FF00,2   CFS        @3
04 CFS              FFF7 9672-E03 FFE2,2   CFS                                                                                   *
05 CFS              FFF8 9672-E03 FFE6,2   CFS              05 CFS                            FFF8 CFS        FFE6,2   CFS        C2
                                                            09 BL                             0910 3880-3     0910,8   3380       *
                                                            09 BL                             0920 3880-3     0920,8   3380       *1
10 CTC_S EE AC C3   4010 9672-R72 4010,4   9672-CTC        10 CTC EE AC C3         AC C3     4010 SCTC     1 4010,4   SCTC
10 CTC_S EE AC C3   4020 9672-R72 4020,4   9672-CTC        10 CTC EE AC C3         AC C3     4020 SCTC     2 4020,4   SCTC
10 CTC_S EE AC CB   4030 9672-R72 4030,4   9672-CTC        10 CTC EE AC CB         AC CB     4030 SCTC     1 4030,4   SCTC
10 CTC_S EE AC CB   4040 9672-R72 4040,4   9672-CTC                                                                            *1
10 CTC_S EE AC ED   4230 9672-R72 4230,4   9672-CTC        10 CTC EE AC ED         AC ED     4230 SCTC     1 4230,4   SCTC
10 CTC_S EE AC ED   4240 9672-R72 4244     9672-CTB        10 CTC EE AC ED         AC ED     4240 SCTC     2 4244     BCTC
11 CNC_S D0 AE FE   001E 9032-3   001E     9032-3          11 CNC D0 AE FE         AE FE     001E 9032-3     001E     9032-3
11 CNC_S D0 AE D8   2000 9394-3   2000,14  9395-B13        11 CNC D0 AE D8         AE D8     2000 3990-6     2000,14  3390
11 CNC_S D0 AE D8   2000 9394-3   200E,18                  11 CNC D0 AE D8         AE D8     2000 3990-6     200E,18  3390
12 CNC_?                                          OFFL    12 CNC
13 CNC_?                                          OFFL    13 CNC
14 CNC_S ED AA D8   0B30 3490-A20 0B30,16  3490-B40        14 CNC ED AA D8         AA D8     0B30 3490       0B30,16  3490
14 CNC_S ED AA EA   0B50 3490-C2A 0B50,2   3490-C2A        14 CNC ED AA EA         AA EA     0B50 3490       0B50,2   3490
14 CNC_S ED AA EA   0B50 3490-C2A 0B52,14                  14 CNC ED AA EA         AA EA     0B50 3490       0B52,14  3490
                                                            15 CVC                            0BA0 3480       0BA0,16  3480       *
18 CNC_S E5 AA FE   001A 9032     001A     9032             18 CNC E5 AA FE         AA FE     001A 9032       001A     9032
18 CNC_S E5 AA E4   0CC0 3990-6   0CC0,8   3390-A28         18 CNC E5 AA E4         AA E4     0CC0 3990-6     0CC0,8   3390
18 CNC_S E5 AA E4   0CC0 3990-6   0CC8,24  3390-B2C         18 CNC E5 AA E4         AA E4     0CC0 3990-6     0CC8,24  3390
18 CNC_S E5 AA E4   0CC0 3990-6   0CE0,32  9392-B10         18 CNC E5 AA E4         AA E4     0CC0 3990-6     0CE0,32  3390
19 CNC_S F5 AA FE   001A 9032     001A     9032             19 CNC F5 AA FE         AA FE     001A 9032       001A     9032
1C CNC_S            0F00          0F00,2                    1C CNC                  77 96     0F00 3174     1 0F00,2   3791L      *1
1C CNC_S            0F02          0F02,2                    1C CNC                  77 95     0F02 3174     2 0F02,2   3791L      *
20 OSA              0210 9676     0214,11                   20 OSA                            0210 OSA        0214,11  OSA
20 OSA              0210 9676     021F     9676-2           20 OSA                            0210 OSA        021F     OSAD
2C CNC_S ED AC D8   5100          5100,4                    2C CNC ED AC D8         AC D8     5100 SCTC     2 5100,4   SCTC
2F CNC_S A0 01 81   200A 3990-6   0219,2   3390-B3C                                                                            *
2F CNC_S A0 01 81   200A 3990-6   021B                 Y UNKN                                                                 *
40 CNC_S 8F 70 E5   9101 3990-L03 9100,4   3380-AK4         40 CNC B6 6F 8F 8F 70 E5 70 E5    9101 3990       9100,4   3380
40 CNC_S 8F 70 E5   9101 3990-L03 9104,8   3380-BK4         40 CNC B6 6F 8F 8F 70 E5 70 E5    9101 3990       9104,8   3380
                                                                                              01B0 3172       01B0,16  3172       O4
                                                                                              0640 3990       0640,8   3380       O
                                                                                              0740 SCTC       0740,16  SCTC       O
                                                                                              0730 SCTC       0730,16  SCTC       O
```

Figure 147. Example and Legend of an I/O Path Report (Part 1 of 2)

```
                                        I/O PATH REPORT                      TIME: 08:05    DATE: 1996-11-28  PAGE V-   6
KEY                 KEY DESCRIPTION
---                 ---------------
SENSED DATA      -  I/O CONFIGURATION DATA RETRIEVED BY SENSING I/O
CHP ID           -  SENSED CHANNEL PATH ID
CHP TYPE         -  SENSED CHANNEL PATH TYPE
DYN.SWITCH PI    -  SENSED DYN. SWITCH INPUT PORT (CHANNEL PATH SIDE)
DYN.SWITCH SW    -  SENSED DYNAMIC SWITCH ID
DYN.SWITCH PO    -  SENSED DYN. SWITCH OUTPUT PORT (CONTROL UNIT SIDE)
CONTROL UNIT NUMB-  SENSED CONTROL UNIT NUMBER
CONTROL UNIT TYPE-  SENSED CONTROL UNIT TYPE
DEVICE NUMBER    -  SENSED DEVICE NUMBER AND RANGE
DEVICE TYPE      -  SENSED DEVICE TYPE
DEVICE O         -  SENSED DEVICE(S) OFFLINE INDICATOR
                    Y - OFFLINE
                    BLANK - NOT OFFLINE
PATH STAT        -  IF BLANK, SENSED I/O PATH IS ONLINE
                    IF OFFL, SENSED I/O PATH IS OFFLINE
                    IF UNKN, STATUS OF SENSED I/O PATH IS UNKNOWN
IODF DATA        -  I/O CONFIGURATION DEFINITIONS IN IODF
CHP ID           -  DEFINED CHANNEL PATH ID
CHP TYPE         -  DEFINED CHANNEL PATH TYPE
SWITCH PI        -  DEFINED SWITCH INPUT PORT (CHANNEL PATH SIDE)
SWITCH SW        -  DEFINED SWITCH ID
SWITCH PO        -  DEFINED SWITCH OUTPUT PORT (CONTROL UNIT SIDE)
CHAINED PI       -  DEFINED CHAINED SWITCH INPUT PORT
CHAINED SW       -  DEFINED CHAINED SWITCH ID
CHAINED PO       -  DEFINED CHAINED SWITCH OUTPUT PORT
DYNSW SW         -  DEFINED DYNAMIC SWITCH FOR CHANNEL PATH
DYNSW LA         -  DEFINED DYNAMIC LINK ADDRESS FOR CONTROL UNIT
CONTROL UNIT NUMB-  DEFINED CONTROL UNIT NUMBER
CONTROL UNIT TYPE-  DEFINED CONTROL UNIT TYPE
CONTROL UNIT L   -  DEFINED CONTROL UNIT LOGICAL ADDRESS
DEVICE NUMBER    -  DEFINED DEVICE NUMBER AND RANGE
DEVICE TYPE      -  DEFINED DEVICE TYPE
D                -  IF C, ONLY DEFINED TO CHANNEL SUBSYSTEM
                    IF O, ONLY DEFINED TO OS CONFIGURATION
                    IF *, DIFFERENCES WERE FOUND BETWEEN THE 2 SIDES
                    IF @, INDICATES C AND * FROM ABOVE
```

Figure 147. Example and Legend of an I/O Path Report (Part 2 of 2)

`DYN.SWITCH` Contains either the switch information for the dynamic switch in the path or the dedicated switch if there is no dynamic switch.

`PATH STAT` Represents the status of the I/O path between the CHPID and the devices that it is connected to.

OFFL Represents the situations where there is no I/O path to be found or when the I/O path is offline.

UNKN Represents the situations where the I/O path is currently in a pending state or when the MVS-type environment is running as a guest on a VM system and the path status can not be obtained from the system.

Supported Hardware Report

The Supported Hardware Report shows the actual status of the hardware supported in your installation. It shows the following supported hardware:

- Processors
- Control units
- Devices including:
  - Device characteristics
  - Control unit attachments
- MVS devices including:
  - Device capabilities
  - Parameters (with selection values) / features
- VM devices including
  - device capabilities
  - parameters/features

The following figure shows you an example of a supported hardware report. The example may differ from the report you get on your system, because the data depend on the installed processor support modules and UIMs.

```
                                   SUPPORTED HARDWARE - PROCESSORS              TIME: 09:02  DATE: 2001-12-20  PAGE T-   1
TYPE-MODEL MOD SUPLEVID IOCP SYSTEM    SUPPORTED CHPID TYPES              DYN MIF PLEX DCM CAS WI RI CHPID CU   LCU  SUBCH LPAR
__________ ___ ________ ____ ________ ___________________________________ ___ ___ ____ ___ ___ __ __ _____ ____ ____ _____ ____
2003-1C5   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-102   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-102   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-103   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-103   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-104   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-104   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-105   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-105   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-106   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-106   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-107   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-115   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-115   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-116   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-116   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-124   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-125   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-125   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-126   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-126   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-135   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-135   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-136   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-136   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-146   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-146   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-156   167 H960703  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-156   177 H970513  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-2C5   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-202   177 H980430  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-203   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-204   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-205   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-206   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-207   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-215   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-216   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-224   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-225   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-227   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-237   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-246   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-247   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2003-257   177 H971001  IZP  2003,1    BL,BY,CNC,CTC,CVC,CBY,OSA,ISD      Y   Y   Y    N   N   N  Y  128   6144 3072 24576  10
2064-1C1   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C2   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C3   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C4   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C5   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C6   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
2064-1C7   200 H000931  IYP  2064,1    BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, Y   Y   Y    Y   N   Y  Y  256   8192 4096 64512  15
                                       FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP,
                                       ICP,IQD
```

Figure 148. Supported Hardware Report - Processors (Part 1 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 2

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
2064-1C8	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-1C9	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-100	201	H000931	IYP	2064,2	CFR,CFS,CBR,CBS,CFP,CBP,ICP	Y	Y	Y	N	N	Y	Y	64	8192	4096	64512	15
2064-101	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-101	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-102	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-102	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-103	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-103	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-104	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-104	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-105	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-105	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-106	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-106	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-107	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-107	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-108	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-108	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-109	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-109	202	H010931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-110	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-111	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-112	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-113	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-114	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15

Figure 148. Supported Hardware Report - Processors (Part 2 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 3

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
2064-113	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-114	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-115	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-116	200	H000931	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD	Y	Y	Y	Y	N	Y	Y	256	8192	4096	64512	15
2064-2C1	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C2	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C3	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C4	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C5	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C6	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C7	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C8	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2C9	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-2LF	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-210	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-211	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-212	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-213	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-214	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-215	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2064-216	202	H020415	IYP	2064,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,OSD,OSE,CFP,CBP, ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-0A1	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-0A2	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-0B1	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-0CF	207	H020331	IYP	2066,2	CFR,CFS,CFP,CBP,ICP	Y	Y	Y	N	N	Y	Y	64	8192	4096	64512	15
2066-0C1	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15

Figure 148. Supported Hardware Report - Processors (Part 3 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 4

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
2066-0E1	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-0LF	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-001	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-002	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-003	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
2066-004	206	H020331	IYP	2066,1	CNC,CTC,CVC,CFR,CFS,CBY,FC,FCV, OSD,OSE,CFP,CBP,ICP,IQD,FCP	Y	Y	Y	Y	Y	Y	Y	256	8192	4096	64512	15
3000-A10	179	H971001	IZP	3000,1	BL,BY,CNC,CTC,CVC,CBY,OSA,ISD	Y	Y	Y	N	N	N	Y	32	6144	3072	24576	10
3000-A20	179	H971001	IZP	3000,1	BL,BY,CNC,CTC,CVC,CBY,OSA,ISD	Y	Y	Y	N	N	N	Y	32	6144	3072	24576	10
3090-100S	002	230387	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-110J	002	230395	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-120E	001	223670	IOP		BL,BY	N	N	N	N	N	N	N	24	2304	1024	4096	4
3090-120J	002	230395	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-120S	002	230387	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-15T	020	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-150E	001	223670	IOP		BL,BY	N	N	N	N	N	N	N	24	2304	1024	4096	4
3090-150J	002	230395	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-150S	002	230387	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-17T	020	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-170J	002	230395	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-170S	002	230387	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-18T	020	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-180E	002	223675	IOP		BL,BY	N	N	N	N	N	N	N	32	2304	1024	4096	4
3090-180J	010	227540	IOP		BL,BY	N	N	N	N	N	N	N	32	6144	2048	24576	7
3090-180J	020	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-180S	010	228862	IOP		BL,BY	N	N	N	N	N	N	N	32	6144	2048	24576	7
3090-200E	003	223675	IOP		BL,BY	N	N	N	N	N	N	N	64	2304	1024	4096	4
3090-200J	011	227540	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-200J	021	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-200S	011	228862	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-25T	022	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-250J	004	230395	IOP		BL,BY	N	N	N	N	N	N	N	64	2304	1024	4096	4
3090-250S	004	230387	IOP		BL,BY	N	N	N	N	N	N	N	64	2304	1024	4096	4
3090-28T	022	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-280E	004	223675	IOP		BL,BY	N	N	N	N	N	N	N	64	2304	1024	4096	4
3090-280J	012	227540	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-280J	022	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-280S	012	228862	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-300E	003	223675	IOP		BL,BY	N	N	N	N	N	N	N	64	2304	1024	4096	4
3090-300J	011	227540	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-300J	021	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	64	6144	2040	24440	7
3090-300S	011	228862	IOP		BL,BY	N	N	N	N	N	N	N	64	6144	2048	24576	7
3090-380J	013	227540	IOP		BL,BY	N	N	N	N	N	N	N	96	6144	2048	24576	7
3090-380J	023	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-380S	013	228862	IOP		BL,BY	N	N	N	N	N	N	N	96	6144	2048	24576	7
3090-400E	005	223675	IOP		BL,BY	N	N	N	N	N	N	N	128	2304	1024	4096	4
3090-400J	014	227540	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
3090-400J	024	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-400S	014	228862	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
3090-500E	005	223675	IOP		BL,BY	N	N	N	N	N	N	N	128	2304	1024	4096	4
3090-500J	014	227540	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
3090-500J	024	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-500S	014	228862	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
3090-600E	005	223675	IOP		BL,BY	N	N	N	N	N	N	N	128	2304	1024	4096	4
3090-600J	014	227540	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
3090-600J	024	227574	IXP	3090,1	BL,BY,CNC,CTC,CVC	N	N	N	N	N	N	N	128	6144	2040	24440	7
3090-600S	014	228862	IOP		BL,BY	N	N	N	N	N	N	N	128	6144	2048	24576	7
4381-90E	100				BL,BY	N	N	N	N	N	N	N	12	256	256	2048	
4381-91E	100				BL,BY	N	N	N	N	N	N	N	12	256	256	2048	
4381-92E	101				BL,BY	N	N	N	N	N	N	N	24	256	256	2048	
7060-H30	189	H990930	IZP	7060,1	BL,BY,CNC,CTC,CVC,CBY,DSD,ICR,ICS, EIO	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15
7060-H50	189	H990930	IZP	7060,1	BL,BY,CNC,CTC,CVC,CBY,DSD,ICR,ICS, EIO	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15

Figure 148. Supported Hardware Report - Processors (Part 4 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 5

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
7060-H55	187	H010131	IZP	7060,2	BL,BY,CNC,CTC,CVC,CBY,OSA,FC,FCV, ICR,ICS,OSD,OSE	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15
7060-H70	189	H990930	IZP	7060,1	BL,BY,CNC,CTC,CVC,CBY,DSD,ICR,ICS, EIO	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15
7060-H75	187	H010131	IZP	7060,2	BL,BY,CNC,CTC,CVC,CBY,OSA,FC,FCV, ICR,ICS,OSD,OSE	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15
7060-P30	189	H990930	IZP	7060,1	BL,BY,CNC,CTC,CVC,CBY,DSD,ICR,ICS, EIO	Y	Y	Y	N	N	N	Y	256	8192	4096	36864	15
9021-330	045	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9021-340	045	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9021-500	046	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9021-520	052	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	3072	24576	7
9021-520	062	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	10
9021-580	046	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9021-620	047	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	2040	24440	7
9021-640	053	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	3072	24576	7
9021-640	063	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-660	054	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	3072	24576	7
9021-660	064	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-711	062	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	10
9021-711	072	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	116	6144	3072	24576	10
9021-711	086	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	80	6144	3072	24576	10
9021-720	047	229910	IXP	9021,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	2040	24440	7
9021-740	053	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	3072	24576	7
9021-740	063	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-820	051	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	256	6144	3072	24576	7
9021-820	061	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-821	063	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-821	073	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-821	087	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-822	064	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-822	074	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	232	6144	3072	24576	10
9021-822	088	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	160	6144	3072	24576	10
9021-831	063	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-831	073	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-831	087	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-832	065	228250	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	192	6144	3072	24576	10
9021-832	075	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	244	6144	3072	24576	10
9021-832	089	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	208	6144	3072	24576	10
9021-860	051	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	256	6144	3072	24576	7
9021-860	061	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-9X2	061	H950718	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-9X2	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-9X2	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-900	051	228110	IXP	9021,2	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	256	6144	3072	24576	7
9021-900	061	228150	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-941	063	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-941	073	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-941	087	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	10
9021-942	061	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-942	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-942	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-952	061	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-952	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-952	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-962	061	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-962	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-962	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-972	061	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-972	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-972	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-982	061	228215	IZP	9021,2	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-982	071	228270	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9021-982	085	236420	IZP	9021,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	N	N	N	N	N	256	6144	3072	24576	10
9121-180	035	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	32	6144	2040	24440	7
9121-190	035	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	32	6144	2040	24440	7
9121-210	036	C22822	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	48	6144	2040	24440	7
9121-260	036	C22822	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	48	6144	2040	24440	7
9121-311	032	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-311	038	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9121-311	094	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	64	6144	3072	24576	7

Figure 148. Supported Hardware Report - Processors (Part 5 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 6

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
9121-320	036	C22822	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	48	6144	2040	24440	7
9121-411	032	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-411	038	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9121-411	094	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-440	036	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	48	6144	2040	24440	7
9121-480	036	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	48	6144	2040	24440	7
9121-490	037	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	96	6144	2040	24440	7
9121-511	032	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-511	038	C35932	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9121-511	094	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-521	032	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-521	038	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9121-521	094	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-522	033	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-522	095	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-570	037	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	96	6144	2040	24440	7
9121-610	037	C23074	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	96	6144	2040	24440	7
9121-621	032	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-621	038	C35932	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	64	6144	2040	24440	7
9121-621	094	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	64	6144	3072	24576	7
9121-622	033	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-622	039	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	2040	24440	7
9121-622	095	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-732	033	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-732	039	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	2040	24440	7
9121-732	095	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-742	033	C35945	IZP	9121,1	BL,BY,CNC,CTC,CVC	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9121-742	039	C35936	IXP	9121,1	BL,BY,CNC,CTC,CVC	Y	N	N	N	N	N	N	128	6144	2040	24440	7
9121-742	095	C35954	IZP	9121,1	BL,BY,CNC,CTC,CVC,CFS,CBY,OSA	Y	Y	N	N	N	N	N	128	6144	3072	24576	7
9221-120	110	C85851	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	N	N	N	N	N	N	N	28	4096	2040	16344	4
9221-120	115	C86035	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	28	4096	2040	16344	4
9221-130	110	C85851	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	N	N	N	N	N	N	N	28	4096	2040	16344	4
9221-130	115	C86035	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	28	4096	2040	16344	4
9221-150	110	C85851	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	N	N	N	N	N	N	N	28	4096	2040	16344	4
9221-150	115	C86035	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	28	4096	2040	16344	4
9221-170	111	C85851	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	N	N	N	N	N	N	N	32	4096	2040	16344	4
9221-170	116	C86035	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-191	116	C86452	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-200	116	C86035	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-201	116	C86452	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-211	116	C86452	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-221	116	C86452	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9221-421	116	C86452	IXP	9221,1	BL,BY,CNC,CTC,CVC,IOC	Y	N	N	N	N	N	N	32	4096	2040	16344	4
9672-E01	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E02	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E03	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E04	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E05	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E06	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E07	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-E08	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-P01	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-P02	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-P03	160	H940318	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-RA2	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-RA4	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RA5	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RA6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RA6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RB4	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RB5	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RB6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RB6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RC4	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RC5	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15

Figure 148. Supported Hardware Report - Processors (Part 6 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 7

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
9672-RC6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RC6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RD6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RD6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RX3	162	H950426	IZP	9672,3	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	192	6144	3072	24576	10
9672-RX4	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RX5	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RX6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RX6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-RY4	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-RY5	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R06	181	H980730	IZP	9672,5	CFR,CFS,CBR,CBS,ICR,ICS	Y	Y	Y	N	N	Y	Y	32	8192	4096		15
9672-R11	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R12	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R14	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R15	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R16	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R16	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R21	160	H950303	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-R21	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R22	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R24	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R25	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R26	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R26	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R31	160	H950303	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-R31	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R32	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R34	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R35	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R36	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R36	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R41	160	H950303	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-R41	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R42	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R44	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R45	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R46	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R46	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R51	160	H950303	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-R51	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R52	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R53	162	H950426	IZP	9672,3	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	192	6144	3072	24576	10
9672-R54	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R55	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R56	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R56	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R61	160	H950303	IZP	9672,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	56	4096	2048	16384	10
9672-R61	163	H940623	IZP	9672,1	BL,BY,CNC,CTC,CVC,CBY,OSA	Y	Y	Y	N	N	N	Y	48	4096	2048	16384	10
9672-R63	162	H950426	IZP	9672,3	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	192	6144	3072	24576	10
9672-R64	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15

Figure 148. Supported Hardware Report - Processors (Part 7 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 8

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
9672-R65	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R66	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R66	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R72	161	H950425	IZP	9672,2	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	128	6144	3072	24576	10
9672-R73	162	H950426	IZP	9672,3	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	192	6144	3072	24576	10
9672-R74	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R75	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R76	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R76	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R83	162	H950426	IZP	9672,3	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	192	6144	3072	24576	10
9672-R84	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R85	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R86	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R86	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R94	166	H960703	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R95	169	H970610	IZP	9672,4	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	Y	256	6144	3072	24576	15
9672-R96	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-R96	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-T16	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-T16	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-T26	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-T26	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XX7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XX7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XY7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XY7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XZ7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-XZ7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X17	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X17	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X27	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X27	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X37	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X37	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X47	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X47	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X57	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X57	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X67	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15

Figure 148. Supported Hardware Report - Processors (Part 8 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 9

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
9672-X67	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X77	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X77	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X87	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X87	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X97	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-X97	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-YX6	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-YX6	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y16	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y16	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y26	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y26	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y36	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y36	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y46	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y46	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y56	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y56	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y66	180	H981015	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y66	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y76	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y76	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y86	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y86	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y96	180	H980730	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Y96	184	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZX7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZX7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZY7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZY7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZZ7	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-ZZ7	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z17	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15

Figure 148. Supported Hardware Report - Processors (Part 9 of 10)

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 10

TYPE-MODEL	MOD	SUPLEVID	IOCP	SYSTEM	SUPPORTED CHPID TYPES	DYN	MIF	PLEX	DCM	CAS	WI	RI	CHPID	CU	LCU	SUBCH	LPAR
9672-Z17	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z27	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z27	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z37	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z37	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z47	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z47	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z57	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z57	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z67	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z67	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z77	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z77	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z87	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z87	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z97	182	H990531	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9672-Z97	186	H991130	IZP	9672,6	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA, FC,FCV,CBR,CBS,ICR,ICS,OSD,OSE	Y	Y	Y	N	N	Y	Y	256	8192	4096	36864	15
9673-001	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-002	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-003	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-004	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-005	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-006	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-007	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9673-008	165	H941102	IZP	9673,1	BL,BY,CNC,CTC,CVC,CFR,CFS,CBY,OSA	Y	Y	Y	N	N	N	N	56	4096	2048	16384	10
9674-C01	171	H940318	IZP	9674,1	CFR	Y	Y	Y	N	N	N	Y	32	0	0		10
9674-C02	172	H950427	IZP	9674,2	CFR	Y	Y	Y	N	N	N	Y	32	0	0		10
9674-C03	173	H950427	IZP	9674,3	CFR	Y	Y	Y	N	N	N	Y	32	0	0		10
9674-C04	174	H960703	IZP	9674,4	CFR	Y	Y	Y	N	N	N	Y	32	0	0		10
9674-C05	175	H970610	IZP	9674,4	CFR	Y	Y	Y	N	N	N	Y	32	0	0		10

SUPPORTED HARDWARE - PROCESSORS TIME: 09:02 DATE: 2001-12-20 PAGE T- 11

KEY	KEY DESCRIPTION
TYPE-MODEL	- SUPPORTED PROCESSOR TYPE
MOD	- INDEX OF PROCESSOR SUPPORT MODULE
SUPLEVID	- SUPPORT LEVEL ID
IOCP	- PREFIX OF IOCP PROGRAM FOR THIS SUPPORT LEVEL
SYSTEM	- IOCP SYSTEM VALUE
SUPPORTED CHPID TYPES	- LIST OF CHANNEL PATH TYPES WHICH ARE SUPPORTED BY THIS CONTROL UNIT
DYN	- DYNAMIC SUPPORT
MIF	- SUPPORT OF SHARED CHANNEL PATHS (MIF)
PLEX	- PARALLEL SYSPLEX CAPABILITY
DCM	- DYNAMIC CHPID MANAGEMENT SUPPORT
CAS	- SUPPORT OF FICON 2-SWITCH CASCADED SWITCHING
WI	- WRITE IOCDS REGARDLESS OF CPC TYPE
RI	- RECEIVE IOCDS WRITTEN REGARDLESS OF CPC TYPE
CHPID	- MAXIMUM NUMBER OF SUPPORTED CHPIDS
CU	- MAXIMUM NUMBER OF ATTACHABLE CONTROL UNITS
LCU	- MAXIMUM NUMBER OF LOGICAL CONTROL UNITS
SUBCH	- MAXIMUM NUMBER OF SUBCHANNELS
LPAR	- MAXIMUM NUMBER OF LOGICAL PARTITIONS
Y	- PROCESSOR HAS THE CAPABILITY
N	- CAPABILITY IS NOT AVAILABLE

Figure 148. Supported Hardware Report - Processors (Part 10 of 10)

```
                                        SUPPORTED HARDWARE - CONTROL UNITS  (1)       TIME: 13:24  DATE: 2001-12-05  PAGE T-  13
TYPE-MODEL    UIM U PROTCL DP IO SUPPORTED CHPID TYPES      ATTACHABLE DEVICES
____________ ___ _ ______ __ __ ________________________ ____________________________________________________________________
AFP1          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1,AFP1-0,2710,3160,3170,3300,3825,3827,3828,3829,3831,3835,3900,3935,
                                                            4000,4370
CTC           014 N D      D  2  BL,CVC,EIO                 CTC,CTCA
DUMMY         050 N D,S,S4 D  2  BL,BY,CNC,CTC,CVC,CBY,FCV,
                                 EIO                        DUMMY
FCP           254 N              FCP                        FCP
FCTC          014 N           2  FC                         FCTC
NOCHECK       256 N D,S,S4 S  2  BL,BY,CNC,CTC,CVC,IOC,CBY,
                                 FC,FCV,EIO                 AFP1-0,BCTC,BSC1,BSC2,BSC3,CTC,CTCA,DUMMY,FB512,FCTC,HFGD,ICABSCA,
                                                            ICAELAN,ICAHDLC,ICAILAN,ICASDLC,ICATELE2,RS6K,SCTC,SWCH,TWX,WTTA,1030,
                                                            1050,1050X,115A,1287,1288,1403-N1,1403-2,1403-3,1403-5,1403-7,2032,
                                                            2250-3,2305-2,2501-B1,2501-B2,2540P-1,2540R-1,2701,2710,2740,2740C,
                                                            2741C,2741P,3088,3151,3160,3161,3162,3163,3167,3170,3172,3174,3178,3179,
                                                            3180,3180-1,3190,3191,3192,3192-F,3193,3194,3203-4,3203-5,3211,3216,
                                                            3251,3262-13,3262-3,3262-5,3268-2,3270,3270-X,3272,3274,3277-1,3277-2,
                                                            3278-1,3278-2,3278-2A,3278-3,3278-4,3278-5,3279-S2B,3279-S3G,3279-2,
                                                            3279-2A,3279-2B,3279-2C,3279-2X,3279-3,3279-3A,3279-3B,3279-3X,3284-1,
                                                            3284-2,3286-1,3286-2,3287-1,3287-1C,3287-2,3287-2C,3288,3289-1,3289-2,
                                                            3290,3300,3330-1,3330-11,3330-2,3330V,3333-1,3333-11,3340,3344,3350,
                                                            3350P,3351P,3370,3375,3380,3380-CJ2,3380A,3380B,3390,3390A,3390B,3420-3,
                                                            3420-4,3420-5,3420-6,3420-7,3420-8,3422,3423,3424,3430,3471,3472,3480,
                                                            3481,3482,3483,3490,3505,3525,3540,3590,3704,3705,3720,3725,3737,3745,
                                                            3746,3767-1,3767-2,3791L,3800-1,3800-3,3800-6,3800-8,3812,3816,3820,
                                                            3827,3828,3829,3831,3835,3851,3886,3890,3895,3900,3935,3995,3995-SDA,
                                                            3995-151,3995-153,4000,4224,4245,4248,4250,4370,5080,5081,5210,6090,
                                                            6262,7171,7770-3,8232,83B3,9032,9032-3,9032-5,9033,9332-40,9332-42,
                                                            9332-60,9332-62,9335-B1,9336-10,9336-20,9345,9348-1
OSA           058 N           2  OSA,OSD,OSE                OSA,OSAD
RS6K          056 N D,S,S4 S4 2  BL,CNC,CVC,FCV,EIO         RS6K,3274
RS6K-2        056 N           2  CNC,FCV                   RS6K
SCTC          014 N           2  CNC,CTC,FCV               BCTC,CTCA,SCTC
SWCH          051 Y           2  CNC,FCV                   SWCH
1287          032 N D      D  2  BL,BY,CVC,CBY,EIO          1287
1288          032 N D      D  2  BL,BY,CVC,CBY,EIO          1288
2032          051 Y           2  FC                         SWCH,2032
2105          002 Y S,S4   S  2  CNC,FC,FCV                 3380,3380A,3380B,3390,3390A,3390B,3420
2501          012 N D      D  2  BL,BY,CBY,EIO              2501
2701          024 N D      D  2  BL,BY,CVC,CBY,EIO          BSC1,BSC2,BSC3,TWX,WTTA,1030,1050,1050X,115A,2701,2740,2740C,2740X,2741,
                                                            2741C,2741P,3151,3161,3162,3163,3167,3767-1,3767-2,83B3
2710          022 N D,S,S4 S  2  BL,CNC,CVC,FCV,EIO         AFP1-0,2710
2821          012 N D      D  2  BL,BY,CVC,CBY,EIO          1403,2540,2540P-1,2540R-1
2835-2        269 N D      D  2  BL,CVC,EIO                 2305-2
2840-2        277 N D      D  2  BL,BY,CBY,EIO              2250-3
3088          014 N D,S,S4 S  2  BL,CVC,EIO                 CTC,CTCA,3088
3160          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,3160
3170          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,3170
3172          057 N D,S,S4 S4 2  BL,CNC,CVC,FCV,EIO         3172
3174          027 N D,S    D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  3151,3174,3178,3179,3180,3190,3191,3192,3193,3194,3262,3262-13,3262-3,
                                                            3268,3270,3270-X,3278,3279,3286,3287,3289,3290,3471,3472,3481,3482,3483,
                                                            3791L,3812,3816,4201,4202,4207,4208,4224,4234,4245-D12,4245-D20,4250,
                                                            5210
3203          012 N D      D  2  BL,BY,CVC,CBY,EIO          3203
3258          277 N D      D  1  BL,CVC,EIO                 2250-3,3250,3251
3262          268 N D      D  2  BL,BY,CVC,CBY,EIO          3262-5
3272          027 N D      D  2  BL,BY,CVC,CBY,EIO          3151,3178,3179,3180,3190,3191,3192,3193,3194,3262,3262-13,3262-3,3268,
                                                            3270,3270-X,3272,3274,3277,3278,3279,3284,3284-1,3284-2,3286,3287,3288,
                                                            3289,3290,3791L,3812,3816,4224,4234,4245-D12,4245-D20,4250,5210
3274          027 N D      D  2  BL,BY,CVC,CBY,EIO          3151,3178,3179,3180,3190,3191,3192,3193,3194,3262,3262-13,3262-3,3268,
                                                            3270,3270-X,3274,3277,3278,3279,3284,3284-1,3284-2,3286,3287,3288,3289,
                                                            3290,3471,3472,3481,3482,3483,3791L,3812,3816,4224,4234,4245-D12,
                                                            4245-D20,4250,5210
3300          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,3300
3380-CJ2      002 N S      S  2  BL,CVC,EIO                 3380,3380-CJ2
3422          005 N D,S    D  1  BL,CVC,EIO                 3422
3423          005 N D,S,S4 D  1  BL,CVC,EIO                 3423
3424          005 N S      S  2  BL,CVC,EIO                 3424
3430          005 N D      D  1  BL,CVC,EIO                 3430
3480          005 Y D,S,S4 S  2  BL,CNC,CVC,FCV,EIO         3480
```

Figure 149. Supported Hardware Report - Control Units (1) (Part 1 of 3)

```
                                        SUPPORTED HARDWARE - CONTROL UNITS  (1)       TIME: 13:24  DATE: 2001-12-05  PAGE T-  14
TYPE-MODEL    UIM U PROTCL DP IO SUPPORTED CHPID TYPES      ATTACHABLE DEVICES
_____________ ___ _ _______ __ __ ____________________ ____________________________________________________________________
3490          005 Y D,S,S4 S  2  BL,CNC,CVC,ISD,FC,FCV,EIO  3490
3490-C1A      005 Y D,S,S4 S  2  BL,CNC,CVC,FC,FCV,EIO      3490
3490-C10      005 Y D,S,S4 S  2  BL,CNC,CVC,ISD,FC,FCV,EIO  3490
3490-C11      005 Y D,S,S4 S  2  BL,CNC,CVC,ISD,FC,FCV,EIO  3490
3490-C2A      005 Y D,S,S4 S  2  BL,CNC,CVC,FC,FCV,EIO      3490
3490-C22      005 Y D,S,S4 S  2  BL,CNC,CVC,FC,FCV,EIO      3490
3505          012 N D      D  2  BL,BY,CVC,CBY,EIO          3505,3525
3540          032 N D      D  2  BL,BY,CVC,CBY,EIO          3540
3590          005 Y D,S,S4 S  2  BL,CNC,CVC,FC,FCV,EIO      3590
3704          023 N D      D  2  BY,CBY                     BSC1,BSC2,BSC3,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3151,3161,3162,3163,3167,3174,3232,3271,3274,3276,3704,3767-1,
                                                            3767-2,3791L,83B3
3705          023 N D      D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  BSC1,BSC2,BSC3,NCP,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3151,3161,3162,3163,3167,3174,3232,3271,3274,3276,3705,3767-1,
                                                            3767-2,3791L,83B3
3720          023 N D      D  2  BL,BY,CVC,CBY,EIO          BSC1,BSC2,BSC3,NCP,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3151,3161,3162,3163,3167,3174,3232,3271,3274,3276,3720,3767-1,
                                                            3767-2,3791L,83B3
3725          023 N D      D  2  BL,BY,CVC,CBY,EIO          BSC1,BSC2,BSC3,NCP,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3161,3162,3163,3167,3174,3232,3271,3274,3276,3725,3767-1,3767-2,
                                                            3791L,83B3
3737          014 N D,S    S  2  BL,CVC,EIO                 CTC,CTCA,3737
3745          023 N D,S    D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  BSC1,BSC2,BSC3,NCP,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3161,3162,3163,3167,3174,3232,3271,3274,3276,3745,3767-1,3767-2,
                                                            3791L,83B3
3746          023 N D,S    D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  BSC1,BSC2,BSC3,NCP,TWX,WTTA,1030,1050,1050X,115A,2740,2740C,2740X,2741C,
                                                            2741P,3174,3232,3271,3274,3276,3745,3767-1,3767-2,3791L,83B3
3791L         027 N D,S    D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  3151,3178,3179,3180,3190,3191,3192,3193,3194,3262,3262-13,3262-3,3268,
                                                            3270,3270-X,3272,3277,3278,3279,3284-1,3284-2,3286,3287,3288,3289,3290,
                                                            3791L,3812,3816,4224,4234,4245-D12,4245-D20,4250,5210
3800-1        011 N D,S    D  2  BL,BY,CVC,CBY,EIO          3800-1
3800-3        011 N D,S    D  2  BL,BY,CVC,CBY,EIO          AFP1,3800-3
3800-6        011 N D,S    D  2  BL,BY,CVC,CBY,EIO          AFP1,3800-6
3800-8        011 N D,S    D  2  BL,BY,CVC,CBY,EIO          AFP1,3800-8
3803          005 N D      D  1  BL,CVC,EIO                 3420
3811          012 N D      D  2  BL,BY,CVC,CBY,EIO          3211,3216
3820          022 N D,S4   D  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1,3820
3825          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1,AFP1-0,3825
3827          022 N D,S    S  2  BL,BY,CVC,CBY,EIO          AFP1,AFP1-0,3827
3828          022 N D,S    S  2  BL,BY,CVC,CBY,EIO          AFP1,AFP1-0,3828
3829          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,3829
3830-2        257 N D      D  2  BL,CVC,EIO                 3330-1,3330-11,3330-2,3333-1,3333-11,3340,3344,3350
3830-3        271 N D      D  2  BL,CVC,EIO                 3330-11,3330V,3350
3831          022 N D,S    S  2  BL,BY,CVC,CBY,EIO          AFP1-0,3831
3835          022 N D,S    S  2  BL,BY,CVC,CBY,EIO          AFP1,AFP1-0,3835
3851          271 N D      D  2  BL,BY,CVC,CBY,EIO          3851
3880-1        258 N D,S    S  2  BL,CVC,EIO                 3330-1,3330-11,3330-2,3333-1,3333-11,3340,3344,3350,3370,3375
3880-11       259 N D,S    S  2  BL,CVC,EIO                 3330-1,3330-11,3330-2,3333-1,3333-11,3340,3344,3350,3350P,3370,3375
3880-13       002 N D,S    S  2  BL,CVC,EIO                 3380
3880-2        002 N D,S    S  2  BL,CVC,EIO                 3330-1,3330-11,3330-2,3333-1,3333-11,3340,3350,3370,3375,3380
3880-21       259 N D,S,S4 S  2  BL,CVC,EIO                 3351P
3880-23       002 N D,S,S4 S  2  BL,CVC,EIO                 3380
3880-3        002 N D,S    S  2  BL,CVC,EIO                 3380
3880-4        258 N D,S    S  2  BL,CVC,EIO                 3375
3880P         259 N D,S,S4 S  2  BL,CVC,EIO                 3350P,3351P
3886          032 N D      D  2  BL,BY,CVC,CBY,EIO          3886
3890          032 N D      D  2  BL,BY,CVC,CBY,EIO          3890
3895          032 N D      D  2  BL,BY,CVC,CBY,EIO          3895
3900          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1,AFP1-0,3900
3935          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,3935
3990          002 Y S,S4   S  2  BL,CNC,CVC,ISD,DSD,FCV,EIO 12345678-4444,3380,3390
3990-1        002 N S      S  2  BL,CVC,EIO                 3380
3990-2        002 Y S,S4   S  2  BL,CNC,CVC,ISD,DSD,FCV,EIO 3380,3390
3990-3        002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         3380,3390
3990-6        002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         3380,3390
3995          053 Y D,S,S4 S4 2  BL,CNC,CVC,FCV,EIO         3995
3995-SDA      053 Y D,S,S4 S4 2  BL,CNC,CVC,FCV,EIO         3995
3995-151      002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         3995-151
```

Figure 149. Supported Hardware Report - Control Units (1) (Part 2 of 3)

```
                                    SUPPORTED HARDWARE - CONTROL UNITS  (1)       TIME: 13:24  DATE: 2001-12-05  PAGE T-  15
TYPE-MODEL    UIM U PROTCL DP IO SUPPORTED CHPID TYPES      ATTACHABLE DEVICES
___________ ___ _ ______ __ __ ___________________________ ______________________________________________________________
3995-153      002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         3995-153
4000          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,4000
4245          012 N D      D  2  BL,BY,CVC,CBY,EIO          4245
4248          012 N D      D  2  BL,BY,CVC,CBY,EIO          3262,4248,6262
4370          022 N D,S,S4 S  2  BL,BY,CNC,CVC,CBY,FCV,EIO  AFP1-0,4370
5088-1        291 N D,S    D  2  BL,CVC,EIO                 HFGD,3251,3279-2B,3279-3B,5080,5081,6090,6091
5088-2        291 N D,S    D  2  BL,CVC,EIO                 HFGD,3251,3279-2B,3279-3B,5080,5081,6090,6091
6098          291 N S,S4   S  2  BL,CVC,EIO                 HFGD,3251,3279-2B,3279-3B,5080,5081,6090,6091
6120          308 N           2  IOC                        3101,3151,3174,3178,3179,3180,3190,3191,3192,3193,3194,3262,3268,3270,
                                                             3277,3278,3279,3286,3287,3289,3290,3812,3816,4224,4245,4250,5210
6135          308 N           1  IOC                        ICAELAN
6139          308 N           1  IOC                        ICAILAN
6140          308 N           1  IOC                        ICAILAN
6241          308 N           1  IOC                        ICATELE2
6242          308 N           1  IOC                        ICATELE2
6243          308 N           1  IOC                        ICATELE2
6244          308 N           1  IOC                        ICATELE2
6251          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6252          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6253          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6254          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6255          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6256          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6257          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6258          308 N           1  IOC                        ICABSCA,ICAHDLC,ICASDLC,ICATELE2
6262          268 N D      D  2  BL,BY,CVC,CBY,EIO          6262
6310          308 N           2  IOC                        FB512,9332,9335,9336
6311          308 N           2  IOC                        9348
7171          027 N D      D  2  BL,CVC,EIO                 3161,3162,3163,3277,3278,3279,3286,3791L,7171
7770-3        023 N D      D  2  BY,CBY                     7770-3
8232          014 N D,S,S4 S  2  BL,CVC,EIO                 8232
9032          051 Y           2  CNC                        SWCH,9032
9032-3        051 Y           2  CNC                        SWCH,9032-3
9032-5        051 Y           2  CNC,FCV                    SWCH,9032-5
9033          051 Y           2  CNC                        SWCH,9033
9340          002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         9345
9341          002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         9345
9343          002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         9345
9343-1        002 Y S,S4   S  2  BL,CNC,CVC,FCV,EIO         9345
                                    SUPPORTED HARDWARE - CONTROL UNITS  (1)       TIME: 13:24  DATE: 2001-12-05  PAGE T-  16
        KEY                       KEY DESCRIPTION
        ---                       ---------------
        TYPE-MODEL              - SUPPORTED CONTROL UNIT TYPE
        UIM                     - INDEX OF UNIT INFORMATION MODULE SUPPORTING THIS CONTROL UNIT TYPE
        U                       - If Y, INDICATES THAT THE UNIT ADDRESS RANGE MUST START WITH 00
                                  WHEN THE CONTROL UNIT IS CONNECTED TO AN ESCON CHANNEL PATH
        DP                      - DEFAULT PROTOCOL FOR PARALLEL CONTROL UNIT
        IO                      - DEFAULT I/O CONCURRENCY LEVEL FOR PARALLEL CONTROL UNIT
        PROTCL                  - PROTOCOL SUPPORTED BY THE CONTROL UNIT TYPE
        SUPPORTED CHPID TYPES   - LIST OF CHANNEL PATH TYPES WHICH ARE SUPPORTED BY THIS CONTROL UNIT TYPE
        ATTACHABLE DEVICES      - LIST OF ATTACHABLE DEVICE TYPES
```

Figure 149. Supported Hardware Report - Control Units (1) (Part 3 of 3)

SUPPORTED HARDWARE - CONTROL UNITS (2) TIME: 13:24 DATE: 2001-12-05 PAGE T- 17

--CONTROL UNIT-- TYPE-MODEL	MD	-ATTACHMENT COUNTS-- CHPMAX	DEVMIN	DEVMAX	-UNIT ADDRESSES-- MIN	MAX	REC	RANGE	----LOGICAL ADDRESSING--- LA	MIN	MAX	MULTHOST	MAXCU	--------LOGICAL PATH -------- MAXPATH	MINGRP	SH	MXESC	MXFIC	DCM
AFP1	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
CTC	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
DUMMY	-	-	-	-	-	-	-	-	Y	0	F	N	-	-	-	-			N
FCP	-	1	-	-	-	256	256	1	N	-	-	-	-	-	-	-			N
FCTC	-	1	-	-	-	-	-	-	Y	-	-	Y	-	-	-	-			N
NOCHECK	-	8	-	-	-	-	-	-	Y	00	FE	Y	-	-	-	-			Y
OSA	-	1	1	255	-	-	-	1	N	-	-	-	-	-	-	-			N
RS6K	-	1	-	-	-	-	-	-	Y	-	-	Y	-	-	-	-			N
RS6K-2	N	1	-	-	-	-	-	-	Y	-	-	Y	-	-	-	-			N
SCTC	-	1	-	-	-	-	-	-	Y	-	-	Y	-	-	-	-			N
SWCH	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
1287	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
1288	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
2032	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
2105	-	-	-	256	-	-	-	-	Y	00	FE	Y	-	2048	2	-	64		Y
2501	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
2701	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
2710	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
2821	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
2835-2	N	-	-	2	-	-	16	-	N	-	-	-	-	-	-	-			N
2840-2	N	-	-	4	-	-	-	-	N	-	-	-	-	-	-	-			N
3088	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3160	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3170	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3172	-	2	-	-	-	-	-	-	Y	-	-	Y	-	-	-	-			N
3174	-	-	-	256	-	-	32	-	Y	0	F	Y	8	-	-	-			N
3203	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3258	-	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
3262	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
3272	-	-	-	32	-	-	32	-	N	-	-	-	-	-	-	-			N
3274	-	-	-	32	-	-	-	-	N	-	-	-	-	-	-	-			N
3300	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3380-CJ2	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3422	-	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
3423	-	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
3424	-	-	-	8	-	-	8	-	N	-	-	-	-	-	-	-			N
3430	-	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
3480	-	-	-	16	16	16	-	-	N	-	-	-	-	-	-	-			N
3490	-	-	-	16	16	16	-	-	Y	00	FE	Y	-	-	-	-			N
3490-C1A	N	-	-	16	2	16	-	-	Y	00	FE	Y	-	-	-	-			N
3490-C10	N	-	-	16	2	16	-	-	Y	00	FE	Y	-	-	-	-			N
3490-C11	N	-	-	16	2	16	-	-	Y	00	FE	Y	-	-	-	-			N
3490-C2A	N	-	-	16	2	16	-	-	Y	00	FE	Y	-	-	-	-			N
3490-C22	N	-	-	16	2	16	-	-	Y	00	FE	Y	-	-	-	-			N
3505	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3540	-	-	-	2	-	-	-	-	N	-	-	-	-	-	-	-			N
3590	-	-	-	16	1	16	-	-	Y	00	FE	Y	-	-	-	-			N
3704	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3705	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3720	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3725	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3737	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3745	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3746	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3791L	-	-	-	256	-	-	32	-	Y	0	F	Y	8	-	-	-			N
3800-1	Y	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3800-3	N	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3800-6	N	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3800-8	N	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3803	-	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
3811	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
3820	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
3825	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3827	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3828	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3829	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3830-2	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N

Figure 150. Supported Hardware Report - Control Units (2) (Part 1 of 3)

--CONTROL UNIT-- TYPE-MODEL	MD	-ATTACHMENT COUNTS-- CHPMAX	DEVMIN	DEVMAX	-UNIT ADDRESSES-- MIN	MAX	REC	RANGE	----LOGICAL ADDRESSING--- LA	MIN	MAX	MULTHOST	MAXCU	--------LOGICAL PATH -------- MAXPATH	MINGRP	SH	MXESC	MXFIC	DCM
3830-3	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3831	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3835	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3851	-	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-1	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-11	N	-	-	64	-	-	32	-	N	-	-	-	-	-	-	-			N
3880-13	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-2	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-21	N	-	-	64	-	-	16	-	N	-	-	-	-	-	-	-			N
3880-23	Y	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-3	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880-4	N	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3880P	-	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
3886	-	-	-	2	-	-	-	-	N	-	-	-	-	-	-	-			N
3890	-	-	-	2	-	-	-	-	N	-	-	-	-	-	-	-			N
3895	-	-	-	2	-	-	-	-	N	-	-	-	-	-	-	-			N
3900	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3935	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
3990	-	-	-	-	-	-	-	-	Y	0	F	Y	-	-	-	-			Y
3990-1	N	-	-	64	-	-	-	-	N	-	-	-	-	8	8	-			N
3990-2	N	-	-	256	-	-	-	-	Y	0	F	Y	-	16	8	-			Y
3990-3	N	-	-	64	-	-	-	-	Y	0	F	Y	-	16	8	-			Y
3990-6	N	-	-	256	-	-	-	-	Y	0	F	Y	-	128	8	-			Y
3995	-	2	-	-	-	-	-	-	N	-	-	-	-	-	-	Y			N
3995-SDA	N	2	-	256	2	256	16	1	N	-	-	-	-	-	-	Y			N
3995-151	N	-	-	96	-	-	-	-	Y	0	F	Y	-	-	-	-			Y
3995-153	N	-	-	96	-	-	-	-	Y	0	F	Y	-	-	-	-			Y
4000	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
4245	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
4248	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
4370	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
5088-1	N	-	-	16	-	-	-	-	N	-	-	-	-	-	-	-			N
5088-2	Y	-	-	32	-	-	-	-	N	-	-	-	-	-	-	-			N
6098	-	-	-	192	-	-	-	-	N	-	-	-	-	-	-	-			N
6120	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6135	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6139	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6140	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6241	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6242	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6243	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6244	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6251	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6252	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6253	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6254	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6255	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6256	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6257	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6258	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
6262	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
6310	-	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
6311	-	-	-	64	-	-	-	-	N	-	-	-	-	-	-	-			N
7171	-	-	-	64	-	-	32	-	N	-	-	-	-	-	-	-			N
7770-3	N	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
8232	-	-	-	-	-	-	-	-	N	-	-	-	-	-	-	-			N
9032	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
9032-3	N	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
9032-5	N	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
9033	-	-	-	1	-	-	-	-	N	-	-	-	-	-	-	-			N
9340	-	-	-	256	-	-	-	-	N	-	-	-	-	64	64	-			Y
9341	-	-	-	16	-	-	-	-	N	-	-	-	-	2	2	-			Y
9343	-	-	-	64	-	-	-	-	N	-	-	-	-	64	64	-			Y
9343-1	N	-	-	64	-	-	-	-	N	-	-	-	-	64	64	-			Y

Figure 150. Supported Hardware Report - Control Units (2) (Part 2 of 3)

```
                                  SUPPORTED HARDWARE - CONTROL UNITS  (2)       TIME: 13:24  DATE: 2001-12-05  PAGE T-  19
KEY                       KEY DESCRIPTION
---                       ---------------
TYPE-MODEL              -  SUPPORTED CONTROL UNIT TYPE
MD                      -  IF Y, MODEL IS DEFAULT
ATTACHMENT CNT CHPMAX -  MAXIMUM NUMBER OF CHANNEL PATHS THAT CAN BE CONNECTED TO C/U
               DEVMIN -  MINIMUM NUMBER OF DEVICES THAT MUST BE CONNECTED TO C/U
               DEVMAX -  MAXIMUM NUMBER OF DEVICES THAT CAN BE CONNECTED TO C/U
UNIT ADDRESSES    MIN -  MINIMUM NUMBER OF UNIT ADDRESSES THAT MUST BE DEFINED TO C/U
                  MAX -  MAXIMUM NUMBER OF UNIT ADDRESSES THAT CAN BE DEFINED TO C/U
                  REC -  RECOMMENDED NUMBER OF UNIT ADDRESSES
                RANGE -  MAXIMUM NUMBER OF UNIT ADDRESS RANGES THAT CAN BE DEFINED TO C/U
LOGICAL ADDRESSING LA -  IF Y, C/U SUPPORTS LOGICAL ADDRESSING (CUADD)
                  MIN -  MINIMUM VALUE OF ALLOWED LOGICAL ADDRESS (CUADD)
                  MAX -  MAXIMUM VALUE OF ALLOWED LOGICAL ADDRESS (CUADD)
             MULTHOST -  IF Y, MULTIPLE HOSTS CAN CONNECT TO THE SAME LOGICAL ADDRESS (CUADD)
               MAXCU -  MAXIMUM NUMBER OF LOGICAL CONTROL UNITS SUPPORTED (CUADD)
LOGICAL PATHS MAXPATH -  MAXIMUM NUMBER OF LOGICAL PATHS SUPPORTED BY C/U
               MINGRP -  MINIMUM GROUP ATTACHMENT VALUE FOR LOGICAL PATHS
                   SH -  IF Y, ONLY SINGLE HOST CAN ATTACH TO CONTROL UNIT AT A TIME
                MXESC -  MAXIMUM NUMBER OF LOGICAL PATHS PER ESCON PORT
                MXFIC -  MAXIMUM NUMBER OF LOGICAL PATHS PER FICON PORT
DCM                     -  DYNAMIC CHPID MANGEMENT SUPPORT

Y                       -  CONTROL UNIT HAS THE CAPABILITY
N                       -  CONTROL UNIT DOES NOT HAVE THE CAPABILITY
-                       -  UIM DOES NOT DEFINE A VALUE OR VALUE IS NOT APPLICABLE
```

Figure 150. Supported Hardware Report - Control Units (2) (Part 3 of 3)

SUPPORTED HARDWARE - DEVICES TIME: 13:24 DATE: 2001-12-05 PAGE T- 20

TYPE-MODEL	UIM	MVS	VM	MX	GR	RL	RH	RD	TM	ST	ATTACHABLE TO CU
AFP1-0	022	Y	Y	N	N	1	4095	1	Y	Y	AFP1,NOCHECK,2710,3160,3170,3300,3800-3,3800-6,3800-8,3820,3825,3827,3828,3829, 3831,3835,3900,3935,4000,4370
BCTC	014	Y	Y	N	N	1	4095	1	N	Y	NOCHECK,SCTC
BSC1	026	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
BSC2	026	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
BSC3	026	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
CTC	014	Y	Y	N	N	1	4095	1	N	Y	CTC,NOCHECK,3088,3737
CTCA	270	N	Y	N	N	1	4095	1	N	Y	CTC,NOCHECK,SCTC,3088,3737
DUMMY	050	Y	Y	N	N	1	4095	1	Y	Y	DUMMY,NOCHECK
FB512	258	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6310
FCP	254	N	N	N	N	1	4095	1	N	N	FCP
FCTC	014	Y	N	N	N	1	4095	1	N	Y	FCTC,NOCHECK
HFGD	291	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,5088-1,5088-2,6098
ICABSCA	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6251,6252,6253,6254,6255,6256,6257,6258
ICAELAN	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6135
ICAHDLC	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6251,6252,6253,6254,6255,6256,6257,6258
ICAILAN	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6139,6140
ICASDLC	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6251,6252,6253,6254,6255,6256,6257,6258
ICATELE2	308	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,6241,6242,6243,6244,6251,6252,6253,6254,6255,6256,6257,6258
OSA	058	Y	N	N	N	1	4095	2	N	Y	OSA
OSAD	058	Y	N	N	N	1	4095	1	N	Y	OSA
RS6K	056	Y	Y	N	N	1	4095	1	N	Y	NOCHECK,RS6K,RS6K-2
SCTC	014	Y	Y	N	N	1	4095	1	N	Y	NOCHECK,SCTC
SWCH	051	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,SWCH,2032,9032,9032-3,9032-5,9033
TWX	025	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
WTTA	025	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
1030	024	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
1050	024	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
1050X	024	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
115A	024	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
1287	032	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,1287
1288	032	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,1288
1403-N1	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
1403-2	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
1403-3	268	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
1403-5	268	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
1403-7	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
2032	051	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,2032
2250-3	277	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2840-2,3258
2305-2	269	N	Y	Y	N	1	1	1	Y	Y	NOCHECK,2835-2
2501-B1	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2501
2501-B2	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2501
2540P-1	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
2540R-1	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2821
2701	279	N	Y	N	N	1	4095	1	Y	N	NOCHECK,2701
2710	022	Y	N	N	N	1	4095	1	Y	Y	AFP1,NOCHECK,2710
2740	024	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
2740C	024	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
2740X	024	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
2741C	025	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
2741P	025	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,3746
3088	014	Y	Y	N	N	1	4095	32	N	Y	NOCHECK,3088
3151	281	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3174,3272,3274,3704,3705,3720,3791L,6120
3160	022	Y	N	N	N	1	4095	1	Y	Y	AFP1,NOCHECK,3160
3161	281	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,7171
3162	281	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,7171
3163	281	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745,7171
3167	281	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,2701,3704,3705,3720,3725,3745
3170	022	Y	N	N	N	1	4095	1	Y	Y	AFP1,NOCHECK,3170
3172	057	Y	N	N	N	1	4095	1	N	Y	NOCHECK,3172
3174	027	Y	Y	N	N	1	4095	1	Y	N	NOCHECK,3174,3704,3705,3720,3725,3745,3746,6120
3178	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3179	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3180	260	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3180-1	004	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3190	260	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3191	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3192	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120

Figure 151. Supported Hardware Report - Devices (Part 1 of 4)

SUPPORTED HARDWARE - DEVICES TIME: 13:24 DATE: 2001-12-05 PAGE T- 21

TYPE-MODEL	UIM	MVS	VM	MX	GR	RL	RH	RD	TM	ST	ATTACHABLE TO CU
3192-F	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3193	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3194	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3203-4	012	Y	N	N	N	1	4095	1	Y	Y	NOCHECK,3203
3203-5	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3203
3211	012	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3811
3216	278	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3811
3250	277	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3258
3251	277	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3258,5088-1,5088-2,6098
3262-13	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,4248,6120
3262-3	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,4248,6120
3262-5	268	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3262,3272,3274,3791L,4248,6120
3268-2	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3270	260	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3270-X	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3272	027	Y	N	N	N	1	4095	1	Y	N	NOCHECK,3272,3791L
3274	027	Y	Y	N	N	1	4095	1	Y	N	NOCHECK,RS6K,3272,3274,3704,3705,3720,3725,3745,3746
3277-1	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3272,3274,3791L,6120,7171
3277-2	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3272,3274,3791L,6120,7171
3278-1	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3278-2	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3278-2A	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3278-3	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3278-4	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3278-5	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-S2B	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-S3G	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-2	260	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-2A	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-2B	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,5088-1,5088-2,6098,6120,7171
3279-2C	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-2X	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-3	260	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-3A	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3279-3B	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,5088-1,5088-2,6098,6120,7171
3279-3X	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3284-1	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3272,3274,3791L
3284-2	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3272,3274,3791L
3286-1	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3286-2	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120,7171
3287-1	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3287-1C	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3287-2	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3287-2C	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3288	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3272,3274,3791L
3289-1	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3289-2	031	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3290	004	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,3174,3272,3274,3791L,6120
3300	022	Y	N	N	N	1	4095	1	Y	Y	AFP1,NOCHECK,3300
3330-1	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11,3880-2
3330-11	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3830-3,3880-1,3880-11,3880-2
3330-2	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11,3880-2
3330V	271	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3830-3
3333-1	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11,3880-2
3333-11	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11,3880-2
3340	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11,3880-2
3344	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3880-1,3880-11
3350	257	N	Y	N	N	1	4095	2	Y	Y	NOCHECK,3830-2,3830-3,3880-1,3880-11,3880-2
3350P	259	N	Y	Y	N	2	8	2	Y	Y	NOCHECK,3880-11,3880P
3351P	259	N	Y	Y	N	2	4	2	Y	Y	NOCHECK,3880-21,3880P
3370	258	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3880-1,3880-11,3880-2
3375	258	N	Y	N	N	1	4095	1	Y	Y	NOCHECK,3880-1,3880-11,3880-2,3880-4
3380	002	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2105,3380-CJ2,3880-13,3880-2,3880-23,3880-3,3990,3990-1,3990-2,3990-3, 3990-6
3380-CJ2	002	Y	Y	N	N	1	4095	1	Y	Y	NOCHECK,2105,3380-CJ2,3880-13,3880-2,3880-23,3880-3,3990,3990-1,3990-2,3990-3, 3990-6
3380A	002	Y	N	Y	N	1	4095	1	Y	Y	NOCHECK,2105
3380B	002	Y	N	Y	N	1	4095	1	Y	Y	NOCHECK,2105

Figure 151. Supported Hardware Report - Devices (Part 2 of 4)

```
                                        SUPPORTED HARDWARE - DEVICES                TIME: 13:24  DATE: 2001-12-05  PAGE T-  22
TYPE-MODEL    UIM MVS VM  MX GR RL RH   RD TM ST ATTACHABLE TO CU
_____________ ___ ___ __  __ __ __ ____ __ __ __ ______________________________________________________________________________
3390          002  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3990,3990-2,3990-3,3990-6
3390A         002  Y  N  Y  N  1 4095  1 Y  Y  NOCHECK,2105
3390B         002  Y  N  Y  N  1 4095  1 Y  Y  NOCHECK,2105
3420-3        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3420-4        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3420-5        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3420-6        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3420-7        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3420-8        005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,2105,3803
3422          005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3422
3423          005  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3423
3424          005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3424
3430          005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3430
3471          004  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3274
3472          004  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3274
3480          005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3480
3481          004  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3274
3482          004  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3274
3483          004  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3274
3490          005  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3490,3490-C1A,3490-C10,3490-C11,3490-C2A,3490-C22
3505          012  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3505
3525          012  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3505
3540          032  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3540
3590          005  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3590
3704          023  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3704
3705          023  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3705
3720          023  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3720
3725          023  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3725
3737          014  Y  Y  N  N  1 4095  1 N  Y  NOCHECK,3737
3745          023  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3745,3746
3746          023  Y  N  N  N  1 4095  1 Y  N  NOCHECK
3767-1        024  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,2701,3704,3705,3720,3725,3745,3746
3767-2        024  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,2701,3704,3705,3720,3725,3745,3746
3791L         027  Y  N  N  N  1 4095  1 Y  N  NOCHECK,3174,3272,3274,3704,3705,3720,3725,3745,3746,3791L,7171
3800-1        011  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3800-1
3800-3        011  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3800-3
3800-6        011  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3800-6
3800-8        011  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3800-8
3812          031  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3174,3272,3274,3791L,6120
3816          287  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,3174,3272,3274,3791L,6120
3820          022  Y  Y  N  N  1 4095  1 Y  N  NOCHECK,3820
3825          022  Y  Y  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3825
3827          022  Y  Y  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3827
3828          022  Y  Y  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3828
3829          022  Y  N  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3829
3831          022  Y  N  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3831
3835          022  Y  Y  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3835
3851          271  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,3851
3886          032  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3886
3890          032  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3890
3895          032  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3895
3900          022  Y  Y  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3900
3935          022  Y  N  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,3935
3995          053  Y  Y  N  Y  1    1  1 N  Y  NOCHECK,3995,3995-SDA
3995-SDA      053  Y  N  N  N  1  256 16 N  Y  NOCHECK,3995-SDA
3995-151      002  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3995-SDA,3995-151
3995-153      002  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3995-SDA,3995-153
4000          022  Y  N  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,4000
4224          031  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3174,3272,3274,3791L,6120
4245          012  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,4245,6120
4248          012  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,4248
4250          031  Y  N  N  N  1 4095  1 Y  Y  NOCHECK,3174,3272,3274,3791L,6120
4370          022  Y  N  N  N  1 4095  1 Y  Y  AFP1,NOCHECK,4370
5080          291  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,5088-1,5088-2,6098
5081          291  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,5088-1,5088-2,6098
5210          031  Y  Y  N  N  1 4095  1 Y  Y  NOCHECK,3174,3272,3274,3791L,6120
6090          291  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,5088-1,5088-2,6098
6091          291  N  Y  N  N  1 4095  1 Y  Y  NOCHECK,5088-1,5088-2,6098
```

Figure 151. Supported Hardware Report - Devices (Part 3 of 4)

```
                                    SUPPORTED HARDWARE - DEVICES                  TIME: 13:24  DATE: 2001-12-05  PAGE T-  23
TYPE-MODEL    UIM MVS VM  MX GR RL RH   RD TM ST ATTACHABLE TO CU
____________ ___ ___ __  __ __ __ ____ __ __ __ ____________________________________________________________________________
6262         268  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,4248,6262
7171         027  Y   Y  N  N   1 4095  1 Y  N  NOCHECK,7171
7770-3       023  Y   N  N  N   1 4095  1 Y  N  NOCHECK,7770-3
8232         014  Y   Y  N  N   1 4095 32 N  Y  NOCHECK,8232
83B3         025  Y   N  N  N   1 4095  1 Y  Y  NOCHECK,2701,3704,3705,3720,3725,3745,3746
9032         051  Y   Y  N  N   1 4095  1 Y  Y  NOCHECK,9032
9032-3       051  Y   N  N  N   1 4095  1 Y  Y  NOCHECK,9032,9032-3
9032-5       051  Y   N  N  N   1 4095  1 Y  Y  NOCHECK,9032,9032-5
9033         051  Y   Y  N  N   1 4095  1 Y  Y  NOCHECK,9033
9332-40      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9332-42      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9332-60      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9332-62      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9335-B1      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9336-10      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9336-20      258  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6310
9345         002  Y   Y  N  N   1 4095  1 Y  Y  NOCHECK,9340,9341,9343,9343-1
9348-1       261  N   Y  N  N   1 4095  1 Y  Y  NOCHECK,6311
                                    SUPPORTED HARDWARE - DEVICES                  TIME: 13:24  DATE: 2001-12-05  PAGE T-  24
        KEY                 KEY DESCRIPTION
        ---                 ---------------
        TYPE-MODEL        - SUPPORTED DEVICE TYPE
        UIM               - INDEX OF UNIT INFORMATION MODULE SUPPORTING THIS DEVICE TYPE
        MVS               - DEVICE IS SUPPORTED FOR MVS DEFINITION
        VM                - DEVICE TYPE IS SUPPORTED FOR VM DEFINITION
        MX                - DEVICE IS A MULTI-EXPOSURE DEVICE OR A PARALLEL  ACCESS VOLUME DEVICE
        GR                - DEVICE IS A GROUP DEVICE
        RL                - MINIMUM NUMBER OF DEVICES TO BE DEFINED
        RH                - MAXIMUM NUMBER OF DEVICES TO BE DEFINED
        RD                - DEFAULT NUMBER OF DEVICES TO BE DEFINED
        TM                - DEFAULT TIMEOUT VALUE
        ST                - DEFAULT STADET VALUE
        ATTACHABLE TO CU  - LIST OF CONTROL UNIT TYPES TO WHICH DEVICE TYPE IS ATTACHABLE
        Y                 - DEVICE TYPE HAS THE CAPABILITY
        N                 - CAPABILITY IS NOT AVAILABLE
```

Figure 151. Supported Hardware Report - Devices (Part 4 of 4)

```
                                    SUPPORTED HARDWARE - MVS DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  25
TYPE-MODEL    UIM GENERIC  DPREF DYN 4DIG UCB NIP SUPPORTED PARAMETERS (VALUES) / FEATURES
____________ ___ ________ _____ ___ ____ ___ ___ ____________________________________________________________________________
AFP1-0        022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
BCTC          014 BCTC      8350  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
BSC1          026 AAA9      6900  N   N    N   N  (R)ADAPTER(BSCA),FEATURE,OFFLINE,(R)TCU(2701,2702,2703) / DUALCODE,DUALCOMM
BSC2          026 AAAA      7000  N   N    N   N  (R)ADAPTER(BSCA),FEATURE,OFFLINE,(R)TCU(2701,2702,2703) / AUTOANSR,AUTOCALL,
                                                   DUALCODE,DUALCOMM
BSC3          026 AAAB      7100  N   N    N   N  (R)ADAPTER(BSCA),FEATURE,OFFLINE,(R)TCU(2701,2702,2703) / AUTOPOLL,DUALCODE,
                                                   DUALCOMM
CTC           014 CTC       8400  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / 370
DUMMY         050 DUMMY    99991  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
FCTC          014 FCTC      8301  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
OSA           058 OSA       8360  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
OSAD          058 OSAD      8361  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
RS6K          056 RS6K      8389  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
SCTC          014 SCTC      8300  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
SWCH          051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
TWX           025 AAA7      6700  N   N    N   N  (R)ADAPTER(TELE2),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR,AUTOCALL
WTTA          025 AAAD      7300  N   N    N   N  (R)ADAPTER(TELEW),OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,2703)
1030          024 AAA1      6100  N   N    N   N  (R)ADAPTER(IBM2),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOPOLL
1050          024 AAA2      6200  N   N    N   N  (R)ADAPTER(IBM1,IBMT),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOPOLL,AUTOANSR,AUTOCALL
1050X         024 AAAG      9700  N   N    N   N  (R)ADAPTER(IBM1,IBMT),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR,AUTOCALL
115A          024 AAA5      6500  N   N    N   N  (R)ADAPTER(TELE1),OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,2703)
1287          032 1287      5000  N   N    N   N  OFFLINE
1288          032 1288      5100  N   N    N   N  OFFLINE
1403-N1       012 1403      2100  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / UNVCHSET
1403-2        012 1403      2100  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / UNVCHSET
1403-7        012 1403      2100  Y   Y    N   N  OFFLINE,DYNAMIC
2032          051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
2501-B1       012 2501      2300  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE
2501-B2       012 2501      2300  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE
2540P-1       012 2540-2    2900  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE
2540R-1       012 2540      2800  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE
2710          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
2740          024 AAA8      6800  N   N    N   N  (R)ADAPTER(IBM1),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOPOLL,AUTOANSR,AUTOCALL,CHECKING,INTERRUPT,OIU,SCONTROL,XCONTROL
2740C         024 AAAI      9900  N   N    N   N  (R)ADAPTER(IBM1),(R)FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR,AUTOCALL,CHECKING
2740X         024 AAAH      9800  N   N    N   N  (R)ADAPTER(IBM1),(R)FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR,AUTOCALL,CHECKING
2741C         025 AAAF      7500  N   N    N   N  (R)ADAPTER(IBM1),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR
2741P         025 AAAE      7400  N   N    N   N  (R)ADAPTER(IBM1),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                   2703) / AUTOANSR
3088          014 CTC       8400  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / 370
3160          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3170          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3172          057 3172      8398  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
3174          027 3174      7650  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3178          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                   KB70KEY,KB78KEY,KB81KEY
3179          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                   KB70KEY,KB78KEY,KB81KEY
3180-1        004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                   KB70KEY,KB78KEY,KB81KEY
3191          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                   KB70KEY,KB78KEY,KB81KEY
3192          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                   KB70KEY,KB78KEY,KB81KEY
3192-F        004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                   UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
```

Figure 152. Supported Hardware Report - MVS Devices (Part 1 of 4)

```
                                        SUPPORTED HARDWARE - MVS DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  26
TYPE-MODEL    UIM GENERIC  DPREF DYN 4DIG UCB NIP SUPPORTED PARAMETERS (VALUES) / FEATURES
____________ ___ ________ _____ ___ ____ ___ ___ ____________________________________________________________________________
                                                  KB70KEY,KB78KEY,KB81KEY
3193         004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3194         004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3203-4       012 3203      2000  Y   Y    N   N  OFFLINE,DYNAMIC
3203-5       012 3203      2000  Y   Y    N   N  OFFLINE,DYNAMIC
3211         012 3211      1900  Y   Y    N   N  OFFLINE,DYNAMIC
3262-13      031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3262-3       031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3268-2       031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3270-X       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3272         027 3791L     7700  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3274         027 3274      7675  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3277-1       004 3277-1    3700  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3277-2       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-1       004 3277-1    3700  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-2       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-2A      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-3       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-4       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3278-5       004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-S2B     004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-S3G     004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-2A      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-2B      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-2C      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-2X      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-3A      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-3B      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3279-3X      004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
```

Figure 152. Supported Hardware Report - MVS Devices (Part 2 of 4)

```
                                   SUPPORTED HARDWARE - MVS DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  27
TYPE-MODEL    UIM GENERIC  DPREF DYN 4DIG UCB NIP SUPPORTED PARAMETERS (VALUES) / FEATURES
_____________ ___ ________ _____ ___ ____ ___ ___ ____________________________________________________________________________
                                                  KB70KEY,KB78KEY,KB81KEY
3284-1        031 3284-1    4100  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3284-2        031 3284-2    4200  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3286-1        031 3286-1    4300  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3286-2        031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3287-1        031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3287-1C       031 3286-1    4300  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3287-2        031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3287-2C       031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3288          031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3289-1        031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3289-2        031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3290          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3300          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3380          002 3380       290  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
3380-CJ2      002 3380       290  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
3380A         002 3380       290  Y   Y    Y   N  PRIVATE: WLMPAV
3380B         002 3380       290  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY,PRIVATE: WLMPAV / SHARED,SHAREDUP
3390          002 3390       280  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
3390A         002 3390       280  Y   Y    Y   N  PRIVATE: WLMPAV
3390B         002 3390       280  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY,PRIVATE: WLMPAV / SHARED,SHAREDUP
3420-3        005 3400-3    1210  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / DATACONV,DUALDENS,SHARABLE,7-TRACK,9-TRACK
3420-4        005 3400-5    1200  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARABLE,9-TRACK,OPT1600
3420-5        005 3400-3    1210  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / DATACONV,DUALDENS,SHARABLE,7-TRACK,9-TRACK
3420-6        005 3400-5    1200  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARABLE,9-TRACK,OPT1600
3420-7        005 3400-3    1210  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / DATACONV,DUALDENS,SHARABLE,7-TRACK,9-TRACK
3420-8        005 3400-5    1200  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARABLE,9-TRACK,OPT1600
3422          005 3400-6    1220  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARABLE,9-TRACK,OPT1600
3423          005 3423      1380  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
3424          005 3400-6    1220  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARABLE
3430          005 3400-6    1220  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / 9-TRACK,OPT1600
3471          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3472          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3480          005 3480      1100  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY,PRIVATE: LIBRARY,AUTOSWITCH,LIBRARY-ID,LIBPORT-ID,
                                                  MTL / SHARABLE,COMPACT
3481          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3482          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3483          004 3277-2    3800  Y   Y    Y   Y  FEATURE,OFFLINE,DYNAMIC,LOCANY / ASCACHAR,ASCBCHAR,DOCHAR,FRCHAR,GRCHAR,KACHAR,
                                                  UKCHAR,AUDALRM,MAGCDRD,NUMLOCK,PTREAD,SELPEN,ASKY3277,DEKY3277,EBKY3277,OCKY3277,
                                                  KB70KEY,KB78KEY,KB81KEY
3490          005 3490      1000  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY,PRIVATE: LIBRARY,AUTOSWITCH,LIBRARY-ID,LIBPORT-ID,
                                                  MTL / SHARABLE,COMPACT
3505          012 3505      2400  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE
3525          012 3525      2500  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / CARDIMAGE,TWOLINE,MULTILINE
3540          032 3540      5600  N   N    N   N  OFFLINE
3590          005 3590-1     950  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY,PRIVATE: LIBRARY,AUTOSWITCH,LIBRARY-ID,LIBPORT-ID,
                                                  MTL / SHARABLE,COMPACT
3704          023 3704      7800  Y   Y    N   N  ADAPTER(CA1),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3705          023 3705      7600  Y   Y    N   N  (R)ADAPTER(TYPE1,TYPE2,TYPE3,TYPE4),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3720          023 3720      7575  Y   Y    N   N  (R)ADAPTER(TYPE5),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3725          023 3725      7550  Y   Y    N   N  (R)ADAPTER(TYPE5),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3737          014 CTC       8400  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / 370
3745          023 3745      7450  Y   Y    N   N  (R)ADAPTER(TYPE6,TYPE7),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3746          023 3746      7551  Y   Y    N   N  (R)ADAPTER(TYPE6,TYPE7),OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3767-1        024 AAA8      6800  N   N    N   N  (R)ADAPTER(IBM1),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                  2703) / AUTOPOLL,AUTOANSR,AUTOCALL,CHECKING,INTERRUPT,OIU,SCONTROL,XCONTROL
3767-2        024 AAA8      6800  N   N    N   N  (R)ADAPTER(IBM1),FEATURE,OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,
                                                  2703) / AUTOPOLL,AUTOANSR,AUTOCALL,CHECKING,INTERRUPT,OIU,SCONTROL,XCONTROL
```

Figure 152. Supported Hardware Report - MVS Devices (Part 3 of 4)

```
                                    SUPPORTED HARDWARE - MVS DEVICES             TIME: 13:24  DATE: 2001-12-05  PAGE T-  28
TYPE-MODEL    UIM GENERIC  DPREF DYN 4DIG UCB NIP SUPPORTED PARAMETERS (VALUES) / FEATURES
____________ ___ ________ _____ ___ ____ ___ ___ ____________________________________________________________________________
3791L         027 3791L     7700  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
3800-1        011 3800      1780  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER,CGS1,CGS2
3800-3        011 3800      1780  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3800-6        011 3800      1780  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER,CGS1,CGS2
3800-8        011 3800      1780  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3812          031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
3820          022 3820      1800  Y   Y    N   N  OFFLINE,DYNAMIC
3825          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3827          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3828          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3829          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3831          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3835          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3886          032 3886      4900  N   N    N   N  OFFLINE
3890          032 3890      4800  N   N    N   N  OFFLINE
3895          032 3895      5400  N   N    N   N  OFFLINE
3900          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3935          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
3995          053 3995      8600  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
3995-SDA      053 3995      8600  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
3995-151      002 3390       280  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
3995-153      002 3390       280  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
4000          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
4224          031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
4245          012 4245      1890  Y   Y    N   N  OFFLINE,DYNAMIC
4248          012 4248      1850  Y   Y    N   N  OFFLINE,DYNAMIC
4250          031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
4370          022 AFP1      1750  Y   Y    N   N  FEATURE,OFFLINE,DYNAMIC / BURSTER
5210          031 3286-2    4400  N   N    N   N  FEATURE,OFFLINE / DOCHAR,FRCHAR,GRCHAR,KACHAR,UKCHAR,PTREAD
7171          027 3791L     7700  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
7770-3        023 AAAC      7200  Y   Y    N   N  OFFLINE,DYNAMIC,OWNER(VTAM,OTHER)
8232          014 CTC       8400  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / 370
83B3          025 AAA6      6600  N   N    N   N  (R)ADAPTER(TELE1),OFFLINE,SETADDR(0,1,2,3),(R)TCU(2701,2702,2703)
9032          051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
9032-3        051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
9032-5        051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
9033          051 SWCH     10500  Y   Y    Y   N  OFFLINE,DYNAMIC,LOCANY
9345          002 9345       270  Y   Y    Y   N  FEATURE,OFFLINE,DYNAMIC,LOCANY / SHARED,SHAREDUP
                                    SUPPORTED HARDWARE - MVS DEVICES             TIME: 13:24  DATE: 2001-12-05  PAGE T-  29
        KEY                             KEY DESCRIPTION
        ---                             ---------------
        TYPE-MODEL                    - SUPPORTED DEVICE TYPE
        UIM                           - INDEX OF UNIT INFORMATION MODULE SUPPORTING THIS DEVICE TYPE
        GENERIC                       - GENERIC DEVICE TYPE
        DPREF                         - DEFAULT DEVICE PREFERENCE VALUE
        DYN                           - DEVICE SUPPORTS DYNAMIC I/O RECONFIGURATION
        4DIG                          - DEVICE TYPE SUPPORTS DEVICE NUMBERS GREATER THAN 0FFF
        UCB                           - DEVICE TYPE SUPPORTS UCB BEING LOCATED ABOVE 16 MB
        NIP                           - DEVICE TYPE SUPPORTED AS NIP CONSOLE
        SUPPORTED PARAMETERS (VALUES) / FEATURES  -  LIST OF SUPPORTED PARAMETERS (WITH SELECTION VALUES) AND FEATURES
        Y                             - DEVICE TYPE HAS THE CAPABILITY
        N                             - CAPABILITY IS NOT AVAILABLE
        (R)                           - PARAMETER IS REQUIRED
        PRIVATE:                      - START OF PARAMETERS PRIVATE TO UIM
```

Figure 152. Supported Hardware Report - MVS Devices (Part 4 of 4)

```
                                        SUPPORTED HARDWARE - VM DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  30
TYPE-MODEL    UIM VM D/T        CONS        SUPPORTED PARAMETERS / FEATURES
____________ ___ _____________ ____        ______________________________________________________________________________________
AFP1-0        278 AFP1           N          OFFLINE,UIRATE
BCTC          270 CTCA           N          OFFLINE,UIRATE
BSC1          282 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
BSC2          282 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
BSC3          282 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
CTC           270 CTCA           N          OFFLINE,UIRATE
CTCA          270 CTCA           N          OFFLINE,UIRATE
DUMMY         306 DUMMY          N          CLASS,OFFLINE,UIRATE / DPS,RESERVE
FB512         258 FB-512         N          OFFLINE,SHARED,UIRATE
HFGD          291 HFGD           N          OFFLINE,UIRATE
ICABSCA       308 ICA            N          ADAPTER,OFFLINE,UIRATE
ICAELAN       308 ICA            N          ADAPTER,OFFLINE,UIRATE
ICAHDLC       308 ICA            N          ADAPTER,OFFLINE,UIRATE
ICAILAN       308 ICA            N          ADAPTER,OFFLINE,UIRATE
ICASDLC       308 ICA            N          ADAPTER,OFFLINE,UIRATE
ICATELE2      308 ICA            N          ADAPTER,OFFLINE,UIRATE
RS6K          312 3088           N          OFFLINE,UIRATE
SCTC          270 CTCA           N          OFFLINE,UIRATE
SWCH          307 9032           N          OFFLINE,UIRATE
TWX           281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
1050          280 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
1050X         280 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
1403-N1       268 1403           N          AFP,CHARS,CLASS,DEST,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
1403-2        268 1403           N          AFP,CHARS,CLASS,DEST,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
1403-3        268 1403           N          AFP,CHARS,CLASS,DEST,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
1403-5        268 1403           N          AFP,CHARS,CLASS,DEST,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
1403-7        268 1403           N          AFP,CHARS,CLASS,DEST,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
2250-3        277 2250           N          OFFLINE,UIRATE
2305-2        269 2305-2         N          OFFLINE,SHARED,UIRATE
2501-B1       266 2501           N          CLASS,OFFLINE,UIRATE
2501-B2       266 2501           N          CLASS,OFFLINE,UIRATE
2540P-1       268 2540P          N          CLASS,FORM,OFFLINE,SEP,UIRATE
2540R-1       266 2540R          N          CLASS,OFFLINE,UIRATE
2701          279 2701           N          ADAPTER,OFFLINE,UIRATE
2740          280 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
2740C         280 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
2740X         280 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
2741C         281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
2741P         281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3088          270 3088           N          OFFLINE,UIRATE
3151          281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3161          281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3162          281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3163          281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3167          281 3705           N          ADAPTER,BASEADD,OFFLINE,SETADDR,UIRATE
3174          283 3705           N          ADAPTER,CPNAME,MODEL,OFFLINE,UIRATE
3178          260 3178           Y          MODEL,OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3179          260 3179           Y          MODEL,OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3180          260 3180           Y          MODEL,OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3190          260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3191          260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3192          260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3192-F        260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3193          260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3194          260 3190           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3203-5        268 3203-5         N          AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE / UNVCHSET
3211          268 3211           N          AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,INDEX,OFFLINE,SEP,UIRATE / UNVCHSET
3216          278 AFP1           N          OFFLINE,UIRATE
3250          277 3250           N          OFFLINE,UIRATE
3251          277 3250           N          OFFLINE,UIRATE
3262-13       287 3287           N          OFFLINE,UIRATE
3262-3        287 3287           N          OFFLINE,UIRATE
3262-5        268 3262           N          AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE
3268-2        287 3287           N          OFFLINE,UIRATE
3270          260 3270           Y          MODEL,OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3270-X        260 3270           Y          MODEL,OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3274          283 3705           N          ADAPTER,CPNAME,MODEL,OFFLINE,UIRATE
3277-1        260 3277           Y          OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
```

Figure 153. Supported Hardware Report - VM Devices (Part 1 of 3)

```
                                        SUPPORTED HARDWARE - VM DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  31
TYPE-MODEL    UIM VM D/T        CONS        SUPPORTED PARAMETERS / FEATURES
____________ ___ ____________ ____        ____________________________________________________________________________________
3277-2        260 3277           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-1        260 3278           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-2        260 3278           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-2A       260 3278-2A        Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-3        260 3278-3         Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-4        260 3278-4         Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3278-5        260 3278-5         Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-S2B      260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-S3G      260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-2        260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-2A       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-2B       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-2C       260 3279-2C        Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-2X       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-3        260 3279-3         Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-3A       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-3B       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3279-3X       260 3279           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3284-1        287 3284           N         OFFLINE,UIRATE
3284-2        287 3284           N         OFFLINE,UIRATE
3286-1        287 3286           N         OFFLINE,UIRATE
3286-2        287 3286           N         OFFLINE,UIRATE
3287-1        287 3287           N         OFFLINE,UIRATE
3287-1C       287 3287           N         OFFLINE,UIRATE
3287-2        287 3287           N         OFFLINE,UIRATE
3287-2C       287 3287           N         OFFLINE,UIRATE
3288          287 3288           N         OFFLINE,UIRATE
3289-1        287 3289           N         OFFLINE,UIRATE
3289-2        287 3289           N         OFFLINE,UIRATE
3290          260 3290           Y         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
3330-1        257 3330-1         N         OFFLINE,SHARED,UIRATE
3330-11       257 3330-11        N         OFFLINE,SHARED,UIRATE
3330-2        257 3330-2         N         OFFLINE,SHARED,UIRATE
3330V         271 3330           N         OFFLINE,SHARED,UIRATE
3333-1        257 3330-1         N         OFFLINE,SHARED,UIRATE
3333-11       257 3330-11        N         OFFLINE,SHARED,UIRATE
3340          257 3340           N         OFFLINE,SHARED,UIRATE
3344          257 3340           N         OFFLINE,SHARED,UIRATE
3350          257 3350           N         OFFLINE,SHARED,UIRATE
3350P         259 3350P          N         OFFLINE,SHARED,UIRATE
3351P         259 3351P          N         OFFLINE,SHARED,UIRATE
3370          258 3370           N         OFFLINE,SHARED,UIRATE
3375          258 3375           N         OFFLINE,SHARED,UIRATE
3380          258 3380           N         OFFLINE,SHARED,UIRATE
3380-CJ2      258 3380           N         OFFLINE,SHARED,UIRATE
3390          258 3390           N         OFFLINE,SHARED,UIRATE
3420-3        261 3420-3         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3420-4        261 3420-4         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3420-5        261 3420-5         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3420-6        261 3420-6         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3420-7        261 3420-7         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3420-8        261 3420-8         N         OFFLINE,UIRATE / CONV,DUALDENS,TRANS,7-TRACK
3422          261 3422           N         OFFLINE,UIRATE
3424          261 3424           N         OFFLINE,UIRATE
3430          261 3430           N         OFFLINE,UIRATE
3480          261 3480           N         OFFLINE,UIRATE
3490          261 3490           N         OFFLINE,UIRATE
3505          266 3505           N         CLASS,OFFLINE,UIRATE
3525          268 3525           N         CLASS,FORM,OFFLINE,UIRATE
3704          279 3704           N         ADAPTER,BASEADD,CPNAME,MODEL,OFFLINE,SETADDR,UIRATE
3705          279 3705           N         ADAPTER,BASEADD,CPNAME,MODEL,OFFLINE,SETADDR,UIRATE
3720          279 3705           N         ADAPTER,CPNAME,MODEL,OFFLINE,UIRATE
3725          279 3705           N         ADAPTER,BASEADD,CPNAME,MODEL,OFFLINE,SETADDR,UIRATE
3737          270 CTCA           N         OFFLINE,UIRATE
3745          279 3705           N         ADAPTER,BASEADD,CPNAME,MODEL,OFFLINE,SETADDR,UIRATE
3800-1        267 3800           N         AFP,CHARS,CLASS,DEST,DPMSIZE,FCB,FLASH,FORM,IMAGE,OFFLINE,SEP,UIRATE / 4WCGMS
3800-3        267 3800-3         N         AFP,CHARS,CLASS,DEST,DPMSIZE,FCB,FLASH,FORM,IMAGE,OFFLINE,SEP,UIRATE / 4WCGMS
3800-6        267 3800-3         N         AFP,CHARS,CLASS,DEST,DPMSIZE,FCB,FLASH,FORM,IMAGE,OFFLINE,SEP,UIRATE / 4WCGMS
```

Figure 153. Supported Hardware Report - VM Devices (Part 2 of 3)

```
                                        SUPPORTED HARDWARE - VM DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  32
TYPE-MODEL    UIM VM D/T        CONS        SUPPORTED PARAMETERS / FEATURES
___________ ___ ___________ ____          ____________________________________________________________________________________
3800-8        267 3800-8         N         AFP,OFFLINE,UIRATE / 4WCGMS
3812          287 3287           N         OFFLINE,UIRATE
3816          287 3287           N         OFFLINE,UIRATE
3820          278 3820           N         OFFLINE,UIRATE
3825          278 AFP1           N         OFFLINE,UIRATE
3827          278 AFP1           N         OFFLINE,UIRATE
3828          278 AFP1           N         OFFLINE,UIRATE
3835          278 AFP1           N         OFFLINE,UIRATE
3851          271 3851           N         OFFLINE,SHARED,UIRATE
3890          288 3890           N         OFFLINE,UIRATE
3900          278 AFP1           N         OFFLINE,UIRATE
3995          309 3088           N         OFFLINE,UIRATE
3995-151      258 3390           N         OFFLINE,SHARED,UIRATE
4224          287 3287           N         OFFLINE,UIRATE
4245          268 4245           N         AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE
4248          268 4248           N         AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE
5080          291 5080           N         OFFLINE,UIRATE
5081          291 5080           N         OFFLINE,UIRATE
5210          287 3287           N         OFFLINE,UIRATE
6090          291 5080           N         OFFLINE,UIRATE
6091          291 5080           N         OFFLINE,UIRATE
6262          268 4248           N         AFP,CHARS,CLASS,DEST,FCB,FOLD,FORM,IMAGE,OFFLINE,SEP,UIRATE
7171          283 3278           N         OFFLINE,UIRATE / EMUL3270,E3270HLD,OPRDR
8232          270 3088           N         OFFLINE,UIRATE
9032          307 9032           N         OFFLINE,UIRATE
9033          307 9033           N         OFFLINE,UIRATE
9332-40       258 9332           N         OFFLINE,SHARED,UIRATE
9332-42       258 9332           N         OFFLINE,SHARED,UIRATE
9332-60       258 9332           N         OFFLINE,SHARED,UIRATE
9332-62       258 9332           N         OFFLINE,SHARED,UIRATE
9335-B1       258 9335           N         OFFLINE,SHARED,UIRATE
9336-10       258 9336           N         OFFLINE,SHARED,UIRATE
9336-20       258 9336           N         OFFLINE,SHARED,UIRATE
9345          258 9345           N         OFFLINE,SHARED,UIRATE
9348-1        261 9348           N         OFFLINE,UIRATE / DUALDENS
                                        SUPPORTED HARDWARE - VM DEVICES              TIME: 13:24  DATE: 2001-12-05  PAGE T-  33
        KEY                                 KEY DESCRIPTION
        ---                                 ---------------
        TYPE-MODEL                       -  SUPPORTED DEVICE TYPE
        UIM                              -  INDEX OF UNIT INFORMATION MODULE SUPPORTING THIS DEVICE TYPE
        VM D/T                           -  VM DEVICE TYPE
        CONS                             -  DEVICE TYPE IS SUPPORTED AS VM CONSOLE
        SUPPORTED PARAMETERS / FEATURES  -  LIST OF SUPPORTED PARAMETERS AND FEATURES
        Y                                -  DEVICE TYPE HAS THE CAPABILITY
        N                                -  CAPABILITY IS NOT AVAILABLE
```

Figure 153. Supported Hardware Report - VM Devices (Part 3 of 3)

I/O Definition Reference

```
                              I/O DEFINITION REFERENCE - DEVICES        TIME: 17:31  DATE: 1996-11-18  PAGE W- 305

3490                TAPE      Magnetic Tape Subsystem                                                        /   1
UNIT=3490

                    Physical Configuration Information

                    Physical Device Types

                    Physical Device
                    3490-B20
                    3490-B40
                    Attachable to the following control units
                    3490-A10
                    3490-A20

                    Physical Device
                    (Integrated Tape Subsystem)
                    3490-C10
                    3490-C11
                    3490-C22

                    Physical Device
                    (Integrated Tape Subsystem inside a 3494)
                    3490-C1A
                    3490-C2A

                    Physical Device
                    3494 and 3495 are tape libraries containing automation,
                    library manager, one or more tape control units, storage
                    cells and tape cartridges. To prepare the IODF, no need
                    to define 3494 and 3495 explicitly. However, need to
                    indicate the tape devices as library tape devices by
                    specifying LIBRARY=YES in the device definition.

                    Logical Configuration Rules

                    For Channel Subsystem
                    - Up to maximum 4 channel paths for A10, 8 for A20,
                     2 for C1A or C2A.
                    - Range of 16 unit addresses for control unit. Also
                     accept a minimum of 2 addresses for integrated tape
                     subsystem.

                    For Operating System
                    - LIBRARY=YES, if devices are installed in a system-
                     managed IBM 3494 or IBM 3495 Tape Library.
                    - LIBRARY=YES or NO for BTLS managed library drives
                    - DYNAMIC=YES, if devices are dynamically reconfigured
                    - AUTOSWITCH=YES, if tape drives are dynamically switched
                     between system (MVS/ESA 5.2.0)

                    Configuration Example
                     CHPID PATH=(22,27),TYPE=CNC
```

Figure 154. Example of a I/O Definition Reference (Part 1 of 5)

```
                                I/O DEFINITION REFERENCE - DEVICES        TIME: 17:31  DATE: 1996-11-18  PAGE W- 306

3490                TAPE      Magnetic Tape Subsystem                                                          /   2
                     CNTLUNIT CUNUMBR=0501,PATH=(22,27),UNIT=3490,         X
                          UNITADD=((00,16))
                     IODEVICE ADDRESS=(540,016),CUNUMBR=(0501),UNIT=3490,  X
                          OFFLINE=YES,DYNAMIC=YES,                          X
                          USERPRM=((LIBRARY,YES),(AUTOSWITCH,YES))

                    Software Prerequisites
                     Minimum version and release to operate the device in
                     MVS/ESA environment:

                    - MVS/SP - JES2 3.1
                    - MVS/DFP 3.1

                    Minimum Product Levels

                    - DFSORT release 11 (release 12 for C1A,C2A)
                    - EREP 3.4 (3.5 for C1A,C2A)
                    - DFHSM 2.6
                    - DFDSS 2.5

                    References

                    - MVS/ESA & MVS/XA Support for 3490 Magnetic Tape
                     Subsystem.  GC28-1141
                    - IBM 3490E Planning and Migration Guide GC35-0219
                    - IBM 3490  Planning and Migration Guide GC35-0116

                    Notes

                    - For the latest information, contact your local IBM
                     Marketing Representative.

                    -end-

Device number definition values: ADDRESS=(device number<,number-of-devices>)

    device number: 1 - 4 hexadecimal number in the range 0000 - FFFF.

    number-of-devices: Number of sequential device numbers to be assigned to the devices.
                    Minimum value:    1
                    Default value:    1
                    Maximum value: 4095


Channel Subsystem information:
------------------------------

    When attached to a parallel interface:
                    I/O interface time out function default: TIMEOUT=YES
                    Status verification facility default:    STADET=YES
```

Figure 154. Example of a I/O Definition Reference (Part 2 of 5)

```
                                I/O DEFINITION REFERENCE - DEVICES        TIME: 17:31  DATE: 1996-11-18  PAGE W- 307

3490                TAPE      Magnetic Tape Subsystem                                                          /   3
 ____________________________________________________________________________________________________________________
    Unit address: UNITADD=xx
                    The unit address is a hexadecimal value from 00 to FF which must be specified
                    in the unit address range of the control unit.
                    Default unit address are the last 2 digits of the device number.


MVS configuration information:
------------------------------

    Generic name: 3490        It may be modified dependent on the specified features.

    Support of dynamic I/O reconfiguration:      Yes
    Support of device numbers greater than 0FFF: Yes
    Support of UCBs above 16 MB storage:         Yes

    Required parameters: None.

    Optional parameters:

    OFFLINE         Device considered online or offline at IPL
                    Default value: OFFLINE=NO

                    Specifies whether MVS is to consider the device
                    online or offline at IPL.

                    Yes      The device is considered offline at IPL.

                    No       The device is considered online at IPL.
                            (Default)

                    If MVS needs the device during IPL, specify No.

    DYNAMIC         Device supports dynamic configuration

                    Specify yes to indicate that the device is to be
                    eligible for Dynamic I/O Configuration.

    LIBRARY         Device supports auto tape library

                    Data type is YES or NO
                    Pre-selected:  No

                    Specify YES to indicate that the device belongs
                    to an automated tape library.

    AUTOSWITCH      Device is automatically switchable

                    Data type is YES or NO
                    Pre-selected:  No

                    Specify YES to indicate that the device should
```

Figure 154. Example of a I/O Definition Reference (Part 3 of 5)

```
                              I/O DEFINITION REFERENCE - DEVICES        TIME: 17:31  DATE: 1996-11-18  PAGE W- 308

3490                TAPE      Magnetic Tape Subsystem                                                          /   4
                    be treated as an automatically switchable device

    Supported features:

    ALTCTRL         Separate physical control unit path

                    Specify Yes to indicate that there is a separate
                    physical control unit path to the device.

    SHARABLE        Device is Sharable between systems

                    Specify Yes to indicate that the 3803 two-channel
                    switch is used for partitioning and that magnetic
                    tape drives can be shared between two processors.

                    Do not allocate or unload a shared tape drive.

                    If specify Yes for SHARABLE, HCD forces a value of
                    Yes for the OFFLINE parameter, even if you specify
                    No for OFFLINE.

    COMPACT         Compaction

                    Specify Yes to indicate that compaction is
                    available for tape devices.

                    Compaction is a method of compressing and encoding
                    data in order to reduce storage space.
```

Figure 154. Example of a I/O Definition Reference (Part 4 of 5)

```
                           I/O DEFINITION REFERENCE - DEVICES              TIME: 17:31  DATE: 1996-11-18  PAGE W- 403

                                                          INDEX

    AFP1-0 ...... W-   1           3088 ........ W-  95           3279-2C ..... W- 209           3480 ........ W- 300
    BCTC ........ W-   3           3151 ........ W-  97           3279-2X ..... W- 116           3481 ........ W- 116
    BSC1 ........ W-   5           3160 ........ W-  98           3279-3 ...... W- 216           3482 ........ W- 116
    BSC2 ........ W-   8           3161 ........ W- 100           3279-3A ..... W- 217           3483 ........ W- 116
    BSC3 ........ W-  11           3162 ........ W- 101           3279-3B ..... W- 223           3490 ........ W- 306
    ...............................................................................................................
```

Figure 154. Example of a I/O Definition Reference (Part 5 of 5)

Graphical Configuration Reports

This section contains one example for an LCU report. “Create or View Graphical Configuration Reports” on page 218 describes how to produce this report.

LCU Report

The LCU report shows all logical control units for the designated processor. Each diagram shows one or more logical control units.



IODF Compare Reports

The following figures show examples of IODF compare reports that can be produced by the IODF compare function of HCD. Not all possible reports are shown, and not all examples are shown completely. “Compare Functions” on page 226 describes how to produce these reports.

Processor Compare Report

```
                                Processor Compare Report                      TIME: 16:13  DATE: 1997-10-21  PAGE A -    1

            New IODF name:  USER.IODF03.WORK                      Old IODF name:  HCD.IODF01.WORK

                          Limited to New Processor Id:  PROC1     Old Processor Id:  PROC2

|---------------------------|----------------------|----------------------|-----------------------------------------------------|
| PROC                      | New IODF             | Old IODF             | Description                                         |
|---------------------------|----------------------|----------------------|-----------------------------------------------------|
| PROC1                     | Actual Data          | Old Data             |                                                     |
|                           |----------------------|----------------------|-----------------------------------------------------|
|                           | LPAR                 | BASIC                | Processor Configuration Mode                        |
|                           | 9021-900             | 9021-720             | Processor Type                                      |
|                           | 1234569021           | 2345679021           | Processor Serial Number                             |
|                           | This is the main p +  | This is the second +  | Processor Description                               |
|                           | rocessor             |  processor           |   continued                                         |
|---------------------------|----------------------|----------------------|-----------------------------------------------------|
```

Figure 155. Example of a Processor Compare Report

Partition Compare Report

```
                                Partition Compare Report                      TIME: 16:13  DATE: 1997-10-21  PAGE B -   1

            New IODF name:  USER.IODF03.WORK                      Old IODF name:  HCD.IODF01.WORK

                          Limited to New Processor Id:  PROC1     Old Processor Id:  PROC1

|---------------------------|----------------------|----------------------|-----------------------------------------------------|
| PROC     PART             | New IODF             | Old IODF             | Description                                         |
|---------------------------|----------------------|----------------------|-----------------------------------------------------|
| PROC1    TEST4            | Added                |                      |                                                     |
|                           |----------------------|----------------------|-----------------------------------------------------|
|                           | 6                    |                      | Partition Number                                    |
|                           | CF/OS                |                      | Partition Usage                                     |
|                           | cf test system2      |                      | Partition Description                               |
|---------------------------|----------------------|----------------------|-----------------------------------------------------|
```

Figure 156. Example of a Partition Compare Report

Channel Path Compare Report

```
                    Channel Path Compare Report                    TIME: 14:21  DATE: 2000-12-08  PAGE C -    3

New IODF name:  BOKA.IODF38                          Old IODF name:  BOKA.IODF38.TEMP

                Limited to New Processor Id:  FR38LPAR  Old Processor Id:  FR38LPAR
```

PROC CHPID	New IODF	Old IODF	Description
FR38LPAR 05 continued	Actual Data	Old Data	
	UTCPLX38	same	Channel Path I/O Cluster Name
	>> 6E FB	>> same	Connected to Switch, Port
FR38LPAR 06	Actual Data	Old Data	
	CNC	same	Channel Path Type
	SHR	same	Channel Path Operation Mode
		same	Channel Path Description
	6F	same	Connects to Dynamic Switch
	not managed	same	Channel Path Managed Indicator
	none	same	Channel Path I/O Cluster Name
	>> F38A	>> same	Partition in Access List
	>> F38B	>> same	Partition in Access List
	>> F38C	>> same	Partition in Access List
	>> F38D	>> same	Partition in Access List
	>> F38E	>> same	Partition in Access List
	>> F38F	>> same	Partition in Access List
	>> F38G	>> same	Partition in Access List
	>> F38H	>> same	Partition in Access List
	>> 5100	>> same	Attached Control Unit
	>> 5100,24	>> same	Attached Device, Range
	>> 5118,232	>> same	Attached Device, Range
	>> 6F B3	>> same	Connected to Switch, Port

Figure 157. Example of a Channel Path Compare Report

Control Unit Attachment Compare Report

```
                    Control Unit Attachment Compare Report         TIME: 14:21  DATE: 2000-12-08  PAGE D -    4

New IODF name:  BOKA.IODF38                          Old IODF name:  BOKA.IODF38.TEMP

              Limited to New Processor Id:  FR38LPAR  Old Processor Id:  FR38LPAR
```

PROC	CU	New IODF	Old IODF	Description
FR38LPAR	2000	Actual Data	Old Data	
		S *	same	Protocol
		2 *	same	I/O Concurrency Level
		1	same	Control Unit Address
		00,256	same	Unit Address, Number of addresses
		>> 07.9B	>> same	Connected Channel Path, Destination Link Address
		>> 0C.70	>> same	Connected Channel Path, Destination Link Address
		>> 6B.9E	>> same	Connected Channel Path, Destination Link Address
		5	same	Number of Connected Managed Channel Paths
FR38LPAR	2200	Actual Data	Old Data	
		S *	same	Protocol
		2 *	same	I/O Concurrency Level
		3	same	Control Unit Address
		00,256	same	Unit Address, Number of addresses
		>> 0B.B9	>> same	Connected Channel Path, Destination Link Address
		>> 17.9B	>> same	Connected Channel Path, Destination Link Address
		>> 6B.9A	>> same	Connected Channel Path, Destination Link Address
		5	same	Number of Connected Managed Channel Paths

Figure 158. Example of a Control Unit Attachment Compare Report

Device Attachment Compare Report

```
                    Device Attachment Compare Report              TIME: 08:41  DATE: 1997-11-06  PAGE E -    1

        New IODF name:  REDDE.IODF00.COMP1                    Old IODF name:  REDDE.IODF00.COMP2

                    Limited to New Processor Id:  LPARPROC  Old Processor Id:  LPARPROC
                    Limited to New Partition Id:  PART1     Old Partition Id:  PART3
```

PROC Device, Range	New IODF	Old IODF	Description
LPARPROC 0100,16	Actual Data	Old Data	
	00	same	Unit Address
	Yes	same	Illegal Status Detection Facility
	No	same	Timeout Facility
	undefined	same	Preferred Channel Path
	>> PART1	>> new added	Partition in Explicit Device Candidate list
	>> PART3	>> same	Partition in Explicit Device Candidate list
	>> access list	>> candidate list	Relation to Limiting LPAR
LPARPROC 0200,15	Actual Data	Old Data	
	00	same	Unit Address
	Yes	same	Illegal Status Detection Facility
	No	same	Timeout Facility
	undefined	same	Preferred Channel Path
	>> access list	>> candidate list	Relation to Limiting LPAR

Figure 159. Example of a Device Attachment Compare Report

Control Unit Compare Report

```
                    Control Unit Compare Report                   TIME: 08:41  DATE: 1997-11-06  PAGE F -    1

        New IODF name:  REDDE.IODF00.COMP1                    Old IODF name:  REDDE.IODF00.COMP2

                    Limited to New Processor Id:  LPARPROC  Old Processor Id:  LPARPROC
                    Limited to New Partition Id:  PART1     Old Partition Id:  PART3
```

CU	New IODF	Old IODF	Description
0200	Actual Data	Old Data	
	3990	same	Control Unit Type
		same	Control Unit Serial Number
		same	Control Unit Description
	>> BASPROC	>> new added	Attached to Processor
	>> LPARPROC	>> same	Attached to Processor
	>> 0200,15	>> same	Attached Device, Range
	>> 020F	>> same	Attached Device, Range
	>> 0210,11	>> same	Attached Device, Range
	>> 01 E4	>> same	Connected to Switch, Port
	>> 01 E5	>> same	Connected to Switch, Port
	>> access list	>> candidate list	Relation to Limiting LPAR

Figure 160. Example of a Control Unit Compare Report

Device Compare Report

```
                    Device Compare Report                    TIME: 08:41  DATE: 1997-11-06  PAGE G -    1

New IODF name:  REDDE.IODF00.COMP1                  Old IODF name:  REDDE.IODF00.COMP2

                Limited to New Processor Id:  LPARPROC  Old Processor Id:  LPARPROC
                Limited to New Partition Id:  PART1     Old Partition Id:  PART3
```

Device, Range	New IODF	Old IODF	Description
0100	Actual Data	Old Data	
	9032	same same same	Device Type Serial Number Device Description
	>> BASPROC >> old deleted >> LPARPROC	>> new added >> BASPROC1 >> same	Attached to Processor Attached to Processor Attached to Processor
	>> 0100	>> same	Connected to Control Unit
	>> access list	>> candidate list	Relation to Limiting LPAR
0200,15	Actual Data	Old Data	
	3390	same same same	Device Type Serial Number Device Description
	>> BASPROC >> LPARPROC	>> new added >> same	Attached to Processor Attached to Processor
	>> 0200 >> 0210	>> same >> same	Connected to Control Unit Connected to Control Unit
	>> OSOSOSOS	>> same	Attached to Operating System Configuration
	>> access list	>> candidate list	Relation to Limiting LPAR

Figure 161. Example of a Device Compare Report

Switch Compare Report

```
                    Switch Compare Report                    TIME: 13:40  DATE: 1997-03-27  PAGE H -    1

New IODF name:  BERT.IODF99.TESTMSG1                Old IODF name:  BERT.IODF99.TESTMSG
```

SWITCH	New IODF	Old IODF	Description
01	Actual Data	Old Data	
	9032	same same same	Switch Type Switch Serial Number Description
	>> 1000 1000 >> 1010 1010 >> 1020 1020	>> same >> same >> same	Switch Control unit, switch device Switch Control unit, switch device Switch Control unit, switch device
02	Actual Data	Old Data	
	9032	same same same	Switch Type Switch Serial Number Description
	>> 2222 2222 >> 3333 3333 >> 4444 4444	>> same >> 4444 4444 >> new added	Switch Control unit, switch device Switch Control unit, switch device Switch Control unit, switch device

Figure 162. Example of a Switch Compare Report

Switch Detail Compare Report

```
                    Switch Detail Compare Report                    TIME: 10:38  DATE: 1997-10-09  PAGE I -    9

        New IODF name:  BERT.IODFAA.XMIT.PROD.WORK            Old IODF name:  BERT.IODFAA.XMIT.PROD

                       Limited to New Switch Id:  01      Old Switch Id:  01
```

SWITCH	PORT	New IODF	Old IODF	Description
01	B0	Actual Data	Old Data	
		installed	same	Port Installed Flag Port Name
		>> 0800 >> X9672 31	>> same >> same	Attached to Control Unit Attached to Processor, Channel Path
01	B1	Actual Data	Old Data	
		installed CU_400	same CU_500	Port Installed Flag Port Name
		>> 0800	>> 0500	Attached to Control Unit
01	B2	Actual Data	Old Data	
		installed PROCA_CP18 occupied	same not occupied	Port Installed Flag Port Name Port Occupied Flag

Figure 163. Example of a Switch Detail Compare Report

Switch Configuration Detail Compare Report

```
                    Switch Configuration Detail Compare Report      TIME: 13:40  DATE: 1997-03-27  PAGE K -    1

        New IODF name:  BERT.IODF99.TESTMSG1                  Old IODF name:  BERT.IODF99.TESTMSG
```

SWITCH	SWCONFIG	PORT	New IODF	Old IODF	Description
01	BASIC	E1	Actual Data	Old Data	
			Unblocked	same	Blocked / Unblocked Connection
			>> F1	>> same	Port of Dedicated Connection
01	BASIC	E2	Actual Data	Old Data	
			Unblocked	same	Blocked / Unblocked Connection
			>> E7 >> F3 >> F5	>> same >> same >> same	Port of Allowed Connection Port of Allowed Connection Port of Allowed Connection
			>> E8	>> same	Port of Prohibited Connection
01	BASIC	E3	Actual Data	Old Data	
			Unblocked	same	Blocked / Unblocked Connection
			>> E8 >> E9 >> EA	>> same >> same >> same	Port of Prohibited Connection Port of Prohibited Connection Port of Prohibited Connection

Figure 164. Example of a Switch Configuration Detail Compare Report

Esoteric Compare Report

```
                          Esoteric Compare Report                        TIME: 08:32  DATE: 1997-11-06  PAGE P -    1

        New IODF name:  REDDE.IODF00.COMP1                    Old IODF name:  REDDE.IODF00.COMP2

                     Limited to New Operating System Id: OS1       Old Operating System Id:  OS1

|---------------------------|---------------------|---------------------|-------------------------------------------------|
| OSCONFIG EDT      ESOTERIC | New IODF            | Old IODF            | Description                                     |
|---------------------------|---------------------|---------------------|-------------------------------------------------|
| OS1      01       BOBO     |                     | Deleted             |                                                 |
|                           |---------------------|---------------------|-------------------------------------------------|
|                           |                     | No                  | Esoteric is VIO Eligible                        |
|                           |                     |                     | Esoteric Token                                  |
|                           |                     |---------------------|-------------------------------------------------|
|                           |                     |  >> 0201,3          | Assigned Device, Range                          |
|                           |                     |  >> 0205,3          | Assigned Device, Range                          |
|                           |                     |  >> 0300,64         | Assigned Device, Range                          |
|---------------------------|---------------------|---------------------|-------------------------------------------------|
| OS1      01       HUGO     | Added               |                     |                                                 |
|                           |---------------------|---------------------|-------------------------------------------------|
|                           | No                  |                     | Esoteric is VIO Eligible                        |
|                           |                     |                     | Esoteric Token                                  |
|                           |---------------------|                     |-------------------------------------------------|
|                           |  >> 0200,8          |                     | Assigned Device, Range                          |
|                           |  >> 0300,64         |                     | Assigned Device, Range                          |
|---------------------------|---------------------|---------------------|-------------------------------------------------|
| OS1      01       SYSDA    | Actual Data         | Old Data            |                                                 |
|                           |---------------------|---------------------|-------------------------------------------------|
|                           | Yes                 | same                | Esoteric is VIO Eligible                        |
|                           |                     | same                | Esoteric Token                                  |
|                           |---------------------|---------------------|-------------------------------------------------|
|                           |  >> old deleted     |  >> 0204            | Assigned Device, Range                          |
|                           |  >> 0300,64         |  >> same            | Assigned Device, Range                          |
|---------------------------|---------------------|---------------------|-------------------------------------------------|
```

Figure 165. Example of an Esoteric Compare Report

OS Device Compare Report

```
                              OS Device Compare Report                      TIME: 08:32  DATE: 1997-11-06  PAGE R -    1

            New IODF name:  REDDE.IODF00.COMP1                    Old IODF name:  REDDE.IODF00.COMP2

                        Limited to New Operating System Id: OS1       Old Operating System Id:  OS1

|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OS       Device, Range    | New IODF            | Old IODF            | Description                                         |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OS1      0100             | Actual Data         | Old Data            |                                                     |
|                           |---------------------|---------------------|-----------------------------------------------------|
|                           | 9033                | same                | Device Type                                         |
|                           | SWCH                | same                | Name of Generic                                     |
|                           | Yes                 | same                | Value(s) of Parameter OFFLINE                       |
|                           | Yes                 | same                | Value(s) of Parameter DYNAMIC                       |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OS1      0200,32          | Actual Data         | Old Data            |                                                     |
|                           |---------------------|---------------------|-----------------------------------------------------|
|                           | 3390                | same                | Device Type                                         |
|                           | 3390                | same                | Name of Generic                                     |
|                           | No          *       | same                | Value(s) of Parameter OFFLINE                       |
|                           | Yes                 | same                | Value(s) of Parameter DYNAMIC                       |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OSOSOSOS 01D1,4           | Actual Data         | Old Data            |                                                     |
|                           |---------------------|---------------------|-----------------------------------------------------|
|                           | 3390                | same                | Device Type                                         |
|                           | 3390                | same                | Name of Generic                                     |
|                           | No                  | same                | Value(s) of Parameter OFFLINE                       |
|                           | Yes                 | same                | Value(s) of Parameter DYNAMIC                       |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|

 * indicates this value as default value (only shown when both sides exist)
```

Figure 166. Example of an OS Device Compare Report

OS Console Compare Report

```
                              OS Console Compare Report                     TIME: 12:41  DATE: 1997-08-26  PAGE Q -    1

            New IODF name:  USER.IODF03.WORK                      Old IODF name:  HCD.IODF01.WORK

                        Limited to New Operating System Id: OPSYS01   Old Operating System Id:  OPSYS01

|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OSCONFIG DEVICE           | New IODF            | Old IODF            | Description                                         |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OPSYS01  0001             | Actual Data         | Old Data            |                                                     |
|                           |---------------------|---------------------|-----------------------------------------------------|
|                           | 2                   | 1                   | Order Number                                        |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
| OPSYS01  0002             | Added               |                     |                                                     |
|                           |---------------------|---------------------|-----------------------------------------------------|
|                           | 1                   |                     | Order Number                                        |
|---------------------------|---------------------|---------------------|-----------------------------------------------------|
```

Figure 167. Example of an OS Console Compare Report

CSS / Operating System Device Compare

```
                                CSS / OS Device Compare Report                TIME: 08:26  DATE: 1997-11-06  PAGE S -    1

                          IODF Name : REDDE.IODF00.COMP2
                Processor Id: LPARPROC  Partition Name: PART3     ./.   Operating System Configuration Id: OS1
```

Device, Range	Cand?	CSS Device Type	OS Device Type
0100	*	9032	9033
0200			3390
0201,3		3390	same
0204		3390	same
0205,3		3390	same
0208,7		3390	3800-1
020F		3390	3800-1
0210,11	*	3390	same
021B		3390	same
021C,4		3390	same
0220		3380	same
0221,31		3390	same
0300,64	*	3380	same

```
* Devices relate to the limiting LPAR via CHPIDs which have the limiting partition in the candidate list only
```

Figure 168. Example of a CSS / Operating System Device Compare

Appendix C. Problem Determination for HCD

Overview

The information in this appendix is intended to help you diagnose problems that may arise with definitions that were created by the use of HCD. It explains:
- How to identify problems
- What diagnostic information and tools you can use
- How to search problem reporting data bases

Because HCD is part of z/OS, problems with HCD must generally be handled as explained in *z/OS MVS Diagnosis: Procedures*.

Product Identifiers
- Module Prefix: CBD
- Component ID: 5695SC1XL

For more information on identifiers, refer to the *z/OS Program Directory*.

Identifying Problems

Before you can begin to diagnose a system problem, you have to know what kind of problem you have.

The following table contains examples of symptoms you can use to determine a problem. Each symptom refers to a corresponding section for further problem diagnostic.

© Copyright IBM Corp. 1994, 2002

Symptom	Corresponding Section
HCD terminates abnormally	"HCD Abnormal Termination".
Wait State during IPL	"Error During IPL (Wait State Codes)" on page 419.
A function key assignment does not match the functions that can be performed on the panel.	"Problems with Panels and Function Key Assignment" on page 419
Messages CBDA400I to CBDA420I are displayed	"Problems with Help Information Provided by HCD" on page 420
Output of textual report is incorrect or incomplete	"Problems with Output of HCD Textual Reports" on page 422
Output of graphical report is incorrect or incomplete	"Problems with Output of HCD Graphical Reports" on page 422
Messages during initialization of HCD	"Problems During Initialization of HCD" on page 424
A string like ?PARMnn? appears on the Define Device Parameters / Features panel	"Problems with UIMs" on page 425
A UIM is flagged in error on the Installed UIMs panel	"Problems with UIMs" on page 425
Messages during migration	"Resolving Migration Errors" on page 277
HCD does not display an error message when you make a mistake	"HCD Internal Problems" on page 426
An HCD generated IOCP input data set fails when using the IOCP program	"HCD Internal Problems" on page 426
Transmit configuration package action does not produce the expected results	"Problems with the Transmit Configuration Package Action" on page 427
HCD LDAP Backend terminates abnormally	"HCD LDAP Backend Abnormal Termination" on page 431
HCD LDAP Backend returns one of the error codes `LDAP_OPERATIONS_ERROR`, `LDAP_NO_MEMORY`, or `LDAP_LOCAL_ERROR`	"Adverse LDAP Return Code from the HCD LDAP Backend" on page 432
Message `CBD0009E` is printed to the started task's log	"Error in HCD LDAP Backend" on page 432

Figure 169. Symptoms of System Problems

HCD Abnormal Termination

If HCD terminates abnormally, view the HCD message log that contains the termination message CBDA000I specifying the *system abend code* (also called *abend code*) and the *reason code* in the HCD message log.

Refer to the message descriptions shown in *z/OS HCD Messages*. Take the action as described under "Programmer Response". If the message points to a probable logic error in one of the modules of HCD, develop a search argument for the problem-reporting data bases. If the search finds that the problem has been reported before, request the problem fix; if not, report the problem to IBM. For a list of additional information that should be provided, see the appropriate message explanation.

Diagnosing System Abend Code '00F'

If HCD terminates with system abend code '00F', this abend code is accompanied by a reason code, which refers to one of the HCD messages describing the reason of the failure. Note that you have to view the HCD message log for the system abend code and reason code. The reason code consists of eight digits and has the format 'mnnnllll' where:

m Is the prefix indicating the HCD message range:
- **0** CBDAxxxx messages
- **1** CBDBxxxx messages
- **2** CBDCxxxx messages
- **6** CBDGxxxx messages

nnn Is the message number within the HCD message range.

llll Is the message reason code describing in more detail the reason of the message.

The information provided by the abend code can be used as a quick reference into the message. For example, the reason code 00990106 means that:
- The message CBDA099I was issued.
- The message reason code is 0106.

The reason code 00150095 means that:
- The message CBDA015 was issued.
- The message reason code is 95.

Table 7 and Table 8 show what the search argument and the problem data could look like.

Table 7. Search Argument

Search Argument	Description	Example
AB/S0hhh	System abend code	AB/S000F
PRCS/mnnnllll	Reason code	PRCS/00990106
MS/ccccnnns	Message identifier	MS/CBDA099I

Table 8. Problem Data

Problem Data	Example
CBDA000 abend code and reason code	00F and 00990406
CBDA099 reason code	406
CBDA099 additional error information (content of HCDMLOG). It is important that *all* information shown in HCDMLOG is recorded.	
The ID of the panel where the error occurred	CBDPPRF0
Description of what type of action the user wanted to perform when the problem occurred	Add a Processor
The TRACE output data set (See "TRACE Command" on page 437 for instructions how to produce an HCD trace output.)	

ISPF List File and Abend Panel: Additional information on errors may be recorded in the ISPF list file.

For abends, additional information may be displayed on the ISPF abend panel.

Diagnosing System Abend Other than '00F'

If HCD terminates with an abend code other than '00F' (indicated in the terminating message), proceed as follows:

1. Look at the explanation of the abend code and any reason code that accompanies the abend code. Take the recommended actions.
2. Look for any messages that accompany the abend. Take the recommended actions.
3. Obtain the SYS1.LOGREC record. (Format the SYS1.LOGREC record using EREP.)
4. In SYS1.LOGREC find the SDWAVRA information which is as follows:
   - The CSECT (module) names found in the diagnostic stack.

     The CSECT names are separated by a blank. The SDWAVRA contains all CSECT names from the diagnostic stack as long as they fit into it. If the SDWAVRA is too small to contain all names, the premature end of the CSECT name trace is indicated by an asterisk.
   - The data from each diagnostic stack entry that is marked as VRA data.

     This is normally the input parameter list of the modules corresponding to the CSECT name trace.

Table 9 and Table 10 show what the search argument and the problem data associated with our example could look like.

Table 9. Search Argument

Search Argument	Description	Example
RIDS/CBDccccc	CSECT name	RIDS/CBDMGHCP
AB/S0hhh	System abend code	AB/S0106
PRCS/mnnnllll	Reason code	PRCS/0000000B
MS/cccnnns	Message identifier	MS/CSV011I
FLDS/SDWAVRA VALU/cccc	SDWAVRA contents	

Table 10. Problem Data

Problem Data	Example
SYS1.LOGREC error record	
SDWAVRA information	
Accompanying messages	
Component ID and FMID	
Linkage editor output	
Description of what type of action the user wanted to perform when the problem occurred	

Table 10. Problem Data (continued)

Problem Data	Example
The TRACE output data set (See "TRACE Command" on page 437 for instructions how to produce an HCD trace output.)	

Error During IPL (Wait State Codes)

IOS may issue wait state codes during IPL when using an IODF to perform an IPL. The wait state codes indicate that there is a problem, for example, with an IODF data set or with device specifications in the IODF or UIM. The reason codes with the wait state codes point to the cause of the problem. For information about the codes, refer to *z/OS MVS System Codes*.

Depending on the code that was issued, you have to use the arguments that apply to the specific situation listed in the box below. The same applies for submitting problem data.

Table 11 and Table 12 show what the search argument and the problem data could look like.

Table 11. Search Argument

Search Argument	Description	Example
WS/D0hhh	Wait state code	WS/D0083
PRCS/mnnnllll	Reason code	PRCS/00000002
MS/cccnnns	Message identifier	
PIDS/name of UIM	Program name	PIDS/CBDUS005
VALU/Ccccccccc (if applicable)	Message variable text	

Table 12. Problem Data

Problem Data	Example
Wait State Code	D0083
Reason Code	01
Accompanying message	
UIM name (if available)	CBDUS005
Stand-alone dump	
IODF dump	

Problems with Panels and Function Key Assignment

If problems with panels or the assignment of function keys occur, ensure the following:

- Data set SYS1.SCBDTENU must be allocated to ISPTLIB and data set SYS1.SCBDPENU to ISPPLIB.
- SYS1.SCBDCLST must be allocated to SYSPROC

- SYS1.SCBDPENU, SYS1.SCBDMENU, and SYS1.SCBDTENU must be dynamically allocated when HCD has been started. Compare with LIBDEF definitions in CBDCHCD.

If the library allocation is correct, develop a search argument, and if no problem solution is found, report the problem. To display the panel identifier, use the ISPF command PANELID. The name of the function panel will be shown in the upper left corner of the panel.

Table 13 and Table 14 show what the search argument and the problem data could look like.

Table 13. Search Argument

Search Argument	Description	Example
RIDS/CBDccccc	Panel identifier	RIDS/CBDPHW10

Table 14. Problem Data

Problem Data	Example
Panel identifier and name of the panel where the error was detected.	CBDPHW10 Define, Modify, or View Configuration Data
Type of error found.	

Problems with Help Information Provided by HCD

Messages that relate to problems with the HCD help facility have the identifiers CBDA400I to CBDA420I. Use the commands:

- HELPID to display the name of the help panel at the end of the command line. The name is displayed in the command line just before the scroll field. It can be used as search argument.
- HELPTEST to display the help panel while in help mode. It allows you to review or test any help panel while in help mode. That is, it eliminates the need to create the appropriate situation if a review or test of a help panel is required.

  This command can also be used to get the help information for a message. The help member for a message consists of the message ID minus the trailing severity indicator (such as "I"). For example, the help member for message CBDA200I has the name CBDA200. It is therefore possible to get an explanation for messages that are not yet defined in the messages manual.

LookAt System for Online Message Lookup

LookAt is an online facility that allows you to look up explanations for z/OS messages and system abends.

Using LookAt to find information is faster than a conventional search because LookAt goes directly to the explanation.

LookAt can be accessed from the Internet or from a TSO command line.

You can use LookAt on the Internet at:

```
http://www.ibm.com/servers/eserver/zseries/zos/bkserv/lookat/lookat.html
```

To use LookAt as a TSO command, LookAt must be installed on your host system. You can obtain the LookAt code for TSO from the LookAt Web site by clicking on the **News and Help** link or from the *z/OS Collection*.

To find a message explanation from a TSO command line, simply enter: **lookat** *message-id* as in the following:

```
lookat cbda100i
```

This results in direct access to the message explanation for message CBDA100I.

To find a message explanation from the LookAt Web site, simply enter the message ID. You can select the release if needed.

Note: Some messages have information in more than one book. For such messages, LookAt prompts you to choose which book to open.

Problem with Content, Wording, Mismatch

If problems with content, wording, or mismatches are encountered, obtain the help panel name by using the HELPID command. The help panel name is displayed at the end of the command line.

Table 15 shows what the search argument could look like.

Table 15. Search Argument

Search Argument	Description	Example
RIDS/CBDcccc	Help panel name	RIDS/CBDF403
RIDS/CBDccccc	Panel identifier	RIDS/CBDPDVF0

Problem Shown by Help Messages CBDA400I or CBDA405I

If message CBDA400I or CBDA405I is issued, check:

1. The library concatenation for your HCD invocation.
2. That the help members are installed in the proper libraries (in SYS1.SCBDHENU).
3. That the help library is allocated either in LINKLST member or to ISPLLIB.

Problem Shown by Help Messages Other than CBDA400I and CBDA405I

If a message in the range CBDA400I to CBDA420I but other than CBDA400I and CBDA405I occurs, you have probably encountered a logic error in the dialog.

Table 16 and Table 17 show what the search argument and the problem data could look like.

Table 16. Search Argument

Search Argument	Description	Example
MS/cccnnns	Message identifier	MS/CBDA404
RIDS/CBDcccc	Help panel name	RIDS/CBDF401

Table 17. Problem Data

Problem Data	Example
Message identifier of the message that was issued. All additional information shown in the message, such as the name of the help panel or the reference phrase.	CBDA404
Panel identifier	CBDPDVF0
Help panel name	CBDF401

Table 17. Problem Data (continued)

Problem Data	Example
Description of the related field (in case of field help).	Action entry field
Name of the action choice (in case of action bar help).	
Name of the command (in case of command help).	

Problems with Output of HCD Textual Reports

Use this procedure if you find problems that relate to the HCD report facility.

1. Check the output of the report job for messages that provide additional information.
2. For incorrect or incomplete output:
   a. Compare the contents of the IODF with the output. For example, if the device features are not shown correctly in the OS device detail report, use the action ***View device definition*** on the I/O Device List panel to display the definitions of the device for which the report seems to be incorrect.
   b. If you find out that the definitions in the IODF are correct, but the report output is incorrect, report this problem to IBM.

Table 18 shows what the problem data could look like.

Table 18. Problem Data

Problem Data	Example
Type of report that was to be created.	Control unit detail report
JCL that was used to create the report.	
The content of the IODF for which the report was requested. Refer to "TRACE Command" on page 437 to create an IODF dump.	

Problems with Output of HCD Graphical Reports

When you have any problems printing or viewing a graphical configuration report, read the following problem descriptions. If you have any other problem, report the problem to IBM.

Screen Shows Four Dots

When displaying the configuration, the screen shows only four dots.

Check that the background and foreground color you specified in the HCD profile match. Choose a foreground color that is visible on the background color.

Incorrect DCF, GDF, or GML Format in Output Data Set

You can simply check, whether you have created the output format you have specified in the profile using the keyword GCR_FORMAT. Browse or edit the created data set.

BookMaster format will look like this:

```
:userdoc
.layout 1
.dr thick weight .4mm
.rh on
.sp 2
```

DCF format will look like this:

```
.df graph font X0GT20
.tr 31 AC BE BC 76 AB 30 BB 15 8F 77 CB 78 CC 80 EB 64 EC 6A FA 24 BF
.ll 240mm
.dr thick weight .4mm
.rh on
.sp 2
```

GML format will look like this:

```
:gdoc
.df graph font X0GT20
.tr 31 AC BE BC 76 AB 30 BB 15 8F 77 CB 78 CC 80 EB 64 EC 6A FA 24 BF
.ll 240mm
.dr thick weight .4mm
.rh on
.sp 2
```

If the output is not correct, make sure that:

- The HCD profile is allocated with ddname HCDPROF before invoking HCD.
- The profile contains the keywords GCR_FORMAT=DCF or GML and GCR_FONT with an appropriate font (for example, X0GT20 for 3820 printers).

For information on how to specify keywords in the HCD profile, refer to "Defining an HCD Profile" on page 41.

Illegible Printout when Using DCF or GML

The output of a report data set contains correct DCF and GML format, but the printout is illegible.

Make sure that:

- A monospaced font (for example, X0GT20 for 3820 printers) is specified in the HCD profile using the keyword GCR_FONT.
- The specified font is installed on your printer.

Output Exceeds Page Boundary

The printed output exceeds page boundary.

Make sure that:

- During printing you specified a parameter to print the report in landscape format, that is to rotate the printout by 90 degree.
- The parameter LAYOUT 1 was specified to use the full page for the report.

Box Characters Are Not Correct

When using DCF formatting, the box characters are not correct.

The graphical print facility uses special hex characters for the various box characters. These special characters are then translated to real box characters by means of the .tr command. If the selected font does not contain the box characters, you must either choose another font or modify the .tr command in the file generated by the graphical print facility. See the following table for information on which hex combinations HCD uses for the various box characters.

```
.tr 31 AC BE BC 76 AB 30 BB 15 8F 77 CB 78 CC 80 EB 64 EC 6A FA 24 BF
```

where

31	Upper left corner	**78**	Downward T
BE	Upper right corner	**80**	Leftward T
76	Lower left corner	**64**	Rightward T
30	Upper right corner	**6A**	Bar
15	Junction (+)	**24**	Hyphen (dash)
77	Upward T		

Table 19 shows what the problem data could look like.

Table 19. Problem Data

Problem Data	Example
Type of report that was to be created.	LCU report
The content of the IODF for which the report was requested. Refer to "TRACE Command" on page 437 to create an IODF dump.	

Problems During Initialization of HCD

If a problem occurs during initialization, HCD does one of the following:

- Issues a message and continues the initialization
- Terminates the initialization

Whether the initialization of HCD *continues* or *terminates* depends on the error that is encountered as explained in the following.

Initialization Continues

If a UIM service routine encounters an error during initialization, HCD works without this UIM. HCD pops up messages on the userapos.s terminal to inform the user that messages were written to the message log.

Note: If an error is encountered in a UIM *and* if SYSUDUMP is allocated, HCD does not continue. An HCD abend '00F' is forced to provide a dump at the point where the error was detected.

Use the option ***List Installed UIMs*** to display the panel "Installed UIMs". On this panel, the UIM is marked as in error. (Refer to "Query Installed UIMs" on page 238.)

If you do not have access to any UIM, check if your UIMs are correctly installed. In the HCD profile you can specify the name and volume serial number of the library that contains the UIMs (see "Defining an HCD Profile" on page 41). If you do not specify a name in the profile, SYS1.NUCLEUS is assumed as default names for the UIMs.

Initialization Is Terminated

The initialization is terminated either with an abend or with a message.

In case of an abend, the dialog:

- Pops up message CBDA040I on the user's terminal. The message informs the user that HCD has abnormally terminated.
- Puts message CBDA050I with abend code '00F' in the message log. The message also provides a reason code.
- Puts the message that is issued by a UIM service routine in the message log.

If an error is encountered in a UIM *and* if SYSUDUMP is allocated, an HCD abend '00F' is forced to provide a dump at the point where the error was detected.

Message CBDA041I: Means that HCD is not able to find the UIMs. If this message is issued during initialization using the "CIT" variable, make sure that the UIMs are installed in SYS1.NUCLEUS.

Table 20 and Table 21 show what the search argument and the problem data could look like.

Table 20. Search Argument

Search Argument	Description	Example
MS/cccnnns	Message identifier	MS/CBDA041I
PIDS/UIM name	UIM name	

Table 21. Problem Data

Problem Data	Example
UIM name	
Message ID(s) and full message text	CBDA041I
TRACE output data set Refer to "TRACE Command" on page 437.	

Problems with UIMs

For information on converting and testing UIMs, refer to *z/OS MVS Device Validation Support* .

The following explanations apply to UIMs provided by the installation and to UIMs provided by IBM.

Messages During Initialization of HCD

Internal logic errors in UIMs are primarily found during the initialization of HCD. Refer to "Problems During Initialization of HCD" on page 424 for information on how to proceed in case of initialization problems.

UIM Problems After Initialization of HCD

Internal logic errors in UIMs may also be discovered:

- During the definition of a device (as a string like ?PARMnn? on the Device Parameter Feature panel). Message CBDA381I indicates that you may have installed a back-level UIM.
- On the Installed UIMs panel when a UIM is flagged in error. In this case messages CBDA070I or CBDA096I may be issued. Message CBDA070I means that the UIM does not match the corresponding UDT. Message CBDA096I means an unresolvable conflict between a VM and MVS UIM.

You can use the message log, together with SYSUDUMP and HCDTRACE to find the error in the UIM that failed.

If the error relates to an installation-provided UIM, make appropriate corrections. For information on converting UIMs, refer to *z/OS MVS Device Validation Support* .

If the error relates to a UIM provided by IBM, report the problem.

Table 22 and Table 23 show what the search argument and the problem data could look like.

Table 22. Search Argument

Search Argument	Description	Example
MS/cccnnns	Message identifier	CBDA070I
PIDS/UIM name	UIM name	CBDUS025

Table 23. Problem Data

Problem Data	Example
UIM name	CBDUS025
Message ID(s) and full message text	CBDA070I
Type of action the user wanted to perform	List installed UIMs
TRACE output data set Refer to “TRACE Command” on page 437.	

HCD Internal Problems

When you have one of the following error situations, you probably have detected an internal HCD error:

- HCD displays wrong messages or does not display a message at all when you made a mistake.
- An HCD generated IOCP input data set causes error messages when using the IOCP program.

Report problems like this to IBM.

Table 24 and Table 25 show what the search argument and the problem data could look like.

Table 24. Search Argument

Search Argument	Description	Example
MS/cccnnns	Message identifier	
RIDS/CBDcccc	Panel identifier	RIDS/CBDPCH30

Table 25. Problem Data

Problem Data	Example
Message ID(s)	
Panel identifier	CBDPCH30
Type of action the user wanted to perform	Change Channel path definition
Description of configuration	

Problems with the Transmit Configuration Package Action

If a problem occurs during the ***Transmit configuration package*** action, HCD may:

- Not start the action due to authorization problems
- Not submit the job
- Submit the job but not complete it

Job Steps of the Transmit Procedure

Transmit configuration package builds a batch job with multiple steps. The step names are:

GO Creates an IDCAMS CLUSTER for a temporary work IODF.

ALLOCT2 Creates an IDCAMS CLUSTER for a temporary production IODF.

INIT1 Initializes the temporary work IODF.

INIT2 Initializes the temporary production IODF.

BLDPR1 The processor configurations that are contained in the configuration package are built into a data set as control statements. The processor list is specified via DD name HCDCNTL. If a processor contains a CFS channel path that has a connection to a CF partition external to the configuration package, the processor containing the CF partition is also included in the output data set.

MIGRPR1 The generated processor configuration control statements are migrated into the temporary work IODF while preserving the processor tokens from the master IODF.

PRINTPR1 The MESSAGES and LISTING data set are deleted if no error occurred.

BLDOS1 All OS configurations included in the configuration package are built into a data set as control statements. The OS configuration list is specified via DD name HCDCNTL.

MIGROS1 The generated OS configuration control statements are migrated into the temporary work IODF.

PRINTOS1 The MESSAGES and LISTING data set are deleted if no error occurred.

BLDSW1 The switch configurations of all switches containing ports that are connected to either a channel path or control unit of the processors of the configuration package are built into a data set as contol statements. The switch list is specified via DD name HCDCNTL.

MIGRSW1 The generated switch configuration control statements are migrated into the temporary work IODF.

PRINTSW1 The MESSAGES and LISTING data sets are deleted if no error occurred.

BPROD A temporary production IODF is built from the temporary work IODF.

EXPOATT The temporary production IODF is exported attended to the specified user/node ID.

EXPOUATT The production IODF is exported unattended to the specified system.

DEL1 The temporary work IODF is deleted.

DEL2 The temporary production IODF is deleted.

Note: Stepname GO is used for HCDDECK, HCDMLOG, HCDLIB, HCDTRACE, and HCDPROF. Thus, the data sets are made available to the steps which require them.

Temporary Data Sets Created by the Transmit Procedure

The transmit procedure creates the following data sets:

- hlq.IODFxx.zzzz (production IODF)
- hlq.IODFxx.XMIT.package.WORK (work IODF)
- hlq.IODFxx.XMIT.package.DECK (configuration decks)
- hlq.IODFxx.XMIT.package.MSGLOG (HCDMLOG)
- hlq.IODFxx.XMIT.package.sss.MESSAGES (HCDPRINT migration messages)
- hlq.IODFxx.XMIT.package.sss.LISTING (HCDASMP migration listing)

where:

hlq	is the high level qualifier specified on the transmit panel or the HLQ parameter of the batch utility.
xx	is the suffix of the target IODF name specified with the package
package	is the name of the configuration package to be transmitted
zzzz	are the qualifiers 3-n of the target IODF name
sss	qualify the migration type (PR1 for processor, OS1 for operating systems, SW1 for switch configurations)

After a successfully completed transmit action all these data sets, except the message log file, are deleted. The message log file is preserved until it is overwritten, when another transmit action using the same package name and IODF suffix is performed.

Apart from the production IODF, all redundant data sets remaining from a cancelled transmit action are identified by their common data set name qualifiers.

```
hlq.IODFxx.XMIT.package.
```

Authorization Problems

Because the last sent date of the IODF from which the transmit action is performed is updated with the current date, you require write access to the accessed production IODF. Otherwise message CBDG247I is displayed.

You also need permission to write to the data sets with the qualifiers of the IODF to be created and transmitted.

Job Is Not Submitted

If the work IODF or production IODF to be created temporarily exists already, it is not possible to start the transmit action. This may happen when a previous transmit job was cancelled, ended with an error or another transmit job is running which uses the same high level qualifier and target IODF name.

Depending on the source of the problem this may be resolved by deleting the existing temporary IODFs or by specifying a different high level qualifier for the target IODF.

Job Is Not Completed

The transmit action generates a batch job. Check the HCD message log file to find out if the job was executed. It is shown as a sequence of HCD batch job steps ending with a successful export message. There are several possible causes if this is not the case:

- JCL errors: check the job output. To see all statements including the inline statements which are generated by the HCD dialog and submitted, issue

  ```
  TRACE ON ID=JCL
  ```

  and perform the transmit action. For an example of a trace refer to“Customization Unsuccessful” on page 429.

- If the HCD message log file shows that a particular step failed, check the job output for potential allocation problems.
- If one of the migration steps failed, check the LISTING and MESSAGES data sets. (Refer to "Temporary Data Sets Created by the Transmit Procedure" on page 428 for more information on the data sets created during the action.) Ensure that the same versions of UIMs are available for the ***Transmit configuration package*** action as for creation of the IODF.

  The MESSAGES and LISTING data sets, as well as the generated decks, are deleted if no errors occurred. If you want to keep them, you can modify the conditional statements in procedure CBDJXMIT for the migrate steps. Do this by copying CBDJXMIT to a new procedure.

Proceed as follows, if you need to trace particular steps:

1. Define a profile including a TRACE statement.
2. Specify the stepname.HCDPROF DD with the profile name.
3. Allocate a trace data set name.
4. Specify GO.HCDTRACE DD with the name of the trace data set in order to use it for all steps to be traced or stepname.HCDTRACE to use the trace data set only for the single step.
5. To specify HCDDECK, HCDMLOG, HCDLIB, HCDTRACE, or HCDPROF use GO as the step name. The other steps refer to the definitions in the GO step. If you want to preserve a specific output data set, pre-allocate it to HCDDECK (see "Build I/O Configuration Statements" on page 295).

Customization Unsuccessful

This section describes points to be considered when customizing the transmit procedure.

The transmit procedure exploits the migration batch utility, which uses parsing macro CBDZPARS (residing in SYS1.MACLIB). If you want to use a different macro library, specify this as GO.HCDLIB

The dialog always generates and submits the following statements:

- All parameters for procedure CBDJXMIT
- The JOB card, JOBLIB and overwrite statements given by the user
- IDCAMS DEFINE CLUSTER and DELETE CLUSTER statements in steps GO, ALLOCT2, DEL1 and DEL2
- An HCDCNTL DD statement for at least one of BLDPR1, BLDOS1 or BLDSW1 job steps, dependent on the package content
- The SYSTSIN for EXPOATT or EXPOUATT, depending on whether attended or unattended export is selected

The following is a sample trace showing the batch job built by a transmit action.

```
09:53:01  97-11-04  Trace started.
//XMIT     JOB (3243),'OS390H1',MSGCLASS=X,CLASS=A,REGION=4M
//JOBLIB   DD DSN=SYS1.SCBDHENU,DISP=SHR
//XMT0    EXEC PROC=CBDJXMIT,PR=1,OS=1,SW=1,
//             ATTEND=1,RECORDS='1684',
//             DESC1='IODFST',DESC2='IODF88',
//             QUALX='IODF88.XMIT.CB88',
//             IODFTP='OS390H1.IODF88',
//             IODFTW='OS390H1.IODF88.XMIT.CB88.WORK',
//             IODFSP='IODFST.IODF11.MASTER'
//GO.SYSIN DD *
 DEFINE CLUSTER(                          -
```

```
       NAME ( OS390H1.IODF88.XMIT.CB88.WORK.CLUSTER) -
       LINEAR                                        -
       RECORDS (1684) -
       VOLUMES (DS7001)) -
       DATA(NAME(OS390H1.IODF88.XMIT.CB88.WORK))
/*
//ALLOCT2.SYSIN DD *
 DEFINE CLUSTER(                                     -
       NAME ( OS390H1.IODF88.CLUSTER) -
       LINEAR                                        -
       RECORDS (1684) -
       VOLUMES (DS7001)) -
       DATA(NAME(OS390H1.IODF88))
/*
//BLDPR1.HCDCNTL DD *
CB88
CF14    ,CF
/*
//BLDOS1.HCDCNTL DD *
B710
/*
//BLDSW1.HCDCNTL DD *
71
72
74
77
/*
//EXPOATT.SYSTSIN DD *
    CALL 'SYS1.LINKLIB(CBDMGHCP)', +
    'EXPORT,OS390H1,PKSTCB88'
/*
//DEL1.SYSIN DD *
       DELETE OS390H1.IODF88.XMIT.CB88.WORK.CLUSTER
/*
//DEL2.SYSIN DD *
       DELETE OS390H1.IODF88.CLUSTER
/*
09:53:29  97-11-04  Trace stopped.
```

Table 26 shows what the problem data could look like.

Table 26. Problem Data

Problem Data	**Example**
Job output	See example trace shown in section "Customization Unsuccessful" on page 429.
Message log file	
Trace of failing step	
Deck for failing step	
LISTING data set	See"Job Steps of the Transmit Procedure" on page 427
MESSAGES data set	See"Temporary Data Sets Created by the Transmit Procedure" on page 428
Submitted job (via TRACE ID=JCL)	
Procedure used (if modified)	

HCD LDAP Backend Abnormal Termination

There are two different locations at which the HCD LDAP Backend might terminate abnormally:

- The z/OS LDAP Server address space
- The HCD instance address space

The way to find out more information about the abnormal termination depends on in which of these locations it terminated see "LDAP Server Address Space" or "HCD Instance Address Space".

In general, whenever the HCD LDAP Backend or parts of it terminate abnormally, some global resources may remain in memory. These resources are so called POSIX message queues and are used for the Inter Process Communication (IPC) between the HCD LDAP Backend and the HCD instances. They have to be removed from the system manually.

To remove POSIX message queues from the system proceed as follows:

1. Look into the LDAP server started task log to find the identifiers (ID's) of all message queues allocated: The HCD LDAP Backend prints out all ID's using the message `CBD0004I`. Note that you have to find all of these `CBD0004I` messages.
2. Use the UNIX System Services command line tool `ipcs` to list all the POSIX message queues in memory.
3. Find those identifiers in the list which correspond to POSIX message queues belonging to the abnormally terminated HCD LDAP Backend.
4. Remove the appropriate message queues using UNIX System Service command line tool `ipcrm`.

LDAP Server Address Space

In general, diagnostic output can be found in the z/OS LDAP Server started task log. Investigate this log to find information, about the system or user abend code, the reason code, and additional messages and follow the instructions in "HCD Abnormal Termination" on page 416.

For more information on problem determination, refer to the manual *z/OS MVS Diagnosis: Procedures*. In the section on how to obtain a dump of the abnormally terminated program, determine whether the problem was caused by the HCD LDAP Backend or by any other program in the z/OS LDAP Server address space.

HCD Instance Address Space

Since an HCD instance resides in a different address space (created with a call to `spawn()`) to that of the corresponding LDAP server, it is not permitted to print its output to the LDAP server started task log. Instead, an HCD instance creates an HFS file containing diagnostic output. The name and location of this file follows the conventions described in the publication *z/OS Language Environment Debugging Guide* in the chapter "Using Language Environment Debugging Facilities". Note that the environment variable `_CEE_DMPTARG` is set to `/tmp` by default.

Example:
Assume that a language environment dump of the HCD instance with the process ID 197 is taken at 05:55:01 pm on September 18, 1998. The file containing the dump will be called `CEEDUMP.19980918.175501.197` and it will be located in the HFS directory `/tmp`.

Adverse LDAP Return Code from the HCD LDAP Backend

Each LDAP client's request is answered by the LDAP server with an LDAP response containing a return code for the request. Such a return code can be either good (LDAP_SUCCESS) or bad (e.g. LDAP_UNWILLING_TO_PERFORM). These numeric return codes can be transformed into text messages (e.g. "DSA is unwilling to perform.") using the LDAP client API.

Return codes such as LDAP_OPERATIONS_ERROR, LDAP_NO_MEMORY, or LDAP_LOCAL_ERROR typically indicate a problem within the LDAP server, the HCD LDAP Backend, or the LDAP client. If you assume the problem to be located in the LDAP server or the HCD LDAP Backend, look into the LDAP server started task log and search for error messages.

Return codes such as LDAP_INAPPROPRIATE_MATCHING, LDAP_INVALID_DN_SYNTAX, or LDAP_UNWILLING_TO_PERFORM typically indicate a malformed LDAP request. Check if your request conforms with the appropriate constraints. You may also check the LDAP server started task log for error messages.

Error in HCD LDAP Backend

If the HCD LDAP Backend's message CBD0009E is printed to the LDAP server started task log, an error situation was encountered inside the HCD LDAP Backend while performing an operation. Switch on LDAP server debug level LDAP_DEBUG_ERROR and reproduce the problem. The log will contain more information concerning the reason of the error. You may additionally specify debug level LDAP_DEBUG_TRACE to get detailed informations about the operations performed by the HCD LDAP Backend.

The following illustrates two typical error situations with advice on how to check for these problems.

HCD Instance Startup Fails

If an HCD instance cannot be started correctly, this will not lead to error messages in the LDAP server started task log or to bad return codes for the LDAP client in all cases.

Consider the following possible scenario: The LDAP server is started together with the HCD LDAP Backend which, in turn, launches at least one HCD instance. All launched HCD instances fail to start. As the HCD LDAP Backend has no indication that the HCD instances failed to start, it will wait forever for an acknowledgement from the HCD instances. Incoming requests will be scheduled for an HCD instance and will be blocked up until an acknowledge arrives. In this way, the requests will never be performed and no LDAP response will be sent to the requesting LDAP client.

From the LDAP client's point of view: If the very first request for the HCD LDAP Backend is pending for a long time, the HCD instances might have failed to start up. In general, if one HCD instance fails to start up, all HCD instances will fail.

To check to see whether an HCD instance faild to start, look in the LDAP server started task log: HCD LDAP Backend's message CBD0007I will indicate how many HCD instances will be started. If all of these HCD instances are able to start up correctly, you will find an appropriate number of CBD1002I messages. If you cannot find them it's most probable that the HCD instances failed to start up.

HCD Instance User ID Switch Fails

If you have set up the z/OS LDAP Server or the HCD LDAP Backend incorrectly, the HCD instances might have problems switching their User ID appropriately. It might be possible that the User ID switch fails completely, or only for one or more specific User IDs.

If you assume that LDAP requests can't be performed because of a failed User ID switch, you can check your assumption as follows:
Search for the `CBD0009E` message in the LDAP server started task log. If you can find it switch on LDAP server debug level `LDAP_DEBUG_ERROR` and search for message `EDC5139I`. This message indicates that the User ID switch has failed.

Finally, check the setup of your HCD LDAP Backend.

Diagnostic Information and Tools

The information and tools described in this section help you to diagnose system problems.

HCD Messages

In case of an error, HCD issues messages. Depending on what you are currently doing, the messages are written:

- To the terminal as a single message
- To the terminal in a message list
- In a message log
- In a migration log
- In the output of a batch job

Terminal Messages

User-errors, such as erroneous syntax entry and contextually wrong definitions, are handled by the dialog at the time of data entry. That is, the dialog displays messages at the terminal and the user can take corrective action immediately.

Some operations produce multiple messages. In this case, HCD displays a message list. You can save the displayed messages from the message list into the message log. See "Message Lists" on page 74 on how to work with message lists.

Message Log

Errors that are of low interest for the end user, such as incomplete UIMs during initialization, are only written to the message log. The user will be informed about this when leaving the dialog or switching to another IODF. Only in critical situations (for example, when the message log is not available), will the messages be written into the ISPF list data set. If this, however, also fails, the message will be written into the operating system log.

To see a message in the message log, issue the SHOWMSG command or use the ***View message log*** pull-down choice from the ***Query*** action bar on any action list panel.

Migration Log

HCD maintains a migration log that contains messages issued by the migration process. You can view this migration log through ISPF.

Figure 170 on page 434 shows where you can find messages while working with HCD.

Mode of Operation	You Find the Message
Dialog Mode	On the terminal In the message log
Batch mode	In the message log, that is the data set allocated with ddname HCDMLOG In the output (SYSPRINT) of the batch job [1]
Migration of input data sets	In the migration log, that is the data set allocated with ddname HCDPRINT
IPL	Trapped by IPL. A wait state code is issued.
HCD LDAP Backend	In the LDAP response, which the LDAP server sends to the LDAP client. In the z/OS LDAP Server started task's log.
Note: [1] The output shows the message number and text; for explanations refer to *z/OS HCD Messages*.	

Figure 170. Where to Find HCD Messages

LDAP Response

If HCD is used as part of the HCD LDAP Backend, HCD will issue messages if problems occur. These messages can be made visible in the following way:
In general, LDAP clients send their requests to the LDAP server and get an LDAP response for each request. If an LDAP client requests an operation from HCD via the HCD LDAP Backend and HCD encounters any problems while working on the request, HCD issues one or more text messages. These messages are sent back to the LDAP client as a part of the LDAP response and can be extracted using the LDAP client API.

The command line utilities (e.g. `ldapsearch` or `ldapmodify`) part of the z/OS LDAP Server show the messages contained in the LDAP response as "additional info".

z/OS LDAP Server Started Task Log

The HCD LDAP Backend runs as a part of the z/OS LDAP Server and all HCD LDAP Backend messages are printed to the same location as the LDAP server messages. The LDAP server runs as started task for the HCD LDAP Backend and the messages from the server and all of its backends are printed to the LDAP server started task log.

The HCD LDAP Backend and its HCD instances print some informational and error messages to the LDAP server started task log. If the LDAP server debug is switched on (i.e. debug level is not `LDAP_DEBUG_OFF`), all diagnostic output is also printed to the started task log. The regular HCD LDAP Backend messages and the additional debug output can be used to verify that the HCD LDAP Backend is working correctly.

HCD Trace Facility

The output of the HCD trace facility provides information to locate internal HCD problems. It helps the IBM program system representative to identify the cause of a failure.

Data Set

The trace records generated by HCD are recorded in the trace data set.

The trace data set must be preallocated with a ddname of HCDTRACE. If the trace data set is not allocated when HCD is invoked, no tracing takes place. The default CLIST that is provided with HCD allocates a trace data set with the name HCD.TRACE, prefixed by your user ID.

Trace Records

The trace records show the control flow within the various HCD modules. Trace information is written into the trace data set:

- Whenever a module (CSECT) gets control.

  In this case, the passed parameter list is recorded together with the name and description of the invoked module.
- Whenever a module (CSECT) returns to its calling routine.

  The passed parameter list containing the return and reason codes is recorded.

When HCD is invoked, HCD overwrites the existing trace with the new trace data. If you want to retain the existing data, you have to make sure that the data is saved.

Figure 171 on page 436 is an example of a trace output. The following explains the records you see:

```
17:00:13  96-08-01  Trace started
```

The time stamp shows when the trace facility was started. This record is useful to identify the trace data sets when multiple traces are produced on the same day.

```
PUSH CBDMSMSG   -   Message Routine  96214 HCS6031   17001352   08472028
```

This line indicates that control has been passed to another module at a certain time. In this example, the module named CBDMSMSG with service level '96214 HCS6031' received control at 17:00:13.52 at storage address `X'08472028'`. The records also give a short description of what the module does, and the parameter list that is passed to the called module.

```
CBDMSMSG Message destination: Screen
```

This trace entry is written by the called module.

```
POP CBDMSMSG   -   Message Routine                   17001353
```

Indicates that control from the module named CBDMSMSG is returned to the calling routine at 17:00:13.53. Also, the passed parameter list is shown again, but now the parameter list contains the return/reason code indicating how successful the requested function was.

```
17:01:24  96-08-01  Trace stopped
```

The last entry in the trace output is a time stamp that indicates end of tracing.

```
17:00:13  96-08-01  Trace started.
   :
PUSH CBDMSMSG   -   Message Routine  96214 HCS6031 17001352   08472028
00000000    D4E2C740 C3C2C4C1 F1F2F6C9 C9000100   *MSG CBDA126II"""*
00000010    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000020    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000030    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000040    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000050    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000060    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000070    00000000 00000000 00000000 00000000   *"""""""""""""""*
CBDMSMSG Message destination: Screen
00000000    E3D9C1C3 C5408396 94948195 8440A681   *TRACE command wa*
00000010    A2408183 838597A3 85844B              *s accepted.     *
POP  CBDMSMSG   -   Message Routine                         17001353
00000000    D4E2C740 C3C2C4C1 F1F2F6C9 C9000100   *MSG CBDA126II"""*
00000010    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000020    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000030    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000040    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000050    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000060    00000000 00000000 00000000 00000000   *"""""""""""""""*
00000070    00000000 00000000 00000000 00000000   *"""""""""""""""*
    .
    .
    .
17:01:24  96-08-01  Trace stopped.
```

Figure 171. Example: Trace Output

Figure 172 on page 437 is an extract of a trace output when an abend occurred. The following explains the record in the example.

E S T A E: The entries show information that was recorded by the HCD ESTAE routine. Entries under ***Diagnostic stack*** list the modules that were executing when the abnormal termination occurred, together with the service levels. The first entry names the module that ended abnormally; in this example, the module is CBDMDPK5. The entries also show the control flow between the various HCD modules. In this example:

- Module CBDMDPK0 called module CBDMDPK5.
- Module CBDMGDIA called module CBDMDPK0.
- Module CBDMGHCP called module CBDMGDIA.
- and so on.

```
*******************************************************************
*          E S T A E                                              *
*          System abend code  :  00F                              *
*          Reason code        :  00990654                         *
*          HCD version        :  OS/390 2.5.0 HCD                 *
*          Diagnostic stack   :  CBDMDPK5   97207   HCS6051       *
*                                CBDMDPK0   97207   HCS6051       *
*                                CBDMGDIA   97206   HCS6051       *
*                                CBDMGHCP   97207   HCS6051       *
*                                                                 *
*          Module name        :  CBDMGHCP                         *
*          Entry point address:  0003C9C8                         *
*          PSW                :  078D0000 80044498                *
*                                                                 *
*    R0  00000340  R1  8400F000  R2  00044604  R3  062C1494       *
*    R4  062BC4DA  R5  00000005  R6  00000000  R7  062BCAD0       *
*    R8  00000000  R9  062BCAC4  R10 85D0C900  R11 862BB236       *
*    R12 800443A8  R13 062BBF84  R14 062BCAC4  R15 00990654       *
*******************************************************************
```

Figure 172. Example: Trace Output in Case of Abend

Activating the Trace

The trace can be activated either:

- Dynamically by using the TRACE command in the HCD dialog. The command is optional, and can be entered whenever a displayed panel has a command line. For information on the TRACE command, refer to "TRACE Command".
- By invoking HCD (for details see Chapter 12, "How to Invoke HCD Batch Utility Functions" on page 283) with the TRACE option specified in the passed parameter string (this is done automatically by the entry in the CLIST).

```
//BWINJOB  JOB (3259,RZ-28),'BWIN',NOTIFY=BWIN,CLASS=A,
//            MSGCLASS=Q,MSGLEVEL=(1,1),REGION=4M
//REPORT1  EXEC PGM=CBDMGHCP,
//             PARM='TRACE,REPORT,CSMEN,PROC1,PART1,MVS1,00'
                   .
                   .
                   .
//HCDTRACE DD   DSN=BWIN.HCD.TRACE,DISP=OLD
//
```

- By specifying the TRACE command in the HCD profile, see "Defining an HCD Profile" on page 41 for the TRACE profile statement.

The tracing stays active until either turned off by the TRACE command, or until HCD terminates.

TRACE Command

The TRACE command activates and deactivates the HCD trace facility. The command allows you also to limit the detail of data written into the trace data set by requesting that only certain functions and details should be traced.

The TRACE command can be entered on any HCD panel showing a command line. The command can also be specified in the HCD profile (see "TRACE Command" on page 44).

For HCD to write the output to the trace data set, ON must be specified with at least one trace category (or you must have invoked HCD with the TRACE

parameter, see “Activating the Trace” on page 437). To view the trace output, you have to close the trace data set first. You can do this by either leaving HCD or by entering the command TRACE OFF,CLOSE.

The format of the command is as follows:

TRACE Command

```
►►─TRace──┬─ON──┬─ trace-category ─┬──────────────────────────────►◄
          │     │                  │
          ├─────┤ trace-category ──┤
          │     │                  │
          └─OFF─┴──────────────────┴
                │ ┌─────────────┐
                └─┴─,CLOSE──────┴
```

trace-category:

```
   ┌─,──────────────────────────────────────────────────────────────┐
   ▼                                                                 │
├──┬─ALL──────────┬──┬──────────────┬──┬──────────────────────────┬──┤
   ├─Batch────────┤  └─,LEVEL=n─────┘  ├─,ID=IODF──────────────┬──┤
   ├─Command──────┤                    │                        │  │
   ├─Dialog───────┤                    │                        └─,REPAIR─┘
   ├─DYNamic──────┤                    ├─,ID=JCL─────────────────┤
   ├─HOM──────────┤                    └─,ID=IOOPSOUT────────────┘
   ├─Migration────┤
   ├─Repository───┤
   ├─RepService───┤
   ├─RESET────────┤
   ├─Service──────┤
   ├─UIM──────────┤
   ├─UIMService───┤
   ├─Utility──────┤
   ├─Validation───┤
   └─Other────────┘
```

Note: You may abbreviate some of the keywords. The characters you have to use are indicated by uppercase (you must then omit lowercase). For example `RepService` may be abbreviated as `RS`.

ON Starts the trace facility.

OFF Stops the trace facility.

CLOSE Closes the trace data set.

trace category Specifies the functional scope to be traced:

ALL	Trace everything.
Batch	Trace all batch routine.
Command	Trace all command routines.
Dialog	Trace all dialog routines.
DYNamic	Trace all dynamic routines.
HOM	Trace all object management routines.
Migration	Trace all migration routines.
Repository	Trace all repository main routines.
RepService	Trace all repository service routines.

RESET	Reset all currently active categories, LEVEL and ID.
Service	Trace all service routines.
UIM	Trace all UIM routines.
UIMService	Trace all UIM service routines.
Utility	Trace all utility routines.
Validation	Trace all validation routines.
Other	Trace all other not yet mentioned routines.

LEVEL=*n*
Assigns a level of detail to the functions to be traced, where *n* is a decimal number ranging from 0 to 255. If the option is omitted a level of 0 is assumed. The TRACE option described in "Input Parameter String" on page 284 is equivalent to the command `TRACE ON,ALL,LEVEL=255`.

ID=IODF
Writes an IODF dump into the trace data set. This parameter cannot be specified in the HCD profile. If you have a consistent IODF, an output in the trace data set is only shown when you set `LEVEL=128` or higher. Otherwise, an output is only shown if the IODF contains defects.

REPAIR
Removes detected errors in the work IODF and reports corrections in the trace data set. Before you use the REPAIR option, you must set the work IODF in update mode.

ID=JCL
Writes into the trace data set all statements generated and submitted when the ***Transmit configuration package*** action is invoked from the HCD dialog.

ID=IOOPSOUT
Writes into the trace data set all responses of I/O Operations IHVAPI2 calls. These are the results of I/O Operations query requests.

Trace Command via HCD Profile

- If HCD is started with the TRACE keyword, (e.g. HCM is started with the TRACING box in the HCM login panel checked, or via the LDAP server configuration file), initially *all* the trace categories will be traced. After the HCD profile has been read, however, the TRACE parameters there may modify the TRACE behavior.
- The TRACE parameters set in the HCD profile will also influence the TRACE behavior if you activate the tracing in HCM at a later time.
- The TRACE parameters set in the HCD profile will determine the contents of the trace for the rest of the session.
  - If you use the `RESET` option followed by trace categories *cat1,cat2,...,catn*, then only the categories *cat1,cat2,...,catn* will be considered. The `RESET` option must be the first option because the trace categories are additive (LEVEL is set to 0).
  - Specifying the keyword `off` will terminate the startup trace.
  - Specifying the keyword `on` will start the HCD trace (if not already started) and will invoke the trace parameters of the TRACE statement.
  - Specifying `LEVEL=`*n* will set the level of trace detail. If the `LEVEL` parameter is not set, then the trace will use the maximum level of 255.
- If no categories are set explicitly, then all trace categories will be active.

IODF Dump

Use the ID=IODF parameter of the TRACE command to produce an IODF dump. This command goes through your IODF, checks it for corrupted data, and writes all records and defects into the trace data set. If you have a consistent IODF, you must set the LEVEL parameter to `LEVEL=128` or higher to get an output. Otherwise, an output is only shown if the IODF contains defects.

If your IODF has defects, error message CBDA999I 'Defect(s) detected in IODF xxx' is displayed, and message CBDA099I is written into the message log data set. In addition, the trace data set records defects with the string 'Error:' followed by the reason. You can locate the reported defects by searching to that string in the trace data set.

If no defects are detected in the IODF, message CBDA126I 'TRACE command was accepted' is given.

If you cannot invoke HCD, and therefore, cannot use the TRACE command any longer, use a JCL stream for producing a dump. Figure 173 is an example of the JCL stream for producing an IODF dump.

Make changes to the entries according to your installation requirements.

```
//WAS$IODF JOB '3259,BOX01,S=C','SMITH',MSGLEVEL=(1,1),
//             NOTIFY=WAS,CLASS=A,MSGCLASS=Q,REGION=4096K
//PRTVSAM  EXEC PGM=IDCAMS
//INPUT    DD  DSNAME=WAS.IODF02.WORK,DISP=SHR
//OUTPUT   DD  DSNAME=WAS.IODF02.DUMP,UNIT=SYSALLDA,
//             SPACE=(CYL,(20,10)),
//             DCB=(LRECL=125,BLKSIZE=629,RECFM=VBA),
//             DISP=(NEW,CATLG)
//SYSPRINT DD  SYSOUT=*
//SYSIN    DD  *
     PRINT -
       INFILE(INPUT) -
       DUMP -
       OUTFILE(OUTPUT)
/*
//
```

Figure 173. Example: JCL Stream for Producing an IODF Dump

Repair an IODF

If your IODF contains defects, some of them can be repaired with the REPAIR option of the TRACE ID=IODF command.

First, your work IODF must be set in update mode to correct defects. You can do this, for example, by changing a description field in your work IODF. A production IODF cannot be repaired.

To repair defects in your work IODF, add the REPAIR option to the TRACE ID=IODF command: TRACE ON,REPAIR,ID=IODF.

Each corrected defect is recorded in the trace data set with the string 'Defect has been corrected'.

If a defect has been repaired, message CBDA998I, 'Defect(s) detected in IODF xxx. Repair action performed.' is issued. Repeat the TRACE ID=IODF command to check whether all defects could be corrected.

MVS Dumps and Traces

To aid in diagnosing problems, z/OS automatically provides messages and error records, and on request dumps and traces. HCD uses those services to record errors. For information about:

- Dumps and traces, refer to *z/OS MVS Diagnosis: Tools and Service Aids*.
- Using the diagnostic information, refer to *z/OS MVS Diagnosis: Procedures*.

IPCS Reports

z/OS allows you to format dumps into diagnostic reports. To produce the reports, use the Interactive Problem Control System (IPCS).

For information, refer to:
- *z/OS MVS IPCS User's Guide*
- *z/OS MVS IPCS Commands*
- *z/OS MVS IPCS Customization*

LDAP Problem Determination

For additional information you may also refer to the following sections of this chapter: "HCD LDAP Backend Abnormal Termination" on page 431, "Adverse LDAP Return Code from the HCD LDAP Backend" on page 432 and "Error in HCD LDAP Backend" on page 432.

In addition to the regular text messages from the HCD LDAP Backend, debug output can be requested. This debug output is switched on or off by specifying a debug level for the LDAP server (see *z/OS Security Server LDAP Server Administration and Use* and is printed to the same location as the HCD LDAP Backend text messages. HCD LDAP Backend's debug output is only available in english language and character representation IBM-1047.

The HCD LDAP Backend mainly supports two debug levels: `LDAP_DEBUG_ERROR` and `LDAP_DEBUG_TRACE`.

`LDAP_DEBUG_ERROR` causes all the information concerning errors, detected while performing operations, to be printed. From the HCD LDAP Backend's point of view, `LDAP_DEBUG_ERROR` can be switched on regularly without significant performance loss.

`LDAP_DEBUG_TRACE` causes all important program operations to be printed. From the HCD LDAP Backend's point of view, `LDAP_DEBUG_TRACE` should only be used when reproducing error situations for problem determination.

If you have general problems getting the z/OS LDAP Server, RACF Backend, or any other backends running, leave out all HCD LDAP Backend definitions from the started task and LDAP Server configuration files (slapd.conf). If the server and Backends still will not run, contact the LDAP Server Service.

If everything functions correctly without the HCD LDAP Backend and abends with the HCD LDAP Backend, then request a dump and check there for further information.

If the dump indicates that functions in `DLL GLDCMMN` or `GLDUTILS` are missing, it could be that the z/OS LDAP Server functionality is not available.

Searching Problem Reporting Data Bases and Reporting Problems

Search arguments are used to search problem reporting data bases. If the problem being diagnosed was already reported and the symptoms entered into the data base, the search will produce a match.

To perform a search, do the following:

1. Analyze the problem reporting data base and develop a search argument using the information provided in the boxes labeled *Search Argument*.
2. Complete the digits (such as ccc, nnn, hhh) according to the applicable conditions. For example, if the message CBDA099I was received, the developed search argument for *message identifier* would be: MS/CBDA099I. An example is shown in Table 7 on page 417.
3. Use the search arguments to search *problem reporting data bases*. If the search finds that the problem has been reported before, request a fix from IBM.

   If the search is unsuccessful, report the problem to the IBM Support Center. Submit the information that is listed in the *Problem Data* tables. An example is shown in Table 8 on page 417.

For more detailed information on these steps, refer to *z/OS MVS Diagnosis: Procedures*.

Sending an IODF to a Different Location

There may be situations, in which an IODF is to be transferred to a different location or system. Usually, the HCD Export/Import Utility can be used to transmit the IODF to the desired target destination. Sometimes, however, there are situations, where this may not be possible (e.g. a direct connection does not exist). The following steps describe a simple method in which you can transfer your IODF data from one z/OS host to any other z/OS or OS/390 host even if a direct transmission path not available. You can transfer an IODF as an attachment to an e-mail note sent via the internet or stored on a CD-ROM which can be taken to the other location:

1. Examine the size of the IODF, which is to be transferred. Check for the number of allocated 4K blocks (either under the HCD dialog ***Define, modify, or view configuration data***, ***View I/O definition file data*** or via HCM in the IODF Details... dialog). You have to remember this number for later.
2. Use the HCD Export function, found under the HCD dialog ***Define, modify, or view configuration data***, ***Export I/O definition file*** in the HCD dialog. Send the IODF to your own userid i.e. to the userid of the host on which you are currently working. HCD will export the IODF data as a sequential data set to your own userid. If you specify an asterisk (*) for the target user ID and target node ID, the sequential data set is not transmitted but rather written directly to the data set *user*.EXPORTED.IODFnn.xxxx. In this case, you can skip step 4.
3. Exit the HCD dialog.
4. Use the TSO RECEIVE command to retrieve the IODF data from your internal reader. Per default, you will get a sequential data set *user*`.EXPORTED.IODFnn.xxxx`. This data set has the record organization `FB` and `LRECL=BLKSIZE=4096` and the number of blocks as mentioned under 1. above).
5. Download this data set to your workstation. It is important that you ensure that the download is in *binary* mode.

6. To save storage resources, you may consider compressing (zipping) the downloaded file on the workstation.
7. It is now a simple matter to transfer the IODF data to a different location. For this purpose, you can either attach the data to a note and send it via e-mail, or you can write the IODF data to a CD-ROM which can be taken to the other location/workstation.
8. Once the IODF data has arrived at the target workstation, you have to uncompress (unzip) the file if it has been compressed for transportation.
9. On the target z/OS host pre-allocate a data set into which the IODF data is to be uploaded. It must be a sequential data set with `FB, BLKSIZE=LRCL=4096` and the number of blocks must be the number of allocated blocks of the original IODF (see 1. above).
10. Upload the IODF data from the workstation to the z/OS host in binary mode into the pre-allocated sequential data set.
11. Use the HCD Import function, found under the HCD dialog ***Define, modify, or view configuration data***, ***Import I/O definition file*** and specify the sequential data set to be imported into an IODF data set using the name of your choice.

Appendix D. HCD Object Management Services

Programming Interface information

The HCD object management services (HOM) provide an application programming interface for retrieving data from the IODF, such as switch data, device type, or control unit type. The programs requesting the services cannot run in APF-authorized state.

The mapping macros CBDZHRB, CBDZHIEX, CBDZHOEX, and CBDZHCEX (see "Data Input and Output Areas" on page 446, and "Request Block (HRB)" on page 447) are not available as source code. The macros are listed in the *z/OS MVS Data Areas, Vol 1 (ABEP-DALT)* manual, and must be coded by the application writer.

How to Invoke the HOM Services

Programs can invoke the services from the HCD routine CBDMGHOM. An application issuing a request must have its own copy of the CBDMGHOM routine dynamically loaded or linked. For every request, the application has to pass the parameters shown in Figure 174 on page 446 using standard linkage conventions.

© Copyright IBM Corp. 1994, 2002

Register	Contents
0	Undefined
1	Address of five-word parameter list: 1. **Address of request control block (HRB)** 4-byte field containing the address of the request block. The request block contains the function, the object to which the function is applied, and qualifiers, attributes, and parameters. See "Request Block (HRB)" on page 447 for more details. 2. **Address input data or zero** 4-byte field containing the address of the data input block if the request requires input. It is required on a HRB_SETUP request. See "Data Input and Output Areas" for more details. 3. **Address of length of input data or zero** 4-byte field containing the fullword fixed binary integer containing the length of the input data. It must correspond to the exact length of the data contained in the data-input block, that is, no trailing or intermediate blanks are allowed. 4. **Address of pointer to output data or zero** 4-byte field containing the address of the data output block if the request returned output. It is required on HRB_DGET and HRB_MGET requests to obtain the data and messages from the API. See "Data Input and Output Areas" for more details. 5. **Address of length of output data or zero** 4-byte field containing the fullword fixed binary integer containing the length of the output data. The parameters must be coded in the order shown. Only the first parameter (address of request block) is mandatory. The others are optional and depend on the type of request, as shown in Figure 175 on page 449. If you omit an optional parameter, you must specify a zero instead.
2-12	Undefined
13	Address of 18 word save area
14	Return address
15	Entry point address

Figure 174. Registers Used and Parameters Passed

Note: The service supports calls for both 24-bit and 31-bit addressing mode.

Data Input and Output Areas

Data input and output areas must be contiguous areas of main storage allocated by the application in private storage and freed later on.

The areas have no header section, that is, the data starts at the first byte of the area and continues without gaps. The data contained in these areas are the interface records, which are described in the mapping macros CBDZHOEX and CBDZHIEX in *z/OS MVS Data Areas, Vol 1 (ABEP-DALT)*.

For the GET request, the output area might contain the definition of multiple objects on return, whereas the input area normally contains only one object.

Issue a HRB_DGET function to get the provided output data. The size of the output data is returned by the previous GET request. The application is responsible

to allocate the correct output size. If the data does not fit into the size allocated by the application for the output area, the data will be truncated.

Request Block (HRB)

The HOM request block (HRB) you have to set up is described fully as mapping macro CBDZHRB in *z/OS MVS Data Areas, Vol 1 (ABEP-DALT)*. Table 27 summarizes the request block names and constants you can specify for the functions shown in Figure 175 on page 449.

On input, this block contains the detailed request to the HOM services. On output, it contains the data requested, messages, return codes, and reason codes.

The field HRB_OBJECT with all its subfields describes the object that should be processed on the request to the API.

The object code HRB_OBJ_CODE must be coded for every request, because it identifies the class of objects that are subject of the actual request.

The constants and flags required to describe the objects are contained in CBDZHCEX, which is documented in *z/OS MVS Data Areas, Vol 1 (ABEP-DALT)*.

Table 27. Summary of Request Block Names and Related Constants

Name	Constants	Description
HRB_SDESC	HRB_SDESC_C	Request block storage descriptor. Required for all requests.
HRB_LENGTH		Length of the request block HRB.
HRB_USE_IODF		Name of the IODF to be used for the request.
HRB_FUNCTION	HRB_SETUP HRB_OPEN HRB_GET HRB_ACT_STATUS HRB_DGET HRB_MGET HRB_CLOSE HRB_TERMINATE	Function code
HRB_OBJ_CODE	HRB_HCD	Required for SETUP and TERMINATE.
	HRB_IODF	Required for OPEN and CLOSE.
	HRB_PROCESSOR	Required for processor.
	HRB_PCU	Required for physical control unit.
	HRB_DEVICE	Required for device.
	HRB_SWITCH	Required for switch.
	HRB_CHANNEL	Required for channel path.
	HRB_DATA	Required for DGET.
	HRB_MESSAGE	Required for MGET.
	HRB_IODF	Required for ACT_STATUS.
HRB_OBJ_NAME		May be used to specify the name and number of an object. For devices, the number includes the suffix.
HRB_OBJ_NR		

Table 27. Summary of Request Block Names and Related Constants (continued)

Name	Constants	Description
HRB_Q_CODE	HRB_PCU HRB_DEVICE HRB_SWITCH	May be used together with HRB_PROCESSOR to specify that the processor data is qualified by the control unit, device, or switch.
	HRB_PROCESSOR	May be used together with HRB_CHANNEL to determine the kind of channel path data.
HRB_Q_NAME		May be used to specify the qualifier name and number for composite names.
HRB_Q_NR		
HRB_REQ_MODE	HRB_MODE_ID	Gets objects starting with the ID specified. The ID of the object must be set in HRB_OBJ_NR or HRB_OBJ_NAME. The HRB_RANGE_VALUE must not be zero.
	HRB_MODE_FIRST	Gets first object in the defined scope.
	HRB_MODE_LAST	Gets last object in the defined scope.
	HRB_MODE_ALL	Gets all objects in the defined scope.
	HRB_MODE_CHAIN	Gets all objects within the chain defined by the given object, for example, all devices of a multi-exposure device.
HRB_RANGE_VALUE		May be used to specify the number and direction of objects to be processed (positive number = subsequent objects; negative number = preceding objects).
HRB_TRACE	HRB_YES	The request is traced. Make sure that the trace data set is allocated with a DD name of HCDTRACE.
HRB_RESULT		The subfields of HRB_RESULT contain the output of the request, such as the data requested, the size of the output data, or return codes.

Functions

The HCD application programming interface provides the functions described in Figure 175 on page 449. The functions are listed as you need them while requesting data from the HCD HOM services. The constants you have to specify for HRB_FUNCTION and HRB_OBJ_CODE are included in the figure.

Task	Fields in Request Block (HRB)		Explanation
	HRB_FUNCTION=	**HRB_OBJ_CODE=**	
1. Set up the connection to the HCD API			
Setup connection	HRB_SETUP	HRB_HCD	Establish the HCD environment by passing the setup function in the request block. **Input:** HCD session interface (HSI) record.
2. Open the IODF			
Open IODF	HRB_OPEN	HRB_IODF	Open an IODF, for which you have read authority, by passing the HRB_OPEN function in the request block.
3. Request data for HCD objects			
Get Processor	HRB_GET	HRB_PROCESSOR	Issue a request with the GET function to retrieve data from the IODF. The request returns the address and the length of the data output block. Issue a request with the HRB_DGET function to obtain the retrieved information. **Note:** Issue HRB_GET and HRB_MGET before requesting additional data, because the new request deletes all data and messages from the previous request.
Get Channel Path	HRB_GET	HRB_CHANNEL	
Get Switch	HRB_GET	HRB_SWITCH	
Get Physical Control Unit	HRB_GET	HRB_PCU	
Get Device	HRB_GET	HRB_DEVICE	
Get Activation Status	HRB_ACT_STATUS	HRB_IODF	The request allows you to identify the currently active IODF, processor, and so on. **Output:** Activation status interface (ASI) record.
4. Get the data from the previous GET request			
Data Get	HRB_DGET	HRB_DATA	Issue the request with the address and length of the output area to obtain the data retrieved with the previous GET function. **Output:** Interface record for the object.
Message Get	HRB_MGET	HRB_MESSAGE	Check the return and reason code of the previous GET request. If the return code is warning, error, or severe, issue the request with the address and length of the output area to obtain the messages. **Output:** Message interface (MSI) record.
5. Close the IODF			
Close IODF	HRB_CLOSE	HRB_IODF	When you do not need the IODF IODF by issuing anymore, close the IODF by issuing a request with the close function.
6. Terminate the connection to the HCD API			
Terminate connection	HRB_TERMINATE	HRB_HCD	When you do not need the HOM services anymore, terminate the connection by issuing a request with the terminate function.

Figure 175. Functions Provided by the HOM Services

Example

The example shows how to get a range of 20 devices, starting with ID X'414'and connected to control unit X'21'. The example is shown in pseudo-code because the actual syntax and declarations depend on the programming language used.

```
...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_FUNCTION    = HRB_SETUP
HRB_OBJ_CODE    = HRB_HCD
Load or link CBDMGHOM with: (HRB-address,HSI-address,HSI-length,0,0)
 ...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_USE_IODF    = IODF-name
HRB_FUNCTION    = HRB_OPEN
HRB_OBJ_CODE    = HRB_IODF
Load or link CBDMGHOM with: (HRB-address,0,0,0,0)
 ...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_USE_IODF    = IODF-name
HRB_FUNCTION    = HRB_GET
HRB_OBJ_CODE    = HRB_DEVICE
HRB_OBJ_NR      = X'0414000'
HRB_Q_CODE(1)   = HRB_PCU
HRB_Q_NR(1)     = X'00000021'
HRB_REQ_MODE    = HRB_MODE_ID
HRB_RANGE_VALUE = X'00000014'
Load or link CBDMGHOM with: (HRB-address,0,0,0,0)
 ...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_USE_IODF    = IODF-name
HRB_FUNCTION    = HRB_DGET
HRB_OBJ_CODE    = HRB_DATA
Load or link CBDMGHOM with: (HRB-address,0,0,DVI-address,DVI-length)
 ....
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_USE_IODF    = IODF-name
HRB_FUNCTION    = HRB_MGET
HRB_OBJ_CODE    = HRB_MESSAGE
Load or link CBDMGHOM with: (HRB-address,0,0,MSI-address,MSI-length)
 ...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_USE_IODF    = IODF-name
HRB_FUNCTION    = HRB_CLOSE
HRB_OBJ_CODE    = HRB_IODF
Load or link CBDMGHOM with: (HRB-address,0,0,0,0)
 ...
HRB_SDESC       = HRB_SDESC_C
HRB_LENGTH      = length-of-HRB
HRB_FUNCTION    = HRB_TERMINATE
HRB_OBJ_CODE    = HRB_HCD
Load or link CBDMGHOM with: (HRB-address,0,0,0,0)
 ...
```

Return Codes

On return, HRB_RETURN_CODE in the request block HRB contains the severity of an error:

- HRB_SEVERE indicates that processing has been terminated and a new setup is required. Issue HCD_MGET to retrieve the messages describing the error.
- HRB_SYNTAX indicates that the request was given to the API in an incorrect syntax and therefore, the request has not been processed.
- HRB_WARNING and HRB_ERROR are given for the remaining errors. Issue HCD_MGET to retrieve the messages describing the error.
- HRB_OK tells you that no problems occurred.

Reason Codes

HRB_REASON_CODE in the request block HRB specifies the error in more detail.

End of Programming Interface information

Appendix E. Scenarios

The diagram in Figure 176 on page 454 shows an IODF from the viewpoint of the control unit. It shows all attachments of the CU via switches up the processor, as well as the devices attached to the CU. The information displayed for each object is listed below:

- For processors:
  - Processor identification
  - Processor type/model
  - Description
  - Configuration mode
  - Partitions associated with CHPIDs
  - CHPIDs (ID, type, operation mode)
- For switches:
  - Switch identifier and ports
  - Switch type/model
- For CUs:
  - CU type/model
  - CU number
  - Serial number or description
- For devices:
  - Device type/model
  - Device number (starting number and range)

This diagram represents the validated IODF after the completion of the scenario steps described hereafter.

The following scenarios cover the main definition tasks required to produce the IODF illustrated by the diagram. The scenarios have an exemplary character and are not meant to be complete or repetitive (that means, not to show a definition step for every object of the same type).

For detailed information on the ***Define*** tasks refer to Chapter 6, "How to Define, Modify, or View a Configuration" on page 85.

© Copyright IBM Corp. 1994, 2002



Figure 176. Example of a Hardware Configuration

Procedure

The definition method followed in the examples is driven from the Define, Modify, or View Configuration Data panel. If the IODF data set does not exist, you have to create one (see "Specify an IODF" on page 50 for more information).

Define Operating System Configuration Data

You have to define the operating systems running on the processor(s), or in one of its partitions first. This includes their EDTs and esoteric names.

1. On the primary task selection panel, select ***Define, modify, or view configuration data***. Press the Enter key. HCD displays the Define, Modify, or View Configuration Data panel.
2. On the Define, Modify, or View Configuration Data panel, select ***Operating system configurations***. HCD displays the Operating System Configuration List panel. Initially, the panel is empty.
3. Use F11=Add to define an operating system. HCD displays the following panel:

```
──────────────── Add Operating System Configuration ────────────────


Specify or revise the following values.

OS configuration ID  . . . . . OPSYS01
Operating system type  . . . . MVS       +

Description  . . . . . . . . . MVS operating system _________
```

4. Specify the name (ID) of the operating system, its type and description, and press the Enter key. HCD displays the updated Operating System Configuration List panel showing the just defined operating system.

```
  Goto  Backup  Query  Help
------------------------------------------------------------------------------
                    Operating System Configuration List             Row 1 of 1

Select one or more operating system configurations, then press Enter. To
add, use F11.

/ Config. ID   Type     Description
_ OPSYS01      MVS      MVS operating system
****************************** BOTTOM OF DATA ******************************
```

After you have defined the operating system, define the EDTs and the esoterics belonging to the EDTs.

To define an EDT proceed as follows:

1. On the Operating System Configuration List panel, select the operating system and the ***Work with EDTs*** action from the context menu (or action code **s**). HCD displays the EDT List panel. Initially, the panel is empty.
2. Use F11=Add to define an EDT. HCD displays the following panel:

```
──────────────────────────────── EDT List ────────────────────────────────
  Goto  Backup  Query  Help
  ──────────────────────────────── Add EDT ────────────────────────────
  │                                                                    │
  │ Specify the following values.                                      │
  │                                                                    │
  │ Configuration ID . : OPSYS01      MVS operating system             │
  │                                                                    │
  │ EDT identifier . . . A1                                            │
  │ Description  . . . . special ______________________                │
  │                                                                    │
  ──────────────────────────────────────────────────────────────────────
```

3. Specify the EDT identifier and description, and press the Enter key. HCD displays the EDT List panel showing the just defined EDT.

```
──────────────────────────── EDT List ────────────────────────────
  Goto  Backup  Query  Help
-----------------------------------------------------------------
                                                        Row 1 of 1
Command ===> ________________________________________ Scroll ===> PAGE

Select one or more EDTs, then press Enter. To add, use F11.

Configuration ID . : OPSYS01      MVS operating system

/ EDT Last Update By       Description
_ A1  1994-02-11  KLAU     special
************************** BOTTOM OF DATA ****************************
```

4. Define the esoterics for the just defined EDT. Perform the following steps:
   a. On the EDT List panel, select the EDT and the ***Work with esoterics*** action from the context menu (or action code **s**). HCD displays the Esoteric List panel. Initially, the panel is empty.
   b. Use F11=Add to define an esoteric. HCD displays the following panel:

```
──────────────────────────── Esoteric List ───────────────────────────
  Goto  Filter  Backup  Query  Help
-  ──────────────────── Add Esoteric ──────────────────────  ---------
   │                                                        │
   │                                                        │
S  │ Specify the following values.                          │
   │                                                        │
C  │ Esoteric name  . . . ES001 __                          │
E  │ VIO eligible . . . . No     (Yes or No)                │
   │ Token  . . . . . . . ____                              │
/  │                                                        │
*  │                                                        │  *********
   │                                                        │
```

   c. Specify the esoteric name, and whether the esoteric is VIO eligible or not, and press the Enter key. HCD displays the Esoteric List panel showing the esoteric you just defined.

```
──────────────────────────── Esoteric List ────────────────────────────
  Goto  Filter  Backup  Query  Help
-------------------------------------------------------------------
                                                        Row 1 of 1

Select one or more esoterics, then press Enter. To add, use F11.

Configuration ID . : OPSYS01      MVS operating system
EDT identifier . . : A1           special

/ Esoteric  VIO    Token  State
_ ES001     No     ____   No device defined
************************** BOTTOM OF DATA ****************************
```

   The "State" column indicates that no devices are associated with the esoteric. You are going to define the devices later on.

   Use the steps described above to define additional esoterics. After you are done, use F3=Exit to return to the EDT List panel. Use F3=Exit again to return to the Operating System Configuration List panel.

You may define additional operating systems using the steps described above.

Define Switches

Because the configuration contains two ESCON directors (switches), you have to define them at this point. This also includes the definition of the switch configuration for each switch. You will have to connect the switches to the various channel paths and control units at a later time.

1. On the Define, Modify, or View Configuration Data panel, select ***Switches***. Pressing Enter displays the Switch List panel showing all ESCON directors defined in the IODF. Initially, the panel is empty.
2. Use F11=Add to define a switch. HCD displays the following panel:

```
                          Add Switch

 Specify or revise the following values.

 Switch ID . . . . . . . . 98   (00-FF)
 Switch type . . . . . . . 9033           +
 Serial number . . . . . . 55-9999
 Description . . . . . . . First Switch
 Switch address  . . . . . __  (00-FF) for a FICON switch

 Specify the port range to be installed only if a larger range
 than the minimum is desired.

 Installed port range  . . __  -  __  +

 Specify either numbers of existing control unit and device, or
 numbers for new control unit and device to be added.

 Switch CU number(s) . . . 0098  ____  ____  ____  ____  +
 Switch device number(s) . 0098  ____  ____  ____  ____

  F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset   F9=Swap
  F12=Cancel
```

   Enter the required data; you must at least specify:
   - Switch identifier
   - Switch type

   Specify also the switch control unit numbers and switch device numbers. HCD then defines the switch control units, the switch devices, and connects the switch devices to the control units. The switch control units are automatically connected to port FE.
3. Press the Enter key. HCD displays the Switch List panel showing the switch you just created.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                                Switch List         Row 1 of 1 More:       >
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more switches, then press Enter. To add, use F11.

                                                                  CU   Dev
/ ID Type +        Ad Serial-# + Description                      Num. Num.
_ 98 9033          __ 55-9999    First Switch                     0098 0098
****************************** Bottom of data ********************************
```

4. To define the switch configuration, proceed as follows:
   a. On the Switch List panel, select the switch and the ***Work with switch configurations*** (or action code **s**). HCD displays all switch configurations defined for the switch. Initially, the panel is empty.

b. Use F11=Add to define a new switch configuration. HCD displays the following panel:

```
──────────────────── Switch Configuration List ────────────────────
  Goto  Backup  Query  Help
-  ──────────────── Add or Repeat Switch Configuration ──────────────


S   Specify or revise the following values.

S   Switch ID . . . . . . . : 98     First Switch

    Switch configuration ID . basic __
/
*   Description . . . . . . . night shift configuration _____

    Default connection  . . . 1  1.  Allow
                                 2.  Prohibit
```

c. Enter the required data and press the Enter key. HCD displays the Switch Configuration List panel showing the just created switch configuration.

```
──────────────────── Switch Configuration List ────────────────────
  Goto  Backup  Query  Help
-------------------------------------------------------------------------
                                                          Row 1 of 1

Select one or more switch configurations, then press Enter. To add, use F11.

Switch ID  . . . . : 98     First Switch

  Switch       Default
/ Config. ID   Connection + Description
_ BASIC        Allow        night-shift configuration
************************ BOTTOM OF DATA *************************
```

Return to the Switch List panel and repeat the procedure described above to define switch 99 as switch type 9032.

Define Processor Related Data

The definition of a processor consists of defining the processor itself, the partitions and the channel paths.

Define Processor

Define the processor as follows:

1. On the Define, Modify, or View Configuration Data panel select ***Processors***. Press the Enter key. HCD displays the Processor List panel. Initially, the panel is empty.
2. Use F11=Add to define a processor. HCD displays the following panel:

```
                              Add Processor
 Specify or revise the following values.

 Processor ID . . . . . . . . . PROC1 __

 Processor type . . . . . . . . 9021 ___  +
 Processor model  . . . . . . . 900 ____  +
 Configuration mode . . . . . . LPAR   +

 Serial number  . . . . . . . . 1234569021
 Description  . . . . . . . . . This is the main processor ____

 Specify SNA address only if part of an S/390 microprocessor cluster:

 Network name . . . . . . . . . ________  +
 CPC name . . . . . . . . . . . ________  +
```

Enter the required data; you must at least specify:

- Processor identifier
- Processor type/model
- Configuration mode

3. Because more than one support level exists for the 9021-900 processor type, HCD displays the following panel:

```
                         Available Support Levels
                                                  Row 1 of 3 More:       >

 Select one.


   Support Level
   With parallel and ESCON channels and DYNAMIC
   With parallel and ESCON channels, DYNAMIC and EMIF
***************************** BOTTOM OF DATA ******************************



 Command ===> ____________________________________________________________
  F1=Help        F2=Split       F7=Backward    F8=Forward     F9=Swap
 F12=Cancel     F20=Right      F22=Command

                                          ompt   F5=Reset    F9=Swap
 A support level selection is required.
```

Select the appropriate support level (With parallel and ESCON channels, DYNAMIC and EMIF) and press the Enter key.

4. This completes the processor definition and HCD displays the Processor List panel showing the just defined processor.

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                                Processor List        Row 1 of 1 More:       >
Command ===> ___________________________________________________ Scroll ===> PAGE

Select one or more processors, then press Enter. To add, use F11.


/ Proc. ID Type +   Model +  Mode+ Serial-# + Description
_ PROC1    9021     900      LPAR  1234569021 This is the main processor
****************************** Bottom of data ********************************
```

Define Partitions

To define partition(s) for the processor, proceed as follows:

1. On the Processor List panel, select the processor and the ***Work with partitions*** action from the context menu (or action code **p**). HCD displays all partitions defined for the processor. Initially, the panel is empty.
2. Use F11=Add to define a new partition. HCD displays the following panel:

```
                          Partition List
  Goto  Backup  Query  Help
-----------------------------------------------------------------------


Select one or more partitions, then press Enter. To add, use F11.

Processor ID  . . . . : PROC1     This is the main processor
Configuration mode  . : LPAR

/ Partiti                    Add Partition
*********

            Specify the following values.

            Partition name . . . PROD1
            Partition number . . 1
            Partition usage  . . OS    +

Command =   Description  . . . . First production partition __
 F1=Help
 F7=Backw
F12=Cance   F1=Help    F2=Split   F3=Exit    F4=Prompt  F5=Reset
            F9=Swap   F12=Cancel
```

3. Enter the required data; you must at least specify the name of the partition. Press the Enter key. HCD displays the updated Partition List panel showing the just defined partition.

Define the partitions PROD2, TEST1, and TEST2 following the procedure described above. Finally, the Partition List panel looks like the one shown below:

```
                              Partition List
  Goto  Backup  Query  Help
-------------------------------------------------------------------------
                                                                Row 1 of 4

Select one or more partitions, then press Enter. To add, use F11.

Processor ID  . . . . : PROC1     This is the main processor
Configuration mode  . : LPAR

/ Partition Name   Number Usage + Description
_ PROD1            1      OS      First production partition
_ PROD2            2      OS      Second production partition
_ TEST1            3      OS      First test system
_ TEST2            4      OS      Second test system
*************************** BOTTOM OF DATA ****************************
```

Define Channel Path Data

After you finished to define the partitions, you can define the channels. Proceed as follows:

1. On the Processor List panel, select the processor and the ***Work with attached channel paths*** from the context menu (or action code **s**). HCD displays all CHPIDs defined for the processor. Initially, the panel is empty.
2. Use F11=Add to define a new channel path. HCD displays the following panel:

```
                              Add Channel Path


Specify or revise the following values.

Processor ID . . . : PROC1        This is the main processor
Configuration mode : LPAR

Channel path ID  . . . . 01  +
Number of CHPIDs . . . . 4
Channel path type  . . . BL  +
Operation mode . . . . . DED +
Managed  . . . . . . . . No   (Yes or No)   I/O Cluster ________  +
Description  . . . . . . ______________________________

Specify the following values only if connected to a switch:

Dynamic switch ID  . . . __  + (00 - FF)
Entry switch ID  . . . . __  +
Entry port . . . . . . . __  +
```

   Enter the required data; you must at least specify:
   - Channel path identifier
   - Channel path type
   - Operation mode

   Note: Four channel paths are defined in one step.
3. Press the Enter key. HCD displays the Define Access List panel. The panel shows all partitions defined for the processor.

```
──────────────────────────── Define Access List ────────────────────────────
                                                                  Row 1 of 4

Select one or more partitions for inclusion in the access list.

Channel path ID  . . : 01      Channel path type  . : BL
Operation mode . . . : DED     Number of CHPIDs . . : 4

/ Partition Name   Number Usage Description
/ PROD1            1      OS    First production partition
_ PROD2            2      OS    Second production partition
_ TEST1            3      OS    First test system
_ TEST2            4      OS    Second test system
************************* BOTTOM OF DATA **************************
```

4. Select the partition that is to have access to the channel by using a **/**. Because the channel path's operation mode is dedicated, you can only select *one* partition.
5. Press the Enter key. HCD displays the updated Channel Path List.

Define channel paths 10 and 11 in the same way. Note that they are connected to partition PROD2.

The definition of a shared channel path (20 and 21) connected to a switch is slightly different. Proceed as follows:

1. Use F11=Add to define a new channel path. HCD displays the following panel:

```
──────────────────────────── Add Channel Path ────────────────────────────


Specify or revise the following values.

Processor ID . . . : PROC1        This is the main processor
Configuration mode : LPAR

Channel path ID  . . . . 20  +
Number of CHPIDs . . . . 2
Channel path type  . . . CNC  +
Operation mode . . . . . SHR  +
Managed  . . . . . . . . No   (Yes or No)   I/O Cluster ________  +
Description  . . . . . . ________________________________

Specify the following values only if connected to a switch:

Dynamic switch ID  . . .      + (00 - FF)
Entry switch ID  . . . . 98  +
Entry port . . . . . . . C1  +
```

2. Enter the required data. Note that the values for the switch and port values are only valid for channel path 20. After pressing the Enter key, HCD displays the Update Switch Connections panel to the switch and port of channel path 21.

```
──────────── Update Switch Connections ──────────────
                                          Row 1 of 2

Specify or revise the following values.

Processor ID . . . : PROC1

       Dyn +  --Entry +--
CHPID  Switch Switch Port
20            98     C1
21     99     98     C4
*************** BOTTOM OF DATA ****************
```

3. Press the Enter key. HCD displays the Define Access List panel. This panel shows all partitions defined for the processor. Select the partitions that are in the access list of the channel paths.

```
──────────────────── Define Access List ────────────────────
                                                   Row 1 of 4

Select one or more partitions for inclusion in the access list.

Channel path ID  . . : 20      Channel path type  . : CNC
Operation mode . . . : SHR     Number of CHPIDs . . : 2

/ Partition Name   Number Usage Description
/ PROD1            1      OS    First production partition
/ PROD2            2      OS    Second production partition
_ TEST1            3      OS    First test system
_ TEST2            4      OS    Second test system
************************* BOTTOM OF DATA **************************
```

4. Press the Enter key. HCD displays the Define Candidate List panel. Select the partitions that are in the candidate list of the channel paths.

```
──────────────────── Define Candidate List ───────────────────
                                                   Row 1 of 2

Select one or more partitions for inclusion in the candidate list.

Channel path ID  . . : 20      Channel path type  . : CNC
Operation mode . . . : SHR     Number of CHPIDs . . : 2

/ Partition Name   Number Usage Description
_ TEST1            3      OS    First test system
/ TEST2            4      OS    Second test system
************************* BOTTOM OF DATA **************************
```

5. Press the Enter key. HCD displays the updated Channel Path List panel.

Define channel paths 25 and 26 in the same way. The resulting Channel Path List looks as follows:

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                              Channel Path List      Row 1 of 10 More:       >
Command ===> ___________________________________________________ Scroll ===> CSR

Select one or more channel paths, then press Enter. To add use F11.

Processor ID . . . : PROC1
Configuration mode : LPAR

                   DynEntry Entry +
/ CHPID Type+ Mode+ Switch + Sw Port Con Mngd Description
_ 01    BL    DED   __       __ __   Y   No    ____________________________
_ 02    BL    DED   __       __ __   Y   No    ____________________________
_ 03    BL    DED   __       __ __       No    ____________________________
_ 04    BL    DED   __       __ __       No    ____________________________
_ 10    BL    REC   __       __ __       No    ____________________________
_ 11    BL    REC   __       __ __       No    ____________________________
_ 20    CNC   SHR   __       98 C1       No    ____________________________
_ 21    CNC   SHR   99       98 C4       No    ____________________________
_ 25    CNC   DED   98       98 C7       No    ____________________________
_ 26    CNC   DED   99       99 FB       No    ____________________________
 ****************************** Bottom of data ********************************
  F1=Help      F2=Split     F3=Exit     F4=Prompt    F5=Reset     F7=Backward
  F8=Forward   F9=Swap     F10=Actions  11=Add      F12=Cancel   F13=Instruct
 F20=Right    F22=Command
```

To view the matrix of the Channel Path list, scroll to the right with the F20=Right key.

```
  Goto  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                              Channel Path List      Row 1 of 10 More: <
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more channel paths, then press Enter. To add, use F11.

1=PROD1     2=PROD2     3=TEST1     4=TEST2     5=
6=          7=          8=          9=          A=
B=          C=          D=          E=          F=
                          I/O Cluster  --------- Partitions --------
/ CHPID Type+ Mode+ Mngd  Name         1 2 3 4 5 6 7 8 9 A B C D E F
_ 01    BL    DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
_ 02    BL    DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
_ 03    BL    DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
_ 04    BL    DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
_ 10    BL    REC   No    ________     _ a c _ _ _ _ _ _ _ _ _ _ _ _
_ 11    BL    REC   No    ________     _ a c _ _ _ _ _ _ _ _ _ _ _ _
_ 20    CNC   SHR   No    ________     a a _ c _ _ _ _ _ _ _ _ _ _ _
_ 21    CNC   SHR   No    ________     a a _ c _ _ _ _ _ _ _ _ _ _ _
_ 25    CNC   DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
_ 26    CNC   DED   No    ________     a _ _ _ _ _ _ _ _ _ _ _ _ _ _
****************************** Bottom of data ********************************

 F1=Help      F2=Split     F3=Exit      F4=Prompt    F5=Reset     F7=Backward
 F8=Forward   F9=Swap     F10=Actions  F11=Add      F12=Cancel   F13=Instruct
F19=Left     F22=Command
```

Use the F3=Exit key to return to the Processor List panel. Use the F3=Exit key again, to return to the Define, Modify, or View Configuration Data panel.

Define processor PROC2 in the same way.

Complete Switch Definitions

After you have defined the processors and the channel paths, you can complete the switch definitions. Basically you have to connect the switch control units to processor PROC1. Because the switches are chained together, this connection will be established as well.

Connect Switch Control Unit to Processor

1. On the Define, Modify, or View Configuration Data panel, select ***Control units***. Press the Enter key. HCD displays the Control Unit List panel. This panel shows the two switch control units.

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                            Control Unit List                      Row 1 of 2

Select one or more control units, then press Enter.  To add, use F11.

/ CU   Type +        Serial-# + Description
c 0098 9033          55-9999    First Switch
_ 0099 9032          55-8888    Second Switch
****************************** Bottom of data ********************************
```

2. Select control unit 0098 and the ***Change*** action from the context menu (or action code **c**). HCD displays the Change Control Unit Definition panel with the control unit that already has been correctly defined. Press the Enter key. HCD displays the Select Processor / Control Unit panel.

```
                        Select Processor / Control Unit

 Command ===> ___________________________________________ Scroll ===> PAGE

 Select processors to change CU/processor parameters, then press Enter.

 Control unit number . . : 0098     Control unit type . . . : 9033

            ---------------Channel Path ID . Link Address + ---------------
 / Proc. ID 1------ 2------ 3------ 4------ 5------ 6------ 7------ 8------
 s PROC01   _______ _______ _______ _______ _______ _______ _______ _______
 _ PROC02   _______ _______ _______ _______ _______ _______ _______ _______
```

3. Select the processor PROC1 and the ***Select (connect/change)*** action from the context menu (or action code **s**). HCD displays the following panel.

```
Goto  Filter  Backup  Query  Help
──────────────────── Select Processor / Control Unit ────────────────────┐
-  ──────────────────── Change Control Unit Definition ────────────────────┐
   │                                                                      │
   │                                                                      │
   │ S  Specify or revise the following values.                           │
   │                                                                      │
   │ C  Control unit number  : 0098         Type . . . . . . : 9033       │
   │    Processor ID . . . . : PROC1        This is the main processor    │
   │ /                                                                    │
   │    Channel path IDs . . 25 __  __  __  __  __  __  __   +           │
   │    Link address . . . . FE __ ___ ___ ___ ___ ___ ___ ___ +          │
   │                                                                      │
   │ *  Unit address . . . . 00  __  __  __  __  __  __  __   +           │
   │    Number of units  . . ___ ___ ___ ___ ___ ___ ___ ___              │
   │                                                                      │
   │    Logical address  . . __ + (same as CUADD)                         │
   │                                                                      │
   │ C  The following values are required only for parallel channels:     │
   │                                                                      │
   │    Protocol  . . . . . . . . __  + (D, S or S4)                      │
   │ F                                                                    │
   └─ I/O concurrency level . . 2  + (1, 2 or 3)                          │
   │                                                                      │
```

4. Enter the required data; you must at least specify:
   - Channel path
   - Link address
   - Unit address
5. Press the Enter key. HCD displays the Modify Device Parameters panel. This panel indicates that the unit address 98, HCD defined when the switch device was specified, was changed to 00.

```
──────────────────── Select Processor / Control Unit ────────────────────┐
│ ──────────────────── Modify Device Parameters ────────────────────────┐
│ │                                                  Row 1 of 1 More:       >
│ │
│ │ Specify or revise any changes to the device parameters in the list below.
│ │ To view attached control units, scroll to the right.
│ │
│ │ Processor ID  . . . . . : PROC1        This is the main processor
│ │
│ │ ---------Device--------- ---UA----                   Preferred  Exposure
│ │ No., Range Type          Old New + Time-Out  STADET  CHPID +    Device
│ │ 0098,001   9033          98  00    No        Yes     __
│ │ ***************************** BOTTOM OF DATA ******************************
│ │
```

6. Press the Enter key to accept the change. HCD displays the Select Processor / Control Unit panel showing the just specified switch control unit settings.
7. Press once more the Enter key to return to the Control Unit List panel.

Establish the connection of switch 99 to processor PROC1 in the same way.

Complete Port Data

1. On the Define, Modify, or View Configuration Data panel select ***Switches***. The Switch List panel showing all ESCON directors defined in the IODF is displayed.
2. On the Switch List panel, select the switch and the ***Work with ports*** action from the context menu (or action code **p**). HCD displays the Port List, showing all ports with their attachments to channels, control units or other switches that are supported by the selected switch.

```
  Goto  Options  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                                Port List                          Row 1 of 17
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more ports, then press Enter.

Switch ID . . . . . . . : 98   Address :      First Switch
Switch configuration ID : BASIC        night shift configuration

                                 -------------Connection-------------   Ded
/ Port H Name +                     Unit ID           Unit Type     O B Con+
_ C0   Y ______________________                                      N N __
_ C1   Y PROC1CHPID20            PR PROC1    CHPID 20 9021-900      N N __
_ C2   Y ______________________                                      N N __
_ C3   Y ______________________                                      N N __
_ C4   Y PROC1CHPID21            PR PROC1    CHPID 21 9021-900      N N __
_ C5   Y ______________________                                      N N __
_ C6   Y ______________________                                      N N __
_ C7   Y PROC1CHPID25            PR PROC1    CHPID 25 9021-900      N N __
_ C8   N ______________________                                      _ _ __
_ C9   N ______________________                                      _ _ __
_ CA   N ______________________                                      _ _ __
_ CB   N ______________________                                      _ _ __
_ CC   N ______________________                                      _ _ __
_ CD   N ______________________                                      _ _ __
_ CE   N ______________________                                      _ _ __
_ CF   N ______________________                                      _ _ __
_ FE   Y ______________________ CU 0098              9033          N N __
******************************* Bottom of data ********************************
```

3. Specify the port name for all ports attached to the channels and press the Enter key.

Chain the Two Switches Together

1. Select port C5 and the ***Connect to switch*** action from the context menu (or action code **w**). HCD displays the Connect to Switch panel. On this panel you can specify the switch id and the port of the chained switch.

```
  Goto  Options  Filter  Backup  Query  Help
- ┌──────────── Connect to Switch ────────────┐ ---------------------------------
  │                                           │
C │                                           │ _______________ Scroll ===> PAGE
  │  Specify the following values.            │
S │                                           │
  │  Switch ID  : 98  Port . . . : C5         │
S │                                           │ t Switch
S │  Switch ID  . . . . . 99  +               │ t shift configuration
  │  Port . . . . . . . . F0  +               │
  │                                           │ ----Connection-------------   Ded
/ │   F1=Help     F2=Split    F3=Exit         │ D           Unit Type     O B Con+
_ │   F4=Prompt   F5=Reset    F9=Swap         │                           N N __
_ │  F12=Cancel                               │    CHPID 20 9021-942      N N __
  └───────────────────────────────────────────┘                           N N __
_                                                                         N N __
_ C3   Y ______________________                                           N N __
_ C4   Y PROC1CHPID21            PR PROC1    CHPID 21 9021-942      N N __
w C5   Y ______________________                                           N N __
_ C6   Y ______________________                                           N N __
_ C7   Y PROC1CHPID25            PR PROC1    CHPID 25 9021-942      N N __
_ C8   N ______________________                                           _ _ __
_ C9   N ______________________                                           _ _ __
```

2. Press the Enter key. HCD displays the updated Port List panel. Specify the port name for port C5.

   Specify a dedicated connection between port C4 and port C5 and port C1 and C2.

```
  Goto  Options  Filter  Backup  Query  Help
--------------------------------------------------------------------------------
                                Port List                          Row 1 of 17
Command ===> ___________________________________________ Scroll ===> PAGE

Select one or more ports, then press Enter.

Switch ID . . . . . . . : 98   Address :      First Switch
Switch configuration ID : BASIC        night shift configuration

                                 -------------Connection-------------   Ded
/ Port H Name +                     Unit ID           Unit Type     O B Con+
_ C0   Y ________________________                                     N N __
_ C1   Y PROC1CHPID20            PR PROC1    CHPID 20 9021-900      N N C2
_ C2   Y ________________________                                     N N C1
_ C3   Y ________________________                                     N N __
_ C4   Y PROC1CHPID21            PR PROC1    CHPID 21 9021-900      N N C5
_ C5   Y CHAIN_FROM_99 __________ SW 99       PORT  F0 9032          N N C4
_ C6   Y ________________________                                     N N __
_ C7   Y PROC1CHPID25            PR PROC1    CHPID 25 9021-900      N N __
_ C8   N ________________________                                     _ _ __
_ C9   N ________________________                                     _ _ __
_ CA   N ________________________                                     _ _ __
_ CB   N ________________________                                     _ _ __
_ CC   N ________________________                                     _ _ __
_ CD   N ________________________                                     _ _ __
_ CE   N ________________________                                     _ _ __
_ CF   N ________________________                                     _ _ __
_ FE   Y ________________________ CU 0098              9033          N N __
****************************** Bottom of data ********************************
```

3. Use F3=Exit to return to the Switch List panel. Use F3=Exit again to return to the Define, Modify, or View Configuration Data panel.

Define Control Unit Data

After defining the processor, its partitions and channel paths, and switches, you can define control units:

1. On the Define, Modify, or View Configuration Data panel select ***Control units***. Press the Enter key. HCD displays the Control Unit List panel. So far, the panel shows the switch control units.
2. Use F11=Add to define a control unit. HCD displays the following panel:

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                            Control Unit List

Select one or more control units, then press Enter. To add, use F11.

/ CU   Type +        #PR #MC Serial-# + Description
_ 0098 9033          1       55-9999    First Switch
_ 009 ──────────────────────────── Add Control Unit ──────────────────────
*****
        Specify or revise the following values.

        Control unit number  . . . . 00E2  +
        Control unit type  . . . . . 3174 _______  +

        Serial number  . . . . . . . ____
        Description  . . . . . . . . Terminal control unit _________

        Connected to switches  . . . 99 __ __ __ __ __ __ __  +
        Ports  . . . . . . . . . . . E4 __ __ __ __ __ __ __  +

        If connected to a switch:

        Define more than eight ports . . 2 1.  Yes
                                           2.  No
        Propose CHPID/link addresses and
        unit addresses . . . . . . . . . 2 1.  Yes
                                           2.  No
```

Enter the required data; you must at least specify:
- Control unit number
- Control unit type

If the control unit is connected to an ESCON director, also specify the switch/ports.

3. Press the Enter key. HCD displays the Select Processor / Control Unit panel. This panel shows a list of all processors you already have defined.

```
                        Select Processor / Control Unit

 Command ===> ____________________________________________ Scroll ===> PAGE

 Select processors to change CU/processor parameters, then press Enter.

 Control unit number . . : 00E2     Control unit type . . . : 3174

            ---------------Channel Path ID . Link Address + ---------------
 / Proc. ID 1------ 2------ 3------ 4------ 5------ 6------ 7------ 8------
 s PROC1    _______ _______ _______ _______ _______ _______ _______ _______
 _ PROC2    _______ _______ _______ _______ _______ _______ _______ _______
 ****************************** Bottom of data ******************************
```

4. On the Select Processor / Control Unit panel, select the processor and the ***Select (connect/change)*** action from the context menu (or action code **s**). HCD displays the Add Control Unit panel.

```
 Goto  Filter Backup  Query  Help
┌──────────────────────── Select Processor / Control Unit ────────────────────┐
-  ┌──────────────────────────── Add Control Unit ──────────────────────────┐
   │                                                                        │
   │                                                                        │
S  │ Specify or revise the following values.                                │
   │                                                                        │
C  │ Control unit number  : 00E2         Type . . . . . . : 3174            │
   │ Processor ID . . . . : PROC1        This is the main processor         │
/  │                                                                        │
   │ Channel path IDs . . . 21   __   __   __   __   __   __   __    +     │
c  │ Link address . . . . . E4__ ____ ____ ____ ____ ____ ____ ____  +     │
_  │                                                                        │
*  │ Unit address . . . . . 00   __   __   __   __   __   __   __    +     │
   │ Number of units  . . . 32   ___  ___  ___  ___  ___  ___  ___         │
   │                                                                        │
   │ Logical address  . . . __ + (same as CUADD)                            │
   │                                                                        │
   │ Protocol  . . . . . . . . _   + (D,S or S4)                            │
└──│ I/O concurrency level . . 2  + (1, 2 or 3)                             │
   │                                                                        │
```

5. Specify channel path IDs and link address (21 and E401). For this example, change the number of units to 32.

   Press the Enter key. HCD displays the Select Processor / Control Unit panel, now indicating that the processor PROC1 is connected to the control unit. This is shown in the `Att.` column by a `Yes`.

6. This completes the definition of control unit 00E2, because it is only attached to processor PROC1. Press the Enter key to return to the Control Unit List panel now showing the just defined control unit.

```
 Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                           Control Unit List                      Row 1 of 3

Select one or more control units, then press Enter.  To add, use F11.

/ CU   Type +        #PR #MC Serial-# + Description
_ 0098 9033          1       55-9999    First Switch
_ 0099 9032          1       55-8888    Second Switch
_ 00E2 3174          1       __________ Terminal control unit
****************************** Bottom of data ********************************
```

7. The other control units are defined similarly, resulting in the following Control Unit List panel:

```
  Goto  Filter  Backup  Query  Help
------------------------------------------------------------------------------
                            Control Unit List                      Row 1 of 9

Select one or more control units, then press Enter.  To add, use F11.

/ CU   Type +        #PR #MC Serial-# + Description
_ 0098 9033          1       55-9999    First Switch
_ 0099 9032          1       55-8888    Second Switch
_ 00C1 3480          1       __________ ______________________________
_ 00C2 3480          1       __________ ______________________________
_ 00D1 3990-3        1       __________ ______________________________
_ 00D2 3990-3        1       __________ ______________________________
_ 00E1 3274          1       __________ ______________________________
_ 00E2 3174          1       __________ Terminal control unit
_ 00E3 3174          1       __________ ______________________________
****************************** Bottom of data ********************************
```

8. Press the F3=Exit key to return to the Define, Modify, or View Configuration Data panel.

Define I/O Device Data

When you define a device or a group of devices, you have to connect them to the processors (CSS), and then to the operating systems supposed to access the device(s). The operating system definition for the device(s) consists of specifying the parameters and features, and of grouping these device(s) to esoterics.

Proceed as follows:

1. On the Define, Modify, or View Configuration Data panel select ***I/O devices***. Press the Enter key. HCD displays the I/O Device List panel. The panel shows the switch devices.
2. Use F11=Add to define a device or a range of devices. HCD displays the following panel:

```
                                 Add Device

 Specify or revise the following values.

 Device number  . . . . . . . . 0001   (0000 - FFFF)
 Number of devices  . . . . . . 1
 Device type  . . . . . . . . . 3278-3          +

 Serial number  . . . . . . . . _________
 Description  . . . . . . . . . ______________________________

 Volume serial number . . . . . ______  (for DASD)

 Connected to CUs . . 00E1  ____  ____  ____  ____  ____  ____  ____


  F1=Help     F2=Split    F3=Exit     F4=Prompt   F5=Reset    F9=Swap
 F12=Cancel
```

Specify the physical characteristics of the device. You must at least specify:
- Device number
- Device type/model

Specify also the control unit(s) the device is attached to.

Press the Enter key. HCD displays the Device / Processor Definition panel showing all processors that have a path to the control units the device is attached to.

```
Goto  Filter  Backup  Query  Help
──────────────────── Device / Processor Definition ────────────────────
                                                            Row 1 of 2

Select processor(s) to change device/processor definitions, then
press Enter.

Device number  . . : 0001           Number of devices  . : 1
Device type  . . . : 3278-3

/ Processor ID   UA +  Time-Out  STADET  Preferred Explicit Device
                                         CHPID +   Candidate List
_ PROC1          __    Yes       Yes     __        No
_ PROC2          __    Yes       No      __        ___
************************* BOTTOM OF DATA ***************************
```

3. Press the Enter key to accept a default unit address (unit address 01). HCD displays the Define Device to Operating System Configuration panel. This panel shows all operating systems defined in the IODF.

```
Goto  Filter  Backup  Query  Help
──────────── Define Device to Operating System Configuration ────────────
                                                            Row 1 of 1

Select OSs to connect or disconnect devices, then press Enter.

Device number  . : 0001           Number of devices  : 1
Device type  . . : 3278-3

/ Config. ID   Type     Description                      Defined
s OPSYS01      MVS      MVS operating system
************************* BOTTOM OF DATA ***************************
```

To define the device to an operating system proceed as follows:

a. On the Define Device to Operating System Configuration panel, select the operating system and the ***Select (connect/change)*** action from the context menu (or action code **s**). HCD displays the Define Device Parameters / Features panel.

```
                    Define Device Parameters / Features         Row 1 of 21

Specify or revise the values below.

Configuration ID . : OPSYS01      MVS operating system
Device number  . . : 0001         Number of devices  : 1
Device type  . . . : 3278-3

Parameter/  Value    P Req.  Description
Feature
OFFLINE     No               Device considered online or offline at IPL
DYNAMIC     Yes              Device has been defined to be dynamic
ASCACHAR    No               ASCII A Character Generator
ASCBCHAR    No               ASCII B Character Generator
DOCHAR      Yes              United States English Character Generator
FRCHAR      No               French Character Generator
GRCHAR      No               German Character Generator
KACHAR      No               Katakana Character Generator
```

b. Specify the parameters and features and press the Enter key. HCD displays the Assign/Unassign Device to Esoteric panel.

```
                    Assign/Unassign Device to Esoteric          Row 1 of 2

Specify Yes to assign or No to unassign. To view devices already assigned
to esoteric, select and press Enter.

Configuration ID : OPSYS01          MVS operating system
Device number  . : 0001             Number of devices  : 1
Device type  . . : 3278-3           Generic  . . . . . : 3277-2

/ EDT.Esoteric  Assigned  Starting Number Number of Devices
_ A1.ES001      No        ____            ____
_ A1.ES002      No        ____            ____
***************************** BOTTOM OF DATA ******************************
```

c. Overwrite the values in the `Assigned` column to assign (Yes) and unassign (No) devices to the esoterics.

d. Press the Enter key to display the Define Device to Operating System Configuration panel.

e. Press the Enter key to return to the I/O Device List panel.

f. Define additional devices in the same way.

g. Press the F3=Exit key to display the Define, Modify, and View Configuration panel.

Define NIPCON Data

1. On the Define, Modify, or View Configuration Data panel select ***Operating system configurations***. Press the Enter key. HCD displays the Operating System Configuration List panel.
2. On the Operating System Configuration List panel, select the operating system for which a NIP console has to be defined and the ***Work with consoles*** action from the context menu (or action code **n**). Press the Enter key. HCD displays the NIP Console List panel. Initially, the panel is empty.
3. Use the F11=Add key to define a NIP console. HCD displays the following panel:

```
  Goto  Backup  Query  Help
-                        NIP Console List
    Goto  Backup  Query  Help
   ------------------------------------------------------------------
S
F
   Select one or more consoles, then press Enter. To add, use F11.
/
/  Configuration ID . : OPSYS01      MVS operating system
*
   / Order   Device            Add NIP Console
     Number  Number
   ****************                                              **
                     Specify the following values.

                     Device number of console . . . . . 0001

                     Order number . . . . . . . . . . . 1

                      F1=Help    F2=Split   F5=Reset   F9=Swap
                _    F12=Cancel                                  GE
```

4. Enter the required data. Press the Enter key to return to the updated NIP Console List panel.
5. Press the PF3=Exit key to return to the Operating System Configuration List panel.
6. Press the PF3=Exit key to return to the Define, Modify, or View Configuration Data panel.
7. Press the F3=Exit key to return to the primary task selection panel.

Appendix F. IODF Data Model

The following tables describe the IODF data model in terms of object class and attribute definitions. These definitions conform to the data that is kept in the IODF.

The object classes and attribute types introduced by HCD start with the prefix **hcd** which helps with identifying them.

The object hierarchy below the HCD Backend suffix is structured as follows:

```
hcdIodf (RDN: hcdIodfId)
  |
  |
  ├─ hcdControlUnit (RDN: hcdControlUnitNumber)
  |
  |
  ├─ hcdDevice (RDN: hcdDeviceNumber + hcdDeviceSuffix)
  |
  |
  ├─ hcdDistPackage (RDN: hcdDistPackageId)
  |
  |
  ├─ hcdOsConfig (RDN: hcdOsConfigId)
  |     |
  |     |
  |     ├── hcdEligibleDeviceTable (RDN: hcdEligibleDeviceTableId)
  |     |     |
  |     |     ├── hcdEsotericDeviceGroup (RDN: hcdEsotericDeviceGroupId)
  |     |     |
  |     |     └── hcdGenericDeviceType (RDN: hcdGenericDeviceTypeId)
  |     |
  |     └── hcdOsDevice (RDN: hcdDeviceNumber + hcdDeviceSuffix)
  |
  |
  ├─ hcdProcessorConfig (RDN: hcdProcessorConfigId)
  |     |
  |     |
  |     ├── hcdChannelPath (RDN: hcdChannelPathId)
  |     |
  |     ├── hcdCssControlUnit (RDN: hcdControlUnitNumber)
  |     |
  |     ├── hcdCssDevice (RDN: hcdDeviceNumber + hcdDeviceSuffix)
  |     |
  |     ├── hcdIocds (RDN: hcdIocdsId)
  |     |
  |     └── hcdPartition (RDN: hcdPartitionId)
  |
  └─ hcdSwitch (RDN: hcdSwitchId)
        |
        ├─ hcdPort (RDN: hcdPortId)
        |
        └─ hcdSwitchConfig (RDN: hcdSwitchConfigId)
              |
              └─── hcdPortConfig (RDN: hcdPortId)
```

© Copyright IBM Corp. 1994, 2002

IODF Object Class Definitions Within LDAP

The following tables describe the object classes which are used for the HCD LDAP DIT. In addition to other information, they contain the names of the attributes of each object class. The required attributes (shown in the row 'Must Contain') must be specified when adding an object of that class. Their values cannot be deleted. Optional attributes (shown in the row 'May Contain') may not always be required. They may, however, be necessary for certain objects according to HCD configuration rules. Attributes which are used to build the RDN of an object must not be modified for the corresponding object class.

The row 'Supported Requests' contains information about which operations are possible on entries of the corresponding object class. There are some object classes which do not allow all contained (non-RDN) attributes to be added (because they are read-only attributes) or modified. In this case, the list of attributes which may be modified is specified in the 'Supported Requests' row in parentheses after the MODIFY identifier.

Note: For certain entries, there may be restrictions to this general description as a result of HCD configuration rules.

The following rules apply for update requests on control unit and device object classes:

1. Control Unit

The general attributes of a specific control unit exist in an appropriate entry in class `hcdControlUnit`. For each connected processor, the processor related attributes of that control unit are contained in an entry of class `hcdCssControlUnit`. Hence, as a result of this inter-relation, an entry can only be added to class `hcdCssControlUnit` if the corresponding entry in class `hcdControlUnit` is already present. Likewise, if an entry of class `hcdControlUnit` is deleted, all the entries for the corresponding control unit in class `hcdCssControlUnit` will implicitly also be deleted.

2. Devices

In a manner similar to the control units, the general attributes of a specific device exist in an entry of class `hcdDevice` and may additionally exist in entries of classes `hcdCssDevice` and `hcdOsDevice`. The device attributes relating a device to a particular processor are contained in a corresponding entry of class `hcdCssDevice`. Such an entry can only exist if an entry for the device in class `hcdDevice` also exists and the device is connected to a control unit defined via, both an entry in the class `hcdControlUnit`, and an entry in class `hcdCssControlUnit`. This inter-dependency means that it is not possible to explicitly add or delete an entry of class `hcdCssDevice` directly. Instead, an entry of class `hcdCssDevice` will be implicitly added if:

- A control unit defined in an `hcdControlUnit` entry that has the particular device attached to it is defined also as an entry in class hcdCssControlUnit.
- An entry in class `hcdDevice` is created containing the attribute `hcdConnControlUnits` with a control unit number of an `hcdControlUnit` entry that also has a corresponding `hcdCssControlUnit` entry defined.

Implicitly added entries of class `hcdCssDevice` initially have default attribute values. These attributes can be modified to get their proper values.

An entry of class `hcdCssDevice` will be implicitly deleted if:

- The entry in corresponding class `hcdDevice` is deleted, or
- The connected control units in class hcdCssControlUnit are deleted, or
- The connected control units in class hcdControlUnit are deleted.

Changes to the attributes of control unit and device entries may affect all corresponding entries in the same logical control unit of a processor configuration, i.e. all entries of classes `hcdCssControlUnit` and `hcdCssDevice` with the same value of the attribute `hcdLogicalControlUnit`. In such a case, it may be necessary to delete all entries belonging to the same logical control unit and add them again with the changed attributes. This should be done using the update sequence in transaction mode.

For each operating system configuration, the operating system related device attributes are contained in a corresponding entry in class `hcdOsDevice`. An entry in class `hcdOsDevice` can only exist if the corresponding entry in class `hcdDevice` also exists. An entry in class `hcdOsDevice` can be explicitly added or deleted. This means that the device is connected to or disconnected from the operating system configuration. An entry in class `hcdOsDevice` is implicitly deleted if the corresponding entry in class `hcdDevice` is deleted.

If a device entry in class `hcdDevice` is added which has the same RDN attribute (`hcdDeviceNumber`) value of an existing entry in that class, HCD assigns a non-zero suffix to the device number (RDN attribute `hcdDeviceSuffix`) to make the RDN unique. The attribute `hcdDeviceSuffix` cannot be specified with an add request. If the value of attribute `hcdDeviceSuffix` is 0000, it need not be specified in the RDN, as this is the default value. If the value of the attribute `hcdDeviceSuffix` is not equal to 0000, it has to be specified in the RDN of the MODIFY and DELETE requests for the corresponding device entry. Therefore, the complete device RDN has to be retrieved via a preceding search request in order to be able to specify the correct RDN of a device entry.

Class	**hcdChannelPath**
Description	Describes a channel path of the processor configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdProcessorConfig
Must Contain	hcdChannelPathId, hcdChannelPathType, hcdOperationMode, objectClass
May Contain	hcdDescription, hcdDynSwitch, hcdConnChannelPath, hcdAccessingPartitions, hcdCandidatePartitions, hcdConnPort, hcdIsOccupied,hcdIsManaged,hcdSysplex, hcdMaximumFrameSize
Supported Requests	SEARCH ADD MODIFY DELETE
Special Notes	Attribute hcdIsOccupied is only shown if set to Yes.

Class	**hcdControlUnit**
Description	Describes a control unit
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdControlUnitNumber, hcdUnit, objectClass
May Contain	hcdDescription, hcdModel, hcdSerialNumber, hcdConnPorts
Supported Requests	SEARCH ADD MODIFY DELETE

Class	**hcdCssControlUnit**
Description	Describes a control unit from the Channel Subsystem viewpoint
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdProcessorConfig
Must Contain	hcdControlUnitNumber, hcdConnChannelPaths, objectClass
May Contain	hcdUnitAddressRanges, hcdControlUnitAddress, hcdIOConcurrencyLevel, hcdControlUnitProtocol, hcdLogicalControlUnit,hcdManagedChannelPathsCount
Supported Requests	SEARCH ADD (requires the existence of an object in class hcdControlUnit with same RDN) MODIFY (hcdConnChannelPaths, hcdUnitAddressRanges, hcdControlUnitAddress, hcdIOConcurrencyLevel, hcdControlUnitProtocol,hcdManagedChannelPathsCount) DELETE

Class	**hcdCssDevice**
Description	Describes a device from the Channel Subsystem viewpoint
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdProcessorConfig
Must Contain	hcdDeviceNumber, objectClass
May Contain	hcdDeviceSuffix, hcdDeviceRange, hcdUnitAddress, hcdStatusDetection, hcdTimeOut, hcdPreferredChannelPath, hcdCandidatePartitions, hcdLogicalControlUnit

Class	hcdCssDevice
Supported Requests	SEARCH MODIFY (hcdDeviceRange, hcdUnitAddress, hcdStatusDetection, hcdTimeOut, hcdPreferredChannelPath, hcdCandidatePartitions)
Special Notes	For a MODIFY request, hcdDeviceRange specifies the number of devices to which the request will be applied.

Class	hcdDevice
Description	Describes an I/O device
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdDeviceNumber, hcdUnit, objectClass
May Contain	hcdDescription, hcdModel, hcdDeviceSuffix, hcdDeviceRange, hcdSerialNumber, hcdVolser, hcdConnControlUnits
Supported Requests	SEARCH ADD MODIFY (hcdDeviceRange, hcdUnit, hcdDescription, hcdModel, hcdSerialNumber, hcdVolser, hcdConnControlUnits) DELETE
Special Notes	For ADD and MODIFY requests, hcdDeviceRange specifies the number of devices to which the request will be applied.

Class	hcdDistPackage
Description	Describes a distribution package of I/O configurations
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdDistPackageId, objectClass
May Contain	hcdDescription, hcdTargetNode, hcdTargetUser, hcdIsAttended, hcdTargetIodf, hcdTargetVolser, hcdSentDate, hcdSentTime, hcdOsConfigs, hcdProcessorConfigs
Supported Requests	SEARCH ADD MODIFY (hcdDescription, hcdTargetNode, hcdTargetUser, hcdIsAttended, hcdTargetIodf, hcdTargetVolser, hcdOsConfigs, hcdProcessorConfigs) DELETE

Class	**hcdEligibleDeviceTable**
Description	Describes an Eligible Device Table of an OS configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdOsConfig
Must Contain	hcdEligibleDeviceTableId, objectClass
May Contain	hcdDescription, hcdLastUpdateDate, hcdUpdatedBy
Supported Requests	SEARCH ADD MODIFY (hcdDescription) DELETE

Class	**hcdEsotericDeviceGroup**
Description	Describes an esoteric device group of an EDT of an OS configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdEligibleDeviceTable
Must Contain	hcdEsotericDeviceGroupId, objectClass
May Contain	hcdEsotericDeviceGroupToken, hcdVirtualIO, hcdDeviceRanges
Supported Requests	SEARCH ADD MODIFY DELETE
Special Notes	Attribute hcdVirtualIO is only shown if set to Yes.

Class	**hcdGenericDeviceType**
Description	Describes an update to a generic device type for an EDT of an OS configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdEligibleDeviceTable
Must Contain	hcdGenericDeviceTypeId, objectClass
May Contain	hcdDevicePreferenceValue, hcdVirtualIO
Supported Requests	SEARCH MODIFY

Class	hcdGenericDeviceType
Special Notes	Entries of class hcdGenericDeviceType are implicitly added when the first device entry with the corresponding generic device type is added in class hcdOsDevice. An entry of this class is deleted, if the last device with the corresponding generic device type is deleted from class hcdOsDevice. Attribute hcdVirtualIO is only shown if set to Yes.

Class	hcdIocds
Description	Describes an IOCDS of a processor configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdProcessorConfig
Must Contain	hcdIocdsId, objectClass
May Contain	hcdIocdsName, hcdLastUpdateDate, hcdLastUpdateTime, hcdProcessorConfigMode
Supported Requests	SEARCH
Special Notes	Entries in this class are implicitly added when an entry in class hcdProcessorConfig is added. Entries in this class are implicitly deleted if the appropriate entry in class hcdProcessorConfig is deleted.

Class	hcdIodf
Description	Describes the I/O configurations defined in an IODF
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	
Must Contain	hcdIodfId, objectClass
May Contain	hcdIodfType, hcdIodfDescription, hcdBackupIodf, hcdBlocksAllocated, hcdBlocksUsed, hcdCreationDate, hcdLastUpdateDate, hcdLastUpdateTime
Supported Requests	SEARCH MODIFY (hcdIodfDescription)
Special Notes	Entries of this class cannot be added or deleted with the HCD LDAP Backend.

Class	hcdOsConfig
Description	Describes an OS configuration
Type	structural

Class	**hcdOsConfig**
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdOsConfigId, hcdOsConfigType, objectClass
May Contain	hcdDescription
Supported Requests	SEARCH ADD MODIFY (hcdDescription) DELETE

Class	**hcdOsDevice**
Description	Describes an I/O device from the OS viewpoint
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdOsConfig
Must Contain	hcdDeviceNumber, hcdUnit, objectClass
May Contain	hcdDeviceSuffix, hcdDeviceRange, hcdModel, hcdGenericDeviceTypeId hcdDeviceParameters, hcdDeviceFeatures, hcdConsoleNumber
Supported Requests	SEARCH ADD (requires the existence of an object in class hcdDevice with the same RDN) MODIFY (hcdDeviceRange,hcdDeviceParameters, hcdDeviceFeatures, hcdConsoleNumber) DELETE
Special Notes	For ADD and MODIFY requests, hcdDeviceRange specifies the number of devices to which the request will be applied.

Class	**hcdPartition**
Description	Describes a logical partition (LP) of a processor configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdProcessorConfig
Must Contain	hcdPartitionId, objectClass
May Contain	hcdDescription, hcdPartitionNumber, hcdPartitionUsage

Class	hcdPartition
Supported Requests	SEARCH ADD MODIFY DELETE

Class	hcdPort
Description	Describes a port of an ESCON director
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdSwitch
Must Contain	hcdPortId, objectClass
May Contain	hcdPortName, hcdIsOccupied, hcdIsInstalled, hcdConnPort
Supported Requests	SEARCH MODIFY
Special Notes	Attribute hcdIsOccupied is only shown if set to Yes. Entries of this class are implicitly added or deleted if the corresponding switch entry in class hcdSwitch is added or deleted, respectively.

Class	hcdPortConfig
Description	Describes a port configuration of a switch configuration
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdSwitchConfig
Must Contain	hcdPortId, objectClass
May Contain	hcdAllowedDynConnPorts, hcdProhibitedDynConnPorts, hcdDedicatedPort, hcdIsBlocked
Supported Requests	SEARCH MODIFY
Special Notes	Entries in this class are implicitly added or deleted if the corresponding entry in class hcdSwitchConfig is added or deleted, respectively.

Class	hcdProcessorConfig
Description	Describes a processor configuration
Type	structural
OID	
Derived from	top

Class	**hcdProcessorConfig**
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdProcessorConfigId, hcdUnit, hcdProcessorConfigMode, objectClass
May Contain	hcdModel, hcdDescription, hcdSerialNumber, hcdNetworkName, hcdSystem, hcdSupportLevel
Supported Requests	SEARCH ADD MODIFY DELETE

Class	**hcdSwitch**
Description	Describes a switch (ESCON or FICON Director or Fibre Channel switch)
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdIodf
Must Contain	hcdSwitchId, hcdUnit, objectClass
May Contain	hcdDescription, hcdModel, hcdSerialNumber, hcdSwitchAddress
Supported Requests	SEARCH ADD MODIFY DELETE

Class	**hcdSwitchConfig**
Description	Describes a configuration of an ESCON Director
Type	structural
OID	
Derived from	top
Auxiliary Classes	
Possible Superiors	hcdSwitch
Must Contain	hcdSwitchConfigId, objectClass
May Contain	hcdDescription, hcdDefaultConn
Supported Requests	SEARCH ADD MODIFY DELETE

IODF Attribute Table

The following table describes the names and the properties of the attributes (alias names are given in parentheses).

Note: All attribute type names ending with the plural ″s″ represent multi-valued attributes. HCD interprets the values as an ordered list. This is important if there are two lists which have corresponding list items.

Attribute	Description	OID	Syntax	Valued	Access Class
hcdAccessingPartitions (hcdAccList)	Channel path access list (up to 8 char partition names)		cis / 8	multi	normal
hcdAllowedDynConnPorts (hcdAllowedList)	Ports to which an Allowed dynamic connection exists (2 hexadecimal digit port address)		cis / 2	multi	normal
hcdBackupIodf (hcdBkupIodf)	Data set name of backup IODF (up to 35 character full-qualified IODF data set name)		cis / 35	single	normal
hcdBlocksAllocated (hcdAllocBlks)	Number of allocated blocks for IODF (up to 6 digit decimal number, read-only)		cis / 6	single	normal
hcdBlocksUsed (hcdUsedBlks)	Number of used blocks in IODF (up to 6 digit decimal number, read-only)		cis / 6	single	normal
hcdCandidatePartitions (hcdCandList)	Partition candidate list (up to 8 character partition names)		cis / 8	multi	normal
hcdChannelPathId (hcdChpId)	Channel path identifier (2 digit hexadecimal number)		cis / 2	single	normal
hcdChannelPathType (hcdChpType)	Channel path type (3 character channel path type acronym)		cis / 3	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdConnChannelPath (hcdConnChp)	Connected channel path of a coupling facility connection (qualified coupling facility connection: prid.chpid.cunum.devn, where prid is a up to 8 character processor name, chpid is a 2 hex digit channel path, cunum is a 4 hex digit control unit number, devn is a 4 hex digit device number) If the values for cunum and devn are missing, they are defaulted as needed.		cis / 24	single	normal
hcdConnChannelPaths (hcdChpList)	Connected channel paths / link addresses (pp or pp.ll or pp.llll, where pp is the 2-digit hexadecimal number of the channel path, optionally qualified by ll as a 2 hexadecimal number for the link address or by llll as a 4 hexadecimal number for the link address)		cis / 7	multi	normal
hcdConnControlUnits (hcdCuList)	Connected control units (4 hex digit numbers)		cis / 4	multi	normal
hcdConnPort	Connected switch port (qualified port address ss.pp, where ss is the 2 digit hexadecimal switch number, pp is the 2 digit hexadecimal port address)		cis / 5	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdConnPorts (hcdConnPortList)	List of connected switch ports (qualified port addresses ss.pp, where ss is the 2 digit hexadecimal switch number, pp is the 2 digit hexadecimal port address)		cis / 5	multi	normal
hcdConsoleNumber (hcdConsole)	Console order number (up to 2 digit decimal number)		cis / 2	single	normal
hcdControlUnitAddress (hcdCuadd)	Logical control unit address (up to 2 hex digit number)		cis / 2	single	normal
hcdControlUnitNumber (hcdCu)	Control unit number (4 hex digit number)		cis / 4	single	normal
hcdControlUnitProtocol (hcdProt)	Control unit protocol (D, S, S4)		cis / 2	single	normal
hcdCreationDate	Creation Date (yyyy-mm-dd, read-only)		cis / 10	single	normal
hcdDedicatedPort (hcdDedicated)	Port to which a dedicated connection exists (2 digit hexadecimal number)		cis / 2	single	normal
hcdDefaultConn	Dynamic connection default of a switch configuration (ALLOW, PROHIBIT)		cis / 10	single	normal
hcdDescription	Description field (up to 32 character string)		cis / 32	single	normal
hcdDeviceFeatures (hcdFeatList)	Device feature list (up to 10 character identifier)		cis / 10	multi	normal
hcdDeviceNumber (hcdDev)	Device number (4 digit hexadecimal number)		cis / 4	single	normal
hcdDeviceParameters (hcdParmList)	Device parameter list (keyword=value1,...)		cis / 50	multi	normal
hcdDevicePreferenceValue (hcdPrefVal)	Device preference value (up to 8 digit decimal number)		cis / 8	single	normal
hcdDeviceRange (hcdRange)	Range of devices with same attributes (up to 4 digit decimal number)		cis / 4	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdDeviceRanges (hcdDevRngeList)	Device range list (qualified value: xxxx.ddd, where xxxx is a 4 hex digit device number, ddd is a up to 3 decimal digit range number,		cis / 8	multi	normal
hcdDeviceSuffix (hcdSuf)	Device ID suffix (4 digit hexadecimal number)		cis / 4	single	normal
hcdDistPackageId (hcdPkgName)	Name of distribution package (up to 8 alphanumeric character identifier)		cis / 8	single	normal
hcdDynSwitch	Dynamic switch of channel path (2 digit hexadecmial number)		cis / 2	single	normal
hcdEligibleDeviceTableId (hcdEdtId)	EDT identifier (2 character identifier)		cis / 2	single	normal
hcdEsotericDevice GroupId (hcdEsoId)	Esoteric name (up to 8 character identifier)		cis / 8	single	normal
hcdEsotericDevice GroupToken (hcdEsoToken)	Esoteric token (up to 4 decimal digit number)		cis / 4	single	normal
hcdGenericDeviceTypeId (hcdGenId)	Generic device type name (up to 8 character identifier)		cis / 8	single	normal
hcdIocdsId	IOCDS identifier (2 digit hexadecimal number)		cis / 2	single	normal
hcdIocdsName	IOCDS name (up to 8 character identifier)		cis / 8	single	normal
hcdIOConcurrencyLevel (hcdIocl)	I/O concurrency level of control unit (1 digit decimal number)		cis / 1	single	normal
hcdIodfDescription (hcdIodfDesc)	IODF description (up to 128 character string)		cis / 128	single	normal
hcdIodfId	IODF name (up to 35 character full-qualified data set name)		cis / 35	single	normal
hcdIodfType	IODF type (I (initial), W (work), P (production), read-only)		cis / 1	single	normal
hcdIsAttended	Indicates if target node is attended (Yes, No)		cis / 3	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdIsBlocked	Indicates if the port is blocked (Yes, No)		cis / 3	single	normal
hcdIsInstalled	Indicates if object (port) is installed (Yes, No)		cis / 3	single	normal
hcdIsManaged	Indicates if a channel path is managed (Yes, No)		cis / 3	single	normal
hcdIsOccupied (hcdIsOcc)	Indicates if object (port, channel path) is occupied (Yes, No)		cis / 3	single	normal
hcdLastUpdateDate (hcdLastUpdDate)	Date of last update (yyyy-mm-dd, read-only)		cis / 10	single	normal
hcdLastUpdateTime (hcdLastUpdTime)	Time of last update (hh:mm:ss, read-only)		cis / 8	single	normal
hcdLogicalControlUnit (hcdLcu)	Logical control unit number (4 digit hexadecimal number, read-only)		cis / 4	single	normal
hcdManagedChannel PathsCount	Maximum number of managed channel path connections to a control unit (1 digit decimal number)		cis / 1	single	normal
hcdMaximumFrameSize	Maximum frame size for the transmission unit on an IQD channel path in KB (decimal number)		cis / 6	single	normal
hcdModel	Model (4 character identifier)		cis / 4	single	normal
hcdNetworkName (hcdNetName)	CPC network name (up to 8 alphanumeric identifier)		cis / 8	single	normal
hcdOperationMode (hcdOpMode)	Channel path operation mode (DED, REC, SHR)		cis / 3	single	normal
hcdOsConfigId (hcdOsId)	OS configuration identifier (up to 8 alphanumeric character identifier)		cis / 8	single	normal
hcdOsConfigs (hcdOsList)	List of OS configurations (up to 8 alphanumeric character identifiers)		cis / 8	multi	normal
hcdOsConfigType (hcdOsType)	OS configuration type (MVS, VM)		cis / 3	single	normal
hcdPartitionId (hcdPartId)	Logical partition name (up to 8 alphanumeric character identifier)		cis / 8	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdPartitionNumber (hcdPartNo)	Partition image number (1 digit hexadecimal number)		cis / 1	single	normal
hcdPartitionUsage (hcdPartUsage)	Partition usage (OS, CF, CF/OS)		cis / 5	single	normal
hcdPortId	Switch port identifier (2 digit hexadecimal number)		cis / 2	single	normal
hcdPortName	Switch port name (up to 24 character identifier)		cis / 24	single	normal
hcdPreferredChannelPath (hcdPrefChp)	Preferred channel path (2 digit hexadecimal number)		cis / 2	single	normal
hcdProcessorConfigId (hcdProcId)	processor configuration ID (up to 8 alphanumeric charcter identifier)		cis / 8	single	normal
hcdProcessorConfigMode (hcdConfMode)	Processor configuration mode (BASIC, LPAR)		cis / 5	single	normal
hcdProcessorConfigs (hcdProcList)	List of processor configurations (up to 8 alphanumeric character identifiers)		cis / 8	multi	normal
hcdProhibitedDyn ConnPorts (hcdProhibitList)	Ports to which a Prohibited dynamic connection exists (2 digit hexadeciamal numbers)		cis / 2	multi	normal
hcdSentDate	Date of last distribution (yyyy-mm-dd, read-only)		cis / 10	single	normal
hcdSentTime	Time of last distribution (hh:mm:ss, read-only)		cis / 8	single	normal
hcdSerialNumber (hcdSerialNo)	Serial number (up to 10 character serial number)		cis / 10	single	normal
hcdStatusDetection (hcdStadet)	Status detection facility of device (Yes, No)		cis / 3	single	normal
hcdSupportLevel	Processor support level (8 character identifier)		cis / 8	single	normal
hcdSwitchAddress	Address of a Fibre Channel switch in a fabric (2 digit hexadecimal number)		cis / 2	single	normal
hcdSwitchConfigId (hcdSwConfId)	Switch configuration identifier (up to 8 alphanumeric character identifier)		cis / 8	single	normal

Attribute	Description	OID	Syntax	Valued	Access Class
hcdSwitchId (hcdSwID)	Switch identifier (2 digit hexadecimal number)		cis / 2	single	normal
hcdSysplex	Sysplex name (up to 8 character alphanumeric identifier)		cis / 8	single	normal
hcdSystem	CPC system name (up to 8 character alphanumeric identifier)		cis / 8	single	normal
hcdTargetIodf	Data set name of target IODF (up to 35 character full-qualified data set name)		cis / 35	single	normal
hcdTargetNode	Target node (up to 8 character alphanumeric identifier)		cis / 8	single	normal
hcdTargetUser	Target user (up to 8 character alphanumeric identifier)		cis / 8	single	normal
hcdTargetVolser (hcdTargetVol)	Volume serial number of target IODF data set (up to 6 character alphanumeric identifier)		cis / 6	single	normal
hcdTimeOut	Time out facility (Yes, No)		cis / 3	single	normal
hcdUnit	Unit (up to 8 alphanumeric character identifier)		cis / 8	single	normal
hcdUnitAddress (hcdUa)	Unit address (2 digit hexadecimal number)		cis / 2	single	normal
hcdUnitAddressRanges (hcdUaList)	Unit address range of control unit (qualified number xx.ddd, where xx is a 2 digit hexadecimal unit address ddd is a up to 3 digit decimal range)		cis / 6	multi	normal
hcdUpdatedBy	Identifier of last update user (up to 8 alphanumeric character identifier, read-only)		cis / 8	single	normal
hcdVirtualIO (hcdVio)	Virtual I/O (Yes, No)		cis / 3	single	normal
hcdVolser (hcdVolume)	Volume serial number (up to 6 character alphanumeric identifier)		cis / 6	single	normal

Appendix G. Accessibility

Accessibility features help a user who has a physical disability, such as restricted mobility or limited vision, to use software products successfully. The major accessibility features in z/OS enable users to:

- Use assistive technologies such as screen-readers and screen magnifier software
- Operate specific or equivalent features using only the keyboard
- Customize display attributes such as color, contrast, and font size

Using assistive technologies

Assistive technology products, such as screen-readers, function with the user interfaces found in z/OS. Consult the assistive technology documentation for specific information when using it to access z/OS interfaces.

Keyboard navigation of the user interface

Users can access z/OS user interfaces using TSO/E or ISPF. Refer to *z/OS TSO/E Primer*, *z/OS TSO/E User's Guide*, and *z/OS ISPF User's Guide Volume I* for information about accessing TSO/E and ISPF interfaces. These guides describe how to use TSO/E and ISPF, including the use of keyboard shortcuts or function keys (PF keys). Each guide includes the default settings for the PF keys and explains how to modify their functions.

© Copyright IBM Corp. 1994, 2002

Notices

This information was developed for products and services offered in the U.S.A.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10504-1785
U.S.A.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation
Mail Station P300
522 South Road
Poughkeepsie New York 12601-5400
U.S.A.

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation
Licensing
2-31 Roppongi 3-chome, Minato-ku
Tokyo 106, Japan

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law: INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR

© Copyright IBM Corp. 1994, 2002

PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any pointers in this publication to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement. IBM accepts no responsibility for the content or use of non-IBM Web sites specifically mentioned in this publication or accessed through an IBM Web site that is mentioned in this publication.

If you are viewing this information in softcopy form, the photographs and color illustrations may not appear.

Trademarks

The following terms are trademarks of the IBM Corporation in the United States or other countries or both:

- ACF/VTAM
- AFP
- BookMaster
- Common User Access
- CUA
- DB/2
- DFSMS/MVS
- DFSORT
- ESCON
- ES/4381
- ES/9000
- FICON
- GDDM
- IBM
- Language Environment
- Multiprise
- MVS
- MVS/DFP
- MVS/ESA
- MVS/SP
- MVS/XA
- OS/390
- OS/2
- Parallel Sysplex
- Print Services Facility
- Processor Resource/Systems Manager
- PR/SM
- RACF
- Resource Link
- RETAIN
- SP
- System/390
- S/370
- S/390

- S/390 Parallel Enterprise Server
- VM/ESA
- VTAM
- z/OS
- zSeries

UNIX is a registered trademark of The Open Group in the United States and other countries.

LINUX is a registered trademark of Linus Torvalds and others.

Other company, product, and service names may be trademarks or service marks of others.

Programming Interface Information

This guide primarily documents information that is NOT intended to be used as a Programming Interface of Hardware Configuration Definition (HCD).

This book also documents intended Programming Interfaces that allow the customer to write programs to obtain the services of HCD. This information is identified where it occurs, either by an introductory statement to a chapter or section or by the following marking:

Programming Interface information

End of Programming Interface information

Accessing Licensed Books on the Web

z/OS licensed documentation in PDF format is available on the Internet at the IBM Resource Link Web site at:

`http://www.ibm.com/servers/resourcelink`

Licensed books are available only to customers with a z/OS license. Access to these books requires an IBM Resource Link Web userid and password, and a key code. With your z/OS order you received a memo that includes this key code.

To obtain your IBM Resource Link Web userid and password log on to:

`http://www.ibm.com/servers/resourcelink`

To register for access to the z/OS licensed books:

1. Log on to Resource Link using your Resource Link userid and password.
2. Click on **User Profiles** located on the left-hand navigation bar.
3. Click on **Access Profile.**
4. Click on **Request Access to Licensed books.**
5. Supply your key code where requested and click on the **Submit** button.

If you supplied the correct key code you will receive confirmation that your request is being processed. After your request is processed you will receive an e-mail confirmation.

Note: You cannot access the z/OS licensed books unless you have registered for access to them and received an e-mail confirmation informing you that your request has been processed.

To access the licensed books:

1. Log on to Resource Link using your Resource Link userid and password.
2. Click on **Library**.
3. Click on **zSeries**.
4. Click on **Software**.
5. Click on **z/OS**.
6. Access the licensed book by selecting the appropriate element.

Online Message Lookup

The LookAt system for online lookup of all z/OS messages has been introduced. For more information, see "LookAt System for Online Message Lookup" on page 420.

Glossary

This glossary defines technical terms and abbreviations used in the Hardware Configuration Definition (HCD) documentation. If you do not find the term you are looking for, refer to the index of the appropriate HCD manual or view the *IBM Glossary of Computing Terms*, available from: **http://www.ibm.com/ibm/terminology**.

A

Activity log. The activity log is a sequential data set with the name of the associated **IODF** and the suffix ACTLOG. Use the activity log to document all definitions you made to the current IODF using HCD.

B

Base. Base is the base device number of a **multiple exposure** device, which is accessible by more than one device number. You assign the first device number and the system generates the additional device numbers.

C

Central Processor Complex (CPC). A physical collection of hardware that consists of central storage, one or more central processors, timers, and channels.

Coupling Facility (CF). The hardware element that provides high-speed caching, list processing, and locking functions in a sysplex. To enable data sharing between a CF partition and the central processor complexes, special types of high-speed, CF channels are required to provide the connectivity. A receiving CF channel path, attached to a CF partition, is to be connected to a sending CF channel path, attached to a partition in which an operating system (OS) is running.

Coupling Facility Channel. A high bandwidth fiber optic channel that provides the high-speed connectivity required for data sharing between a coupling facility and the central processor complexes directly attached to it.

D

Dynamic reconfiguration. The ability to make changes to the channel subsystem and to the operating system while the system is running.

E

EDT. An EDT (eligible device table) is an installation-defined and named representation of the devices that are eligible for allocation. The EDT defines the **esoteric** and **generic** relationship of these devices. During IPL, the installation identifies the EDT that MVS uses. After IPL, jobs can request device allocation from any of the esoteric device groups assigned to the selected EDT. An EDT is identified by a unique ID (two digits), and contains one or more esoterics and generics. Define at least one EDT for each operating system configuration.

Enterprise Systems Connection (ESCON). A set of products and services that provides a dynamically connected environment using optical cables as a transmission medium.

ESCON Manager (ESCM). A licensed program that provided host control to help manage connections that use ESCON Directors. The functionality has been incorporated into the I/O Operations component of System Automation for OS/390.

ESCON Multiple Image Facility(EMIF). EMIF is now refered to as MIF. See below.

Esoteric. Esoteric (or esoteric device group) is an installation-defined and named grouping of I/O devices of usually the same device group. **EDTs** define the esoteric and generic relationship of these devices. The name you assign to an esoteric is used in the JCL DD statement. The job then allocates a device from that group instead of a specific device number or **generic** device group.

F

FICON. Fiber Connection Environment (FICON) is an improved optical fiber communication method offering channels with high data rate, high bandwidth, increased distance and a greater number of devices per control unit for S/390 systems. It can work together with, or replace ESCON links.

G

Generic. Generic (or generic device type) is an MVS-defined grouping of devices with similar characteristics. For example: the device types 3270-X, 3277-2, 3278-2, -2A, -3, -4, and 3279-2a, -2b, -2c, -3a, -3b belong to the same generic. Every generic has a generic name that is used for device allocation in the JCL DD statement. MVS interprets this name as ″take any

© Copyright IBM Corp. 1994, 2002

device in that group". In an operating system configuration, each **EDT** has the same list of generics. This list can only vary by the **preference** values and **VIO** indicators that are assigned to the generics.

H

HCPRIO data set. The data set containing a real I/O configuration of a VM system.

Hardware Management Console. A console used to monitor and control hardware such as the System/390 microprocessors.

I

IOCDS. An input/output configuration data set (IOCDS) contains different configuration definitions for the selected processor. Only one IOCDS is used at a time. The IOCDS contains I/O configuration data on the files associated with the processor controller on the host processor, as it is used by the channel subsystem. The CSS uses the configuration data to control I/O requests. The IOCDS is built from the production **IODF.**

I/O Cluster. An I/O cluster is a sysplex that owns a managed channel path for an LPAR processor configuration.

IOCP. An IOCP (I/O configuration program) is the hardware utility that defines the hardware I/O configuration to the channel subsystem. For this definition IOCP retrieves information about the following: the channel paths in the processor complex, control units attached to the channel paths, and I/O devices assigned to the control unit.

IODF. An IODF (input/output definition file) is a VSAM linear data set that contains I/O definition information. This information includes processor I/O definitions (formerly specified by **IOCP** input streams) and operating system I/O definitions (formerly specified by **MVSCP** input streams). A single IODF can contain several processor and several operating system I/O definitions. See also 500.

I/O Operations. A component of System Automation for OS/390 providing functionality formerly available with ESCON Manager.

initial program load (IPL). The process that loads the system programs from the auxiliary storage, checks the system hardware, and prepares the system for user operations.

L

LDAP. LDAP (lightweight directory access protocol) is an Internet protocol standard, based on the TCP/IP protocol and serves to access and manipulate data organized in a Directory Information Tree (DIT). LDAP V3 is specified in RFC 2251 and is specifically targeted at management and browser applications that provide read/write interactive access to directories. HCD makes IODF data accessible via LDAP using the z/OS Security Server LDAP Server.

Logical Control Unit. A logical control unit (LCU) can be a single CU with or without attached devices or a group of one or more CUs that share devices. In a channel subsystem, a logical CU represents a set of CUs that physically or logically attach I/O devices in common. A logical CU is built from the information specified in the CU definitions. The physical CUs the device is attached to form part of a logical CU.

Logically Partitioned (LPAR) Mode. A central processor complex (CPC) power-on reset mode that enables use of the PR/SM feature and allows an operator to allocate CPC hardware resources (including central processors, central storage, expanded storage, and channel paths) among logical partitions. Contrast with *basic mode*.

M

Master IODF. A master IODF is a centrally kept IODF containing I/O definitions for several systems or even for a complete enterprise structure. Master IODFs help to maintain consistent I/O data within a system and can provide comprehensive reports. From the master IODF subset IODF may be generated to serve as production IODFs for particular systems within the structure.

Migration. Refers to activities that relate to the installation of a new version or release of a program to replace an earlier level. Completion of these activities ensures that the applications and resources on your system will function correctly at the new level.

Multiple Image Facility (MIF). A facility that allows channels to be shared among PR/SM logical partitions in an ESCON or FICON environment.

Multiple Exposure Device. A multiple exposure device is allocated by a single device number, but accessed by several device numbers, whereby each device number represents one exposure. The device number by which the device is allocated is the **base** exposure; all other device numbers are called non-base exposures.

MVS System. An MVS image together with its associated hardware, which collectively are often referred to simply as a system, or MVS system.

MVSCP. MVSCP (MVS configuration program) is the program that defines the I/O configuration to MVS. For this definition, information about devices, **EDTs,** and **NIP** consoles is required.

N

NIP Console. A NIP (nucleus initialization program) console is a device that NIP uses as a console to display system messages. To define a device as a NIP console, it must first be defined to the channel subsystem and the current operating system (OS) configuration.

P

Peer coupling channel. A peer coupling channel is a coupling channel operating in peer mode, which means it can be used as a sender and receiver at the same time. It may be shared by several logical OS partitions (such as CF sender channels) and by a CF logical partition. In addition, peer channels provide more buffer sets and channel bandwidth than their counterparts. Peer channels are supported only on zSeries 900 servers and their successors.

Preference Value. Preference value is the value that is assigned to each **generic**. This value determines the sequence of allocation. The generics and the associated values are system-defined. The predefined order can be changed by means of the preference value.

Processor Resource/Systems Manager (PR/SM). The feature that allows the processor to use several OS images simultaneously and provides logical partitioning capability. See also *LPAR*.

Production IODF. The production IODF is used by MVS/IPL to build **UCBs** and **EDTs**. It is also used to build **IOCDSs** and IOCP input data sets. Several users can view a production IODF concurrently and make reports of it, but it cannot be modified. The production IODF that is used for IPL must be specified by a LOADxx member. The LOADxx member can reside either in SYS1.PARMLIB or SYSn.IPLPARM. If the LOADxx member resides in SYSn.IPLPARM, then SYSn.IPLPARM must reside on the IODF volume. If the LOADxx member resides in SYS1.PARMLIB, then SYS1.PARMLIB can reside on either the system residence (sysres) volume or the IODF volume.

S

SNA Address. The system network architecture (SNA) address is a means to identify the support element of a CPC configured in a S/390 microprocessor cluster. It consists of the network name (the network identifier of the LAN the support element of a CPC is connected to), and the system name (the identifier of the CPC within the network). In HCD, used as part of a processor definition for a CPC, the SNA address provides the association of a processor defined in the IODF with a CPC configured in an S/390 microprocessor cluster.

Sysplex. A set of operating systems communicating and cooperating with each other through certain multisystem hardware components and software services to process customer workloads. See also *MVS system*.

S/390 Microprocessor Cluster. S/390 microprocessor cluster is a configuration that consists of CPCs (central processor complexes), one or more Hardware Management Consoles, and may have one or more coupling facilities. The support elements that are attached to the CPCs are connected to a network. A Hardware Management Console connected to the same network allows the system operator to configure the CPCs, observe and control hardware operations, and perform software functions.

U

UCB. Unit control block

UIM. UIMs (unit information modules) perform the device-dependent part of the operating system configuration definition. There is a UIM for each supported device or device group. Each UIM recognizes and processes the values coded for its device or device group. HCD routines load all UIMs, either IBM or customer supplied, into virtual storage and make calls to the UIMs:

- During initialization
- During processing of an Add device or Change device request
- During generation of a print report
- During IPL

V

VIO. VIO (virtual input/output) is the allocation of data sets that exist in paging storage only. Only DASDs are eligible for VIO. Data sets are allocated to a paging device instead of to a real device.

W

Work IODF. The work IODF is used to update an I/O definition and reflects the most recent status of the hardware configuration. After you have completed the updates, you can use the work IODF to create a production IODF. While you can update a work IODF and generate reports from it, it cannot be used to build **UCBs** and **EDTs**, nor can it be used to generate an **IOCDS**, or an **IOCP** input data set.

Index

Special Characters

*HCD 193
*$HCDC$ 193

Numerics

4-character model 192
8-character control unit 192

A

abend code
  '00F' 417
  other than '00F' 418
abnormal termination 416
access authority 315
access list 114
accessibility 493
action bar 67, 349
action code 72, 349
action list 71
action-to-action processing 71
actions on objects, migration enhancements 267
activate messages 207
activating
  configuration dynamically 199
  glossary definition 499
  switch configuration 175
  sysplex-wide 203
  trace 437
active hardware configuration token stored 205
active IODF, view 199
active switch 173
active sysplex member list 203
Activity Log panel 62
activity logging
  browsing 231
  description 62
  printing 231
  volume serial number 42
adding
  channel path 112
  configuration package object 59
  configuration packages 57
  consoles 145
  control units 122
  device to esoteric device list, migration 270
  devices 131
  devices to esoterics 97
  EDTs 92
  esoterics 96
  objects through migration 267
  objects with dialog 85
  operating system configuration 89
  partitions 106
  processor 99
advantages of extended migration 252
all-character readable token 192
allocating output data sets
  volume serial number 41
allow hardware deletes 201
alter access 316
alternate DD names 314
analyze errors
  batch migration 251
  dialog migration 250
  HCD problems 415
API provided by HCD 445
application programming interface 445
assembler check, migration 250, 278
assembler statements 242
assembly listing 278
assigning devices to esoterics 97
associated with processor and partition, migration 249
attended export 56
attribute group change 140
auto-assign 24, 124

B

back-level IODF 31, 61
back-level release activate 26
Backend, LDAP 325
backup an IODF 54
base, glossary definition 499
BASIC mode, sysplex wide activate 205
batch jobs
  generated by HCD 84
batch utility
  build configuration statements 295
  build CONFIGxx member 295
  build IOCDS or IOCP input data set 292
  build JES3 initialization stream checker data 295
  build production IODF 290
  build work IODF 291
  compare IODFs or CSS/OS reports 303
  copy IODF 298
  create graphical configuration reports 301
  description 283
  example for copy IODF 310
  example for migration 251
  EXEC procedures 48
  export IODF 308
  functions 283
  import IODF 307
  initialize IODF 285
  input parameter string 284
  job steps during transmit procedure 427
  migrate an input data set 251, 287
  print configuration reports 299
  starting the dialog 284
  upgrade IODF 286
BCTC 149
blocking ports 170
BookMaster 219
BOTTOM command 68
browse activity log 231
build
  CONFIGxx member, dialog 209
  CONFIGxx, batch 295
  HCPRIO input data set, batch 295
  IOCDS, batch 292
  IOCDS, dialog 184
  IOCP input data set 192
  IOCP input data set, batch 292
  IOCP input data set, dialog 191
  JES3, batch 295
  OS configuration data set, dialog 195
  production IODF, batch 252, 290
  production IODF, dialog 180
  S/390 microprocessor IOCDSs, dialog 186
  work IODF, batch 291
build configuration statements 252

C

candidate list 115
cascade switching 153
cascaded FICON fabric 126
catalog
  considerations 319
  scan utility 321
cataloged data set 320
CBDCHCD 39, 40
CBDMGHOM routine 445
centralized navigation 86
CF channel path, migration enhancements 262
CF duplexing 10
chained switches 154, 165
changing
  channel path attributes, migration 270
  channel paths 118
  configuration packages 58
  consoles 146
  control unit and device attributes, migration 270
  control unit attachment parameters for multiple processors 129
  control units 127
  coupling facility connection 120
  CSS-related definitions for a group of devices 138
  device number 141
  devices 137
  DYNAMIC parameter for a group of devices 140
  EDT ID 94
  EDTs 93
  esoterics 97
  esoterics for a group of devices 139

© Copyright IBM Corp. 1994, 2002

changing *(continued)*
IODF description 55
LOCANY parameter for a group of devices 140
operating mode of channel paths 119
operating system configuration 90
operating system configuration ID 90
OS-related definitions for a group of devices 139
partition name, migration 270
partitions 108
ports from installed to uninstalled 167
ports from occupied to not occupied 167
processor 101
processor ID 103
processor mode 103
processor type 101
production IODF 54
switch configuration ID 170
switch configurations 159
switch data 159
switches 159
to another IODF 54
type of CF channel paths 119
type of channel paths 119
type/model of a group of devices 140
channel packaging rules 20
channel path
access list 114
aggregating 120
candidate list 115
changing 118
CHPID statement 261
compare report, example 407
connectivity report, example 359
defining 112
deleting 122
detail report, example 357
migration enhancement 261
operating mode 111
summary report, example 357
working with 111
checking of channel packaging rules 20
CHPID report 218
CHPID statement 261
CLIST used by HCD 40
CNC channel 148
CNC side information 151
CNTLUNIT statement 263
coexistence considerations 63
color settings for graphical reports 43
combined input data sets 249
command line 76
commands
BOTTOM 68
FIND 170
GOTO 78
HELPID 420
HELPTEST 420
how to use 76
INSTRUCT 68
LEFT 68
LOCATE 68
LOCATE, graphical report 223
commands *(continued)*
PANELID 420
PFSHOW 76
REFRESH, graphical report 224
RIGHT 68
SAVE 223, 225
SHOWIODF 55
SHOWMSG 433
SHOWMSG ACTIVATE 202
syntax diagrams, how to read xv
TOP 68
TRACE 437
TRACE, HCM 439
common user access (CUA) 67
compare
CONFIGxx members 211
CSS/OS views, dialog 230
IODFs or CSS/OS Reports, batch 303
IODFs, dialog 226
compare reports
channel path 407
control unit 409
control unit attachment 408
CSS / OS device 414
device 410
device attachment 409
esoteric 412
OS console 413
OS device 413
partition 406
processor 406
switch 410
switch configuration detail 411
switch detail 411
compatibility 63
component ID 415
concatenation 37
configuration data
activating dynamically 199
consolidating 86
define 85
definition sequence 88
delete 85
modify 85
process 179
validation 3
configuration package
define 57
delete 58
edit 58
list 57
problem determination for transmit procedure 427
transmit 60
work with 57
configuration package object
add 59
delete 59
list 58
merge 59
replace 59
work with 58
configuration reports
build with batch 295
CF channel path connectivity report, example 359
configuration reports *(continued)*
channel path detail report, example 357
channel path summary report, example 357
channel subsystem reports, example 355
control unit detail report, example 360
control unit summary report, example 360
CSS report, description 215
CTC connection, description 216
CTC report, example 370
device detail report, example 362
device summary report, example 361
eligible device table report, example 367
examples 355
graphical configuration report 218
I/O definition reference 217
I/O definition reference, example 401
I/O path report 371
I/O path, description 216
IOCDS report, example 356
LCU report, example 405
MVS device detail report, example 367
MVS device report, example 366
NIP console report, example 368
operating system report, description 216
operating system report, example 366
operating system summary report, example 366
partition report, example 355
print with batch 299
printing graphical reports 218
printing textual reports 217
problem determination 422
processor summary report, example 355
supported hardware report 373
supported hardware, description 216
switch configuration detail report, example 365
switch configuration summary report, example 364
switch detail report, example 364
switch report, description 216
switch report, example 364
switch summary report 364
viewing graphical reports 218
VM console report, example 369
VM device detail report, example 369
VM device report, example 368
configuration status 207
CONFIGxx member
build using dialog 209
build with batch 295
compare using dialog 211
connecting
another switch to a switch 165
channel path to switch 163

connecting *(continued)*
control unit to switch 164
coupling facility channel paths 116
connections of switches, possibilities 153
connectivity report, example 359
considerations for IBM ES/4381 processors 248
console
changing 146
configuration report, description 216
configuration report, example 368
deleting 146
report, example 369
working with 145
consolidating configuration data 86
context menu 71
control unit
attachment compare report, example 408
attachment data to processor 124
changing 127
changing attachment parameters for multiple processors 129
CNTLUNIT statement 263
compare report, example 409
configuration report, example 360
defining 122
deleting 131
disconnecting 129
migration enhancement 263
priming, serial number 130
supported by system 236
working with 122
control unit list 87
control unit model 241
control unit number change 25
copying
IODF, batch example 310
IODF, batch utility function 298
IODF, with dialog 55
coupling facility
changing connection 120
connecting channel paths 116
disconnecting channel paths 118
glossary definition 499
overview 10
view information 148
coupling facility connection report 219
CPC (central processor complex)
glossary definition 499
specify name 100
support in HCD 11
Create Work I/O Definition File panel 50
create work IODF from production IODF 54
creating
graphical configuration report, batch 301
graphical configuration report, dialog 218
IODF using batch 251
IODF using dialog 50
JES3 initialization stream checker data 195
new objects 85
cross operating system support 5
CSS (channel subsystem)
configuration report, description 215
configuration report, example 355
group change action 138
overview 1
CSS/operating system device compare report, example 414
CSS/OS report, compare with batch 303
CTC channel 148
CTC connection report
connection report, description 216
diagnostic messages 152
filter 151
incomplete definitions 151
print 152
report, example 370
with MIF 149
with shared channels 149
CTC side information 151
CU list 87
CU report 218
CUADD, CTC connection 149
customizing HCD 37

D

data entry panel 68
data sets
allocation for migration 280
build configuration statements with batch 295
cataloged with esoteric name 320
combined 249
example 193
generated during transmit configuration package 428
migrate with batch 287
migration 239
migration using the dialog 248
relationship in HCD 7
data space 45
DCF 219
DCM 113
ddnames
alternate 314
default for migration 280
standard 312
dedicated connection 153, 169
dedicated operating mode 111
default connection 169
default size, IODF 23
default switch matrix 171
defining
a sample configuration 453
channel path 112
channel path access list 114
configuration data 85
configuration packages 57
connections to switches 163
consoles 145
control units 122
CSS-related definitions for devices 133
devices 131
EDTs 92
esoterics 96
group of channel paths 113
defining *(continued)*
managed channel paths 113
multiple devices in one step 133
operating system configuration 89
OS-related definitions for devices 136
partitions 106
processor 99
processor attachment data 124
switch configurations 168
switches 156
deleting
activate messages 207
channel paths 122
configuration package object 59
configuration packages 58
console list, migration 270
consoles 146
control unit, migration 270
control units 131
device from esoteric device list, migration 270
device, migration 270
devices 145
EDTs 95
esoteric device list, migration 270
esoterics 98
IODF 55
operating system configuration 92
partition, migration 270
partitions 111
processors 106
switch configuration 162
switch-to-switch connection, migration 270
switches 162
switches, confirm 162
developing a migration strategy 27
device
attachment compare report, example 409
changing 137
changing CSS-related definitions for a group 138
changing DYNAMIC parameter 140
changing esoterics for a group 139
changing LOCANY parameter 140
changing number 141
changing OS-related definitions for a group 139
changing type/model of a group of devices 140
compare report, example 410
compare, CSS/operating system 414
configuration report, description 216
defining 131
defining a group in one step 133
defining CSS-related definitions 133
defining OS-related definitions 136
deleting 145
detail report, example 362
disconnecting from operating system 142
identification 133
IODEVICE statement 265
migration enhancement 265
priming, serial number 144

device *(continued)*
priming, volume serial number 144
protection 318
restricting partition access 134
summary report, example 361
supported by system 237
working with 131
device list 87
device serial number 133
device type group change 141
diagnostic information and tools 433
diagnostic message, CTC connection 152
diagnostic messages 370
dialog, usage 67
different IODF levels 63
disability 493
disable write protection 189
disabled marker 167
disabled system names 205
disconnecting
control units from a processor 129
coupling facility channel path connections 118
devices from operating system 142
multiple control units from a processor 129
display active sysplex member list 203
display diagnostic message, CTC connection 152
display graphical reports 222
dualwrite option 185
dumps 440, 441
duplicate control unit 243
duplicate device 246
dynamic channel path management 113
dynamic connection 149, 153
dynamic connection ports 170
DYNAMIC parameter 140
dynamic reconfiguration management
activation 199
back-level release activate 26
failure, sysplex-wide 207
glossary definition 499
hardware and software changes allowed 200
identify device 133
overview 4
profile access 315
rejection 202
resource access 315
software only changes allowed 202
sysplex-wide 203
dynamic switch 153

E

editable fields 74
EDT
changing 93
configuration report, description 216
configuration report, example 367
defining 92
deleting 95
EDT statement 255
glossary definition 499
migration enhancement 255
repeating 94
EDT *(continued)*
working with 92
EDT statement 255
elimination of MVSCP 25
EMIF
glossary definition, see MIF 499
enable write protection 189
ending HCD 40
enhanced migration 252
enhancements for HCD Version 5 20
entry port, CTC connection 149
entry switch 153
environment for HCD 8
error message, CTC connection 151, 152
errors
diagnosis 415
during IPL 419
during migration 250, 279
during transmit procedure 427
ESCON director, CTC connection 149
ESCON Manager 9
ESCON Manager lock 176
ESCON Manager, glossary definition 499
ESCON manager, overview 9
ESCON, glossary definition 499
ESCON, prerequisites 9
esoteric compare report, example 412
esoterics
changing 97
defining 96
deleting 98
device group name 320
glossary definition 499
migration enhancement 256
repeating 98
token 256, 320
token, migration 242
token, overview 25
UNITNAME statement 256
working with 96
establishing coupling facility channel path connections 116
establishing dedicated connections 169
EXEC procedures 48
exit, function key 77
explicit device candidate list 110, 134
export
IODF, batch 308
IODF, dialog 56
extended migration 252

F

fabric 153
failure, diagnosis 415
fast path 78
FCTC 148
fibre channel 13
FICON
cascade switching 153
switch fabric 153
FICON Channel-to-Channel support 148
FICON glossary definition 499
FICON switch
downgrading link address 127
upgrading link address 126
FICON switches 153
fields
editable 74
input and output 69
promptable 75
filter CTC connection 151
filter mode 83
filtering a list 81
FIND command 170
font for graphical reports 43
formatting type for graphical reports 43
four-digit device numbers 25, 131
free space in HSA 205
function keys
actions 67
add 85
backward 68
command 76
Enter 77
exit 77
forward 68
help 76
how to use 76
instruct 68
jump 222
left 68
previous 78
problem determination 419
prompt 69
reset 73
right 68
setting 24 keys on 40
split 322
zoom 223
function parameter strings 284

G

GDDM
installation 37
usage for reports 219
generate switch matrix 171
generic device type, glossary definition 499
generics
migration enhancement 256
UNITNAME statement 256
working with 95
GML 219
GOTO command 78
graphical configuration report
create with batch 301
example 405
font 43
jumping to action lists 222
LCU report, example 405
limiting a graphical report 221
overview 23
prerequisites 219
printing 218
problem determination 422
scaling factor 43
viewing 218
graphical navigation 86
graphical representation 218

group changes
attribute group change for devices 140
CSS group change for devices 138
device type group change 140
esoterics for a group of devices 139
group change action for control units 125
OS group change for devices 139
overview 24

H

hardware and software changes allowed 200
hardware configuration token 205
Hardware Management Console 11
glossary definition 500
hardware report 373
hardware support 22, 233
HCD (Hardware Configuration Definition)
abnormal termination 416
and coupling facility 10
and I/O Operations (ESCON Manager) 9
customizing 37
data sets relationship 7
differences between HCD and MVSCP/IOCP 1
ending 40
environment 8
HCD 5.1, new functions 22
HCD 5.2, new functions 20
HCD 5.2.2, new functions 19
installation considerations 37
LDAP Backend 325
LDAP Backend configuration 334
object management services 445
OS/390 Release 3 HCD, new functions 18
OS/390 Release 5 HCD, new functions 16
OS/390 Release 9 HCD, new functions 15
overview 1
overview of functions 4
product identifier 415
setting up 37
starting 40
HCD profile 41, 193
HCPRIO input data set
build with batch 295
build with dialog 195
glossary definition 500
migration 246
help
how to get 76
problem determination 420
testing panels 420
HELPID command 420
HELPTEST command 420
hiding parameter/feature definitions 142
hierarchical navigation 86
highlighting 69
HOM services 445
HOM services *(continued)*
example 450
functions 448
input and output areas 446
invocation 445
request block (HRB) 447
return codes 451
HSA 204
HSA token 188

I

I/O cluster
glossary definition 500
I/O concurrency level 110, 125, 128, 361, 469
I/O configuration definition reference
configuration report, example 401
description 217
print 299
I/O Operations
glossary definition 500
I/O Operations, overview 9
I/O path list 197
I/O path report
description 216
example 371
IBM ES/4381
build IOCP input data set 191
build production IODF 184
migration considerations 248
IBM-supplied UIMs 29
ID statement 260
identifying problems 415
IEC161I (copy IODF batch utility) 311
IEFESOJL (catalog scan utility) 321
image number, CTC connection 149
import
IODF, batch 307
IODF, dialog 57
incomplete CTC definitions 151
increased system availability 4
incremental update 267
initialization problems 424
initialization stream checker data for JES3 195
initialize IODF from VSAM DIV file 285
input fields 69
input parameter string, batch utilities 284
input to stand-alone IOCP 191
installation-static 241
installation-supplied UIMs 29
installed port range 158
installed ports 167
installed UIMs 238
installing
for migration 33
GDDM 37
HCD 37
INSTRUCT command 68
instruction area 68
insufficient data set sizes 280
interface
batch utility functions 283
dialog 67
interface *(continued)*
HCD object management services 445
introduction 1
invoking batch utility functions 283
IOCDS
build S/390 microprocessor IOCDSs 186
build with batch 292
build with dialog 184
glossary definition 500
report, example 356
token 188
use with HCD 5
write in preparation for processor upgrade 185
IOCONFIG statement 254
IOCP
build input data set with batch 292
build input data set with dialog 191
example 193
glossary definition 500
migrating additional data sets 243
migrating input data sets 239
migration considerations 32
stand-alone 191
use with HCD 1
IODEVICE statement 265
IODF (I/O definition file)
activity logging 50, 62
attributes 50
backup 54
build production IODF, batch 290
build production IODF, dialog 180
build work IODF, batch 291
change description 55
change during session 54
checker function 19
compare 226
compare reports, example 406
compare with batch 303
copy with batch 298
copy with dialog 55
data model 475
data space 45
default size 23
delete 55
description 2, 49
different levels 63
dump 440
enhancements 23
export with batch 308
export with dialog 56
glossary definition 500
import with batch 307
import with dialog 57
initialize 285
LDAP support 325
maintenance 54
master 52
multiple 51
naming conventions 49
object classes and attributes 476
objects managed in 6
prefix 214
release level compatibility 63
repair 440

IODF (I/O definition file) *(continued)*
sharing 51
single 51
space allocation 50
specify 50
subset 52
suffix 214
transfer to a different system or location 442
upgrade with batch 286
upgrade with dialog 31, 61
used at IPL 6
used for last IPL 54
view currently accessed one 55
volume serial number 50
IPL
attribute list 190
attribute management functions 11
errors 419
glossary definition 500
IODF processing 214
manage attributes for S/390 microprocessor 190
specify an IODF 214
with MVSCP 4
IPLADDR value 190
IPLPARM value 190
iQDIO 13
ISPF considerations 321
ISPF list file 418
ISPF table 173
ISPF, tailoring 40

J

JES3 initialization stream checker data 195
JES3, build with batch 295
job statement information 84
jumping from graphical reports 87, 222

K

keyboard 493
keywords in HCD profile 41

L

LCU (logical control unit)
glossary definition 500
report, example 405
report, how to generate 218
LDAP (lightweight directory access protocol)
address space, HCD instance 431
backend abnormal termination 431
backend, supported and non-supported requests 338
error in HCD Backend 432
glossary definition 500
HCD instance startup fails 432
HCD LDAP Backend debug level 336
HCD LDAP Backend, customizing 334
interface capability 5
LDAP (lightweight directory access protocol) *(continued)*
operational behavior 338
problem determination 431, 441
return code 432
server address space 431
server, slapd.conf file parameters 334
support 325
transactions 343
LDAP response messages 434
LEFT command 68
legend, CTC report 370
library concatenation 37
limit CTC connection report 217
limiting a graphical report 221
link address 126
link address, CTC connection 149
lists
action list 71
configuration package list 57
configuration package object list 58
filtering 81
I/O path list 197
numbered selection lists 69
selection methods 69
unnumbered multiple selection lists 70
unnumbered single selection lists 70
working with 69
LOAD parameter 214
LOCANY parameter 140
LOCATE command 68
LOCATE command, graphical report 223
logging 62
logical address 126
LPAR (logical partitions)
defining 106
glossary definition 500

M

main panel 40
maintain IODF 54
manage S/390 microprocessor IPL attributes 190
MAP_CUTYPE 44, 240
mapping of migrated data 242
master IODF 52
glossary definition 500
merge changes 59
matrix, generate switch 171
maximum frame size 114
message list 74, 277
Message List panel 75
message list, CTC connection 152
message log 433
messages
delete 75
explain 75
overview 433
reason code 417
save 75
MIF
defining with HCD 111
glossary definition 500
MIF, CTC connection 149
Migrate IOCP / MVSCP / HCPRIO Data panel 249
migrate switch configuration 173
MIGRATE_EXTENDED 193
migration
additional input data sets 242
advantages 252
assembler check 250
batch utility 287
changing input data sets 240
conflicts 240
consideration 240
control unit type mapping 44, 240
coupling facility updates 251
data set allocation 280
enhancements 26, 252
errors 250
existing input data sets 239
existing switch configurations 173
extended migration 252
for combined IOCP/MVSCP input data set 239
from MVS/370 32
from MVS/ESA SP 4.n 32
from MVS/XA SP 2.n or MVS/ESA SP 3.n 33
log 279
LPAR considerations 239
multiple IOCP/MVSCP statement 239, 242
new parameters 252
overview 27
partial 267
preparation 240
prerequisites for extended migration 193
processing mode 249
processor consideration for IBM ES/4381 248
protocol support for control units 241
return code 250
roadmap 28
sequence 239
setup considerations 33
solving errors 277
strategy 27
termination 250
to z/OS 30
using the HCD batch utility 251
using the HCD dialog 248
validation rules 240
migration log 433
minimum installed port range 257
mixed environment 195
module prefix 415
moving directly 78
multiple exposure device, glossary definition 500
multiple IODFs 51
multiple switch activation 176
MVS device report, example 366
MVS devices 373
MVS/370 user, migrating 32
MVS/ESA SP 3.n 33
MVS/ESA SP 4.n 32
MVS/XA SP 2.n 33

MVSCP (multiple virtual system configuration program)
  differences to HCD 1
  elimination 25, 32
  glossary definition 500
  migrating additional input data sets 246
  migrating input data sets 239
  migration considerations 32
  use with HCD 1

N

naming convention of IODF 49
navigating through HCD 86
navigation map 87
network name 100
new support in HCD Version 5 20
NEWAPPL parameter 29
next POR 212
NIP console
  glossary definition 501
  NIPCON statement 255
  working with 145
NIP console report, example 368
NIPCON statement 255
numbered selection lists 69

O

occupied indicator
  PORT statement 258
occupied ports 167
operating mode
  changing 119
  how to use 111
operating requirements for HCD 8
operating system configuration
  changing 90
  defining 89
  deleting 92
  description 254
  group change action 139
  IOCONFIG statement 254
  migration enhancement 254
  repeating 91
  report, description 216
  reports, example 366
  working with 89
optional comment 225
options for text reports 42
order to define a configuration 88
organization of the book xiv
OS console compare report, example 413
OS device compare report, example 413
OS group change action 139
OS report 216
output field 69
overview of HCD 1
overview, migration 27

P

packaging rules 20
panel
  flow of HCD options 349
  identifier 68, 420
  layout 67
  problem determination 419
  title 68
PANELID command 420
partial migration 267
partition
  changing 108
  compare report, example 406
  configuration report, example 355
  defining 106
  deleting 111
  migration enhancement 261
  repeating 108
  RESOURCE statement 261
  transferring 109
  working with 106
partition access to CHPIDs 201
partition name change 25
partition usage 107
peer coupling channel, glossary definition 501
peer-to-peer communication 148
PFSHOW command 76
planning
  migrating to z/OS 30
  migration consideration 240
  migration, considerations for the MVS/370 user 32
  migration, data set allocation 280
  migration, processor consideration for IBM ES/4381 248
  your configuration 85
planning for migration 27
POR (power-on reset) 4
POR, switch IOCDS 209, 213
port configuration 259
port list 167
port matrix 153, 169
port range 158
PORT statement 258
port, moving switch 160
PORTCF statement 259
ports, blocking 170
PR/SM 10
pre-migration activities 240
preallocation 280
preference value 95
preference value, glossary definition 501
preparing for migration 240
prerequisites 9
previous, function key 78
primary task selection panel 40
priming
  control unit serial number 130
  device data 144
  processor serial number 105
  switch port connection 166
  switch port name 166
  switch serial number 159
printing
  activity log 231
  compare reports 226
  configuration reports, batch 299
  CTC connection 152
printing *(continued)*
  graphical configuration report 219
  graphical reports 221
  list panels 225
  problem determination 422
  textual configuration reports 215
problem determination
  abnormal termination 416
  diagnostic information and tools 433
  errors during IPL 419
  graphical reports 219, 422
  help information 420
  identifying problems 415
  initialization of HCD 424
  IODF dump 440
  panels and function keys 419
  repair an IODF 440
  system abend code '00F' 417
  system abend code other than '00F' 418
  textual reports 422
  trace facility 434
  transmit procedure 427
  UIMs 425
problem reporting data bases 442
process configuration data 179
processing mode, migration 249
processor
  changing 101
  changing type 101
  compare report, example 406
  configuration report, example 355
  defining 99
  deleting 106
  ID statement 260
  migration enhancement 260
  priming, serial number 105
  repeating 104
  support level 100
  supported by system 233
  working with 99
Processor Resource/Systems Manager
  glossary definition 501
processor token 205
processor upgrade, write IOCDS 185
product identifier 415
production IODF
  build with batch 290
  build with dialog 180
  change 54
  format of 49
  glossary definition 501
  how to specify 49
  replace during build production IODF 180
profile 193
profile for HCD 41
programming interface for HCD 283
promptable fields 75
protected devices 318
protocol support for control units, migration 241

Q

QDIO 13
query supported hardware 233

R

RACF 315, 316, 318
re-migrate IOCP input data sets 192
read access 316
reason code 417
receiving an IODF 57
reconfigurable operating mode 111
REFRESH command, graphical report 224
refreshing the active sysplex member list 204
rejection of dynamic activation 202
relationship of data sets 7
release level compatibility 63
removed restrictions 25
repair an IODF 440
repeating
  action 86
  description 86
  EDTs 94
  esoterics 98
  operating system configuration 91
  partitions 108
  processors 104
replacing
  during build production IODF 180
replacing objects through migration 267
reporting problems 442
reports, text, options 42
requirements
  for setting up HCD 37
  for using HCD 8
  migrating IOCP/MVSCP data 240
reset function key 73
reset source configuration sysplex-wide 208
RESOURCE statement 261
restricting partition access for devices 134
restrictions, removed 25
resume activation sysplex-wide 208
return code, migration 250
RIGHT command 68
roadmap, migration 28

S

S/390 microprocessor
  build IOCDSs 186
  manage IPL attributes 190
  support in HCD 11
sample configuration 453
save
  messages 75
  switch configuration 176
SAVE command 223, 225
SAVE command, CTC connection 152
saved switch file 173
scaling factor for graphical reports 43
scenarios 453
scrolling 68
SCTC 149
search order at IPL 214
searching data bases 442
security considerations 315, 318
selection markers 71
selection methods in lists 69
sending an IODF 56
sensing 11, 371
sequence of migration 239
sequence to define a configuration 88
serial number
  control unit 130
  device 144
  processor 105
  switch 159
serial number for device 133
server started task log 434
ServerPac 33
setting up HCD 37
setup considerations for migration 33
severity of messages 152
shared channels, CTC connection 149
shared operating mode 111
sharing IODFs 51, 63, 319
shortcut keys 493
showing parameter/feature definitions 142
SHOWIODF command 55
SHOWMSG ACTIVATE command 202
SHOWMSG command 433
single IODF 51
single point of control 4, 203
single switch activation 176
SMS considerations 321
SNA address 100
  glossary definition 501
software only changes allowed 202
solving migration errors 277
space allocation 50
specifying
  input data sets for migration 249
  IODF, dialog 50
split screen 322
stand-alone CTC adapter 149
stand-alone IOCP 191
standard DD names 312
starting
  HCD 40
  migration 248
  the dialog, batch 284
status of configuration 207
strategy, migration 27
support level 100
supported hardware 233
supported hardware report 373
supported migration paths 28
SWCONF statement 258
switch
  blocking ports 170
  chained switches 154
  changing data 159
  compare report, example 410, 411
  confirming delete 162
  connections to switches 163
  dedicated connection 153
  default connection 169
  defining 156
  defining connections 163
  deleting 162
  disabled marker 167
  dynamic connection 153
  dynamic switch 153
switch *(continued)*
  enhancements 23
  entry switch 153
  graphical report 218
  matrix, default 171
  migrating 173
  migration enhancement 257
  moving ports 160
  port matrix 153
  port range 158
  possible connections 153
  priming, prerequisites 9
  priming, serial number 159
  report, example 364
  supported by system 235
  SWITCH statement 257
  textual report, description 216
  validation 156
  working with 153
switch configuration
  activating 175
  changing 159
  changing ID 170
  compare report, example 411
  defining 168
  definition 153
  deleting 172
  generate matrix 171
  migrating 173
  migration enhancement 258
  report, example 364
  save 176
  select other 168
  SWCONF statement 258
switch IOCDS for next POR 185, 189, 212
switch IOCDS for next POR, sysplex-wide 209, 213
SWITCH keyword 153
switch port
  priming, name and connection 166
SWITCH statement 257
symptom table 415
syntax 253
syntax diagrams, how to read xv
SYS1.LOGREC record 418
SYS1.NUCLEUS 25
SYS1.SAMPLIB 321
sysplex 203
sysplex couple data set 204
sysplex member list 203
sysplex, glossary definition 501
sysplex, support 11
system abend code
  '00F' 417
  other than '00F' 418
system names 204

T

termination
  of initialization 424
  of migration 250
test an activation sysplex-wide 207
test help panel 420
textual configuration report, how to print 215

textual configuration reports, examples 355
title line 68
token 192
token-ring LAN 11
token, esoteric 256
TOP command 68
TRACE command 437
TRACE command and HCM 439
TRACE command in HCD profile 44
TRACE command via HCD profile 439
trace facility 434
transfer of IODF to another location or system 442
transferring partitions 109
transmit a configuration package 60
  problem determination 427
type of channel path, changing 119
typing over existing data 74

U

UIM
  converting MVSCP UIMs 29
  glossary definition 501
  IBM-supplied 29
  installation-supplied 29
  library name 42
  list of installed ones 238
  problem determination 425
  use by HCD 9
unattended export 56
uninstalled ports 167
unit address range 126
UNITNAME statement, esoteric 256
UNITNAME statement, generic 256
unnumbered multiple selection lists 70
unnumbered single selection lists 70
update 325
update access 316
updating parts through migration 267
upgrade
  IODF, batch 286
  IODF, dialog 61
  processor 20
usage type 270
utility functions, batch 283

V

validation
  during build production IODF 180
  during migration 239, 250
  rules for migration 240
  switch configuration data 156
  what HCD does 3
verify CTC connection 148
verify your definitions 220
verifying configuration
  against local system 196
  against remote system 197
verifying configuration, prerequsites 9
view graphically 219
View I/O Definition File Information panel 56
viewing
  activate messages 207
  activity log 231
  CF control unit and devices 148
  configuration data 85
  configuration status 205
  coupling facility information 148
  currently accessed IODF 55
  destination channel path definition 148
  graphical reports 222
  IODF used for last IPL 54, 199
  logical control units 147
  next IODF processor 187
  object definitions 146
  source channel path definition 148
VIO (virtual input/output), glossary definition 501
VM
  build HCPRIO input data set, batch 295
  build OS configuration data set 195
  considerations 322
  console report, example 369
  device detail report, example 369
  device report, example 368
  load UIMs 42
  migration considerations 241
VM guest, sysplex-wide activate 204
VOLSER, other data sets 42
volume serial number, IODF 50
VSAM data set, initialize 285

W

wait state 419
wildcard processing, example 83
work area 68
work IODF
  build with batch 291
  format of 49
  glossary definition 501
  how to specify 49
working with
  channel path 111
  consoles 145
  control units 122
  devices 131
  EDTs 92
  esoterics 96
  generics 95
  operating system configuration 89
  partitions 106
  processors 99
  switches 153
write IOCDS 185
write protection, enable and disable 189

Z

zooming graphical reports 223

Readers' Comments — We'd Like to Hear from You

z/OS
Hardware Configuration Definition
User's Guide

Publication No. SC33-7988-01

Overall, how satisfied are you with the information in this book?

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Overall satisfaction	☐	☐	☐	☐	☐

How satisfied are you that the information in this book is:

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Accurate	☐	☐	☐	☐	☐
Complete	☐	☐	☐	☐	☐
Easy to find	☐	☐	☐	☐	☐
Easy to understand	☐	☐	☐	☐	☐
Well organized	☐	☐	☐	☐	☐
Applicable to your tasks	☐	☐	☐	☐	☐

Please tell us how we can improve this book:

Thank you for your responses. May we contact you? ☐ Yes ☐ No

When you send comments to IBM, you grant IBM a nonexclusive right to use or distribute your comments in any way it believes appropriate without incurring any obligation to you.

Name _____ Address _____

Company or Organization _____

Phone No. _____

Readers' Comments — We'd Like to Hear from You
SC33-7988-01

IBM®

Cut or Fold
Along Line

Fold and Tape | **Please do not staple** | Fold and Tape

NO POSTAGE
NECESSARY
IF MAILED IN THE
UNITED STATES

BUSINESS REPLY MAIL

FIRST-CLASS MAIL PERMIT NO. 40 ARMONK, NEW YORK

POSTAGE WILL BE PAID BY ADDRESSEE

IBM Deutschland Entwicklung GmbH
Department 3248
Schoenaicher Strasse 220
D-71032 Boeblingen
Federal Republic of Germany

Fold and Tape | **Please do not staple** | Fold and Tape

SC33-7988-01

Cut or Fold
Along Line

Program Number: 5694-A01

Printed in the United States of America
on recycled paper containing 10%
recovered post-consumer fiber.

SC33-7988-01

Spine information:

z/OS

z/OS V1R3.0 Hardware Configuration Definition
User's Guide

SC33-7988-01