

Z-ADD10X

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
 - Example
-

Description

Add a distribution list.

This subprogram is the same as Z-ADD10 with the one exception that the parameter ISN uses the format P10.

To add members to the distribution list, you must use Z-ADD17.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the distribution list is to be added.
Password	A8	R		The password of the above cabinet.
Distribution-name	A12	R		The name of the distribution list to be added. When you add a distribution list in cabinet SYSCNT, the Distribution-name must not be the same as the name of an existing cabinet.
Description	A60/1:4	O		A brief description for the distribution list.
Folder-name	A15	O		The folder in which the distribution list is to be stored. You must not specify a TRS folder or system folder (except Work). Default: Work.
File-name	A15	O		The file within the above folder in which the distribution list is to be stored.
ISN	P10		X	The ISN of the new distribution list.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
10	Function not valid for a system folder
51	Invalid name
52	Object with specified name already exists
55	Requested folder/file does not exist
56	Requested folder is a TRS folder
90	Distribution list not added - ID already used for a cabinet
91	Error occurred - distribution list was not added

Subprograms

Z-120
 Z-122
 Z-123
 Z-147
 Z-150
 Z-162
 Z-190
 Z-195
 Z-1200&0

Example

```

0010 DEFINE DATA LOCAL
0020 1 RETURN-CODE          (N2)
0030 1 CABINET              (A8)
0040 1 PASSWORD              (A8)
0050 1 DISTRIBUTION-NAME    (A12)
0060 1 DESCRIPTION           (A60/1:4)
0070 1 FOLDER-NAME          (A15)
0080 1 FILE-NAME             (A15)
0090 1 ISN                  (P10)
0100 END-DEFINE
0110 *
0120 MOVE 'USER-ID'   TO CABINET
0130 MOVE 'PW'          TO PASSWORD
0140 MOVE 'DISTR-1'     TO DISTRIBUTION-NAME
0150 MOVE 'This is the first description line' TO DESCRIPTION(1)
0160 *
0170 CALLNAT 'Z-ADD10X' RETURN-CODE CABINET PASSWORD
0180   DISTRIBUTION-NAME DESCRIPTION(*) FOLDER-NAME FILE-NAME ISN
0190 *
0200 IF RETURN-CODE EQ 0
0210   WRITE 'Distribution list was added'

```

```
0220 ELSE
0230     WRITE 'Return code ' RETURN-CODE
0240 END-IF
0250 *
0260 END
```