

# Z-DIS04A

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
- 

## Description

Display the contents of a specific bulletin board in chronological order.

This subprogram should be invoked iteratively until the return code 77 indicates the end of the list. The Number parameter can be modified between iterative calls.

**Note:**

This subprogram can be used in conjunction with Z-GET04.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Bulletin-name	A15	R		The name of the bulletin board for which you want to display the contents.
Start-date	A8	O		Format yyyymmdd. When you enter an invalid format, it is set to 0.
Sequence	N1	O		1 (ascending) or 2 (descending). Default: 1.
All-objects	A1	O		If marked, all objects are returned. If blank, only documents are returned.
Number	N2	O		The maximum number of objects that are returned with each call. When you do not specify a value, or when you specify a value greater than 20, the default value 20 is used.
Occurrence	N2		X	Number of objects returned with this call.
Bulletin-table (20)				
ISN	P8		X	The ISN of the object which has been sent to the bulletin board.
Subject	A60		X	The subject of the object which has been sent to the bulletin board.
Date-delivered	N8		X	Format yyyymmdd. The date when the object was delivered to the bulletin board.
Sent-by-name	A20		X	The name of the user who sent the object to the bulletin board.
Document-format	A1		X	Any value other than 0 to 9 indicates that the object is not a document. See <i>Document Formats</i> .
Work-parameter	A34			For internal use. See <i>The Work Parameter</i> .

## Return Codes

00	Success
77	End of list
90	Bulletin board name required
91	Bulletin board does not exist

## Subprograms

None