

# Z-MOD17

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
  - Example
- 

## Description

Authorize a user to use another private cabinet, or modify the profile of a user who is authorized to use another private cabinet.

Only the user of a private cabinet can be authorized to use another private cabinet.

When a value other than 0 is returned in the parameter Return-code, BACKOUT TRANSACTION is always issued.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the profile for the authorized user is to be added or modified.
Password	A8	R		The password of the above cabinet.
Member	A8	R		The user who is to be authorized to use the private cabinet or the user whose profile is to be modified.
Profile	A55	R		See the redefinition below.
Redefine Profile				
Security-read	A1	R		The security level for Read. A value between 0 and 9.
Security-modify	A1	R		The security level for Modify. A value between 0 and 9.
Security-copy	A1	R		The security level for Copy. A value between 0 and 9.
Security-print	A1	R		The security level for Print. A value between 0 and 9.
Read-mail	A1	O		If marked, the user can read mail.
Reply	A1	O		If marked, the user can reply to mail.
Forward	A1	O		If marked, the user can forward mail.
Send-mail	A1	O		If marked, the user can send mail.
Display-calendar	A1	O		If marked, the user can display all calendar entries.
Modify-calendar	A1	O		If marked, the user can act upon all calendar entries.
Modify-other-items	A1	O		If marked, the user can modify all other objects.
Erase-other-items	A1	O		If marked, the user can erase all other objects.
Display-other-items	A1	O		If marked, the user can display all other objects.
Filler	A42	O		For future use.

See the *Con-nect User's Guide*, section *Adding Shared Users to Your Private Cabinet* for further information regarding the above parameters.

## Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
90	Both the member and the cabinet must be private
91	A cabinet cannot be shared with itself
92	Requested member cabinet could not be found
93	Invalid security level

## Subprograms

Z-120

Z-122

Z-123

Z-1200&amp;0

## Example

```

0010 *
0020 * Demo program to add a member to a private cabinet, where this member is
0030 * only allowed to display the calendar of the shared private cabinet
0040 *
0050 DEFINE DATA
0060 LOCAL
0070 1 RETURN-CODE          (N2)
0080 1 CABINET              (A8)
0090 1 PASSWORD            (A8)
0100 1 MEMBER              (A8)
0110 1 PROFILE             (A55)
0120 END-DEFINE
0130 *
0140 MOVE 'LS'              TO CABINET
0150 MOVE 'PASSWORD'       TO PASSWORD
0160 MOVE 'ESH'            TO MEMBER
0170 MOVE '6666 X'        TO PROFILE
0180 *
0190 CALLNAT 'Z-MOD17'     RETURN-CODE
0200                       CABINET
0210                       PASSWORD
0220                       MEMBER
0230                       PROFILE
0240 *
0250 IF RETURN-CODE NE 0
0260     WRITE 'Return code' RETURN-CODE
0270 ELSE
0280     WRITE 'Member was modified/added'
0290 END-IF
0300 *
0310 END

```