

Your User Profile

This chapter covers the following topics:

- General Information
 - Modifying Your Profile
 - Date and Time Formats
 - Print Defaults
 - Language, Command Sequence and Autosave
 - Folders and Password
 - Mail Status Message
 - Menu and Overlay Calendar
 - Screen Colors
 - Con-nect Version
-

General Information

The Con-nect administrator has defined a profile for each Con-nect cabinet. This profile consists of:

- a system profile, which applies to all Con-nect users;
- a cabinet profile, which applies to individual cabinets and users; and
- your user profile, which applies to your cabinet and user ID only.

Only the administrator can change the system profile and the cabinet profile. You can modify your user profile to suit your specific needs.

The language in which you work, the sequence in which you can enter commands and objects, the appearance of menus, the name of your default folder, and your password are all determined by your user profile.

Every time you logon to Con-nect, your user profile is activated. For example, if your command sequence is "command object name", you can always use this sequence when you access another cabinet, regardless of the command sequence specified by the person to whom that cabinet has been assigned.

Modifying Your Profile

Issue the following command sequence from any point in Con-nect:

```
MODIFY Profile
```

As a result, the "Modify Profile" screen appears.

```

4:25 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS              Modify Profile                      Monday

Date and Time Formats      _
Print Defaults              _
Language/Command/Autosave _
Folders and Password       _
Mail Status Message        _
Menu and Overlay Calendar  _
Screen Colors              _
Con-nect Version           _

Profile has been modified
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help  Menu  Quit  In   Send  Foldr Docs  Note  Cal   Flip  Last  Home

```

Enter any character in the field adjacent to the part(s) of your profile which you want to modify and press ENTER.

A window appears, displaying the default specifications for that part of your profile. The initial specifications are set by the Con-nect administrator. Any time you modify these specifications, the modifications remain in effect (i.e. become defaults) until you modify them again.

After you have completed your modifications (by typing over the defaults), and have pressed ENTER, a message appears, telling you that the profile was modified. If you marked more than one part to modify, the next window appears, otherwise the "Modify Profile" screen is displayed again.

Date and Time Formats

You can specify how the date and time are displayed in Con-nect screens and in your calendar.

To modify the date and time formats, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:26 PM          * * * C o n - n e c t  3 * * *          3.Nov.2003
Cabinet LS      Modify Profile                          Monday

Date and Time Formats  x  !          Date and Time Formats          !
Print Defaults         _  !  Date format 1.4.5  1 DD                !
Language/Command/Autosave _  !  (Any character as  2 MM  4 MON          !
Folders and Password  _  !  a delimiter)        3 YY  5 YYYY          !
Mail Status Message   _  !  Time format 1    0 24h  1 am/pm        !
Menu and Overlay Calendar _  !  Delimiter :              !
Screen Colors         _  !  Timezone 0    (from datacenter)  !
Con-nect Version      _  !  Week start 1    1-7 Monday-Sunday  !
                                !  Day start 9    0-23 hr              !
                                !  Set cabinet sliding window __ 0-99 or !
                                !  Mark to use system value  X 50      !
Make all required changes and press ENTER to modify
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

Modify the default date and time format specifications by typing over them.

Date format

How the date is displayed in all screens, and the order in which the day, month and year appear. The values mean:

1	The day is shown as a number.
2	The month is shown as a number.
3	The year is shown as a two-digit number.
4	The month is shown as a three-letter abbreviation.
5	The year is shown as a four-digit number.

A delimiter separates the day, month, and year values. You can use any character, including a blank. In the example above, the date format is 1.4.5 which means that the date is displayed as "3.Nov.2003".

Time format

How the time is displayed in all screens. The values mean:

0	24 hour display, e.g. 16:45.
1	AM/PM display, e.g. 4:45 PM.

Delimiter

The character which separates the hour and minute values. You can use any character, including a blank.

Timezone

The local time zone (taken from the data center) is the default, and is specified as 0. You can specify any other time zone by entering the number of hours ahead (e.g. 6) or behind (e.g. -8) your data center time zone; this is helpful when you add calendar entries. However, the upper left corner of all Con-nect screens always shows your local time.

Week start

The day which is shown as the first day of the week in the Con-nect menu, and calendar screens. The values mean:

1	The first day of the week is Monday.
2	The first day of the week is Tuesday.
...	
7	The first day of the week is Sunday.

Day start

The start of a 10-hour period within which you expect the greatest frequency of calendar entries. The time scale of a day shown on "Display Month" screen begins with this time and spans 10 hours. For example, the values mean:

0	The day starts at midnight (12 PM or 0:00) and ends at 10 o'clock in the morning (10 AM or 10:00).
8	The day starts at 8 o'clock in the morning (8 AM or 8:00) and ends at 6:00 o'clock in the evening (6 PM or 18:00).

An asterisk (*) to the left or to the right of the time scale of the "Display Month" screen indicates that a calendar entry occurs before or after the period covered by the scale.

Set cabinet sliding window

The sliding window determines which two-digit year values belong to which century. This is important if the year is shown as YY (code 3) and not as YYYY (code 5).

The sliding window covers a period of 100 years. The start and end of the sliding window is determined by the value you enter in the "Set cabinet sliding window" field or the value in the "Mark to use system value" field. As the range of the sliding window always begins in the past, the value you enter is automatically subtracted from the current year to determine the first year of the window range. To determine the last year of the sliding window, 99 is automatically added to the resulting year.

You can enter a value between 0 and 99.

For example, if the current year is 2004 and you enter 40 as the sliding window, the sliding window will cover the years 1964 to 2063. In this case, a two-digit year value (*nn*) from 64 to 99 is interpreted as 19*nn*, while a two-digit year value (*nn*) from 0 to 63 is interpreted as 20*nn*.

If you specify a value of 0, the sliding window mechanism is not used. This means that when you enter a two-digit year, Con-nect interprets it as in the current century.

Caution:

To insure that the sliding window covers adequate time in the past and in the present, it is recommended that you do not set the sliding window to either the low or top end of the range. For example, if you set the sliding window to 2, the range of the sliding window will be (assuming the current year is 2004) 2002 to 2101. This means that when you enter 95 as a two-digit year, Con-nect will interpret it as 2095 and not 1995.

If you enter a value here, you *must not* mark the "Mark to use system value" field.

Mark to use system value

Mark with any character. The number to the right of this field is the value defined as the system value.

If you mark this field, you *must not* enter a value in the "Set cabinet sliding window" field.

Press ENTER to save your modifications.

Print Defaults

You can specify the instructions which are sent to the printer when you print a Con-nect object.

To modify the print defaults, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:28 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS      Modify Profile                          Monday

Date and Time Formats  _      !          Print Defaults          !
+-----+-----+
Print Defaults         x      ! Printer name                !
!   DAEPRTB2_____ !
Language/Command/Autosave  _  ! Page length 65 Wrap printed line _ !
!   Line width 72   Left margin 0_ !
Folders and Password     _  ! Mark to print _ Info          !
!           _ Attached/Cover notes !
Mail Status Message      _  !           List of replies     !
!           _ List of addressees  !
Menu and Overlay Calendar _  ! Printer profile                !
!   HP-4P_____ !
Screen Colors           _  ! Formatting profile            !
!   FPROFILE_____ !
Con-nect Version       _  +-----+-----+

Make all required changes and press ENTER to modify
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

Modify the print defaults by typing over them.

Printer name

The name of a printer to which a Con-nect object is sent when the PRINT command is issued. (A printer name is a combination of printer profile and printer destination which has been specified by the Con-nect administrator.)

To display a window showing a list of all defined printer names, you must enter an asterisk (*) in this line and press ENTER. To select a printer, you must move the cursor to the name of the printer and press ENTER.

You can also enter HARDCOPY as the printer name. In this case, the printer which has been defined by the Natural variable *HARDCOPY is used.

Page length

The number of lines (1 to 99) per page of printout.

Wrap printed line

Optional - if marked, each line of text which is longer than the physical printer line is wrapped. When this field is not marked (default), lines that are longer than the physical printer line are truncated.

Line width

The number of characters (1 to 249) per line. The line width is only evaluated for certain languages (e.g. Hebrew). In other languages this information is not considered.

Left margin

Optional - the number of blank spaces at the beginning of each printed line.

Mark to print

Any character in the adjacent fields causes the following items to be printed with the object:

- **Info**
Information about when and by whom an object was created, last modified, forwarded and/or sent. For a meeting, the number of attendees and resources that have accepted or declined the meeting is printed as well as the number of all pending invitations.
- **Attached/Cover notes**
Attached notes and cover notes.
- **List of replies**
The list of users who sent a reply to the mail item.
- **List of addressees**
The list of addressees to whom an object was sent.

Printer profile

When an object is printed, the printer profile specified in this line is used.

When your administrator has defined a printer profile for the printer you specified in the "Printer name" line of this window, its name is automatically entered in this line. If you do not want to use this printer profile, you can specify the name of another printer profile.

To display a window listing all defined printer profiles, you must enter an asterisk (*) in this line and press ENTER. To select a printer profile, you must move the cursor to the name of the printer profile and press ENTER.

When this line is blank, a printer profile is not used.

Formatting profile

The name of the profile used to format the printout.

If you do not want to use the default profile when a document is formatted, you enter the name of the profile you want to use on this input line. A profile can be any Con-form document in either cabinet SYSCNT or your own cabinet.

Press ENTER to save your modifications.

Your modifications to the print defaults remain in effect until you change them again.

If you want to change the print defaults only for the current session (i.e. only until you leave Con-nect), you must use the OUTPUT command (see the description of the OUTPUT command in section *Documents*).

Caution:

Every time you access the "Print Defaults" window, the formatting profile that is specified in the "Format *Document-name*" screen or in the "Specify Document Format Options" screen (see the description of the FORMAT command in section *Documents*) is replaced with the formatting profile that is specified in the above window. It is replaced even if you do not modify anything in the above window.

Language, Command Sequence and Autosave

If more than one language is available in your environment, you can select the language you want to use, and the sequence in which you want to enter a command sequence (consisting of command, object and name).

You can change the names of the system folders to the language that is defined with the language code.

You can specify what character you want to use as a blank substitute within object names, and you can specify the default value for the "(Undo *Document-name*)" version of a document.

To modify the defaults, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:41 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS          Modify Profile          Monday

Date and Time Formats  _      !      Language / Command / Autosave      !
Print Defaults         _      !      Language code 1                  !
Language/Command/Autosave x  !      Command sequence mark for      !
                        !      OBJECT name COMMAND          !
Folders and Password  _      !      Rename system folders _      !
Mail Status Message   _      !      Blank substitute                !
Menu and Overlay Calendar _  !      Autosave every 10 modifications !
Screen Colors         _      !
Con-nect Version      _      +-----+

Make all required changes and press ENTER to modify
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help Menu Quit In   Send Foldr Docs Note Cal Flip Last Home

```

Modify the defaults by typing over them.

Language code

The code number of the language to be used. To choose a language from a list of all available languages, you enter a question mark (?) in this field.

Only codes for languages which have been installed on your system are valid. The language codes are:

1	English
2	German
3	French
4	Spanish
5	Italian
6	Dutch
7	Turkish
7	Icelandic
7	Finnish
7	Swedish
8	Danish
8	Hebrew
9	Norwegian
9	Portuguese (Brazilian)
9	Arabic
9	Russian

Command sequence

If you leave this field blank, the default command sequence, as used throughout this documentation, is used: "command object name" ("name" can also be a date or time).

You mark this field with any character if you want to use the alternative command sequence of "object name command".

Rename system folders

Used in conjunction with the "Language code" field. If marked, the names of all system folders (e.g. Inbasket and Outbasket) are translated into the language that has been defined for this cabinet. If not marked, the names of the system folders are not changed.

Blank substitute

The character which you must enter in place of the blank when specifying names, dates or times which contain blanks, so that Con-nect can interpret the name, date or time as one unit.

By default, the blank substitute character is a slash (/); however, your administrator may have changed it. You must *not* use a period (.), an asterisk (*) or the letter X as the blank substitute character.

Autosave

You can enter a number between 1 and 99.

The number you enter here, refers to the "(Undo *Document-name*)" version of a document (it also refers to the menulines in the menu editor). You can specify that this version is updated, for example, every second time you press ENTER while modifying the document in the editor.

See Autosave and UNDO in section *Text Processing* for further information.

Press ENTER to save your modifications.

Folders and Password

You can specify a default folder and file. You can also define the layout for the "Contents of Folder Name" screen and modify your Con-nect password.

To modify the defaults, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:42 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS      Modify Profile                          Monday

Date and Time Formats  _      !          Folders and Password      !
Print Defaults         _      ! Default folder Work          !
                        _      !           File                    !
Language/Command/Autosave  _  ! Customize folder _          !
Folders and Password   x      ! 0 or blank no display      !
Mail Status Message    _      !           1 to sender        !
Menu and Overlay Calendar _  !           2 to any user      !
Screen Colors          _      ! Password                    !
Con-nect Version      _      ! New password                 !
                        _      ! Your administrator may have  !
                        _      ! disallowed specific passwords. !
+-----+
Make all required changes and press ENTER to modify
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

Folders

Modify the default folder and file by typing over them.

Default Folder

The name of the default folder is automatically provided in the "Add" screen when you ADD an object.

You specify a different default folder by entering the name of either an existing folder within your cabinet or the name of a new folder. You must specify a default folder, i.e. this field cannot be left blank.

File

Optional - a file within the default folder.

You specify a file by entering the name of either an existing file within your cabinet or the name of a new file.

Press ENTER to save your modifications.

If you enter the name of a new folder or file in the lines above, a window appears, telling you that the folder or file is not defined and listing those that are. You must then either select one of the existing folders or files, or mark an input field to add the new folder or file (see *The "File" Windows*). You then press ENTER to return to the "Defaults and Password" window.

Folder Layout

Define the layout that is to be used for the "Contents of Folder *Name*" screens in your cabinet:

Mark to Customize Folder

Mark this field and press ENTER to display the "Customize Folder Layout in Cabinet" screen. See *Customizing the Folder Layout* for further information.

It is not possible to define another layout for a system folder, with the exception of folder Work.

Information About Replies

Specify whether the "Reply" column is to be shown in the Inbasket and Outbasket:

Display reply column

Specify one of the following values:

0 or blank	The "Reply" column is not shown.
1	The "Reply" column is shown. A character in this column indicates a reply to/from the sender.
2	The "Reply" column is shown. A character in this column indicates a reply to/from any user.

For further information, see *Checking Your Inbasket* and *Checking Your Outbasket*

Password

Modify your password as follows:

1. Enter your current password in the "Password" line.
2. Enter a new password in the "New Password" line.
3. Press ENTER.
4. Confirm the new password by entering it again in the "New Password" line.
5. Press ENTER.

A message appears, notifying you that your password was changed.

The administrator can specify that the cabinet ID or a specific string cannot be defined as a password. In this case, the password is checked each time you define a new password or access your cabinet. When an invalid password is detected, an appropriate message is displayed and you must define a new password.

Tip:

If you forget your password, ask your administrator to reset it (e.g. to your cabinet ID). You can then define a new password as described above.

Mail Status Message

If you cannot be reached via Con-nect for a while, you can set a mail status message.

You define the time range in which the mail status message is to be displayed. Thereafter, all users that send mail to you in the specified time range will see the message you specified.

You can define a user (Cc) who is to receive copies of all mail items that are sent to you.

Your administrator can also set a mail status message for you, for example, when you are ill.

Note:

The mail status message is not displayed when a user sends a reply to a memo or invitation.

To set a mail status message, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:46 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS          Modify Profile          Monday
+-----+
Date and Time Formats  _      ! Set mail status message: X          !
                                ! Date 04.Nov.2003 to 7.Nov.2003_      !
Print Defaults         _      ! Time 8:00 AM_      to 4:00 PM_      !
                                ! Mark X to hide date and time          !
Language/Command/Autosave  _  ! Set X Cc Eshberry,John_____      !
                                ! JE (User)                                !
                                ! I'm currently not in the office._____ !
Folders and Password   _      ! In urgent cases, call me on my_____ !
                                ! mobile phone._____                  !
Mail Status Message    x      ! _____                              !
                                ! _____                              !
Menu and Overlay Calendar _    ! _____                              !
                                ! _____                              !
Screen Colors          _      ! _____                              !
                                ! _____                              !
Con-nect Version      _      ! _____                              !
+-----+
Modify message and press ENTER. Use QUIT to close the window
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

Enter the following information:

Set mail status message

Enter any character in this field (the cursor is automatically placed in the field) to activate the mail status message.

Date

The (starting) date for the mail status message.

to

Optional - the ending date for the mail status message. It must not occur later than 3 years after the starting date.

Day, month, and (optionally) year must be entered in the same sequence as shown in the upper right corner of the screen. When you abbreviate (truncate) the name of the month, you must make sure that the abbreviation is unique.

Time / to

The time range (start and ending time) in which the mail status message is to appear on the specified day(s). When the mail status message is to appear during the entire day, you specify 12:01 AM to 11:59 PM. See *Time Formats* in section *Basic Calender Information* for further information.

Mark _ to hide date and time

When you mark this field, the date and time range for the mail status message is not displayed in the mail status message window of another user.

Set

To activate the Cc feature, mark this field.

Cc

You can specify who is to receive a copy of each mail item that is sent to you. This can be a nickname, user ID, cabinet name or bulletin board. You can also enter an asterisk (*) to select the addressee from a list.

This feature does not apply to invitations to meetings.

A Cc can also be defined with a user address. See *Modifying Your Own User Address*. However, the Cc defined with the mail status message works independently from Cc and Cc 2 defined in the user address. Thus, 3 different Cc definitions may be in use.

Message text

In the lines below the Cc, type the message you want to be displayed when other users send you mail.

Press ENTER to confirm your modifications.

Issue the QUIT command to close the window and to return to the "Modify Profile" screen.

Caution:

Your modifications are not saved until you quit the "Modify Profile" screen.

When another user sends mail to you within the defined time range, the mail status message is shown.

When the mail status message is active and you access the Con-nect menu within the specified time range, you are notified that you have set a mail status message.

Canceling a Mail Status Message

Cancel the mail status message as follows:

1. Mark the "Mail Status Message" field in the "Modify Profile" screen and press ENTER.
2. In the window, remove the character from the "Set mail status message" field.
3. Press ENTER to confirm your modifications.

The message is still shown in the window, but will not be displayed when someone attempts to send you mail.

4. Issue the QUIT command to close the window and to return to the "Modify Profile" screen.

Menu and Overlay Calendar

You can specify the sequence in which information is displayed on the Con-nect menu, and the character which is used as the vertical border for windows. You can also specify one or two cabinet IDs for your overlay calendar.

To modify the menu display or the overlay calendar, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:49 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS          Modify Profile          Monday

Date and Time Formats  _      !      Menu and Overlay Calendar      !
+-----+
Print Defaults         _      ! Main Menu Name                      !
!      _____!
Language/Command/Autosave  _      !      Display Month  1      !
!      Mail  2      !
Folders and Password     _      !      Calendar  3      !
!      !
Mail Status Message      _      !      Display Day Name  x      !
!      !
Menu and Overlay Calendar  x      ! Overlay Calendar ID 1  _____!
!      ID 2  _____!
Screen Colors           _      !      Window Border  !      !
!      !
Con-nect Version        _      +-----+

Make all required changes and press ENTER to modify
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

Modify the specifications by typing over them.

Main Menu Name

By default, this line is blank and the menu which your administrator has been defined in cabinet SYSCNT is used as your main menu (if your administrator has not defined another menu, the Con-nect menu is the main menu).

If you want to have a menu which you have created (see *Creating Your Own Menus*) displayed as the main menu, or another system menu that has been defined in cabinet SYSCNT (marked with (S) in the "Display Menus" screen), you enter its name in this line.

When you enter a menu name in this line, Con-nect first looks for this menu in the cabinet that you are currently using. If no menu is found in the current cabinet, Con-nect checks cabinet SYSCNT. If no menu with that name is found at all, the Con-nect menu is used.

If you have previously used another menu as the main menu, and now want to use the default menu defined in cabinet SYSCNT again, you leave this line blank.

To activate the new menu, you must first quit Con-nect and then access it again.

Display

The sequence in which information (month, mail, calendar) is shown on the main menu. The values mean:

0	The information is not displayed.
1	The information is displayed first.
2	The information is displayed next.
3	The information is displayed last.

Display Day Name

If this field is marked, the current day name is displayed in the upper right corner of your screens (directly below the date); if the field is left blank, the Con-nect screen number is shown there.

Overlay Calendar ID

Optional - in your private cabinet, you can specify one or two IDs of other private cabinets (which you are allowed to access) for your overlay calendar.

If these users have given you permission to display/modify their calendars with the *SHARE* command, all entries from their calendars are shown on your calendar screens. See *Overlay Calendar* for further information.

In your private cabinet, you can also specify the IDs of public and shared cabinets. In a shared cabinet, only the IDs of other shared or public cabinets can be specified. In a public cabinet, only the IDs of other public cabinets can be specified.

Window Border

The character which is used as the vertical border of all Con-nect windows.

If your terminal supports reverse video, the window border is always shown in reverse video.

Note:

If your terminal does not show the window border in reverse video, it might be necessary to enter the appropriate Natural terminal command. For example, if you are using an IBM terminal type, you enter %T=3278 (or %T=3279 for a color terminal). See the Natural documentation for further information.

Press ENTER to save your modifications.

Screen Colors

You can specify the colors to be used for various types of text if you use a color terminal.

To modify the screen colors, mark the corresponding field in the "Modify Profile" screen and press ENTER.

```

4:51 PM          * * * C o n - n e c t 3 * * *          3.Nov.2003
Cabinet LS          Modify Profile          Monday

Date and Time Formats  _      !          Screen Colors          !
Print Defaults         _      !  Enter Color Number          !
                        !          Default   Intense          !
Language/Command/Autosave  _  !   Text                6       3       !
                        !  Modifiable Field  3       5       !
Folders and Password     _  !   Output                2       7       !
                        !  Window Border     3                !
Mail Status Message     _  !          Color Numbers          !
Menu and Overlay Calendar  _  !   1 Blue                5 Red       !
                        !   2 Green                6 Turquoise !
Screen Colors           x  !   3 Neutral                7 Yellow    !
                        !   4 Pink                !
Con-nect Version       _  +-----+

Make changes and press ENTER to display the new colors
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help  Menu  Quit  In   Send  Foldr  Docs  Note  Cal   Flip  Last  Home

```

The lower part of the window displays the available colors and their numbers.

Enter the number of the colors you want to use in the "Default" and "Intense" columns. When you have completed your entries, press ENTER. The new color assignments are then shown.

Press ENTER again to save these assignments and to close the window.

Note:

If your color terminal does not show the specified colors, it might be necessary to enter the appropriate Natural terminal command. For example, if you are using an IBM terminal type, you enter %T=3279. See the Natural documentation for further information.

Con-nect Version

You can display the version number of the Con-nect version that is installed at your site.

```

2:25 PM          * * * C o n - n e c t 3 * * *          12.Dec.2003
Cabinet LS          Modify Profile          Friday

Date and Time Formats  _      !          Con-nect Version          !
Print Defaults         _      !          Version 3.4.1          !
Language/Command/Autosave  _      !          Installation date 10.Oct.2003          !
Folders and Password   _      !          Installation time 10:50 AM          !
Mail Status Message    _      !          Update level 3          !
Menu and Overlay Calendar  _      !          Update date 30.Oct.2003          !
Screen Colors         _      !          Update time 2:55 PM          !
Con-nect Version      x      !          User ID ESH          !

Press ENTER to display installation history - or QUIT
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Help Menu Quit In Send Foldr Docs Note Cal Flip Last Home

```

The following information is provided:

Version

The version number of the currently installed Con-nect version.

Installation Date/Time

The date and time at which the current version has been installed at your site.

Update Level

The update level indicates the updates that have been installed.

Update Date/Time

The date and time at which the current update has been installed at your site.

User ID

The user ID of the person who has installed Con-nect at your site, or when updates have been installed, the user ID of the person who has installed the currently displayed update.

To display the installation history, press ENTER repeatedly to page through all history windows. To close the window, issue the QUIT command.

```

2:31 PM          * * * C o n - n e c t 3 * * *          12.Dec.2003
Cabinet LS      Modify Profile                          Friday

Date and Time Formats  _      +-----+
!      Con-nect Installation History      !
+-----+
Print Defaults         _      !
!      Version 3.4.1                      !
Language/Command/Autosave  _  !
!      Installation date 10.Oct.2003      !
Folders and Password   _      !
!      Installation time 10:50 AM         !
Mail Status Message   _      !
!      Update level 2                    !
!      Update date 22.Oct.2003          !
Menu and Overlay Calendar _  !
!      Update time 2:53 PM              !
Screen Colors         _      !
!      User ID TPI                      !
Con-nect Version      x      +-----+

Press ENTER to continue - or QUIT
Command /
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help  Menu  Quit  In   Send  Foldr Docs  Note  Cal   Flip  Last  Home
    
```