

Modify Profiles

This chapter covers the following topics:

- Description
- Procedure
- Batch Examples

Description

Program

B06250

Function

Using a pattern cabinet, modify the selected section of the cabinet or user profile for the specified target cabinet(s).

Online Input Screen

```

11:59          * * * C o n - n e c t  3.4.1  * * *          9.Dec.03
Cabinet LS          Modify Profiles          B06250

Only items filled in pattern cabinet are modified.
Mark Details to modify specific items in the user profile.

Select pattern cabinet _____

Select all cabinet profiles to be modified
from cabinet _____ to cabinet _____

or all cabinets contained in (SYSCNT) distribution
list _____

Select items to be modified
  _ Command/object table
  _ Cabinet profile
  _ Security levels
  _ User profile          _ Details
  _ Disallow/reset (Default: Allow/set)
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Menu Quit
Complete the information above and press ENTER to continue

```

Utility Parameters

Parameter	Format	Description
Pattern cabinet	A8	
from cabinet	A8	Either cabinet or distribution list is required
to cabinet	A8	Optional
Distribution list	A12	Either distribution list or cabinet is required
Command/object table	A1	Optional
Cabinet profile	A1	Optional
Security levels	A1	Optional
User profile	A1	Optional
Details	A1	Optional
Disallow/reset	A1	Default: allow/set

Procedure

If cabinets who are members of a distribution list are to be modified, the list must be defined in cabinet SYSCNT. Only members of the distribution list are modified.

When the "Disallow/Reset" field is marked, the filled items in the pattern cabinet are disallowed in the target cabinet(s). In the case of numeric fields (e.g. security levels), they are set to zero.

When the "User profile" field is marked without the "Details" field, all filled items in the user profile of the pattern cabinet are copied. However, the following are never copied: the administrator status, overlay calendar ID and mail status message flag.

To copy items that are not filled in the pattern cabinet, select "User profile" and the "Details" field to display the "Mark to Copy from Pattern" screen.

```

12:02          * * * C o n - n e c t  3.4.1  * * *          9.Dec.03
Cabinet LS          Mark to Copy from Pattern          B06250

_ Date format (1)          _ Time format (2)          _ Delimiter (3)
_ Timezone (4)            _ Week start (5)          _ Day start (6)
_ Sliding window (7)

_ Printer name (11)        _ Page length (12)        _ Line width (13)
_ Mark to print (14)      _ Printer profile (15)    _ Formatting profile (16)
_ Wrap print line (17)    _ Left margin (18)

_ Language code (21)      _ Command sequence (22)  _ Blank substitute (23)
_ Autosave (24)          _ Default folder (31)    _ Default file (32)
_ Folder layout (33)      _ Reply column (34)

_ Main menu name (51)     _ Display month (52)      _ Display mail (53)
_ Display calendar (54)   _ Display day name (55)   _ Window border (56)

_ Screen colors (61)

Mark with X to allow, blank to disallow and press ENTER. Then QUIT to return.
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
          Quit  Mark  Reset

```

From this screen, mark each user profile field to be copied. If a field is not marked it is not copied. See *Con-nect Administration*, section *Cabinet Maintenance* for information on the user profile and security levels.

Each user profile field has been assigned a unique number (displayed to the right of the field in brackets) which is to be used when running this utility in batch. The numbers are as follows:

User Profile Field	Batch Number
Date format	1
Time format	2
Delimiter	3
Timezone	4
Week start	5
Day start	6
Printer name	11
Page length	12
Line width	13
Mark to print	14
Printer profile	15
Formatting profile	16
Wrap print line	17
Left margin	18
Language code	21
Command sequence	22
Blank substitute	23
Autosave	24
Default folder	31
Default file	32
Customize folder contents	33
Display reply column	34
Main menu name	51
Display month	52
Display mail	53
Display calendar	54
Display day name	55
Window border	56
Screen colors	61

For example, the object/command table for cabinets B and C must be modified. Cabinet A is created with only "ADD" and "Address" marked in its object/command table. Using this utility, cabinet A is specified as the pattern cabinet. Cabinet B and C which cannot add addresses are specified as the target cabinets. The "Object/command table" field is marked and the "Disallow/reset" field is blank. When the utility is run, the object/command table for cabinets B and C will be modified so that they are allowed to add

addresses.

Cabinet A is again specified as the pattern cabinet. Cabinet B which can add addresses is specified as the target cabinet. The "Object/command tble" and "Disallow/reset" fields are marked. When the utility is run cabinet B cannot add addresses.

Batch Examples

Disallow cabinet B to add addresses. Cabinet A serves as the pattern cabinet. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B06250 CabA,CabB,,,X,,,,,X
FIN
```

Modify the user profile fields: Date format, Page length, Window border of cabinet B. Cabinet A serves as the pattern cabinet to be copied. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B06250 CabA,CabB,,,,,X,X
1,12,56
FIN
```