

Z-ADD17A

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
-

Description

Add a member to a shared cabinet. The member can be a private cabinet or another shared cabinet.

This subprogram can be used only by a supervisor or cabinet administrator.

If Profile-type 3 (special profile) is specified, the ID of the cabinet which contains the special profile must be entered in the Special-profile parameter. The special profile is then copied and used for this member whenever it accesses the shared cabinet. The Special-profile parameter is ignored for types 1 and 2.

When you add a member to a shared cabinet, the following rules apply:

- the member must not contain a shared cabinet;
- the cabinet specified in the parameter Shared-cabinet must not be a member of another shared cabinet;
- the member must be the ID of a user or cabinet;
- a shared cabinet cannot be a member of itself.

Successful termination of Z-ADD17A always results in an END TRANSACTION. You are not able to control transaction handling.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2		X	
Cabinet	A8	R		The cabinet ID of a supervisor or cabinet administrator.
Password	A8	R		The password of the above cabinet.
Shared-cabinet	A8	R		The name of the shared cabinet to which you want to add a member.
Member	A8	R		The ID of a private or shared cabinet to be added as a member.
Profile-type	A1	O		1=shared profile, 2=private profile or 3=special profile. If left blank, or if an invalid value is specified, the default (1) is used.
Special-profile	A8	R		Only required for Profile-type 3. The ID of the cabinet which contains the profile. This can be a private, shared, public or standalone cabinet.
Member-ISBN	P8		X	The ISBN of the new member.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
15	Invalid administrator status
32	Member (address) could not be found
90	Member not added - contains a shared cabinet
91	Member not added - cabinet is a member of another shared cabinet
92	Member not added - error in parameter list
93	Member not added - cabinet members must be users or cabinets
95	Member not added - it is already a member of this list
97	A shared cabinet cannot be a member of itself
98	Shared cabinet does not exist
99	Special profile does not exist

Subprograms

Z-120

Z-122

Z-123

Z-175

Z-198

Z-1200&0