

Z-ERA17

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
 - Example
-

Description

Erase a member from a distribution list.

You cannot erase a member from a distribution list that has been created for a shared cabinet.

You can specify the following in the parameter Member-name: a Connect user, a bulletin board, a cabinet, another distribution list or an external node (for example, a Telex or SNADS node). You can also specify a nickname for any type of member previously listed.

When you delete a user, you can either specify the user's last and first name or user ID in the parameter Member.

When you specify a bulletin board, a nickname or the user's last and first name in parameter Member, you must also specify the parameter Member-type.

If only one member with the specified name is contained in the distribution list, the parameter Member-type is not necessary.

If the member name is not unique and a member type has not been specified, return code 91 is issued. To prevent return code 91, you should specify parameter Member-type.

If you specify an asterisk (*) in the parameter Member-name, all members of the distribution list are deleted.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the distribution list is stored.
Password	A8	R		The password of the above cabinet.
Distribution-name	A12	R		The name of the distribution list which contains the member to be erased.
Member-name	A20	R*		The name of the member to be erased. Or an asterisk (*) to erase all members of the distribution list. Either Member-name or Member-ISBN, not both.
Member-type	N2	O		Must be one of the following: 1=address (nickname), 4=bulletin board, 5=cabinet, 10=distribution list, 33=user ID (private cabinet), 70=last name, 74=external address.
Member-ISBN	P10	R*		The ISBN of the member to be deleted. Either Member-ISBN or Member-name, not both.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISBN was not found
08	Supply either ISBN or name, not both
09	ISBN does not point to the correct object
30	Distribution list name invalid
32	Member could not be found
51	Invalid member name
53	Requested object does not exist
90	Distribution list belongs to a shared cabinet
91	Member name is not unique
92	Invalid member type
93	No member was erased from the distribution list

Subprograms

Z-0417
Z-120
Z-122
Z-123
Z-147
Z-150
Z-710
Z-713
Z-1200&0

Example

```
0010 DEFINE DATA LOCAL
0020 1 RETURN-CODE          (N2)
0030 1 CABINET             (A8)
0040 1 PASSWORD            (A8)
0050 1 DISTRIBUTION-NAME   (A12)
0060 1 MEMBER-NAME        (A20)
0070 1 MEMBER-TYPE        (N2)
0080 1 MEMBER-ISN         (P10)
0090 END-DEFINE
0100 *
0110 MOVE 'USER ID'      TO CABINET
0120 MOVE 'PW'           TO PASSWORD
0130 MOVE 'DISTR 1'     TO DISTRIBUTION-NAME
0140 MOVE 'USER2 ID'    TO MEMBER-NAME
0150 MOVE 33             TO MEMBER-TYPE
0160 *
0170 CALLNAT 'Z-ERA17' RETURN-CODE
0180                CABINET
0190                PASSWORD
0200                DISTRIBUTION-NAME
0210                MEMBER-NAME
0220                MEMBER-TYPE
0230                MEMBER-ISN
0240 *
0250 IF RETURN-CODE EQ 0
0260     WRITE 'Member' MEMBER-NAME 'from distribution list'
0270         DISTRIBUTION-NAME 'was erased'
0280 ELSE
0290     WRITE 'Return code' RETURN-CODE
0300 END-IF
0310 *
0320 END
```