

# Z-ERAOBJ

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
- 

## Description

Erase a user-defined object.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the user-defined object is to be erased.
Password	A8	R		The password of the above cabinet.
Object-name	A32	R*		The name of the user-defined object. Either Object-name or ISN, not both.
ISN	P8	R*		The ISN of the user-defined object. Either ISN or Object-name, not both.
Object-number	N2	R		The number of the user-defined object.
Deletion-flag	A1	O		If blank, the object is moved to the Wastebasket. If marked, the object is erased from the system.

## Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISN was not found
08	Supply either ISN or name, not both
09	ISN does not point to correct object
68	Object is not a user-defined object
91	Invalid name
93	Requested user-defined object does not exist

## Subprograms

Z-100  
Z-110  
Z-120  
Z-122  
Z-123  
Z-165  
Z-175  
Z-180  
Z-190  
Z-194  
Z-197  
Z-222  
Z-223  
Z-400  
Z-401  
Z-1200&0