

# Z-GET33

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
- 

## Description

Return the date and time formats of a user and the language in which the user works.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2		X	
Cabinet	A8	R		The name of the user's cabinet.
Password	A8			Not validated.
Last-name	A32		X	The last name of the user to whom the cabinet was assigned.
First-name	A32		X	The first name of the user.
Language	N1		X	Only codes for languages which have been installed on your system are valid. The language codes are: 1=English, 2=German, 3=French, 4=Spanish, 5=Italian, 6=Dutch, 7=Turkish, Icelandic, Finnish or Swedish, 8=Danish or Hebrew, 9=Norwegian, Portuguese (Brazilian), Arabic or Russian.
Date-format	A5		X	Indicates how the date is displayed in all screens, and the order in which the day, month and year appear. A delimiter separates the day, month, and year values. The values mean: 1=the day is shown as a number, 2=the month is shown as a number, 3=the year is shown as a two-digit number, 4=the month is shown as a three-letter abbreviation, 5=the year is shown as a four-digit number.
Time-format	N1		X	Indicates how the time is displayed in all screens. 0=24h, 1=am/pm
Time-format-delimiter	A1		X	The character which separates the hour and minute values.
Timezone	N2		X	The number of hours ahead or behind your data center time zone.

## Return Codes

00	Success
02	Invalid cabinet name

## Subprograms

None