

Z-INOBU

This chapter covers the following topics:

- Description
- Parameters
- Return Codes
- Subprograms

Description

Update information for a specific user-defined object.

Parameters which are not completed in the parameter list are updated to blanks. Thus, to retain the existing values, you must specify them once more before you invoke this subprogram.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the user-defined object is stored.
Password	A8	R		The password of the above cabinet.
Object-number	N2	R		The number of the user-defined object
Object-name	A32	R*		The name of the user-defined object. Either Object-name or ISN, not both.
ISN	P8	R*	X	The ISN of the user-defined object. Input: either ISN or Object-name, not both.
Description	A60/1:4	O		A brief description for the user-defined object.
User-data	A60/1:4	O		Can be any information included by the user.
Object-format	A1	O		Can be any user-defined object format. If the object is a document, this can also be a Con-nect document format. See <i>Document Formats</i> .
Private-flag	A1	O		If marked, the user-defined object is a private object.
Security-flags	A1/1:4	O		The security levels for Read, Modify, Copy and Print. Values 0 to 9. The four values must be numeric.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISN was not found
08	Supply either ISN or name, not both
09	ISN does not point to correct object
13	Invalid object number
51	Invalid name
53	Requested object does not exist (has not been defined by administrator)
61	Invalid security flag

Subprograms

Z-120

Z-122

Z-123

Z-1200&0