

Z-MOD01A

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
-

Description

Modify a nickname for an address at an external node. This subprogram applies only to an external node which uses the spool file.

This subprogram does not apply to a transport service node. To modify a nickname for a transport service node, you must use Z-MOD01T.

If you know the Node-name, but do not know the physical address of the external node (Node-parameters) which has been defined by the administrator, you can invoke Z-GET74 prior to Z-MOD01A to obtain the physical address information.

This subprogram does not check whether the information you specify in the Node-parameters corresponds to the information which has been defined by the administrator. Thus, you can specify different address information in the Node-parameters. However, it is your responsibility to specify the correct information.

Parameters which are not completed in the parameter list are deleted from the nickname information. Thus, to retain the existing values, you must specify them once more before you invoke this subprogram. There is one exception: when you do not specify Folder-name and File-name, the nickname is automatically stored in folder Work.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET
Cabinet	A8	R		The cabinet in which the nickname is to be modified.
Password	A8	R		The password of the above cabinet.
Nickname	A20	R*	X	The nickname to be modified. Input: either Nickname or ISN; not both.
ISN	P8	R*	X	The ISN of the nickname to be modified. Input: either ISN or Nickname; not both. You can invoke Z-GET01 prior to Z-MOD01A to obtain the ISN for the desired nickname.
Description	A60/1:4	O		A brief description for the nickname.
Folder-name	A15	O		The folder in which the nickname is to be stored. You must not specify a TRS folder or system folder (except Work). Default: Work.
File-name	A15	O		The file within the above folder in which the nickname is to be stored.
Node-name	A8	R		The name of an existing node which has been added by the administrator.
Node-parameters	A250	R		The physical address of the external node. See <i>External Communication</i> .
Parameter-length	N3	O		The length of the Node-parameters. If you do not know the length, you should not specify a value.
Post-flag	A1	O		Marking this flag is only useful if you send mail using the online Con-nect. If marked, a window appears and you can enter additional information before the mail is sent. Therefore, do not mark this flag if you use Z-MAILA to send mail, since the window does not appear in this case.
Private-flag	A1	O		If marked, the nickname is a private object.
Security-flags	A4	O		The security levels for Read, Modify, Copy and Print. Values 0 to 9.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISN not found
08	Supply either ISN or name, not both
09	ISN does not point to correct object
15	Invalid administrator status
55	Requested folder/file does not exist
56	Requested folder is a TRS folder
73	Invalid folder/file name
91	Invalid name
93	External node or address does not exist
94	Node-name is not a spool file node name

Subprograms

Z-120

Z-122

Z-123

Z-147

Z-150

Z-1200&0