

Z-MOD05M

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
 - Example
-

Description

Modify the language code, system folder names, default command sequence, blank substitute character and autosave interval in the user profile of a specific cabinet.

This subprogram is similar to Z-MOD05E with the exception that you can also rename the cabinet's system folders (including all of their files). The parameter Cabinet-ISBN uses the format P10.

This subprogram can be used only by a supervisor or cabinet administrator. It is not possible to use this subprogram to modify the user profile of the cabinet SYSCNT or to rename the system folders in cabinet SYSCNT.

To get the ISBN for the wanted cabinet, you can invoke either Z-ADD05 or Z-DIS05 prior to this subprogram.

Parameters which are not completed in the parameter list (except Language-code) are deleted from the user profile. Thus, to retain the existing values, you must specify them once more before you invoke this subprogram. If you do not specify a new value for the language code, the old value is retained.

Successful termination of Z-MOD05M always results in an END TRANSACTION. You are not able to control transaction handling.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2		X	
Cabinet	A8	R		The cabinet ID of a supervisor or cabinet administrator.
Password	A8	R		The password of the above cabinet.
Cabinet-name	A8	R*		The name of the cabinet to be modified. Either Cabinet-name or Cabinet-ISBN, not both.
Cabinet-ISBN	P10	R*		The ISBN of the cabinet to be modified. Either Cabinet-ISBN or Cabinet-name, not both.
Language-code	N1	O		Only codes for languages which have been installed on the system are valid. 1=English; 2=German; 3=French; 4=Spanish; 5=Italian; 6=Dutch; 7=Turkish, Icelandic, Finnish, Swedish; 8=Danish, Hebrew; 9=Norwegian, Portuguese (Brazilian), Arabic, Russian. If blank, the previously language code is retained.
Library-name	A8	R		Library in which Con-nect is installed.
Command-sequence	A1	O		If blank, the sequence "command object name" is used. If marked, the alternative sequence "object name command" is used.
Rename-system-folders	A1	O		If marked, the names of all system folders (e.g. Inbasket and Outbasket) are translated into the language that has been defined for this cabinet. If not marked, the names of the system folders are not changed.
Blank-substitute	A1	O		The character which must be entered in place of a blank when specifying a name or date. The characters "*", ".", and "X" are not allowed.
Autosave	N2	O		The frequency with which the "(Undo <i>Document-name</i>)" version of a document or the menulines in the menu editor is updated. You can specify a number between 1 and 99. If a value has not been specified, or if an invalid value has been specified, this is set to 10 (default); a return code is not issued.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
08	Supply either ISN or name, not both
15	Invalid administrator status
91	Supply Cabinet-name or Cabinet-ISBN
93	Language not available
94	Do not use "*", ".", or "X" for the Blank-substitute parameter
95	Enter library name where Con-nect is installed
96	Cabinet-name is not valid
97	Cabinet-ISBN is not valid
99	Cabinet SYSCNT cannot be modified

Subprograms

Z-120
 Z-122
 Z-123
 Z-163
 Z-168
 Z-175
 Z-1200&0

Example

```

*
* Example program to modify the language code of a cabinet
* and to rename the system folders/files of this cabinet
*
DEFINE DATA
LOCAL
1 RETURN-CODE          (N2)
1 CABINET              (A8)
1 PASSWORD             (A8)
1 CABINET-NAME        (A8)
1 CABINET-ISN         (P10)
1 LANGUAGE-CODE       (N1)
1 LIBRARY-NAME        (A8)
1 COMMAND-SEQUENCE    (A1)
1 RENAME-SYSTEM-FOLDERS (A1)
1 BLANK-SUBSTITUTE    (A1)
1 AUTOSAVE            (N2)
END-DEFINE
*
RESET RETURN-CODE
MOVE 'CABINET'        TO CABINET
MOVE 'PASSWORD'      TO PASSWORD
MOVE 'CAB-NAME'      TO CABINET-NAME
MOVE 1                TO LANGUAGE-CODE
MOVE 'LIBRARY'       TO LIBRARY-NAME
MOVE ' '             TO COMMAND-SEQUENCE
MOVE 'X'             TO RENAME-SYSTEM-FOLDERS
MOVE '/'             TO BLANK-SUBSTITUTE
MOVE 5                TO AUTOSAVE
*
CALLNAT 'Z-MOD05M'
    RETURN-CODE
    CABINET
    PASSWORD
    CABINET-NAME
    CABINET-ISN
    LANGUAGE-CODE
    LIBRARY-NAME
    COMMAND-SEQUENCE
    RENAME-SYSTEM-FOLDERS
    BLANK-SUBSTITUTE
    AUTOSAVE
*
IF RETURN-CODE EQ 0
    WRITE 'Cabinet' CABINET-NAME 'was modified'
ELSE
    WRITE 'Return code' RETURN-CODE
END-IF
*
END

```