

Print Document List

This chapter covers the following topics:

- Description
- Procedure
- Batch Example

Description

Program

B07110

Function

Print document list by cabinet, name, folder and date.

Online Input Screen

```

4:32 PM          * * * C O N - N E C T 3 * * *          14.Feb.94
Cabinet LS      Print Document List                    B07110

From Cabinet   _____   to Cabinet   _____
Document      _____
Folder        _____   to Folder    _____
Date          1.Jan.86      to Date     14.Feb.94

Mark  _ to show disk space occupied
      by text lines of document
      (in bytes).

      _ to show cabinet totals ONLY

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Menu Quit
Complete the information above and press ENTER to continue

```

Utility Parameters

Parameter	Format	Description
From Cabinet	A8	
To Cabinet	A8	Optional
From Document	A32	Optional
To Document	A32	Optional
From Folder	A15	Optional
To Folder	A15	Optional
From Date	A11	Default: 1.Jan.86
To Date	A11	Default: current date
Size	A1	Optional
Total Lines Only	A1	Optional

Procedure

Only cabinet administrators can print a list of documents from cabinets other than their own. Users can only print a list of documents from their own cabinet. The exceptions are documents contained in cabinet SYSCNT, which can be viewed by anyone.

When listing documents in cabinets which are not your own, the documents that are marked as private are handled as follows:

- the document list is printed, but the output fields except for cabinet, size and bytes are filled with asterisks. If you have not marked the Size parameter, the field bytes is left blank.

A total-line is produced for every cabinet, showing the total number of documents printed (found) and the total number of bytes (if applicable). A grand total is printed if more than one cabinet is read, and a page break occurs at the start of a different cabinet.

If parameter Total-lines-only is specified, only total lines are printed.

The size refers to the size of the text only. It can be the text of the document, attached notes, enclosed documents, or cover notes.

All documents within a bulletin board can be printed by entering SYSCNTB as the cabinet name and a bulletin board name in the parameter folder-name.

Batch Example

The number of documents in every Con-nect cabinet are to be printed. This would be coded as follows:

```
LOGON SYSCNT2B
MENU B07110 * , * , , , , , , X
FIN
```