

# ACTIVITY

The ACTIVITY direct command allows you to start the permanent activity display of Entire Operations directly.

The command format is:

**ACTIVITY**

When you invoke this command, the following window opens:

```

20.11.01          *** Entire Operations 4.1.1 ***          14:44:55
Owner EXAMPLE          Main Menu          User ID GHH
-----
Main Menu          DC Solutions

1 Networ +-----+ (V132)
2 Active !          ! t (V134)
3 Calend !          ENTIRE OPERATIONS Activity Display !
4 Log In !          !
5 Symbol ! Query Interval (in minutes) ==> 60___ !
6 System !          !
7 Report ! The query interval is the time span until the !
8 Import ! next interruption query by the activity display. !
9 Help ! In between, it can only be interrupted from !
! another terminal running ENTIRE OPERATIONS. !
! !
! PF3 End !
! !
! !
Command => +-----+
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
Help          End          Owner Mail

```

Enter the Query Interval in minutes and press Enter.

The following screen appears:

```

20.11.01          *** Entire Operations 3.2.1 ***          14:47:11
Date 20.11.01          Activity Display          Monitor active 14:46:59
from 14:00:08          Display Interval 20   sec.   Next Interrupt 14:51:29
-----
Network   Job           Run JobId Time  Message
E40-REC-01 E40-J03       1036      14:00 Latest Start 19.11 14:00 exceeded
E40-REC-01 E40-J99999 1036      14:00 Latest Start 19.11 14:00 exceeded
UIX-TEST                2         14:42 File Deletion - Node 501 not active
UIX-TEST                2         14:42 ...

***** Bottom of Data *****

```

The Query Interval is equivalent to the Monitor and cannot be changed.

When the Query Interval has expired, you can restart the Activity Display by entering **Y** in the following window and pressing Enter:

```

20.11.01          *** Entire Operations 3.2.1 ***          14:52:48
Date 20.11.01          Activity Display          Monitor active 14:52:33
from 14:00:08          Display Interval 20   sec.   Next Interrupt 14:53:05
-----
Network   Job           Run JobId Time  Message
E40-REC-01 E40-J03       1036      14:00 Latest Start 18.11 14:00 exceeded
E40-REC-01 E40-J99999 1036      14:00 Latest Start 18.11 14:00 exceeded
UIX-TEST                2         14:42 File Deletion - Node 501 not active
UIX-TEST                2         14:42 ...

          +-----+
          !                                     !
          ! Activity Display was interrupted !
          !                                     !
          !               Restart ==> Y (Y,N) !
          !                                     !
          +-----+

***** Bottom of Data *****

```

Activity monitoring is described in the section System Administrator Services of the Entire Operations Administration Documentation.