

System Messages ESY5900 - ESY5999

Message	Explanation	Action
ESY5900 - Cannot allocate SYSOUT dataset.	Dynamic allocation of SYSOUT dataset failed.	Contact systems programmer.
ESY5901 - Cannot allocate internal reader.	Dynamic allocation of internal reader failed.	Contact systems programmer.
ESY5902 - Dynamic allocation failed.		Contact systems programmer.
ESY5903 - Dynamic allocation failed for temporary dataset.	Dynamic allocation for a temporary dataset failed.	Contact systems programmer.
ESY5904 - Edit not allowed (SCLM protection).	The selected PDS member has been protected by SCLM. Only browsing if this member is allowed, all update actions are denied.	Use SCLM dialog to free member.
ESY5906 - DESERV :1: error, R15=:2:, R0=:3:	An error occurred during execution of a DESERV macro.	Check the R15 and R0 values and if necessary contact Software AG technical support.
ESY5907 - DSPSERV :1: error, R15=:2:, R0=:3:	An error occurred during execution of a DSPSERV macro.	Check the R15 and R0 values and if necessary contact Software AG technical support.
ESY5908 - ALESERV :1: error, R15=:2:, R0=:3:	An error occurred during execution of an ALESERV macro.	Check the R15 and R0 values and if necessary contact Software AG technical support.
ESY5909 - Syntax error in JCL command.	An error was detected when processing START-TIME on a SUBMIT request.	Fix error and resubmit.
ESY5921 - Entire System Server node table not linked.	Entire System Server node table not linked.	Contact systems programmer.
ESY5922 - Entire System Server node :1: not active.		Contact operator or contact systems programmer.
ESY5981 - Invalid value specified (BLKCTRL/BLKSIZE/LRECL).	Invalid value for BLOCK CONTROL, BLOCK SIZE or RECORD LENGTH specified.	Please correct error.
ESY5982 - Error during use of ISAM-key.	Possible reasons: - duplicate key detected for DUPEKY=NO; - key must be generated, but KEYLEN is greater than 8 bytes or no default KEYPOS; - key length of file is greater than 253 bytes; - key not found in ISAM-file; - no key supplied for UPDATE-INPLACE=YES; - invalid key sequence detected	Please check parameters or file attributes.

Message	Explanation	Action
ESY5983 - :1: not supported by :2:.	Various functions are not supported in special modes. E.g. view EVENTING is only available in MULTI USER MODE for BS2000/OSD. Error text "SINGLE USER MODE not supported by EVENTING" occurs.	No action possible.
ESY5984 - Server is not authorized to access.	ESY Server Task is not authorized to access various objects with protection attributes, which not allows access for \$TSOS.	No action possible.
ESY5985 - Access to tape file not allowed.	Access to tape file was requested, but parameter TAPES=NO is specified in ESY startup file.	Please contact your ESY Administrator.
ESY5986 - No or not enough space for :1:.	Various startup parameter sizes are exceeded. See variable text for details.	Please contact your ESY Administrator.
ESY5987 - Job Variable already exists.	An existing job variable cannot be allocated again.	Please check your input values.
ESY5988 - Invalid task type detected.	Task type must have a value between 1 and 7.	Correct program.
ESY5989 - Invalid ELEMENT specification.	Element name must be unique.	Correct element name.
ESY5990 - Field RECORD not found in format buffer.	An attempt was made to read a record without specifying the RECORD field.	Supply field RECORD in program.
ESY5991 - Unknown product.	An invalid PRODUCT value was specified.	Specify valid product code.
ESY5992 - Requested job variable not found.	The requested job variable is not cataloged.	No action required.
ESY5993 - Cannot open file.	An open request failed.	No action required.
ESY5994 - File not on volume.	The requested dataset is not on the specified volume.	No action is required.
ESY5995 - File not in catalog.	The dataset is not cataloged.	Specify VOLSER, or catalog dataset.
ESY5996 - Volume not online.	The specified volume is currently not available.	Contact operator or contact systems programmer.
ESY5997 - Dataset is not PDS or sequential.		No action is required.
ESY5998 - MEMBER not found.	The requested member was not found.	No action is required.
ESY5999 - Entire System Server node :1: not active.		Contact operator or contact systems programmer.