

## Console Messages XCO0050E - XCO0055E

| Message  | Explanation   | Action                      |
|--|---|-----------------------------|
| <b>XCO0050E</b><br>MPM20-error.                | The Terminate-Target call was unsuccessful. Shutdown will continue.   | Please contact Software AG. |
| <b>XCO0051W</b><br>MPM08-error, user gone.     | The Get-User-Buffer call was unsuccessful. The user is probably not active any longer. Entire System Server purged this request from the queue.                   | No action required.         |
| <b>XCO0052W</b><br>MPM12-error, user gone.     | The Post-User call was unsuccessful. The user is probably not active anymore. Entire System Server has purged this reply from the queue.                          | No action required.         |
| <b>XCO0053W</b><br>MPM36-OK, user gone.        | The timeout call (TIME elapsed) for a user was successful. The user is probably not active anymore. Entire System Server has purged this reply from the queue.    | No action required.         |
| <b>XCO0054W</b><br>MPM36-error, user not gone. | The timeout call (TIME elapsed) for a user was unsuccessful. Entire System Server has tried to purge the user, but the user fetched data back at the last moment. | No action required.         |
| <b>XCO0055I</b> Node currently :1:.            | Output of command XSTAT. Possible value for :1: are ACTIVE (normal state) or HALTED (node is halted due to operator command XHALT).                               | No action required.         |