

Console Messages ESY0012I - ESY0019I

Message	Explanation	Action
ESY0012I - VTAM OPERATOR ACB IS NOW OPEN	The VTAM ACB defined in the VTAMACB sysparm was opened successfully.	No action required.
ESY0013I :1:.	Display Entire System Server user(s) as reponse to operator command USERS.	No action required.
ESY0014I - NO VSAM FILES ARE OPEN	No VSAM files are open or DDNAME specified to free does not exist.	No action required.
ESY0015I - :1:	Variable text for display of VSAM files.	No action required.
ESY0016I - VSAM FILE :1: WILL BE FREED	This is a response to the operator command VSAMFREE :1:. The VSAM file with DDNAME :1: will be de-allocated.	No action required.
ESY0017I Requested user(s) not found.	The operator requested to display/cancel a user who is not active.	No action required.
ESY0018I - :1: CANCELLED	User :1: was cancelled due to operator request.	No action required.
ESY0019I - :1:	Variable text for display of active tape drives.	No action required.