

Console Messages ESY0020I - ESY0040I

Message	Explanation	Action
ESY0020I - NO TAPES ALLOCATED	This is a response to operator command TAPES/TAPEFREE xxx. No tape drives are allocated to Entire System Server users.	No action required.
ESY0021I - TAPE UNIT :1: HAS BEEN FREED	This is a response to operator command TAPEFREE xxx. The tape drive at address xxx has been de-allocated.	No action required.
ESY0022I - TAPE UNIT :1: N O T FREED	This is a response to operator command TAPEFREE xxx. The attempt to de-allocate the tape drive at address xxx failed.	No action required.
ESY0023W - MODULE NOT LOADED.	The specified module could not be LOADED.	No action required.
ESY0024I - MODULE RELOADED	The specified module was successfully reloaded.	No action required.
ESY0026I - VTAM PRINTER ACB IS NOW OPEN	The VTAM ACB defined in the SPOOLACB sysparm was opened successfully.	No action required.
ESY0040I - :1:	This message is issued by the EVENTS operator command. It has various formats that will be interpreted by Software AG technical support.	No action required.