

# Console Messages ESY0050W - ESY0059W

---

Message	Explanation	Action
<b>ESY0050W</b> - ENTIRE SYSTEM SERVER IS NOT APF-AUTHORIZED	The load libraries are not defined as APF-authorized. Certain functions will not be available.	No action required.
<b>ESY0054W</b> - NATURAL SUB-TASK MODULE :1: NOT AVAILABLE	The Natural module :1: was not found and could not be loaded. It was specified in the startup parameter 'NATMOD=' . Natural subtasking has been stopped.	Check startup parameter NATMOD and the load libraries.
<b>ESY0055W</b> - CANNOT LOCATE SUBSYSTEM MODULE :1:	Subsystem module SUBSxxxx not found. The names of the subsystems are specified in the startup parameter 'SUBSYS=' . Subsystem cannot be started properly.	Check startup parameter SUBSYS and the load libraries.
<b>ESY0056W</b> - :1: SERVER TASKS ATTACHED (INSTEAD OF :2:)	VSE/ESA only: Startup parameter 'NUMTASK=' specifies the number of server tasks to attach. However, this exceeds the number of tasks allowed by VSE/ESA.	Change value of NUMTASK for the next run of Entire System Server.
<b>ESY0057W</b> - UNKNOWN POWER VERSION. TABLE MUST BE UPDATED	VSE/ESA only.	Contact Software AG.
<b>ESY0058W</b> - "IDENTIFY" TO POWER FAILED. RS=:1:	POWER interface initialization failed with code :1:.	Contact your systems programmer.
<b>ESY0059W</b> - LOAD FOR MODULE :1: FAILED	Module :1: was not found. If it is critical, run will terminate. Otherwise, it will continue.	Check your STEPLIB-concatenation.