

Console Messages ESY0080W - ESY0080W

Message	Explanation	Action
ESY0080W - ATTACH FOR EVENTING TASK FAILED	For VSE/ESA: An attempt to attach a special task needed for the 'EVENTING' view failed.	Check your startup parameter.
ESY0081W User :1: has requested termination.	FUNCTION = 'XEND' in view NATPROC-USERS was issued. Entire System Server will terminate now.	No action required.
ESY0082W - VTAM PRINTER "SETLOGON START" FAILED	A VTAM printer 'SETLOGON START' failed.	Verify your VTAM definitions.
ESY0084W - ALL TASKS ACTIVE - INCREASE "NUMTASK"	VSE/ESA only: All worker subtasks are currently active.	Retry request later. If problem persists, increase the value of the NUMTASK parameter and restart Entire System Server.
ESY0085W - NOT ENOUGH GETVIS TO LOAD NATURAL MODULE	VSE/ESA only: Not enough GETVIS was available in the partition to load the requested Natural module.	If problem persists, restart Entire System Server in a larger partition.