

Console Messages ESY2160E - ESY2169W

Note: All console messages prefixed with ESY2 are valid for BS2000/OSD only.

Message	Explanation	Action
ESY2160E - Missing assignment for LINK :1:.	The ADD-FILE-LINK statement for LINK-NAME :1: is missing.	Add the missing statement in the job control of the requesting task.
ESY2161W - TRACE disabled due to errors.	This is a follow up message for a TRACE error. Consequently, the TRACE environment is disabled.	Check previous console message of the task.
ESY2162E - Mismatching ESY version :1: detected.	The external programs ESYSTOP or ESYTRACE cannot interact with the Entire System Server correctly. The unexpected version :1: has been detected which is not compatible to the current version.	Use the same version of ESYSTOP or ESYTRACE as for Entire System Server.
ESY2163E - Error in :1: occurred - R15: :2:.	Error in UCON interface task occurred in program step :1: (= macro and additional information). Return code of macro is given in :2:. For detailed information see appropriate BS2000/OSD manuals.	Depending on macro and return code.
ESY2164W - Data lost.	On connection to \$CONSOLE one or more message(s) have been lost. (DCAM return code '040014..' for YRECEIVE).	No action required.
ESY2165W - Shortage in resources - probably data lost.	UCON interface task could not receive message from \$CONSOLE because of shortage in BCAM/DCAM resources (DCAM return code '1004....' for YRECEIVE).	Contact your network administrator.
ESY2166E - :1: abended.	The task terminates abnormally. This is a follow up message for a serious error. Task will exit now.	Check previous console messages of the task.
ESY2167E - :1: serialization - Macro :2: R15 :3:.	An error occurred when trying to serialize access to memory pool.	Check return code of specified macro and contact Software AG support for more details.
ESY2168E - :1: central wait RC :2:.	Macro RSOFEI has returned an unrecoverable error.	Check return code and output file for more details.
ESY2169W - :1: not started.	The optional task was not started due to missing startup parameters or due to problems during execution of ENTER.	Check startup parameters related to optional task.