

Sample Configuration Member PXANCONF

- Under OS/390, the APSvrs.USERSRCE dataset contains a sample PXANCONF member.
- Under VSE/ESA, the APSvrs sublibrary contains a sample member PXANCONF.P.

If required, PXANCONF may be copied and modified to produce a number of different configuration options. These options can then be selected by operators when SMARTS is started.

Below is a sample configuration member for OS/390:

```

*
INSTALLATION=-ADATCP-
*----- Work Load Definitions -----*
WORKLOAD-AVERAGE=50
WORKLOAD-MAXIMUM=200
*----- SERVERS -----*
SERVER=(OPERATOR,TLINOPER)
*
SERVER=(POSIX,PAENKERN) POSIX SERVER DEFINITION
*
APPLYMOD=73
APPLYMOD=(92,NO)
*
*       ADATCP Definitions
*
RESIDENTPAGE=ADATCP
ADASVC=249
*
*       SMARTS Parameters
*
CDI_DRIVER=('file,PAAMFSIO')
CDI_DRIVER=('tcpip,PAAOSOCK)
SYSTEM_TRACE_LEVEL=1
TRACE_GROUP_INCLUDE=SIGNAL
TRACE_SYSTEM_INCLUDE=MUTEX

```