

Modifying Output Condition Definitions

To modify an existing output condition

1. Type **M** in the line command input field of the selected condition in the Output Conditions window.

The Output Condition Modification window opens with the current values of the conditions.

The Output Condition Modification and Addition windows have the identical layout. The input fields are explained above under Field Descriptions: Output Condition Addition/Modification.

2. Modify the values.
3. Press PF3 (End) to save the new definition and return to the Output Conditions window.

Note:

After you add or modify an output condition definition, a loop check is performed on the affected network. The same conditions apply as described in the subsection Checking for a Loop in a Job Network in the section Network Maintenance with one exception: if a loop is detected in the job flow, no corresponding message appears.