

Accepting All Symbols and Printing Symbols after Prompting

▶ When you have made all desired modifications

1. You must press PF5 (Acpt) from the **last screen** to confirm symbol prompting and accept all symbols for this activation.

If there are several screens of symbols, ****** more ****** will appear in the bottom line.

2. Press PF8 (Down) to display more symbols until you get to the last screen. You can now accept all symbols by pressing PF5.

You are then asked if you want to print the symbols. A window opens in which you can enter the printer name:

```

20.11.01          *** Entire Operations 4.1.1 ***          16:10:49
Owner   EXAMPLE   Symbol Prompting for Table EXAM-ST1
Network E62-NET   Run 261   on 11.07.96 at 16:08
-----
C  Symbol      Value
-  CLASS      G_____
-  JOBLIB     EOR.EXAMPLE.LOAD_____
-  MSGCLASS   X_____
-  PARM-1     8888_____
-  STEPLIB    EOR.EXAM +-----+
-           _____ !           !
-           _____ !   Printing of Prompted Symbols !
-           _____ !           !
-           _____ !           Printer Selection           !
-           _____ !           !
-           _____ !   Please enter printer: _____ !
-           _____ !           !
-           _____ !   PF3 End                               !
-           _____ !           !
L  long value  +-----+
***** Bottom of Data *****
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
                        Acpt Cncl Up   Down
    
```

3. Enter the printer name in the field Please enter printer.
4. Press Enter to print the symbols to the selected printer.

If you do not want to print the symbols, press PF3 (End) to return to the Symbol Prompting screen.

If you generally do not want to print the symbols or display the above window, enter N for the function Symbol Printing after Prompting under Reporting in your profile settings. For more information, see the subsection Reporting Functions in the section System Administrator Services of the Entire Operations Administration Documentation.