

Network Activation Summary

This function produces a status report of all network activations for a given day, regardless of whether they:

- are waiting for prerequisite resources;
- have already been executed;
- are currently being executed;
- have already been completed.

▶ To display the Network Activation Summary

1. Type its option number in the Option field on the Reporting Menu. Press Enter.

The following windows open:

```

02.11.01          +-----+ :00
Owner EXAMPLE    !                               !
----- !           Network Activation Summary ! ----
           !                               !
Reporting Menu  !                               !
           +-----+
1 Log - Terminated Jobs
2 Log - Abended Jobs
3 Log - Jobs not started
4 Accounting Data
5 Network Description (short)
6 Network Description (detailed)
7 Network Job Flo +-----+
8 Schedule of Job !                               !
9 Network Activat !       Please enter the Date for the Report !
10 Network Schedul !                               !
           !           ==> 02.11.01 !
           !           PF3 End !
           +-----+
Command => 9_____
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
           Help           End                               Menu

```

2. Enter the date for which to compile the summary. This can be any date in the past, present or future. Press Enter.

The following window opens:

```

02.11.01          +-----+ :00
Owner EXAMPLE    !                               !
-----         !           Network Activation Summary ! -----
                !                               !
      Reporting Menu !                               !
                +- +-----+
1  Log - Terminated J !                               !
2  Log - Abended Jobs !           Network Activation Summary !
3  Log - Jobs not sta !                               !
4  Accounting Data   !  Owner   ==> _____ * Select Blank All !
5  Network Descriptio !  Network ==> _____ * Select Blank All !
6  Network Descriptio !                               !
7  Network Job Flo +- !  PF3 End                               !
8  Schedule of Job ! +-----+
9  Network Activat !   Please enter the Date for the Report !
10 Network Schedul !                               !
                !                               ==> 02.11.01 !
                !                               !
                !   PF3 End                               !
                +- +-----+
Command => 9_____
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help           End                               Menu
    
```

3. Enter owner and network for which to display information. You can enter selection criteria with an asterisk *. Press Enter.

A window opens at the bottom of the screen in which you are asked Send Output to Printer?:

```

6  Network Descriptio !                               !
7  Network Job Flo +- !  PF3 End                               !
8  Schedule of Job ! +-----+
9  Network Activat !   Please enter the Date for the Report !
10 Network Schedul !                               !
                ! +-----+
                ! !                               !
                ! !           Send Output to Printer ? N (Y/N) !
                +- !                               !
Command => 9_____ +-----+
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
      Help           End                               Menu
    
```

4. If you enter **Y** and press Enter, output is printed on the printer assigned to Workfile 1. If you enter **N** and press Enter, the Network Activation Summary screen appears, for example:

```
02.11.01                Entire Operations 4.1.1                15:10:15
                        Network Activation Summary for 02.11.01    Page    1
-----
EXAMPLE    E40-REC-01
-----
(1031) 10.07 00:00                Activation Net 11.07 16:00
        01.11 00:00                Symbol Table E40-ST activated

EXAMPLE    E50-USRT
-----
( 750) 11.07 12:00                Network Activation
        11.07 11:50  E50-J3-EOJ JCL Load - No lines generated

( 751) 11.07 13:00                Network Activation
        11.07 12:50  E50-J3-EOJ JCL Load - No lines generated

( 752) 11.07 14:00                Network Activation
        11.07 13:50  E50-J3-EOJ JCL Load - No lines generated

EXAMPLE    E60-FLOW
-----
MORE
```

5. Press Enter to display the next screen, if there is more data.
6. Press PF3 (End) to return to the Reporting Menu.>

Note:

For networks that terminate error-free, only those jobs are displayed that have no successors in the same network.