

System Messages ESY5800 to ESY5899

Message	Explanation	Action
ESY5800 - Specified level is a dataset name.	The specified level name is a dataset name.	No action is required.
ESY5801 - Job not found.	The requested job was not found.	No action is required.
ESY5802 - GETMAIN for CSA area failed.	An attempt was made to access main storage, and GETMAIN for the CSA area failed.	Notify your systems programmer.
ESY5803 - Cannot access data.	An attempt was made to access main storage, and the data specified cannot be accessed.	No action is required.
ESY5804 - Request to access data has timed out.	Main storage was accessed, and SRB was scheduled to run in an address space. SRB must be completed within 10 seconds.	No action is required.
ESY5805 - Invalid TCB address.	An invalid TCB-ADDRESS was specified.	Specify valid TCB-ADDRESS.
ESY5806 - Permanent I/O error on catalog.	A permanent I/O error occurred while accessing the catalog.	This may be a hardware error. Contact data center personell.
ESY5807 - Invalid track address.	An invalid track address was specified.	Specify valid track address.
ESY5809 - Subsystem not active.	<p>The related subsystem has not been started properly. Therefore, the requested function is not available in this run of ESY.</p> <p>The following views return this error code on BS2000/OSD:</p> <ul style="list-style-type: none"> ● views SPOOL-QUEUE, SPOOL-FILES, WRITE-SPOOL if SPOOL=NONE is defined; ● views SEND-MESSAGE, CONSOLE if CONSOLE task is not running; ● views CONSOLE, EVENTING if EVENTING task is not running. 	Contact your administrator to get the subsystem started for the next ESY run.
ESY5810 - Error detected in catalog, processing terminated.	An error in the catalog structure was detected.	Notify your systems programmer.
ESY5811 - Specified level is an empty index.	The level specified is an empty index.	No action is required.
ESY5820 - Unknown command.	A command which is not known to Entire System Server was entered.	Check spelling, syntax of command. Check to see whether command is a Natural command.
ESY5821 - Job no longer active.	An attempt was made to access a job which is no longer active.	No action required.

Message	Explanation	Action
ESY5822 - Logical error on JES3 spool.	A logical error occurred while reading the JES3 spool dataset.	Try again. If the error persists, it may indicate a bad control block on the JES3 spool (which may be caused by a hardware error).
ESY5823 - Requested job in input queue.	An attempt was made to access output data of a job which is in the input queue.	Wait until job is processed.
ESY5824 - I/O error on JES3 spool.	A READ operation to JES3 spool failed to complete normally.	Probably a hardware failure. A JES3 warm start (with analysis) should be considered.
ESY5825 - JES3 command dataset is full.	A WRITE operation to the JES3 command dataset failed, because the dataset is full.	Wait until space becomes available.
ESY5826 - I/O error on JES3 command dataset.	A WRITE attempt to the JES3 command dataset failed.	This is probably a hardware error. If the error persists, it may be advisable to relocate the JES3 command dataset.
ESY5830 - JES interface is not active.	The JES interface is not active.	Check the JES parameter in the Entire System Server parameter file.
ESY5831 - Error during queue initialization.	An error occurred while reading JES control blocks.	This is probably a hardware error. Contact data center personnel.
ESY5832 - Error during queue open.	An error occurred during the opening of the JES spool dataset.	Check with your systems programmer.
ESY5833 - You are not allowed to alter this job.	An attempt was made to modify a job. The user is not authorized to modify the specified job. This error message is issued by the security system with which Entire System Server interfaces.	No action is required.
ESY5834 - Command failed, MGCRC RC = :1:.	A request failed to issue an internal JES or system command.	Check with systems programmer. Contact Software AG technical support.
ESY5840 - VTAM operator ACB is not open.	The VTAM operator ACB was not opened successfully during initialization.	Either active VTAM support has not been requested by the system parameters, or an open error occurred during initialization. The job-log contains further information.
ESY5841 - Error in SENDCMD - RTNCD=:1: FDBK2=:2:.	A VTAM error occurred while sending a command. Note: A more detailed message is returned when field ERROR-TEXT is specified.	Check the command requested. The RTNCD and FDBK2 values are defined in the appropriate VTAM documentation.
ESY5842 - Invalid VTAM command.	An invalid VTAM command was requested.	No action is required.
ESY5845 - Printer is active for user :1:.	Another user is working with the printer.	Wait until printer is not busy anymore.

Message	Explanation	Action
ESY5849 Print failed. Fct=:1: FD=:2: S=:3:.	The print request failed. For further details, check the variable data of FUNCTION, FEEDBACK and STATUS. You may find the explanation of these fields in the VTAM documentation.	Please contact your systems programmer.
ESY5851 - File not on volume.	The requested file does not exist on the specified volume.	No action is required.
ESY5852 - No password supplied / VSAM data space.	No password was specified before attempting to access a password-protected VSAM file.	Specify a password.
ESY5853 - Retention cycle unexpired / NEWNAME exists.	A VTOC-UPDATE RENAME function was attempted; however, the retention cycle is unexpired, and the NEWNAME still exists.	Specify a different NEWNAME, or wait until the retention cycle has expired.
ESY5854 - Permanent I/O error.	A permanent I/O error was detected.	This is probably a hardware error. Contact data center personnel.
ESY5855 - Volume not mounted.	The requested volume was not mounted.	Make sure that the volume is mounted before re-issuing the request.
ESY5856 - Operator unable to mount volume.	The operator is not able to mount the volume.	No action is required.
ESY5857 - File in use.	The file is in use.	Retry later.
ESY5858 - Not authorized.	A security violation was detected.	No action is required.
ESY5859 - File definition not deleted by RACF.	The file definition has not been deleted by RACF.	Execute RACF file deletion.
ESY5860 - Member under MSHP control or changed with MSHP bypass.	Member to be overwritten is under MSHP control or was changed with MSHP bypass.	Use MSHP=YES to indicate MSHP bypass required.
ESY5861 - Member contains SYSIPT data.	Member to be overwritten contains SYSIPT data.	Use INLINE-DATA=YES to confirm SYSIPT data required or INLINE-DATA=OFF to switch off the SYSIPT indicator.
ESY5870 - RECORD field not in search buffer.	RECORD must be specified for WRITE-FILE.	Specify RECORD value.
ESY5871 - MEMBER/MEMBER-TYPE not specified.	The member name and/or type was not specified.	Specify a member name and/or type.
ESY5872 - Record format not supported.	The record format of the desired dataset is not supported.	No action is required.
ESY5873 - RECORD-LENGTH missing.	The RECORD-LENGTH value is missing.	Specify RECORD-LENGTH value.
ESY5874 - RECORD-LENGTH > LRECL.	The specified RECORD-LENGTH value is greater than the LRECL of the dataset.	Specify valid RECORD-LENGTH value.

Message	Explanation	Action
ESY5875 - Position of data field > RECORD-LENGTH.	Invalid parameter specified.	Check program and correct error.
ESY5876 - No 'NEW-' field for CHANGE request.	No NEW-CLASS, NEW-DESTINATION or NEW-USERID field was supplied for the CHANGE request.	Supply 'NEW-' value.
ESY5877 - VSAM (SHOWCAT) processing error.	A SHOWCAT error was detected when processing the requested VSAM catalog.	
ESY5878 - Volume defined as DYNAM/D pool name.	The requested volume is defined to Entire System Server as a DYNAM/D 'virtual' pool name. The requested function cannot be performed.	
ESY5881 - Error occurred while opening file.	An error occurred during OPEN.	Check the status of the dataset.
ESY5882 - Error occurred while closing file.	An error occurred during CLOSE.	Check the status of the dataset.
ESY5883 - Dataset is full.	The dataset is full.	Compress the PDS, or increase the dataset size.
ESY5886 - Event is in use.	An attempt was made to delete an event someone was waiting for.	Issue 'POST' request before deleting an event.
ESY5887 - Event is already defined.	An attempt was made to define an event which already exists.	No action is required.
ESY5888 - Event name must be specified.	An eventing request was issued without specifying the EVENT-NAME.	Specify an EVENT-NAME.
ESY5889 - Permanent I/O error while writing dataset.	An I/O error was detected during WRITE access.	This is probably a hardware error. Contact data center personnel.
ESY5890 - Event does not exist.	The specified event does not exist.	No action is required.
ESY5891 - Timeout waiting for event.	A timeout happened before the event was posted.	No action is required.
ESY5893 - Getmain failed.	There was not sufficient storage available to proceed with the request.	Notify systems programmer.
ESY5894 - Enable Eventing failed.	Internal eventing error occurred.	Contact technical support of Software AG.
ESY5899 - Permanent I/O error while reading dataset.	An I/O error was detected during READ access.	This is probably a hardware error. Contact data center personnel.