

Console Messages XCO0020I - XCO0029I

Message	Explanation	Action
XCO0020I X-COM stopped	X-COM nucleus is calling the termination handler for shutdown	No action required
XCO0021W This X-COM is no longer active	X-COM nucleus has successfully executed the termination handler	No action required
XCO0022I X-COM cancel will proceed	The operator command XCANCEL to cancel Entire System Server was entered	No action required
XCO0023I X-COM halted	The operator command XHALT was entered. This means that no more calls are possible, but the Entire System Server task is still available and can be restarted with the XSTART command	No action required
XCO0024I X-COM started	The operator command XSTART was entered. This means that calls are now processed again	No action required
XCO0025I X-COM end will proceed	The operator command XEND to end Entire System Server was entered	No action required
XCO0026E APPL stop error	The shutdown handler has returned an error	Please contact Software AG
XCO0027E Timer error	Setup of timer services has failed. X-COM nucleus terminates abnormally	Please contact Software AG
XCO0028I Number of active users = :1:	Output of command XUSER reporting the current number of user requests	No action required
XCO0029I Highest number of active users = :1:	Output of command XUSER reporting the highest number of user requests	No action required