

Console Messages XCO2001E - XCO2009E

Note: All console messages prefixed with XCO2 are valid for BS2000/OSD only.

Message	Explanation	Action
XCO2001E Error during READ of startup parms.	Bad file format or I/O error during read of startup parameter file.	Parameter file must be a SAM or an ISAM file with variable or fixed record length.
XCO2002E More than :1: parameter cards not possible.	The maximum number :1: of startup parms is exceeded.	Reduce the number of startup parm cards in your parameter file. Check the default values of the parameters to avoid setting the values explicitly.
XCO2003E LOAD for module :1: failed - abend.	Module :1: could not be found. You need Entire System Server or Adabas libraries with module :1: to start the Entire System Server.	Copy the missing module into your library and start the Entire System Server again. Don't rename modules in the load libraries eg. from NAME to NAME.OLD. It could create problems during load.
XCO2004E X-COM abended.	An unrecoverable error has occurred. X-COM terminates abnormally.	Look at the previous error messages of X-COM.
XCO2005E Wrong X-COM parameter :1:.	An invalid value for :1: was specified in startup parameters.	Verify Entire System Server startup parameter :1: and set a proper value.
XCO2006E ADAMPM - wrong version found.	The loaded module ADAMPM has a wrong version.	Check your Adabas library or contact Software AG.
XCO2007E BS2000/OSD V.2 or above is required.	The Entire System Server is compiled for BS2000/OSD Version 2 or above. It cannot run on OSD Version 1 or below.	Upgrade of BS2000/OSD is required.
XCO2008E MPM12-error, CQE is not active.	The Post-User call has been rejected due to bad status of command queue element. The reply cannot be delivered.	No action required.
XCO2009E MPM36 impossible because CQE not active.	The timeout call (TIME elapsed) has been rejected due to bad status of command queue element.	No action required.