

Z-ERA01

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
-

Description

Erase a nickname.

This subprogram applies to a nickname for an internal Con-nect address, a nickname for an external address using the spool file, and a nickname for an external address using the transport service.

When the Deletion-flag is blank, the nickname is moved to the Wastebasket of the cabinet. When the Deletion-flag is marked or when the nickname is already stored in the Wastebasket, the nickname is erased from Con-nect and cannot be recovered.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the nickname is to be erased.
Password	A8	R		The password of the above cabinet.
Nickname	A20	R*		The nickname to be erased.
ISN	P8	R*		The ISN of the nickname to be erased. If both ISN and nickname are supplied, their consistency with one another is verified. You can invoke Z-GET01 or Z-GET01T prior to Z-ERA01 to obtain the ISN for the desired nickname.
Deletion-flag	A1	O		If blank, the nickname is moved to the Wastebasket. If marked, the nickname is erased from Con-nect.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISN was not found
09	ISN does not point to a correct object
91	Invalid name
92	Address does not exist
99	ISN and nickname are not consistent

Subprograms

Z-120

Z-122

Z-123

Z-1200&0