

Z-GET27

This chapter covers the following topics:

- Description
 - Parameters
 - Return Codes
 - Subprograms
-

Description

Return information about a reference document.

When you return information for a reference document which is currently stored in the Inbasket file New, the corresponding address list is updated so that the reception status of the reference document indicates that it has been read. Additionally, the reference document is moved from the file New to file Opened. In this case, END TRANSACTION is automatically issued.

Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2	O	X	Input -1: no ET.
Cabinet	A8	R		The cabinet in which the reference document is stored.
Password	A8	R		The password of the above cabinet.
Ref-document-name	A32	R*		The name of the reference document for which you want to return information. Either Ref-document-name or ISN, not both.
ISN	P8	R*		The ISN of the reference document for which you want to return information. Either ISN or Ref-document-name, not both.
Description	A60/1:4		X	The description of the reference document.
Keywords	A15/1:6		X	Keywords are helpful later when you search for an object.
Title	A60		X	The title of the work.
Writer	A60		X	The writer of the work.
Private-flag	A1		X	If marked, the reference document is a private object.
Security-flags	A4		X	The security levels for Read, Modify and Copy. Values 0 to 9. The security level for Print (fourth byte) is not used for reference documents.
Folder-name	A15		X	The folder in which the reference document is stored.
File-name	A15		X	The file within the above folder in which the reference document is stored.
Author-user-ID	A8		X	Name of the cabinet in which the reference document was added.
Date-created	N8		X	Format yyymmdd. The date when the reference document was added.

Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
04	ISN was not found
08	Supply either ISN or name, not both
09	ISN does not point to correct object
51	Invalid name
53	Requested object does not exist

Subprograms

Z-120

Z-122

Z-123

Z-147

Z-165

Z-175

Z-177

Z-194

Z-197

Z-222

Z-223

Z-400

Z-401

Z-1200&0