

Jobs Schedule

This subsection covers the following topics:

- Invoking the Jobs Schedule
- Column Headings: Production Plan

Invoking the Jobs Schedule

The Jobs Schedule option on the Reporting Menu displays a jobs schedule for a specific date range.

To invoke the Jobs Schedule

1. Type its option number in the Option field on the Reporting Menu. Press Enter.

A window opens in which you can specify a date range:

```

02.11.01          *** Entire Operations 4.1.1 ***          12:30:56
Owner EXAMPLE          Reporting Menu          User ID GHH
-----
Reporting Menu

1 Log - Terminated Jobs
2 Log - Abended Jobs
3 Log - Jobs not started
4 Accounting Data
5 Network Description (short)
6 Network Description (detailed)
7 Network Job Flow Display +-----+
8 Schedule of Jobs          !          !
9 Network Activation Summar ! Schedule of Jobs !
10 Network Schedule Overview !          !
          !          Start Date  ==> 02.11.01 !
          !          !          End Date  ==> 02.11.01 !
          !          !          !          !          !
Command => 8_____ ! Enter          PF3 End !
Enter-PF1---PF2---PF3---PF4---P +-----+ 12---
          Help          End          Menu

```

2. Enter the Start Date and End Date required and press Enter.

The following window opens:

```

02.11.01          *** Entire Operations 4.1.1 ***          12:30:56
Owner EXAMPLE          Reporting Menu          User ID GHH
-----
Reporting Menu
+-----+
1 Log - Terminated J !                               !
2 Log - Abended Jobs !           Schedule of Jobs      !
3 Log - Jobs not sta !                               !
4 Accounting Data !   Owner   ==> EXAMPLE___ * Select Blank All !
5 Network Descriptio !   Network ==> _____ * Select Blank All !
6 Network Descriptio !                               !
7 Network Job Flow D !   PF3 End                       !
8 Schedule of Jobs +-----+
9 Network Activation Summar !   Schedule of Jobs      !
10 Network Schedule Overview !                               !
                               !   Start Date   ==> 02.11.01      !
                               !                               !
                               !   End Date     ==> 02.11.01      !
                               !                               !
Command => 8_____ !   Enter                               PF3 End   !
Enter-PF1---PF2---PF3---PF4---P +-----+ 12---
Help           End                               Menu
    
```

3. Enter owner and network for which to display information. You can enter selection criteria with an asterisk *. Press Enter.

A window opens at the bottom of the screen:

```

6 Network Descriptio !                               !
7 Network Job Flow D !   PF3 End                       !
8 Schedule of Jobs +-----+
9 Network Activation Summar !   Schedule of Jobs      !
10 Network Schedule Overview !                               !
                               +-----+
                               !                               !
                               !   Send Output to Printer ? N (Y/N)      !
                               !                               !
Command => 8_____ +-----+
Enter-PF1---PF2---PF3---PF4---P +-----+ 12---
Help           End                               Menu
    
```

4. If you enter **Y** and press Enter, output is printed.
If you enter **N** and press Enter, the schedule appears on the screen.

A schedule for the given range appears on your screen or is printed in the following format:

```

02.11.01          *** Entire Operations 4.1.1 ***          17:33:52
                  Production Plan 02.11.01 thru 02.11.01
-----
02.11.01
  Owner      Network      Job      Description      Start  Elapsed
-----
ASF          ASF-COPY    JOB-01    LMS-JOB          00:00
                                LMS-JOB

EXAMPLE      E40-REC-01  E40-J01   Run is always okay
                                E40-J02   ABEND=SE37 1st run
                                E40-J03   Run only after recovery
                                E40-J99999 Reset all conditions

SN           A-1        HUGO-1
                                HUGO-2    05:00
                                IMP-TEST  00:00

                                DEMO-NET  JOB1      firST-JOB    09:15

Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12---
                                End          Down          Menu

```

5. Press PF8 (Down) or Enter to scroll down the schedule.
6. Press PF3 (End) to return to the Reporting Menu.

Column Headings: Production Plan

Meaning of column headings:

Field	Description
Owner	Owner name of job.
Network	Network name of job.
Job	Job name.
Description	Short description of job as defined in job definition.
Start	Scheduled starting time of job.
Elapsed	Estimated running time of job.