

Messages and Codes - EOR1301 - EOR1500

This subsection covers the following topics:

- Displaying a Long Message Text
- Messages EOR1301 - EOR1500 in Numerical Order

Displaying a Long Message Text

▶ To display a long message text

- Use the direct command

HELP MSG <message-code>

Messages EOR1301 - EOR1500 in Numerical Order

Message	Explanation	Action
EOR1301 - Job not executing or submitted, not cancelled	The requested function could not be performed.	
EOR1302 - Selected Item is not a job, or job was not submitted	The sysout can only be displayed, if the item is an operating system job, and if it has already been submitted.	
EOR1304 - Job executing.:1:command not possible.	The requested function could not be performed.	
EOR1305 - Job currently executing	A resubmission is allowed only, if the current job is no more active in the operating system.	Wait until termination of the current job, or cancel the current job first.
EOR1306 - Job is not in HOLD Status	The requested function could not be performed.	
EOR1312 - No JCL Location defined	For this function (at least) a JCL location is necessary.	Make a JCL definition for the Job.
EOR1313 - No JCL for this Job Type	This job type does not require a JCL definition.	
EOR1315 - Job executing. JCL cannot be regenerated.	The requested function could not be performed.	
EOR1317 - Active JCL Generation Error	An error occurred during the generation or regeneration of the active JCL. The reason appears as message text in the active jobs list.	

EOR1318 - Active JCL exchanged	The definition of JCL location was modified for an active job. Entire Operations unloaded the current active JCL for this job and loaded the new one to it's own active JCL repository.	
EOR1321 - File Name / Natural Library or Member missing		Correct error.
EOR1323 - Type must be ' ,'*','JOB','STC','INI','TSU'	Possible Types for Selection: Blank or * All Tasks JOB Jobs STC Started Tasks INI Initiators TSU TSO Users	Correct error.
EOR1324 - Type must be ' ,'*','BATCH','DIALOG','TP'	Possible types for selection (BS2000): empty or * - all jobs BATCH - batch jobs only DIALOG - dialog jobs only TP - batch with TP privilege	Correct error.
EOR1350 - No active Job	No active job was found (eventually for the selection).	
EOR1360 - Deactivation of:1:in Progress	The deactivation of a job network or a single job has been initialized. It will be performed in the background by the EOR Monitor. Therefore the job network may remain active for a while.	
EOR1371 - Sub-Network is executing	Function was aborted.	
EOR1372 - Sub-Network was already executed	Function was aborted.	Re-generate the 'JCL' of the sub-network, and retry this function.
EOR1407 - Invalid Condition Status Code (0=free, 1=in use, 2=exclusive)		Correct error.
EOR1419 - Exclusive usage can be set by the Monitor only		Correct error.
EOR1430 - No Loop in Network:1:	The job network definition has been checked for an eventual circular dependency of jobs via their input and output conditions. No circle has been found.	

EOR1431 - Definition Loop in:1:	The job network contains a circular dependency of jobs via their input and output conditions. The job network may be executed with this loop but user has to be aware that this might cause an endless loop when the network is executed.	Remove the input or output condition definition(s), which caused the loop. Use the 'Dependencies' function to get an overview.
EOR1432 - Loop check limit:1:exceeded. Loop check stops.	The loop checks ends after 1000 jobs. This message is issued if in the first 1000 jobs no loop was detected. Note: 1000 is the current limit.	
EOR1451 - Predecessor Job not found	You tried to connect a job with a non-existent predecessor.	Use the wildcard option to find an existing job.
EOR1452 - Jobs not connected	You tried to disconnect 2 jobs that are not connected directly by any condition. The function was not performed.	
EOR1453 - Jobs already connected by:1:	You tried to connect 2 jobs that are already connected by the condition shown in the message. The function was not performed.	
EOR1454 - Recursive Connection not allowed	It is impossible to connect a job to itself.	
EOR1455 - Jobs connected by:1:	The jobs are now connected by the existing or newly generated condition, which is shown in the message.	
EOR1456 - Jobs disconnected	The requested disconnection was successful.	
EOR1457 - Several Predecessor Jobs	The disconnection was not performed, because the connecting condition is output condition of several jobs. Several job connections would be interrupted. The function was aborted.	Remove the output condition definition of the wanted predecessor job.
EOR1458 - Several Successor Jobs	The disconnection was not executed, because the linking output condition is input condition for several jobs. Several jobs would therefore be disconnected.	Perform the disconnection manually by deleting the successor job's input condition.

EOR1459 - No Disconnection in other Network	The job dependency display currently shows a job from another network than it was invoked from. Due to possible different granting rights for the other network, a disconnection is not allowed.	Use the 'Dependencies'/'Disconnect' function from the job which is affected.
EOR1460 - No Connection in other Network	The job dependency display currently shows a job from another network than it was invoked from. Due to possible different granting rights for the other network, a connection is not allowed.	Use the 'Dependencies'/'Connect' function from the job which is affected.
EOR1481 - Only possible with Reference = RUN	The requested special input condition dependency is only possible, is the condition reference is set to 'RUN'. This is necessary, because the condition can be prompted by any user interaction.	Correct error.
EOR1500 - You have Mail	There are messages in your Entire Operations mailbox.	Use the direct command 'MAIL' to see your messages.