

Parameters

To invoke a SYSERR function, on the SYSERR main menu, enter the code for the function desired and one or more of the parameters described below. Any restrictions which apply are mentioned in the explanations of the individual functions. See also the section Functions.

Below is information on:

- Message Type
 - Library
 - Message Number
 - Language Codes
-

Message Type

Specifies the type of message to be processed. The table below lists the message types available.

Type	Explanation
NS	Natural short messages
NL	Natural long messages
US	User-defined short messages
UL	User-defined long messages

Library

Specifies the library for which messages are to be entered or maintained. Field contents are ignored when accessing Natural messages.

Message Number

Specifies the first and last number for the range. The maximum message number for a library is 9999. The message number 0000 is not allowed. To specify only one message number, either enter the number of the message in the left Message Number field and clear the right field, or enter the number in both fields.

Language Codes

Specifies a maximum of 9 from 60 available language codes. The language codes are single alphanumeric characters in the ranges 1 - 9, A - Z and a - y. To view or select language codes, enter a question mark (?) in the first position of the Language Codes field and press ENTER. For more information, see the system variable *LANGUAGE in the Natural Programming Reference documentation.