

Operator Commands

MVS operator communication with the SAF Server is achieved using the OS/390 Modify (F) command. All operator commands for the SAF Kernel are prefixed with SAF. For example:

```
F jobname ,SAF SSTAT
```

The available operator commands are:

- SSHUT
 - SREST
 - SSTAT
 - SUSERS
 - SUSTAT user-id
 - SSNAP hhhhhhhh
 - SHELP
-

SSHUT

Perform an orderly shutdown of the SAF Kernel started task. This command should always be used to request an orderly termination.

SREST

Restart the SAF Kernel, ensuring that all data held in its cache is flushed. Any data held by the security system itself in the SAF Kernel address space is also flushed. The operation is transparent to all on-line and batch users.

SSTAT

Display general statistics on the operator console for the SAF Kernel.

SUSERS

Display a list of active users.

SUSTAT user-id

Display statistics for a specified user.

SSNAP hhhhhhh

Display a selected portion of the SAF Kernel's memory. Operation is not terminated.

SHELP

Display all possible SAF Kernel operator commands.